MIT FIELD CARD

Media Ingest Tool · card offload, verify and logs

NEW NEW SHOW

```
mit init ~/Shows/ShowName/ingest
```

Answers questions and writes `project.json`. New season: add `--from` and the last show's folder. Check a show with `mit config`.

START EACH MORNING

Open Terminal and go into the show's folder (the one with `project.json`). Type `cd ` , drag the folder in from Finder, press Return.

```
cd ~/Shows/ShowName/ingest
```

Every `mit` command after that uses this show's settings. Check where you are with `pwd`.

CARD OFFLOAD A CARD

```
mit ingest
```

Source card path	drag the card in, e.g. `/Volumes/Untitled`
Destinations	`Return` for the defaults
Camera ID	e.g. `A` , `DR1`
Shoot date [10132026]	`Return` . If clips cross midnight it asks you to type the shoot day.
Use these for 10/13/2026?	First card of a day only. `Return` keeps; `n` edits each field (Return keeps · type replaces · `-` removes).
Is this the same card? Recopy it as …	Only after a failed or interrupted copy. `y` recopies under the same name.
Card name ABC261013A01	`Return` ; `n` lets you type a reel number
Media type [VIDEO]	`Return` . A red box means check before overriding.
Notes for this card	e.g. "card ejected mid-clip 0032", or `Return`
Start offload?	`y`

RESULT WHAT THE END MEANS

PASS	Every file verified on every drive. The summary lists each drive's free space.
FAIL (red box)	Don't reuse the card. Run `mit ingest` again and answer `y` to recopy it.
Interrupted (Ctrl-C, cable)	Nothing lost. Run `mit ingest` again; it offers to recopy under the same name.
`warning:` lines	The media is safe; something else (log, report) needs a rerun. The warning names the command.

Before a card goes back to camera: it must show PASS, and the wrap check below must pass on both drives.

WRAP END OF DAY

Re-check today's cards on each drive (reads every byte again):

```
mit verify --drive DRV01A --date 10132026
mit verify --drive DRV01B --date 10132026
```

Add or change the day's notes, header fields or crew:

```
mit daylog 10132026
```

Proxies, only if post needs them: `mit proxies --drive DRV01A --date 10132026`

SHIP SHUTTLE DRIVE ARRIVES

```
mit verify --drive DRV01B
```

Checks every card the drive's log lists. A missing card folder is a FAIL. Exit status 0 = all passed.

FIX IF SOMETHING'S OFF

YOU SEE	DO
"same physical disk"	Use two separate drives. Partitions of one drive don't count.
"Not enough free space"	Nothing was copied. Swap in a drive with room.
"Destinations disagree about … reels"	Stop. The drives don't match; check for a half-copied card.
Master log not updated / damaged	`mit log rebuild`
Report or day log needs refreshing	`mit report 10132026`
New laptop, project totals gone	`mit history rebuild --dest DRV01A --dest DRV02A`
Older card has no ASC MHL	`mit mhl --drive DRV01A`
Spreadsheet out of date	`mit log export`

NAME READING A CARD NAME

ABC	261013	A	01
SHOW	YYMMDD	CAMERA	REEL

Drone 1, second card: `ABC261013DR102`. Reels count up per camera per day, across all drives.

DRIVE WHERE THINGS ARE

```
DRV01A/
├─ 10132026/                 shoot date, MMDDYYYY
│  ├─ VIDEO/ABC261013A01/    the card, exactly as shot
│  │     ascmhl/             ASC MHL hash list
│  │     ABC261013A01_report.html
│  ├─ AUDIO/  STILLS/        created when needed
│  └─ PROXIES/ABC261013A01/  only if made
├─ _REPORTS/10132026/        job reports, daily card log
├─ _LOGS/                    media_log.sqlite, DRV01A_media_log.xlsx
└─ _INCOMPLETE/              failed copies moved aside (delete by hand)
```

The tool never deletes or overwrites media. Full details: README in the tool's folder · github.com/kegurugi/media-ingest-tool