

A.4.19 SMS/CBS 7-bit Oriya/Odia Alphabet (0x19)

A.4.19.1 SMS/CBS 7-bit Oriya/Odia Alphabet (0x19) base table

				b7	0	0	0	0	1	1	1	1
				b6	0	0	1	1	0	0	1	1
				b5	0	1	0	1	0	1	0	1
b4	b3	b2	b1		0	1	2	3	4	5	6	7
0	0	0	0	0	୦ 0B01	ଐ 0B10	SP 0020	0 0030	୩ 0B2C	୦ 0B3E	୦ 0B55	p 0070
0	0	0	1	1	୦ 0B02	ୠ 005F	ୢ 0B24	1 0031	ୡ 0B2D	୦ 0B3F	a 0061	q 0071
0	0	1	0	2	୦୪ 0B03		ୢ 0B1F	2 0032	ୢ 0B2E	୦୧ 0B40	b 0062	r 0072
0	0	1	1	3	ଅ 0B05	ଓ 0B13	# 0023	3 0033	ୡ 0B2F	ୠ 0B41	c 0063	s 0073
0	1	0	0	4	ଅ 0B06	ଐ 0B14	ଅ 0B25	4 0034	ୡ 0B30	ୠ 0B42	d 0064	t 0074
0	1	0	1	5	ଇ 0B07	୩ 0B15	୦ 0B20	5 0035		ୠ 0B43	e 0065	u 0075
0	1	1	0	6	ଇ 0B08	୩ 0B16	୩ 0B26	6 0036	୩ 0B32	ୠ 0B62	f 0066	v 0076
0	1	1	1	7	ୡ 0B09	ୢ 0B17	ୢ 0B21	7 0037	୩ 0B33	ୠ 0B56	g 0067	w 0077
1	0	0	0	8	ୡ 0B0A	ୢ 0B18	ୢ 0B27	8 0038		ୠ 0B47	h 0068	x 0078
1	0	0	1	9	ୢ 0B0B	ୢ 0B19	ୢ 0B22	9 0039	ୢ 0B35		i 0069	y 0079
1	0	1	0	A	LF 000A	ୢ 0B1A	* 002A	: 003A	ୢ 0B38	ୠ 0B48	j 006A	z 007A
1	0	1	1	B	ୢ 0B0C	SS2 ----	+ 002B	; 003B	ୢ 0B37	ୠ 0B57	k 006B	
1	1	0	0	C		ୢ 0B1B	, 002C	ୢ 0B23	ୢ 0B36		l 006C	
1	1	0	1	D	CR 000D	ୢ 0B1C	ୢ 0B28	ୢ 0B2A	ୢ 0B39	ୠ 0B4B	m 006D	
1	1	1	0	E	ୢ 0B0F	ୢ 0B1D	ୢ 002E	ୢ 0B2B	ୠ 0B3C	ୠ 0B4C	n 006E	୦ 0970
1	1	1	1	F		ୢ 0B1E	/ 002F	? 003F	ୠ 0B4D, 200C	ୠ 0B4D	୦ 006F	

In the event that an MS receives a code where a symbol is not represented in the above table then the MS shall display the REPLACEMENT CHARACTER (U+FFFD).

LF: LINE FEED; moves to the next line (with implied carriage return).

CR: CARRIAGE RETURN; CR is not used as CR but is used as a filler after the actual SMS/CBS message text. CR should not occur inside a message text, but if it does, it must be converted to LF. Note though that <SS2,CR> is actually CSI (see next table), and that "CR" is not a filler, nor LF.

SS2: SINGLE SHIFT TWO; This code shifts the next 7-bit code unit to refer to an extension of this table (subclause A.4.19.2).

When splitting a message text into submessages, there must be no cut right after an SS2.

U+0B4D: ORIYA SIGN VIRAMA: This is a control character for forming conjuncts. If the display font does not support the requested conjunct, U+0B4D is a combining character with nominal glyph.

A.4.19.2 SMS/CBS 7-bit Oriya/Odia Alphabet (0x19) extension (SS2) table

				b7	0	0	0	0	1	1	1	1
				b6	0	0	1	1	0	0	1	1
				b5	0	1	0	1	0	1	0	1
b4	b3	b2	b1		0	1	2	3	4	5	6	7
0	0	0	0	0	@ 0040	< 003C	୪ 0B6A	୨ 0B60	 007C	P 0050	¼ 00BC	Δ 26A0
0	0	0	1	1	£ 00A3	= 003D	୫ 0B6B	୩ 0B61	A 0041	Q 0051	½ 00BD	∞ 221E
0	0	1	0	2	\$ 0024	> 003E	୨ 0B6C	୧ 0B44	B 0042	R 0052	¾ 00BE	² 00B2
0	0	1	1	3	¥ 00A5	₹ 20B9	୭ 0B6D	୧ 0B63	C 0043	S 0053	“ 201C	³ 00B3
0	1	0	0	4	§ 00A7	^ 005E	Γ 0B6E		D 0044	T 0054	” 201D	ξ 0B3D
0	1	0	1	5	" 0022		℄ 0B6F		E 0045	U 0055	¤ 00A4	
0	1	1	0	6	€ 20AC		୧ 0B5F		F 0046	V 0056	Ω 03A9	
0	1	1	1	7	% 0025	(0028	୫ 0B71		G 0047	W 0057	μ 03BC	
1	0	0	0	8	& 0026	) 0029	{ 007B	୧ 200D,0B4D	H 0048	X 0058	° 00B0	
1	0	0	1	9	' 0027	 0964	} 007D		I 0049	Y 0059	× 00D7	
1	0	1	0	A	FF 000C	 0965	୧୪ 0B67,2044,0B6A	≈ 2248	J 004A	Z 005A	÷ 00F7	
1	0	1	1	B	- 2212	SS3 ----	୧୨ 0B67,2044,0B68	≠ 2260	K 004B		± 00B1	
1	1	0	0	C	! 0021	o 0B66	୧୪ 0B69,2044,0B6A	[005B	L 004C		‰ 2030	
1	1	0	1	D	CSI 009B	୧ 0B67	≤ 2A7D	~ 007E	M 004D		« 00AB	
1	1	1	0	E	- 002D	9 0B68	≥ 2A7E	] 005D	N 004E		» 00BB	
1	1	1	1	F		୧ 0B69	\ 005C	· 00B7	O 004F		' 2019	୨ 0B70

In the event that an MS receives a code where a symbol is not represented in the above table then the MS shall display the REPLACEMENT CHARACTER (U+FFFD).

FF: FORM FEED; This code is defined as a Page Break character (with implied carriage return). Any mobile station which does not have pagination shall treat it as a LINE FEED (with implied carriage return).

CSI: CONTROL SEQUENCE INTRODUCER; enables decimal character references, enables styling.

SS3: SINGLE SHIFT THREE; This code is reserved for the extension to another extension table. When splitting a message text into submessages, there must be no cut right after an SS3.

U+2044 FRACTION SLASH; the sequence may need to be isolated from adjacent digits by ZWNJ.