
Annex B (informative): Guidelines for creating 7-bit alphabet tables (base and extensions)

B.1 Introduction

Please see the numerous examples above for format. The tables need to be carefully constructed.

When reviewing it is important to consider which letters are in modern use, which punctuation and currency symbols are in modern use, as well as the Unicode normalisation (in particular NFC) and which characters may be produced by composition in case there is no space (in the locking shift and SS2 tables; SS3 should be avoided). If not all relevant letters fit in the tables, some may be accessible using combining marks.

In some cases, one may need to rely on the decimal character reference mechanism (section D) for some characters. Certain internationally useful symbols should be included, at the same position as in the existing 7-bit alphabets. Certain characters, LF, CR, SS2, FF, CSI, SS3, SP, as well as *, #, /, \, +, 0-9, a-z (lowercase) must be in the same positions as all 7-bit alphabet tables.

B.2 Templates for defining 7-bit alphabet tables

See numerous examples in the subsections A.4.x.1 above for how base tables are defined. LF, CR, SS2, SP, as well as *, #, /, \, +, 0-9, _, a-z (lowercase) must be in the same positions in all 7-bit alphabet tables.

See numerous examples in the subsections A.4.x.2 above for how single shift tables are defined. FF, CSI, and SS3 must be in the same positions in all 7-bit alphabet tables (except that CSI does not exist for 0x00-0x0F, nor does really SS3).

B.3 Void

