

1 Gain law

(bars: lengths by R ; $a_o := \Delta t / (\gamma_N R)$, $a_{\text{nom}} := a_o R$, $\bar{a} := a / a_{\text{nom}}$, $\bar{f} := a_o f$, $\bar{a} \bar{f} = \Delta \bar{w}$; $e_\theta = \theta - \hat{\theta}$; $\mathbb{E}[\cdot]$ over the noise; $P_{ij}[k] = \mathbb{E}[e_i[k] e_j[k]]$ posterior at k , P^f forecast; $\bar{w}_d[k]$ known)

$$\bar{a}_{\text{true}}(\bar{w}) = 1 - \frac{9}{8\bar{w}} + \frac{1}{2\bar{w}^3} - \frac{57}{100\bar{w}^4} + \frac{1}{5\bar{w}^5} + \frac{7}{200\bar{w}^{11}} - \frac{1}{25\bar{w}^{12}}$$

$$\bar{a}'_{\text{true}}(\bar{w}) = \frac{9}{8\bar{w}^2} - \frac{3}{2\bar{w}^4} + \frac{57}{25\bar{w}^5} - \frac{1}{\bar{w}^6} - \frac{77}{200\bar{w}^{12}} + \frac{12}{25\bar{w}^{13}}$$

$$\bar{a}''_{\text{true}}(\bar{w}) = -\frac{9}{4\bar{w}^3} + \frac{6}{\bar{w}^5} - \frac{57}{5\bar{w}^6} + \frac{6}{\bar{w}^7} + \frac{231}{50\bar{w}^{13}} - \frac{156}{25\bar{w}^{14}}$$

$$\begin{aligned} \bar{a}'[k] &:= \bar{a}'_{\text{true}}(\bar{w}_d[k] - \delta \hat{w}_3[k]), & \bar{a}''[k] &:= \bar{a}''_{\text{true}}(\bar{w}_d[k] - \delta \hat{w}_3[k]) \\ \frac{\partial \bar{a}'[k]}{\partial \bar{a}_w} &= 0, & \frac{\partial \bar{a}'[k]}{\partial \delta \bar{w}_3} &= -\bar{a}''[k], & a_w &= a_o \bar{a}_w \end{aligned}$$

2 Jacobians

(row 4 of F_e , first order in the step; the exact-map corrections, relative size $\bar{a}'[\Delta \bar{w}_d + (1 - \lambda_c) \delta \hat{w}_3] / (1 - \hat{a}_w) \approx 10^{-2}$, are not carried)

$$F_e(4, 3) = (1 - \lambda_c) \bar{a}'[k] - \bar{a}''[k] [\Delta \bar{w}_d[k] + (1 - \lambda_c) \delta \hat{w}_3[k]]$$

$$F_e(4, 4) = 1 + F_{dw}[k] \bar{a}'[k]$$

3 True dynamics

$$(\delta \bar{w}_j[k] := \delta \bar{w}[k - d + j - 1], \quad j = 1, \dots, d + 1, \quad d = 2)$$

$$\bar{w}[k] = \bar{w}_d[k] - \delta \bar{w}_3[k]$$

$$\bar{w}_d[k + 1] = \bar{w}_d[k] + \Delta \bar{w}_d[k]$$

$$\delta \bar{w}_1[k + 1] = \delta \bar{w}_2[k]$$

$$\delta \bar{w}_2[k + 1] = \delta \bar{w}_3[k]$$

$$\delta \bar{w}_3[k + 1] = \lambda_c \delta \bar{w}_3[k] - F_{dw}[k] e_{\bar{a}_w}[k] - \varepsilon_w[k]$$

$$\bar{w}[k + 1] - \bar{w}[k] = \Delta \bar{w}_d[k] + (1 - \lambda_c) \delta \bar{w}_3[k] + F_{dw}[k] e_{\bar{a}_w}[k] + \varepsilon_w[k]$$

$$\bar{a}_w[k + 1] = \bar{a}_{\text{true}}(\bar{w}[k + 1])$$

$$F_{dw}[k] = \bar{f}_{dw}[k] + (1 - \lambda_c) \sum_{i=1}^d \bar{f}_{dw}[k - i]$$

$$\varepsilon_w[k] = \bar{a}_w[k] \bar{f}_T[k] + (1 - \lambda_c) \sum_{i=1}^d \bar{a}_w[k - i] \bar{f}_T[k - i] - (1 - \lambda_c) n_w[k]$$

4 Process model

$$\mathbf{x} = [\delta\bar{w}_1, \delta\bar{w}_2, \delta\bar{w}_3, \bar{a}_w]^\top \quad (d = 2)$$

5 Estimator

$$\begin{aligned} \delta\hat{w}_1[k+1] &= \delta\hat{w}_2[k] \\ \delta\hat{w}_2[k+1] &= \delta\hat{w}_3[k] \\ \delta\hat{w}_3[k+1] &= \lambda_c \delta\hat{w}_3[k] \\ \hat{a}_w[k+1] &= \hat{a}_w[k] + \bar{a}'[k] [\Delta\bar{w}_d[k] + (1 - \lambda_c) \delta\hat{w}_3[k]] \\ &\quad + \frac{1}{2} \bar{a}''[k] [\Delta\bar{w}_d[k] + (1 - \lambda_c) \delta\hat{w}_3[k]]^2 \\ &\quad + \frac{1}{2} \bar{a}''[k] \left[(1 - \lambda_c)^2 P_{33}[k] + 2(1 - \lambda_c) F_{dw}[k] P_{34}[k] + F_{dw}[k]^2 P_{44}[k] + Q_{33}[k] \right] \\ &\quad - \bar{a}''[k] \left[(1 - \lambda_c) P_{33}[k] + F_{dw}[k] P_{34}[k] \right] \end{aligned}$$

code: the first two terms of the $\hat{a}_w$ row are carried by the exact step,

$$\begin{aligned} &\frac{\bar{a}'[k] (1 - \hat{a}_w[k]) [\Delta\bar{w}_d[k] + (1 - \lambda_c) \delta\hat{w}_3[k]]}{(1 - \hat{a}_w[k]) + \bar{a}'[k] [\Delta\bar{w}_d[k] + (1 - \lambda_c) \delta\hat{w}_3[k]]} \\ &= \bar{a}'[k] [\Delta\bar{w}_d[k] + (1 - \lambda_c) \delta\hat{w}_3[k]] - \frac{\bar{a}'[k]^2}{1 - \hat{a}_w[k]} [\Delta\bar{w}_d[k] + (1 - \lambda_c) \delta\hat{w}_3[k]]^2 + \mathcal{O}(3) \end{aligned}$$

whose second-order coefficient is $-\bar{a}''/(1 - \hat{a}_w)$ instead of $\frac{1}{2}\bar{a}''$; the difference $\frac{1}{2}(\bar{a}''[k] + 2\bar{a}'[k]^2/(1 - \hat{a}_w[k]))[\Delta\bar{w}_d[k] + (1 - \lambda_c) \delta\hat{w}_3[k]]^2$ is added together with the two mean lines (pred_mean2).

6 Error dynamics

(True – Estimator)

$$\begin{aligned} e_{\delta\bar{w}_1}[k+1] &= e_{\delta\bar{w}_2}[k] \\ e_{\delta\bar{w}_2}[k+1] &= e_{\delta\bar{w}_3}[k] \\ e_{\delta\bar{w}_3}[k+1] &= \lambda_c e_{\delta\bar{w}_3}[k] - F_{dw}[k] e_{\bar{a}_w}[k] - \varepsilon_w[k] \\ e_{\bar{a}_w}[k+1] &= [1 + F_{dw}[k] \bar{a}'[k]] e_{\bar{a}_w}[k] + \left[(1 - \lambda_c) \bar{a}'[k] - \bar{a}''[k] [\Delta\bar{w}_d[k] + (1 - \lambda_c) \delta\hat{w}_3[k]] \right] e_{\delta\bar{w}_3}[k] \\ &\quad + \bar{a}'[k] \varepsilon_w[k] + (\text{second order, below}) \end{aligned}$$

$$F_e[k] = \begin{bmatrix} 0 & 1 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 0 & 0 & \lambda_c & -F_{dw} \\ 0 & 0 & (1 - \lambda_c) \bar{a}' - \bar{a}'' [\Delta \bar{w}_d + (1 - \lambda_c) \delta \hat{w}_3] & 1 + F_{dw} \bar{a}' \end{bmatrix}, \quad \mathbf{q}[k] = \begin{bmatrix} 0, 0, -\varepsilon_w, \bar{a}'[k] \varepsilon_w \end{bmatrix}^\top$$

known and unknown parts of the true step, and the two starting points

$$\begin{aligned} \bar{w}[k+1] - \bar{w}[k] &= \left[\Delta \bar{w}_d[k] + (1 - \lambda_c) \delta \hat{w}_3[k] \right] + \left[(1 - \lambda_c) e_{\delta \bar{w}_3}[k] + F_{dw}[k] e_{\bar{a}_w}[k] + \varepsilon_w[k] \right] \\ \bar{w}[k] &= (\bar{w}_d[k] - \delta \hat{w}_3[k]) - e_{\delta \bar{w}_3}[k] \end{aligned}$$

truth, second order about $\bar{w}_d[k] - \delta \hat{w}_3[k]$

$$\begin{aligned} \bar{a}'_{\text{true}}(\bar{w}[k]) &= \bar{a}'[k] - \bar{a}''[k] e_{\delta \bar{w}_3}[k] + \mathcal{O}(e^2), \quad \bar{a}''_{\text{true}}(\bar{w}[k]) = \bar{a}''[k] + \mathcal{O}(e) \\ \bar{a}_w[k+1] - \bar{a}_w[k] &= \bar{a}'_{\text{true}}(\bar{w}[k]) [\bar{w}[k+1] - \bar{w}[k]] + \frac{1}{2} \bar{a}''_{\text{true}}(\bar{w}[k]) [\bar{w}[k+1] - \bar{w}[k]]^2 + \mathcal{O}(3) \\ &= \bar{a}'[k] \left[\Delta \bar{w}_d[k] + (1 - \lambda_c) \delta \hat{w}_3[k] \right] + \bar{a}'[k] \left[(1 - \lambda_c) e_{\delta \bar{w}_3}[k] + F_{dw}[k] e_{\bar{a}_w}[k] + \varepsilon_w[k] \right] \\ &\quad - \bar{a}''[k] e_{\delta \bar{w}_3}[k] \left[\Delta \bar{w}_d[k] + (1 - \lambda_c) \delta \hat{w}_3[k] \right] \\ &\quad + (1 - \lambda_c) e_{\delta \bar{w}_3}[k] + F_{dw}[k] e_{\bar{a}_w}[k] + \varepsilon_w[k] \\ &\quad + \frac{1}{2} \bar{a}''[k] \left[\Delta \bar{w}_d[k] + (1 - \lambda_c) \delta \hat{w}_3[k] \right]^2 \\ &\quad + \bar{a}''[k] \left[\Delta \bar{w}_d[k] + (1 - \lambda_c) \delta \hat{w}_3[k] \right] \left[(1 - \lambda_c) e_{\delta \bar{w}_3}[k] + F_{dw}[k] e_{\bar{a}_w}[k] + \varepsilon_w[k] \right] \\ &\quad + \frac{1}{2} \bar{a}''[k] \left[(1 - \lambda_c) e_{\delta \bar{w}_3}[k] + F_{dw}[k] e_{\bar{a}_w}[k] + \varepsilon_w[k] \right]^2 \end{aligned}$$

estimator, second order (first two terms of the $\hat{a}_w$ row)

$$\hat{a}_w[k+1] - \hat{a}_w[k] = \bar{a}'[k] \left[\Delta \bar{w}_d[k] + (1 - \lambda_c) \delta \hat{w}_3[k] \right] + \frac{1}{2} \bar{a}''[k] \left[\Delta \bar{w}_d[k] + (1 - \lambda_c) \delta \hat{w}_3[k] \right]^2$$

truth – estimator

$$\begin{aligned} e_{\bar{a}_w}[k+1] - e_{\bar{a}_w}[k] &= \bar{a}'[k] \left[(1 - \lambda_c) e_{\delta \bar{w}_3}[k] + F_{dw}[k] e_{\bar{a}_w}[k] + \varepsilon_w[k] \right] \\ &\quad - \bar{a}''[k] e_{\delta \bar{w}_3}[k] \left[\Delta \bar{w}_d[k] + (1 - \lambda_c) \delta \hat{w}_3[k] \right] \\ &\quad + (1 - \lambda_c) e_{\delta \bar{w}_3}[k] + F_{dw}[k] e_{\bar{a}_w}[k] + \varepsilon_w[k] \\ &\quad + \bar{a}''[k] \left[\Delta \bar{w}_d[k] + (1 - \lambda_c) \delta \hat{w}_3[k] \right] \left[(1 - \lambda_c) e_{\delta \bar{w}_3}[k] + F_{dw}[k] e_{\bar{a}_w}[k] + \varepsilon_w[k] \right] \\ &\quad + \frac{1}{2} \bar{a}''[k] \left[(1 - \lambda_c) e_{\delta \bar{w}_3}[k] + F_{dw}[k] e_{\bar{a}_w}[k] + \varepsilon_w[k] \right]^2 + \mathcal{O}(3) \end{aligned}$$

mean, with A1 $\mathbb{E}[e_{\delta \bar{w}_3}] = \mathbb{E}[e_{\bar{a}_w}] = 0$, A2 $\mathbb{E}[\delta \hat{w}_3 e_{\delta \bar{w}_3}] = \mathbb{E}[\delta \hat{w}_3 e_{\bar{a}_w}] = \mathbb{E}[\delta \hat{w}_3 \varepsilon_w] = 0$, A3 $\mathbb{E}[\varepsilon_w e] = 0$, $\mathbb{E}[\varepsilon_w^2] = Q_{33}$

$$\begin{aligned} \mathbb{E}[e_{\bar{a}_w}[k+1]] - \mathbb{E}[e_{\bar{a}_w}[k]] &= -\bar{a}''[k] \left[(1 - \lambda_c) P_{33}[k] + F_{dw}[k] P_{34}[k] \right] \\ &\quad + \frac{1}{2} \bar{a}''[k] \left[(1 - \lambda_c)^2 P_{33}[k] + 2(1 - \lambda_c) F_{dw}[k] P_{34}[k] \right. \\ &\quad \left. + F_{dw}[k]^2 P_{44}[k] + Q_{33}[k] \right] \end{aligned}$$

compensation: the two lines added to $\hat{\bar{a}}_w[k+1]$ (Estimator section)

$$\mathbb{E}[e_{\bar{a}_w}[k+1]] - \mathbb{E}[e_{\bar{a}_w}[k]] = 0$$

code: with the exact step in place of $\bar{a}'[\cdot] + \frac{1}{2}\bar{a}''[\cdot]^2$ the mean gains $\frac{1}{2}(\bar{a}''[k] + 2\bar{a}'[k]^2/(1-\hat{\bar{a}}_w[k]))[\Delta\bar{w}_d[k] + (1-\lambda_c)\delta\hat{\bar{w}}_3[k]]^2$, which `pred_mean2` adds back.

7 Measurement and innovation

$$\begin{aligned}\nabla_d \bar{w}_d[k] &= \bar{w}_d[k] - \bar{w}_d[k-d] \\ y_1[k] &= \delta \bar{w}_1[k] + n_w[k] \\ y_2[k] &= \bar{a}_w[k-d] + n_a[k], \quad \text{Var}(n_a) = R_2 \\ \bar{a}_w[k-d] &= \bar{a}_w[k] - \bar{a}'[k] \nabla_d \bar{w}_d[k] \quad (\text{first order, as in the code})\end{aligned}$$

$$H[k] = \begin{bmatrix} 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \end{bmatrix}, \quad L[k] = P^f H^\top (H P^f H^\top + R)^{-1}$$

$$e_{y_1}[k] = e_{\delta \bar{w}_1}[k] + n_w[k], \quad e_{y_2}[k] = e_{\bar{a}_w}[k] + n_a[k]$$

8 Process and measurement noise

$$\begin{aligned}\kappa_T &:= \frac{4k_B T a_o}{R}, \quad \text{Var}(\bar{a}_w[k] \bar{f}_T[k]) = \kappa_T \bar{a}_w[k] \rightarrow \kappa_T \hat{\bar{a}}_w[k], \quad \sigma_{n_w}^2 = \frac{\sigma_n^2}{R^2} \\ Q_{33} &= \kappa_T \left(\hat{\bar{a}}_w[k] + (1-\lambda_c)^2 (\hat{\bar{a}}_w[k-1] + \hat{\bar{a}}_w[k-2]) \right) + (1-\lambda_c)^2 \sigma_{n_w}^2 \\ Q_{34} &= Q_{43} = -\bar{a}'[k] Q_{33}, \quad Q_{44} = \bar{a}'[k]^2 Q_{33}\end{aligned}$$

$$\begin{aligned}R &= \text{diag}(R_1, R_2), \quad R_1 = \sigma_{n_w}^2, \quad R_2 = 2a_{\text{cov}}^2 IF_{\text{var}}(\hat{\bar{a}}_w) (\hat{\bar{a}}_w + \xi)^2 \\ IF_{\text{var}}(\hat{\bar{a}}_w) &= 1 + 2 \left[c_1 u^2 + 2c_2 u(1-u) + c_3(1-u)^2 \right], \quad u = \frac{\hat{\bar{a}}_w}{\hat{\bar{a}}_w + \xi}, \quad \xi = \rho_n \frac{\sigma_{n_w}^2}{\kappa_T}\end{aligned}$$

$$(c_1 = 1.42044, c_2 = 0.0098975, c_3 = 0.098910, \rho_n = 0.350941, a_{\text{cov}} = 0.05)$$