

Equation of motion

$$h[k+1] = h[k] + a_h[k]\{f_{dh}[k] + f_T[k]\} + \delta h_D[k],$$

Motion error

$$\delta h[k+1] = \delta h[k] + \Delta h_d[k] - a_h[k]\{f_{dh}[k] + f_T[k]\} - \delta h_D[k],$$

$\delta h[k] = h_d[k] - h[k]$, $h_d[k]$ is the desired motion trajectory, $\delta h_D[k]$ is the motion error caused by the disturbance, and $\Delta h_d[k] = h_d[k+1] - h_d[k]$ is the desired motion step size. Radius R enters through $\bar{h} = h/R$; hence $\Delta h_d = R \Delta \bar{h}_d$ and $d/dh = (1/R) d/d\bar{h}$.

Measurement

(d -step delay)

$$\delta h_m[k] = \delta h[k-d] + n_h[k],$$

Control objective: $\delta h[k+1] = \lambda_c \cdot \delta h[k]; \quad 0 \leq \lambda_c < 1$

Ideal control effort (no measurement delay):

$$\bar{f}_{dh}[k] = a_h^{-1}[k]\{\Delta h_d[k] + (1 - \lambda_c) \delta h[k] - \delta h_D[k]\}$$

Motion error:

$$\delta h[k+1] = \delta h[k] + \Delta h_d[k] - a_h[k]\{\bar{f}_{dh}[k] + f_T[k]\} - \delta h_D[k] = \lambda_c \cdot \delta h[k] - a_h[k]f_T[k]$$

d -step measurement delay:

$$\delta h[k] = \delta h[k-d] + \sum_{i=1}^d \Delta h_d[k-i] - \sum_{i=1}^d a_h[k-i]\{f_{dh}[k-i] + f_T[k-i]\} - \sum_{i=1}^d \delta h_D[k-i]$$

Ideal control effort (with d -step measurement delay):

$$\begin{aligned} \bar{f}_{dh}[k] = a_h^{-1}[k] \Big\{ & \underbrace{\left[\Delta h_d[k] + (1 - \lambda_c) \sum_{i=1}^d \Delta h_d[k-i] \right]}_{\Delta h_d^d[k]} + (1 - \lambda_c) \left[\delta h[k-d] - \sum_{i=1}^d a_h[k-i] f_{dh}[k-i] \right] \\ & - \underbrace{\left[\delta h_D[k] + (1 - \lambda_c) \sum_{i=1}^d \delta h_D[k-i] \right]}_{\delta h_D^d[k]} \Big\} \end{aligned}$$

Motion error:

$$\delta h[k+1] = \lambda_c \cdot \delta h[k] - \underbrace{\left\{ a_h[k]f_T[k] + (1 - \lambda_c) \sum_{i=1}^d a_h[k-i]f_T[k-i] \right\}}_{\delta h_T^d[k]}$$

Implementable control effort

$(\delta \hat{h}_D^d \equiv 0$: disturbance not estimated)

$$f_{dh}[k] = \hat{a}_h^{-1}[k] \left\{ \Delta h_d^d[k] + (1 - \lambda_c) \left[\delta h_m[k] - \sum_{i=1}^d \hat{a}_h[k-i] f_{dh}[k-i] \right] \right\}$$

Motion error

$$\delta h[k+1] = \lambda_c \cdot \delta h[k] - a_h[k] [f_{dh}[k] - \bar{\bar{f}}_{dh}[k]] - \delta h_T^d[k]$$

$$a_h[k] \bar{\bar{f}}_{dh}[k] = \Delta h_d^d[k] + (1 - \lambda_c) \left[\delta h[k-d] - \sum_{i=1}^d a_h[k-i] f_{dh}[k-i] \right] - \delta h_D^d[k]$$

$$a_h[k] f_{dh}[k] = (1 + e_{a_h}[k] \hat{a}_h^{-1}[k]) \left\{ \Delta h_d^d[k] + (1 - \lambda_c) \left[(\delta h[k-d] + n_h[k]) - \sum_{i=1}^d \hat{a}_h[k-i] f_{dh}[k-i] \right] \right\}$$

$$\begin{aligned} a_h[k] f_{dh}[k] - a_h[k] \bar{\bar{f}}_{dh}[k] &= e_{a_h}[k] f_{dh}[k] + (1 - \lambda_c) n_h[k] \\ &\quad + (1 - \lambda_c) \sum_{i=1}^d (a_h[k-i] - \hat{a}_h[k-i]) f_{dh}[k-i] + \delta h_D^d[k] \end{aligned}$$

Gain model (definitions only; $a_o = a_{nom}$ = far-field gain, $\bar{h}_d = h_d/R$):

$$\begin{aligned} a_h[k] &= a_h(h_d[k]) - a'_h[k] \delta h[k], & a_h(h_d[k+1]) &= a_h(h_d[k]) + a'_h[k] \Delta h_d[k], \\ a'_h[k] &:= \left. \frac{da_h}{dh} \right|_{h_d} = \frac{s_h[k]}{R}, & s_h[k] &:= \left. \frac{da_h}{d\bar{h}} \right|_{h_d} = \frac{p[k]}{\bar{h}_d - 1} \frac{a_h[k](a_o - a_h[k])}{a_o}. \end{aligned}$$

Radius R

(one bridge) $\bar{h}_d = h_d/R$ is the only place R enters. The slope has a physical and an $\bar{h}$ face, $a'_h = s_h/R$ with $s_h := da_h/d\bar{h}$ (R -free). In a product $a'_h \cdot L$: for the trajectory step $L = \Delta h_d = R \Delta \bar{h}_d$ the R cancels ($a'_h \Delta h_d = s_h \Delta \bar{h}_d$); for a tracking-error length $L \in \{\delta h, F_{dh} e_{a_h}, \varepsilon_h\}$ the $1/R$ stays ($a'_h L = (s_h/R)L$).

Gain-error back-step ($O(\Delta h_d)$ slope-error correction dropped):

$$a_h[k-i] - \hat{a}_h[k-i] \approx e_{a_h}[k] - (h_d[k] - h_d[k-i]) (a'_h[k] - \hat{a}'_h[k]) \approx e_{a_h}[k]$$

$$a_h[k] f_{dh}[k] - a_h[k] \bar{\bar{f}}_{dh}[k] \approx e_{a_h}[k] \underbrace{\left\{ f_{dh}[k] + (1 - \lambda_c) \sum_{i=1}^d f_{dh}[k-i] \right\}}_{F_{dh}[k]} + \delta h_D^d[k] + (1 - \lambda_c) n_h[k]$$

$$\delta h[k+1] = \lambda_c \cdot \delta h[k] - F_{dh}[k] \cdot e_{a_h}[k] - \delta h_T^d[k] - \underbrace{\left\{ \delta h_T^d[k] + (1 - \lambda_c) n_h[k] \right\}}_{\varepsilon_h[k]}$$

True gain recursion

(exact curve swept to $h_d[k+1]$; leading order; a'_h expanded)

$$\boxed{\begin{aligned} a_h[k+1] &= a_h + s_h[k] \Delta \bar{h}_d + \frac{s_h[k]}{R} [(1-\lambda_c) \delta h + F_{dh} e_{a_h} + \varepsilon_h], & s_h[k] &= \frac{p}{\bar{h}_d - 1} \frac{a_h(a_o - a_h)}{a_o} \\ p[k+1] &= p \end{aligned}}$$

True state equation

($\delta h_D^d \equiv 0$; leading order)

$$\begin{aligned} \delta h_1[k+1] &= \delta h_2[k] \\ \delta h_2[k+1] &= \delta h_3[k] \\ \delta h_3[k+1] &= \lambda_c \delta h_3[k] - F_{dh}[k] e_{a_h}[k] - \varepsilon_h[k] \\ a_h[k+1] &= a_h[k] + s_h[k] \Delta \bar{h}_d + \frac{s_h[k]}{R} [(1-\lambda_c) \delta h_3 + F_{dh} e_{a_h} + \varepsilon_h] \\ p[k+1] &= p[k] \end{aligned}$$

State vector: $\mathbf{x}[k] = [\delta h_1, \delta h_2, \delta h_3, a_h, p]^\top[k]$.

Output equation

(leading-order delay back-off, $\Delta \bar{H}_d = (h_d[k] - h_d[k-d])/R$)

The gain readout is *not* a white measurement of a_h . Write the single-sample readout

$$u[k] := \frac{\delta h_r^2[k] - C_n \sigma_{n_h}^2}{C_{dpmr} 4k_B T}, \quad \mathbb{E} u[k] = a_h[k-d].$$

Subtracting and dividing by constants leaves the $\hat{\sigma}_{\delta h_r}^2$ EWMA recursion invariant, so a_{hm} is an *exact* AR(1) filter of u :

$$\boxed{a_{hm}[k] = (1 - a_{cov}) a_{hm}[k-1] + a_{cov} u[k], \quad \text{pole } \phi = 1 - a_{cov}.}$$

Feeding a_{hm} itself as a white measurement counts the same noise $\sum_\tau \phi^\tau$ times over, i.e. over-states its information by $(1 + \phi)/(1 - \phi) = (2 - a_{cov})/a_{cov}$. The increment cancels the pole exactly, with no free parameter:

$$\begin{cases} y_1[k] = \delta h_m[k] = \delta h_1[k] + \underbrace{n_h[k]}_{r_1[k]} \\ y_2[k] = a_{hm}[k] - (1 - a_{cov}) a_{hm}[k-1] = a_{cov} u[k], & \mathbb{E} y_2[k] = a_{cov} a_h[k-d] \end{cases}$$

$a_h[k-d] \approx a_h[k] - s_h[k] \Delta \bar{H}_d[k]$ (same leading-order back-off)

$$\mathbf{y}[k] = \mathbf{H} \mathbf{x}[k] + \mathbf{r}[k], \quad \mathbf{H} = \begin{bmatrix} 1 & 0 & 0 & 0 & 0 \\ 0 & 0 & 0 & a_{cov} & -a_{cov} \Delta \bar{H}_d \frac{s_h[k]}{p} \end{bmatrix}$$

Row 2 is the earlier row scaled by a_{cov} : y_2 still observes a_h directly ($O(\Delta \bar{H}_d)$ correction to H_{24} dropped) and p still enters only through the delay. Whitening also removes the EWMA group delay $(1 - a_{cov})/a_{cov} \approx 19$ steps, which the d -step back-off alone did not cover — $u[k]$ is the instantaneous readout, so only the d -step sensor delay is left. Curvature bias $\frac{1}{2} a_h'' \sigma_h^2$ in u folded into r_2/R_2 (deferred).

Estimator (model)

($\hat{a}_h$ swept by $\hat{s}_h[k]$; $\hat{p}$ random walk)

$$e_{\delta h_1} = \delta h_1 - \hat{\delta h}_1, \quad e_{a_h} = a_h - \hat{a}_h, \quad e_p = p - \hat{p}$$

$$e_{y_1} = e_{\delta h_1} + \underbrace{n_h}_{r_1}, \quad e_{y_2} = a_{hm} - (\hat{a}_h - \Delta \bar{H}_d \hat{s}_h[k]) = e_{a_h} - \Delta \bar{H}_d \frac{\hat{s}_h[k]}{\hat{p}} e_p + \underbrace{n_a}_{r_2}$$

$$\delta \hat{h}_1[k+1] = \delta \hat{h}_2 + \ell_{11} e_{y_1} + \ell_{12} e_{y_2}$$

$$\delta \hat{h}_2[k+1] = \delta \hat{h}_3 + \ell_{21} e_{y_1} + \ell_{22} e_{y_2}$$

$$\delta \hat{h}_3[k+1] = \lambda_c \delta \hat{h}_3 + \ell_{31} e_{y_1} + \ell_{32} e_{y_2}$$

$$\hat{a}_h[k+1] = \hat{a}_h + \hat{s}_h[k] \Delta \bar{h}_d + (1-\lambda_c) \frac{\hat{s}_h[k]}{R} \delta \hat{h}_3 + \ell_{41} e_{y_1} + \ell_{42} e_{y_2}$$

$$\hat{p}[k+1] = \hat{p} + \ell_{51} e_{y_1} + \ell_{52} e_{y_2}$$

Error dynamics

(True – Estimator; leading order, **Lr** dropped. $s_a[k] := \partial s_h / \partial a_h = \frac{p}{h_d-1} \frac{a_o-2a_h}{a_o}$, $\partial s_h / \partial p = s_h[k]/p$)

$$e_{\delta h_1}[k+1] = e_{\delta h_2} - \ell_{11} e_{\delta h_1} - \ell_{12} e_{a_h} + \ell_{12} \Delta \bar{H}_d \frac{s_h[k]}{p} e_p$$

$$e_{\delta h_2}[k+1] = e_{\delta h_3} - \ell_{21} e_{\delta h_1} - \ell_{22} e_{a_h} + \ell_{22} \Delta \bar{H}_d \frac{s_h[k]}{p} e_p$$

$$e_{\delta h_3}[k+1] = \lambda_c e_{\delta h_3} - \underbrace{F_{dh} e_{a_h}}_{q_3} - \ell_{31} e_{\delta h_1} - \ell_{32} e_{a_h} + \ell_{32} \Delta \bar{H}_d \frac{s_h[k]}{p} e_p$$

$$\begin{aligned} e_{a_h}[k+1] = & \left(1 + \Delta \bar{h}_d s_a[k] + \frac{s_h[k]}{R} F_{dh}\right) e_{a_h} + (1-\lambda_c) \frac{s_h[k]}{R} e_{\delta h_3} \\ & + \Delta \bar{h}_d \frac{s_h[k]}{p} e_p + \underbrace{\frac{s_h[k]}{R} \varepsilon_h}_{q_4} - \ell_{41} e_{\delta h_1} - \ell_{42} e_{a_h} + \ell_{42} \Delta \bar{H}_d \frac{s_h[k]}{p} e_p \end{aligned}$$

$$e_p[k+1] = e_p - \ell_{51} e_{\delta h_1} - \ell_{52} e_{a_h} + \ell_{52} \Delta \bar{H}_d \frac{s_h[k]}{p} e_p$$

$$\mathbf{F}_e[k] = \begin{bmatrix} 0 & 1 & 0 & 0 & 0 \\ 0 & 0 & 1 & 0 & 0 \\ 0 & 0 & \lambda_c & -F_{dh} & 0 \\ 0 & 0 & (1-\lambda_c) \frac{s_h[k]}{R} & 1 + \Delta \bar{h}_d s_a[k] + \frac{s_h[k]}{R} F_{dh} & \Delta \bar{h}_d \frac{s_h[k]}{p} \\ 0 & 0 & 0 & 0 & 1 \end{bmatrix}$$

$$\mathbf{e}[k+1] = \mathbf{F}_e[k] \mathbf{e}[k] - \mathbf{L}[k] \mathbf{H} \mathbf{e}[k] + \mathbf{q}[k]$$

Which F_{dh} enters $\mathbf{F}_e$

(the dynamics above are exact; the KF's precondition is not) The boxed motion error is exact with the *realised* f_{dh} . Handing that same F_{dh} to the filter is nevertheless illegitimate: a KF's gain recursion assumes $\mathbf{F}_e[k]$ is independent of the noises, and

$$f_{dh}[k] \ni (1-\lambda_c) \hat{a}_h^{-1} \delta h_m[k] = (1-\lambda_c) \hat{a}_h^{-1} (\delta h[k-d] + n_h[k]),$$

so F_{dh} carries the very thermal history and sensor noise that sit in ε_h . Then $\mathbf{P}$ and $\mathbf{L}$ become innovation-correlated and $\mathbb{E}[\mathbf{L} \text{innov}] \neq 0$ — a *rectification*: a noise multiplied by itself is one-signed whatever the noise does, so it accumulates instead of averaging out, and the minus sign of $F_{e,34}$ sends

$\hat{a}_h$ downward. Measured in far-field positioning with the realised force, the y_1 channel dragged $\hat{a}_h$ down by 24.3% of a_h over 12s, monotonically and without settling; the drift scales with $(1 - \lambda_c)$ and is insensitive to σ_{n_h} (an $80\times$ sweep moves it 2%), as the thermal—not sensor—path predicts.

Split the force into its exogenous mean and its noise-driven remainder,

$$F_{dh} = F_{dh}^{\det} + F_{dh}^{\text{noise}}, \quad f_{dh}^{\det}[k] = \hat{a}_h^{-1} \left\{ \Delta h_d^d[k] - (1 - \lambda_c) \sum_{i=1}^d \hat{a}_h[k-i] f_{dh}^{\det}[k-i] \right\},$$

i.e. the control law with $\delta h_m := 0$, run on its own history: purely trajectory-driven, hence exogenous. The mean enters the Jacobian; the remainder is a multiplicative noise whose variance belongs in Q_{33} :

$$F_{e,34} = -F_{dh}^{\det}[k], \quad \Delta Q_{33} = \text{Var}(F_{dh}^{\text{noise}}) \mathbb{E}[e_{a_h}^2].$$

$\Delta Q_{33} \sim [(1-\lambda_c)\sigma_{\delta h_m}/\hat{a}_h]^2 \mathbb{E}[e_{a_h}^2] \approx 3 \times 10^{-7} \mu\text{m}^2$ against $Q_{33} = 4k_B T a_h \approx 2.4 \times 10^{-4} \mu\text{m}^2$ — three orders down, so it is dropped. With $F_{e,34} = -F_{dh}^{\det}$ the same y_1 contribution measures +0.0% and $\hat{a}_h$ stops drifting. Where the trajectory is stationary $F_{dh}^{\det} = 0$ and y_1 carries no gain information at all — correct, since with no commanded motion the only gain information is the fluctuation statistics, which is precisely what y_2 reads. $\mathbf{q} = [0, 0, q_3, q_4, 0]^\top$: $q_3 = -\varepsilon_h$, $q_4 = (s_h[k]/R)\varepsilon_h = a'_h[k]\varepsilon_h$ (rank-1 gain block, fully correlated $q_4 = -a'_h[k]q_3$); Q values below. Leading order keeps each channel's leading term ($F_{e,44}$'s $\Delta \bar{h}_d s_a$, and p 's sole plant path $F_{e,45} = \Delta \bar{h}_d s_h[k]/p$) but drops the same-order correction to the already- $O(1)$ $H_{24}=1$.

Process noise Q

(Path C strict: only the current white thermal drives Q ; the ε_h MA(d) tail $\rightarrow$ closed-loop variance, $n_h \rightarrow R_1$) $\varepsilon_h = \delta h_T^d + (1-\lambda_c)n_h$ mixes the thermal MA(d) tail and sensor noise; a valid KF Q keeps only the *current* white thermal step $a_h f_T[k]$, with $\text{Var}(a_h f_T) = a_h^2 \sigma_{f_T}^2 = 4k_B T a_h[k]$ (fluctuation–dissipation: $\sigma_{f_T}^2 = 4k_B T \gamma / \Delta t$, $a_h = \Delta t / \gamma$). With $q_3 = -a_h f_T[k]$, $q_4 = a'_h a_h f_T[k]$:

$$\begin{aligned} Q_{33}[k] &= 4k_B T a_h[k], & Q_{44}[k] &= a'_h[k]^2 Q_{33}[k], & Q_{34}[k] &= -a'_h[k] Q_{33}[k], \\ Q_{55} &= 0 \quad (p \text{ constant; optional floor } \sigma_p^2 \text{ if slow drift allowed}). \end{aligned}$$

The MA-tail inflation of σ_{th}^2 (past thermal, cross-step correlated) is the standard correlated-noise KF trade-off, carried by the closed-loop variance, not Q (as in the baseline Path C).

Measurement noise R

($\mathbf{R} = \text{diag}(R_1, R_2)$) $R_1 = \sigma_{n_h}^2$ (sensor noise on δh_m). For y_2 start from the *marginal* variance of the un-whitened readout a_{hm} , which is the baseline R_2 chain unchanged (identical IIR readout, $a_x \rightarrow a_h$): from the random tracking-error component δh_r ,

$$\hat{\sigma}_{\delta h_r}^2[k] = C_{dpmr} 4k_B T a_h[k] + C_n \sigma_{n_h}^2, \quad \text{Var}(a_{hm}[k]) = R_2^{\text{int}}[k] := K_{var} \text{IF}_{var} (a_h[k] + \xi)^2,$$

$$K_{var} = \frac{2a_{cov}}{2 - a_{cov}}, \quad \xi := \frac{C_n}{C_{dpmr}} \frac{\sigma_{n_h}^2}{4k_B T}.$$

For the AR(1) recursion above the stationary variance is $\text{Var}(a_{hm}) = a_{cov} \text{Var}(u) / (2 - a_{cov})$, so the whitened increment $y_2 = a_{cov} u$ satisfies $\text{Var}(y_2) = a_{cov}(2 - a_{cov}) \text{Var}(a_{hm})$, giving

$$R_2[k] = a_{cov}(2 - a_{cov}) R_2^{\text{int}}[k] + a_{cov}^2 \left(\sum_{j=1}^d (d-j+1)^2 \right) Q_{44}[k]$$

Substituting K_{var} collapses the first term to $2a_{cov}^2 \text{IF}_{var}(a_h + \xi)^2$. R_2^{int} is the marginal variance of a_{hm} 's error and already carries u 's own residual colour through IF_{var} , so the map $a_{cov}(2 - a_{cov})$ is all that converts marginal to whitened. The d -step q_4 accumulation (delay-propagation analogue of the baseline's +5 Q_{77}) rides

on $y_2 = a_{cov}u$ and so scales by a_{cov}^2 . Net effect versus feeding a_{hm} white: the KF's per-sample information drops by $(2 - a_{cov})/a_{cov}$, and a_{cov} — an internal IIR parameter — stops leaking into results, which is the acceptance test for this section. Deferred: the a_{hm} curvature/Jensen bias $\frac{1}{2}a_h''\sigma_h^2$ from the thermal excursion σ_h^2 .

Pending (not re-derived here): C_{dpmr} , C_n are the full- a_{pd} closed forms implemented in `build_eq17_6state_constants` (3.1610, 1.1093 at $\lambda_c=0.7$, $a_{pd}=0.05$). The $a_{pd} \rightarrow 0$ simplification $2 + 1/(1 - \lambda_c^2)$, $2/(1 + \lambda_c)$ quoted in earlier drafts of this file is stale — using it would bias a_{hm} by -20% .

Prior on p

(initial P_{55} — pinned by two asymptotic limits, not fitted to c) p is only weakly observable ($H_{25} = O(\Delta \bar{H}_d)$), so $P_{55}[0]$ sets how far $\hat{p}$ can be pushed by y_2 noise before real information arrives. It must therefore state a genuine belief about p — and that belief does not require knowing $c(\bar{h})$: it follows from the two regimes in which sphere-wall drag is known analytically.

Near wall (lubrication). Brenner's solution for a sphere approaching a plane diverges as $c_\perp \rightarrow 1/(\bar{h}-1)$ for $\bar{h} \rightarrow 1$. Matching that divergence in $c_\perp = 1 + K/(\bar{h}-1)^p$ forces $p = 1$.

Far field (method of reflections). $c_\perp - 1 = \frac{9}{8}\bar{h}^{-1} + O(\bar{h}^{-3})$, and $\bar{h} - 1 \rightarrow \bar{h}$, so again $p = 1$.

$p = 1$ is therefore not a fit but the exponent both analytically known regimes demand. Equating the model slope with the true one, $s_h = \frac{p}{h-1} \frac{a_h(a_o - a_h)}{a_o}$ versus $da_h/d\bar{h} = -a_o c'/c^2$, defines the exponent the real curve requires at each height,

$$p_{\text{eff}}(\bar{h}) := -c'(\bar{h}) \frac{\bar{h} - 1}{c(\bar{h}) - 1},$$

which the two limits pin at $p_{\text{eff}}(1^+) = p_{\text{eff}}(\infty) = 1$ (numerically 0.9994 and 1.0001). The prior then only has to cover how far the interpolation between the two anchors strays; for the Brenner/Goldman series that excursion is $\max_{\bar{h}} |p_{\text{eff}} - 1| = 0.034$ at $\bar{h} = 1.22$, over the *whole* domain. Hence

$$\boxed{\sqrt{P_{55}[0]} = 0.035 \quad (\perp \text{ axis, all } \bar{h}).}$$

Seeding $a_h[0]$

(no $c(\bar{h})$ anywhere, at init or later) The far-field anchor used above also seeds the gain: $c_\perp \simeq 1 + \frac{9}{8}/\bar{h}_0$, $c_\parallel \simeq 1 + \frac{9}{16}/\bar{h}_0$, needing only $\bar{h}_0$ (the wall position, assumed known).

$$\boxed{a_h[0] = \frac{a_o}{1 + \frac{9}{8}/\bar{h}_0} \quad (\perp), \quad \sqrt{P_{44}[0]}/a_h = 5/\bar{h}_0^2.}$$

Against the exact curve the seed errs 0.05/0.25/1.23/4.91% at $\bar{h}_0 = 50/22.2/10/5$ (i.e. $\simeq 1.25/\bar{h}_0^2$), versus 2.3/5.3/12.6/28.5% for the flat a_o assumption. $P_{44}[0]$ is that residual with a $4\times$ margin — it must *match* the seed, not be inflated to buy correction room: a 5.33% seed error under a 1% prior moved only 0.9% in 12 s, while the matched pairs converge.

Being domain-wide, this prior needs no recomputation when the trajectory changes. The *structure* of the argument (both ends pinned at $p = 1$) uses only the two published asymptotics; the *width* 0.034 is read off the series in use, and is the one modelling input that remains.

The $\parallel$ axes have no near-wall anchor: Goldman's result there is *logarithmic*, not a power law, so $p_{\text{eff}}(1^+) \rightarrow 0$ (numerically 0.0055 at $\bar{h} = 1.001$) while $p_{\text{eff}}(\infty) = 1$; over $\bar{h} \in [2, 22]$ it sweeps $0.717 \rightarrow 0.979$. The ansatz has nothing to pin near the wall — a structural failure of the power law for $\parallel$, not something a wider prior repairs. The $\parallel$ axes are outside the scope of this 1-D wall-normal derivation.



