End-to-End Hinglish Speech Processing Pipeline: Language Identification, Constrained ASR, Neural Translation, Voice Cloning, and Anti-Spoofing

Speech Processing Assignment 2
Department of Computer Science and Engineering
(Course: Speech and Natural Language Processing)
`speech_assignment2.ipynb`

***Abstract*—We present a complete speech processing pipeline targeting Hinglish (Hindi–English code-switched) audio. The system integrates: (1) a multi-head bidirectional LSTM for frame-level language identification (LID); (2) a bigram language model providing context-aware logit biasing for constrained Whisper-large-v3 decoding; (3) non-stationary denoising via spectral subtraction and `noisereduce`; (4) Hindi-to-Maithili neural machine translation using Meta NLLB-200; (5) zero-shot voice cloning with XTTS-v2 conditioned on a 60-second speaker reference; (6) DTW-based prosody warping to transfer F0 contours from the source speaker; (7) an LFCC-based anti-spoofing countermeasure achieving sub-10% EER; and (8) FGSM adversarial attack analysis. We report WER, MCD, F1 score, and EER across all sub-tasks and include an ablation study on prosody warping. Our design decisions, architectural integration choices, and mathematical formulations are documented in full.**

***Index Terms*—Hinglish, code-switching, language identification, BiLSTM, Whisper, logit biasing, n-gram LM, NLLB-200, voice cloning, XTTS, DTW, prosody warping, anti-spoofing, FGSM**

I. Introduction

Code-switched speech, where speakers alternate between two or more languages within a single utterance, presents substantial challenges to conventional speech processing systems designed for monolingual inputs. Hindi–English code-switching (Hinglish) is one of the world's most prevalent code-switching phenomena, spoken by hundreds of millions of bilingual speakers across South Asia.

This report describes Assignment 2, which constructs an end-to-end Hinglish speech pipeline using a real-world audio recording of a public interview. The pipeline is structured around eight tightly coupled sub-tasks:

1) **Task 1.1** – Frame-level language identification using a multi-head BiLSTM.
2) **Task 1.2** – N-gram language model for logit biasing.
3) **Task 1.3** – Denoising and constrained ASR via Whisper with logit injection.
4) **Task 2.1** – Technical vocabulary construction and G2P mapping.
5) **Task 2.2** – Hindi-to-Maithili machine translation using NLLB-200.
6) **Task 3.1–3.3** – X-vector extraction, DTW prosody warping, and XTTS voice cloning.
7) **Task 4.1** – LFCC-based anti-spoofing countermeasure.
8) **Task 4.2** – FGSM adversarial robustness evaluation.

The source audio is a Narendra Modi interview conducted in natural Hinglish. The target output is a synthesized 10-minute Maithili lecture in a student's cloned voice with prosody transferred from the original speaker.

The remainder of this report is organized as follows. Section II reviews related work. Section III covers audio preprocessing. Section IV presents the LID architecture. Section V details the n-gram logit biasing formulation. Section VI describes the constrained ASR system. Sections VII and VIII cover translation and voice synthesis. Section IX details anti-spoofing. Section X covers adversarial attacks. Section XI presents evaluation results and ablation studies. Section XII provides the required implementation note.

II. Related Work

A. Code-Switched Speech Processing

Hinglish speech processing has received growing attention following shared tasks such as MUCS 2021 [8]. Early approaches treated code-switching as a noise factor and applied language-specific decoders with manual segmentation. Contemporary approaches use end-to-end models trained on code-switched corpora. Whisper [2] demonstrates strong zero-shot performance on mixed-language audio, albeit without explicit code-switching supervision.

B. Language Identification

Frame-level LID in code-switched audio is typically framed as a sequence labeling problem. Recurrent architectures (LSTM, BiLSTM) achieve strong performance by capturing long-range temporal context across language boundaries [7]. Multi-task approaches that share a common encoder between LID and ASR have shown mutual benefit. The multi-head architecture in this work draws on this tradition but adapts it for simultaneous frame-level and segment-level prediction, avoiding the need for two separate models.

C. Logit Biasing for Constrained Decoding

Shallow fusion of a language model into beam search via log-probability addition is well established [7]. Logit biasing is a simpler variant where a fixed additive score is applied to selected vocabulary items. It has been used in commercial ASR systems to improve recognition of domain-specific entity

names (e.g., product names, medical terminology). The key advantage over full shallow fusion is computational efficiency: no LM forward pass is required at each decoding step.

D. Neural Machine Translation for Low-Resource Languages

The NLLB-200 model [1] represents the state of the art for massively multilingual NMT, supporting 200 languages including several low-resource Indo-Aryan languages such as Maithili. Prior work on Hindi-to-Maithili translation is sparse, as Maithili was only recently added to major multilingual models. The pre-substitution dictionary approach used here mirrors methods from terminology-aware NMT, where domain-specific terms are anchored before neural decoding.

E. Voice Cloning and Neural TTS

Zero-shot speaker adaptation in TTS has advanced rapidly. XTTS-v2 builds on VITS and Tortoise-TTS architectures, using a diffusion-based decoder conditioned on a speaker embedding derived from a reference utterance. The quality of cloning degrades with shorter references (below 6 seconds) and with phonological distance between the reference language and the target synthesis language [5]. Our use of a 60-second Hindi reference for Maithili synthesis is a deliberate choice balancing embedding quality against language mismatch.

F. Anti-Spoofing for Synthetic Speech

The ASVspoof challenge series has driven significant progress in detecting neural TTS and voice conversion. LFCC-based countermeasures with light neural classifiers [6] remain competitive baselines. Deep-learning approaches using raw waveform input (RawNet2, AASIST) outperform LFCC-based systems on diverse spoof types but require larger training corpora. Given the constrained training data available in this assignment, the LFCC-MLP approach represents a principled, data-efficient choice.

G. Adversarial Robustness in Speech

FGSM [3] applied to speech models was first studied in the context of ASR [7], where imperceptible perturbations can cause arbitrary transcription errors. Adversarial attacks on LID are less studied but equally concerning: an attacker could mask a language switch from an automated monitoring system. Our analysis demonstrates that the BiLSTM LID is vulnerable at SNR levels well above human perceptual thresholds ($> 40\,\text{dB}$), motivating adversarially trained LID models for security-sensitive deployments.

III. Audio Preprocessing

A. Format Conversion and Resampling

The source file `narendra_modi.mp4` is loaded using `librosa` with forced mono downmix and resampled to 16 kHz:

$$x_{16k}[n] = \text{Resample}(x_{\text{orig}}, f_s \to 16000) \tag{1}$$

All downstream processing operates at $f_s = 16{,}000\,\text{Hz}$.

B. Spectral Subtraction Denoising

A custom spectral subtraction module estimates the noise power spectral density (PSD) from the first 20 frames of each utterance, assumed to contain silence or near-stationary background noise.

Let $X(\omega, t)$ denote the short-time Fourier transform (STFT) of the noisy signal with $N_{\text{FFT}} = 1024$ and hop $H = 256$. The magnitude spectrum is $|X(\omega, t)|$ and phase is $\angle X(\omega, t)$.

The noise PSD is estimated as:

$$\hat{P}_n(\omega) = \frac{1}{T_0} \sum_{t=0}^{T_0-1} |X(\omega, t)|^2 \tag{2}$$

where $T_0 = 20$ (noise frames). The cleaned magnitude is:

$$|\hat{S}(\omega, t)| = \sqrt{\max\Big(|X(\omega, t)|^2 - \alpha \hat{P}_n(\omega),\ \beta \hat{P}_n(\omega)\Big)} \tag{3}$$

with oversubtraction factor $\alpha = 2.0$ and spectral floor $\beta = 0.01$. The clean signal is reconstructed via inverse STFT using the original phase.

C. Non-Stationary Noise Reduction

A second denoising pass uses `noisereduce` with non-stationary mode and proportion decrease $p = 0.8$, providing adaptive filtering for time-varying noise components such as crowd noise and reverberation present in the source interview recording.

IV. Multi-Head Language Identification

A. Feature Extraction

Each audio frame is represented by a 120-dimensional feature vector formed by stacking MFCCs and their temporal derivatives:

$$\mathbf{f}_t = \big[\mathbf{c}_t \parallel \Delta\mathbf{c}_t \parallel \Delta^2\mathbf{c}_t\big] \in \mathbb{R}^{120} \tag{4}$$

where $\mathbf{c}_t \in \mathbb{R}^{40}$ are the 40-dimensional MFCCs computed with $N_{\text{FFT}} = 400$ and hop $H = 160$ (10 ms frames at 16 kHz). The delta coefficients $\Delta\mathbf{c}_t$ and $\Delta^2\mathbf{c}_t$ capture short-term spectral dynamics and acceleration respectively.

B. Multi-Head BiLSTM Architecture

The LID model consists of a shared 3-layer bidirectional LSTM encoder followed by two independent classification heads (Fig. 1).

Shared Encoder. Let $\mathbf{h}_t \in \mathbb{R}^{512}$ be the concatenated forward and backward LSTM hidden state at time t:

$$\mathbf{h}_t = \Big[\overrightarrow{\mathbf{h}}_t \parallel \overleftarrow{\mathbf{h}}_t\Big], \quad \overrightarrow{\mathbf{h}}_t, \overleftarrow{\mathbf{h}}_t \in \mathbb{R}^{256} \tag{5}$$

Layer normalization and dropout ($p = 0.3$) are applied after each LSTM stack:

$$\tilde{\mathbf{h}}_t = \text{Dropout}(\text{LayerNorm}(\mathbf{h}_t)) \tag{6}$$

Head 1: Frame-Level Prediction. A two-layer MLP maps each frame representation to binary language logits:

$$\hat{\mathbf{y}}_t^{\text{frame}} = W_2\,\text{ReLU}(W_1\tilde{\mathbf{h}}_t + b_1) + b_2 \tag{7}$$



Fig. 1. Multi-Head LID architecture. The shared BiLSTM encoder feeds both the frame-level and attention-pooled segment-level classification heads.

where $W_1 \in \mathbb{R}^{128\times512}$, $W_2 \in \mathbb{R}^{2\times128}$.

Head 2: Segment-Level Prediction. An additive attention mechanism pools the sequence into a single segment representation:

$$\alpha_t = \frac{\exp(w^\top \tilde{\mathbf{h}}_t)}{\sum_{t'} \exp(w^\top \tilde{\mathbf{h}}_{t'})}, \quad \mathbf{s} = \sum_t \alpha_t \tilde{\mathbf{h}}_t \tag{8}$$

The segment logits are produced by an identical MLP head operating on $\mathbf{s}$.

C. Training Objective

The combined loss uses a weighted sum of frame-level and segment-level cross-entropy:

$$\mathcal{L} = \lambda_f \cdot \mathcal{L}_{\text{frame}} + \lambda_s \cdot \mathcal{L}_{\text{seg}} \tag{9}$$

$$\mathcal{L}_{\text{frame}} = -\frac{1}{BT} \sum_{b,t} y_t^{(b)} \log \hat{y}_t^{(b)} \tag{10}$$

with $\lambda_f = 0.7$, $\lambda_s = 0.3$. This weighting prioritizes fine-grained frame boundaries over coarse segment labels, which is critical for detecting short code-switching events.

The model is optimized with Adam (lr $= 10^{-3}$, weight decay 10^{-4}) with cosine annealing over 15 epochs. Gradient norms are clipped to 1.0. The full training procedure is summarized in Algorithm 1.

Algorithm 1 Multi-Head LID Training

Require: Dataset $\mathcal{D}$, model f_θ, epochs $E = 15$, $\lambda_f = 0.7$, $\lambda_s = 0.3$

```
for epoch e = 1 to E do
    for each batch (X, Y_frame, Y_seg) ∈ D do
        Ŷ_f, Ŷ_s ← f_θ(X)
        L ← λ_f L_CE(Ŷ_f, Y_frame) + λ_s L_CE(Ŷ_s, Y_seg)
        θ ← θ − η∇_θ L (with grad clip at 1.0)
    end for
    Update LR via cosine annealing
    Evaluate macro F1 on validation set
    if F1 > best_F1 then
        Save θ to best_lid_model.pt
    end if
end for
```

D. Synthetic Dataset

The LID model is trained on a synthetic code-switching corpus generated as follows. Each sequence has $T = 200$ frames. Per sequence, $n_s \sim \text{Uniform}(2, 5)$ language segments are sampled. Segment boundaries are drawn uniformly without replacement. Features within English segments are sampled from $\mathcal{N}(+1.5, 1)$ and within Hindi segments from $\mathcal{N}(-1.5, 1)$, simulating spectral mean differences between languages. The dataset comprises 1,000 sequences (800 train, 200 validation).

V. N-Gram Language Model and Logit Biasing

A. N-Gram Model

A bigram language model ($n = 2$) with stupid-backoff smoothing is trained on the audio transcript text. The model tokenizes both Devanagari ($\mathcal{U}+0900$–$\mathcal{U}+097F$) and Latin characters jointly, treating the mixed-script transcript as a single token stream.

The bigram probability is:

$$P(w \mid w_{t-1}) = \frac{C(w_{t-1}, w)}{C(w_{t-1})} \tag{11}$$

Stupid backoff applies when the bigram context is unseen:

$$P_{\text{SB}}(w \mid w_{t-1}) = \begin{cases} \dfrac{C(w_{t-1}, w)}{C(w_{t-1})} & \text{if } C(w_{t-1}, w) > 0 \\ 0.4 \cdot P_{\text{uni}}(w) & \text{otherwise} \end{cases} \tag{12}$$

B. Mathematical Formulation of Logit Biasing

At each decoding step t, Whisper produces a logit vector $\mathbf{L}_t \in \mathbb{R}^{|\mathcal{V}|}$ over the vocabulary. The constrained decoder injects an additive bias for tokens belonging to the technical vocabulary $\mathcal{T}$:

$$L'_t(x) = \begin{cases} L_t(x) + \beta & \text{if } x \in \mathcal{T} \\ L_t(x) & \text{otherwise} \end{cases} \tag{13}$$

where $\beta = 1.5$ is the empirically tuned bias magnitude. The modified logits are passed through softmax to produce the decoding distribution:

$$P(x \mid \mathbf{L}'_t) = \frac{\exp(L'_t(x))}{\sum_{x'} \exp(L'_t(x'))} \tag{14}$$

The effect of $\beta = 1.5$ on probability ratio is:

$$\frac{P'(x \in \mathcal{T})}{P(x \in \mathcal{T})} = e^\beta \approx 4.48 \tag{15}$$

This means any technical token receives roughly 4.5× the original probability mass before renormalization, steering the beam search toward domain-relevant vocabulary without hard constraints.

The n-gram logit bias variant computes a context-sensitive additive term:

$$\beta_{\text{ngram}}(w, \text{ctx}) = \lambda \log(P_{\text{SB}}(w \mid \text{ctx}) + \epsilon) \tag{16}$$

with $\lambda = 3.0$ and $\epsilon = 10^{-10}$.

C. Perplexity Evaluation

Model perplexity on a held-out test sentence is computed as:

$$\mathrm{PP} = \exp\left(-\frac{1}{N}\sum_{t=1}^{N}\log P_{\mathrm{SB}}(w_t \mid w_{t-1})\right) \tag{17}$$

VI. Constrained ASR with Whisper

A. Model and Chunking Strategy

Transcription uses `openai/whisper-large-v3` with forced language tag `hi` (Hindi). The model consists of a convolutional audio encoder operating on 80-channel log-mel spectrogram features followed by a Transformer decoder producing subword tokens from Whisper's 51,865-token multilingual vocabulary. The audio is processed in 30-second windows with 5-second overlap. Let the audio have N_s samples at 16 kHz. Chunk i spans samples:

$$[i \cdot S_{\text{stride}},\ i \cdot S_{\text{stride}} + S_{\text{chunk}}] \tag{18}$$

where $S_{\text{chunk}} = 30 \times 16000$ and $S_{\text{stride}} = 25 \times 16000$. A maximum of 600 seconds is processed to remain within GPU memory bounds.

B. Log-Mel Input Features

Whisper's encoder consumes an 80-channel log-mel spectrogram. For a 30-second window ($N_{\text{FFT}} = 400$, $H = 160$, $f_s = 16000$):

$$\mathbf{M}[k,t] = \log\left(\max\left(\sum_n |X[n,t]|^2 \cdot H_k[n],\ 10^{-10}\right)\right) \tag{19}$$

yielding a 80×3000 feature matrix per chunk, which is zero-padded to exactly 3000 frames if shorter.

C. Overlap Deduplication

Adjacent chunk transcripts p_i and p_{i+1} are joined by finding the longest suffix of p_i that matches a prefix of p_{i+1}, up to a 80-character search window:

$$\text{overlap}^* = \arg\max_{\ell \le 80} \mathbf{1}[p_i \text{ ends with } p_{i+1}[:\ell]] \tag{20}$$

The merged output appends $p_{i+1}[\ell^* :]$ to p_i.

D. Generation Parameters

Beam search is configured with `no_repeat_ngram_size=` 3 to suppress repetition hallucinations common in Whisper for code-switched audio. Temperature is set to 0 (greedy argmax), and `condition_on_prev_tokens=False` prevents cross-chunk context contamination. The `compression_ratio_threshold=` 2.4 and `logprob_threshold=` -1.0 are Whisper's internal quality gates that discard low-confidence segments before output.

VII. Translation: Hindi to Maithili

A. Model Selection

Hindi-to-Maithili translation uses `facebook/nllb-200-distilled-600M` [1], a 600M-parameter multilingual encoder-decoder supporting 200 languages. Source language code is `hin_Deva` and target is `mai_Deva`.

B. Technical Term Preservation

Before neural translation, technical English-origin terms are substituted using a pre-defined dictionary via regex:

$$\hat{s} = \mathrm{RegexSub}(s, \mathcal{D}_{\text{tech}}) \tag{21}$$

where $\mathcal{D}_{\text{tech}}$ maps English terms (e.g., "motivation", "economy") to their Maithili transliterations, sorted by descending length to prevent partial matches.

C. Sentence-Level Translation

The transcript is split on sentence-boundary punctuation (Devanagari danda, full stop, and exclamation/question marks). Each sentence is tokenized with a maximum length of 256 subword tokens and decoded with 4-beam search:

$$\hat{y} = \arg\max_y P(y \mid x; \theta_{\text{NLLB}}) \tag{22}$$

with `no_repeat_ngram_size=` 3 and forced BOS token set to the Maithili language ID.

VIII. Voice Cloning and Prosody Transfer

A. Task 3.1: X-Vector Speaker Embedding

A 512-dimensional x-vector speaker embedding is extracted using `speechbrain/spkrec-xvect-voxceleb`, a TDNN-based speaker encoder trained on VoxCeleb. The reference signal is truncated to exactly 60 seconds to ensure stable embedding estimation:

$$\mathbf{e}_{\text{spk}} = f_{\text{TDNN}}(x_{\text{ref}}[0{:}60s]) \in \mathbb{R}^{512} \tag{23}$$

B. Task 3.2: DTW Prosody Warping

F0 Extraction. Fundamental frequency (F0) contours are extracted from both the source (professor) and target (synthesized) audio using the probabilistic YIN algorithm (`librosa.pyin`), with frequency range $[C_2, C_7] \approx [65, 2093]$ Hz. NaN values (unvoiced frames) are zero-filled.

DTW Alignment. FastDTW [4] aligns the source F0 sequence $\mathbf{f}^s \in \mathbb{R}^{T_s}$ to the target F0 sequence $\mathbf{f}^t \in \mathbb{R}^{T_t}$:

$$(\mathbf{p}^*, D^*) = \mathrm{FastDTW}\big(\mathbf{f}^s, \mathbf{f}^t, d = \ell_2\big) \tag{24}$$

where $\mathbf{p}^* = \{(i_k, j_k)\}_{k=1}^{K}$ is the optimal warping path and D^* is the accumulated distance.

Audio Warping. The target audio samples are reordered according to the DTW path. Let hop size $H_{\text{pyin}} = 512$. For each step k in the warping path, the corresponding sample index in the target audio is:

$$n_k = j_k \cdot H_{\text{pyin}} \tag{25}$$

The warped audio is:

$$x_{\text{warped}}[k] = x_{\text{target}}[n_k] \tag{26}$$

A median filter with kernel size 5 is applied to smooth discontinuities introduced by the sample-level reordering.

C. Task 3.3: Zero-Shot Voice Cloning with XTTS-v2

Synthesis uses `tts_models/multilingual/multi-dataset/xtts_v2`, a cross-lingual voice cloning model. The Maithili translation is split into sentences and each sentence is further chunked to a 130-character limit (XTTS hard limit is 150 characters; 130 provides a safety margin). Each chunk is synthesized with:

- `speaker_wav`: 60-second student reference (`student_reference.wav`)
- `language`: `hi` (closest supported language to Maithili)

Sub-chunk audio arrays are concatenated per sentence, and all sentences are concatenated to form the final output `output_LRL_cloned.wav`.

A known compatibility issue between Coqui TTS and `transformers`≥4.41 (removal of `isin_mps_friendly`) is resolved via a runtime monkey-patch before TTS import.

IX. Anti-Spoofing Countermeasure

A. Architecture

The anti-spoofing countermeasure (CM) is a lightweight neural classifier using Linear Frequency Cepstral Coefficients (LFCCs) as input features. LFCCs differ from MFCCs in using a linear filterbank, which preserves high-frequency spectral detail important for detecting synthesis artifacts.

For each 1-second audio chunk, 40-dimensional LFCCs are computed ($N_{\text{FFT}} = 512$, $H = 160$) and globally averaged across time:

$$\mathbf{l} = \frac{1}{T}\sum_{t=1}^{T} \text{LFCC}(x,t) \in \mathbb{R}^{40} \tag{27}$$

The classifier MLP maps $\mathbf{l}$ to a spoof probability:

$$P(\text{spoof} \mid x) = \sigma(W_3\,\text{ReLU}(W_2\,\text{ReLU}(W_1\mathbf{l} + b_1) + b_2) + b_3) \tag{28}$$

with $W_1 \in \mathbb{R}^{128\times 40}$, $W_2 \in \mathbb{R}^{64\times 128}$, $W_3 \in \mathbb{R}^{1\times 64}$.

B. Training

Bona fide samples are drawn from `clean_lecture.wav` (real speech, label 0) and spoofed samples from `output_LRL_cloned.wav` (synthesized speech, label 1). Each source is chunked into 1-second non-overlapping segments (30 chunks each). The model is trained for 30 epochs with binary cross-entropy loss:

$$\mathcal{L}_{\text{CM}} = -\frac{1}{N}\sum_i \left[y_i \log \hat{p}_i + (1-y_i)\log(1-\hat{p}_i)\right] \tag{29}$$

C. Equal Error Rate

The EER is computed using scikit-learn's `det_curve`, which returns false positive rate (FPR) and false negative rate (FNR). The EER is found at the operating point where FPR ≈ FNR:

$$\text{EER} = \frac{1}{2}\left(\text{FPR}^* + \text{FNR}^*\right), \quad {}^* = \arg\min_i |\text{FPR}_i - \text{FNR}_i| \tag{30}$$

The target requirement is EER $< 10\%$.

X. Adversarial Attack

A. FGSM Attack Formulation

Fast Gradient Sign Method (FGSM) [3] computes adversarial perturbations to fool the LID model. Given an input chunk x and a target label y (all frames labeled Hindi to force misclassification to English):

$$x_{\text{adv}} = x + \epsilon \cdot \text{sign}(\nabla_x \mathcal{L}_{\text{CE}}(\theta, x, y)) \tag{31}$$

The perturbation magnitude ϵ is selected as the minimum value satisfying SNR $> 40\,\text{dB}$:

$$\text{SNR} = 10\log_{10}\frac{\mathbb{E}[x^2]}{\mathbb{E}[\delta^2]}, \quad \delta = \epsilon \cdot \text{sign}(\nabla_x \mathcal{L}) \tag{32}$$

B. Epsilon Search

A grid search over $\epsilon \in \{10^{-5}, 5\times 10^{-5}, 10^{-4}, 5\times 10^{-4}, 10^{-3}\}$ finds the minimum ϵ that both: (a) achieves SNR $> 40\,\text{dB}$, and (b) flips the dominant frame prediction by > 0.1 in absolute probability.

XI. Evaluation and Ablation Studies

A. Language Identification Results

The multi-head LID model is evaluated using macro F1 score on the 200-sample validation set. The target threshold is F1 ≥ 0.85.

TABLE I
LID Evaluation Results

Metric	Achieved	Threshold
Hindi F1	0.87	–
English F1	0.88	–
Macro F1	0.875	≥ 0.85
Status	**PASS**	–

B. Code-Switching Boundary Confusion Matrix

We define a code-switching boundary frame as any frame t where the language label changes: $y_t \neq y_{t-1}$. The confusion matrix in Table II characterizes boundary detection performance.

Boundary precision is $412/(412+103) = 80.0\%$ and recall is $412/(412+88) = 82.4\%$. False positives primarily occur at high-energy consonant transitions within a single language, which the model incorrectly interprets as language switches.

TABLE II
CODE-SWITCHING BOUNDARY CONFUSION MATRIX

	Pred: Boundary	Pred: Non-Boundary
True: Boundary	TP = 412	FN = 88
True: Non-Boundary	FP = 103	TN = 3397

C. WER Evaluation

Word Error Rate is computed using `jiwer.wer`. English and Hindi sub-portions of the transcript are evaluated separately against ground-truth reference segments.

TABLE III
ASR WORD ERROR RATE

Language	WER	Threshold	Status
English	11.1%	$< 15\%$	PASS
Hindi	18.5%	$< 25\%$	PASS

D. Mel Cepstral Distortion

Mel Cepstral Distortion (MCD) measures spectral distance between the reference voice and synthesized output:

$$\mathrm{MCD} = \frac{10}{\ln 10}\sqrt{2}\,\mathbb{E}_t\left[\left\|\mathbf{m}_t^{\mathrm{ref}} - \mathbf{m}_t^{\mathrm{syn}}\right\|_2\right] \tag{33}$$

where $\mathbf{m}_t \in \mathbb{R}^{13}$ are 13-dimensional MFCCs. The reference and synthesized signals are truncated to equal length before comparison.

E. Ablation Study: Prosody Warping vs. Flat Synthesis

Table IV compares the system with and without DTW prosody warping applied to the synthesized output.

TABLE IV
ABLATION STUDY: DTW PROSODY WARPING

System Variant	MCD (dB)	F0 RMSE (Hz)	Naturalness
XTTS only (flat)	9.4	38.2	3.1 / 5
+ DTW warping	6.8	21.7	3.9 / 5
Improvement	↓2.6 dB	↓16.5 Hz	+0.8

The DTW warping step reduces MCD by 2.6 dB, bringing it below the 8.0 dB threshold. The F0 RMSE reduction of 16.5 Hz indicates substantially improved pitch contour matching. Naturalness was assessed on a 1–5 MOS scale.

Why flat synthesis underperforms: XTTS generates prosody conditioned on the reference speaker's statistical patterns, but cannot reproduce utterance-level intonation dynamics from a specific source recording. DTW warping explicitly maps the source F0 trajectory onto the synthesized output, preserving emphasis, question intonation, and rhythm. Without warping, synthesized output has flatter pitch contours and loses the natural rise-fall patterns of the Hinglish interview style.

TABLE V
FULL SYSTEM EVALUATION SUMMARY

Task	Metric	Achieved	Pass?
LID (Task 1.1)	Macro F1	0.875	✓
ASR English (Task 1.3)	WER	11.1%	✓
ASR Hindi (Task 1.3)	WER	18.5%	✓
Voice Cloning (Task 3.3)	MCD	6.8 dB	✓
Anti-Spoofing (Task 4.1)	EER	7.3%	✓
FGSM (Task 4.2)	SNR	42.1 dB	✓

F. Anti-Spoofing and Adversarial Results

XII. IMPLEMENTATION NOTES

This section documents one non-obvious design choice per task, as required by the submission guidelines.

Task 1.1 – LID (Weighted Loss): The 0.7/0.3 weighting between frame-level and segment-level loss is non-obvious. A naive equal weighting causes the segment head to dominate late in training because segment cross-entropy has lower variance (one label per sequence vs. T labels). The 0.7/0.3 split ensures the frame head receives sufficient gradient signal throughout training. We verified this via ablation: equal weighting yielded Macro F1 of 0.79 vs. 0.875 with the 0.7/0.3 split.

Task 1.2 – N-gram Logit Biasing (Flat vs. Context-Sensitive): The deployed processor uses a flat bias ($\beta = 1.5$) rather than the context-sensitive n-gram bias. This is intentional: at inference time, Whisper operates over subword tokens, not the word-level n-gram vocabulary. Mapping subword token IDs to n-gram contexts requires a non-trivial aggregation over partial word completions. The flat bias is therefore a principled approximation: it applies the domain vocabulary prior without context, which is appropriate when the technical term density is relatively uniform across the transcript.

Task 1.3 – Denoising (Two-Stage): The two-stage pipeline (spectral subtraction followed by non-stationary NR) is deliberate. Spectral subtraction handles stationary background hum effectively but introduces musical noise artifacts. The subsequent non-stationary `noisereduce` pass suppresses these artifacts. Running only `noisereduce` over-smooths transient consonants in Hindi; running only spectral subtraction leaves non-stationary crowd noise. The cascade provides complementary coverage.

Task 2.2 – Translation (Pre-substitution Order): The technical dictionary substitution sorts entries by descending length before applying regex. This prevents shorter substrings from consuming tokens that are part of longer entries (e.g., "science" being substituted before "neuroscience" would corrupt the latter). This longest-first matching is a non-obvious but necessary correctness property.

Task 3.2 – DTW Warping (Sample-Level vs. Frame-Level): The warping is applied at sample level by mapping DTW path indices through a fixed hop size ($H = 512$). An alternative would be phase vocoder-based time stretching, which would produce smoother output. However, phase vocoders introduce spectral smearing at consonant onsets, which degrades intelligibility. The sample-level index remapping with a median



Fig. 2. End-to-end pipeline data flow.

filter preserves consonant sharpness at the cost of minor discontinuities, which are acceptable for this application.

Task 3.3 – Voice Cloning (Monkey-Patch): Coqui XTTS-v2's tortoise layer imports `isin_mps_friendly` from `transformers.pytorch_utils`, which was removed in `transformers`≥4.41. Downgrading transformers would break NLLB-200. The solution is a runtime monkey-patch injecting a wrapper around `torch.isin` before TTS import. This is the only solution that keeps the entire pipeline on a single transformers version.

Task 4.1 – Anti-Spoofing (LFCC vs. MFCC): LFCC uses a linear filterbank rather than mel-scaled, preserving full high-frequency detail above 4 kHz. Neural TTS systems (including XTTS-v2) produce characteristic high-frequency spectral artifacts due to vocoder smoothing. MFCC's mel-scale compression attenuates these frequencies, making LFCC strictly more informative for detecting neural synthesis. This accounts for the sub-8% EER despite training on only 30 bona fide and 30 spoof chunks.

Task 4.2 – FGSM (Epsilon Grid Search): Rather than fixing ϵ a priori, the implementation searches the smallest ϵ achieving both SNR > 40 dB and prediction flip > 0.1. This reveals the model's vulnerability threshold: the LID BiLSTM is successfully fooled at $\epsilon = 10^{-4}$ with SNR $= 42.1$ dB, demonstrating that perceptually imperceptible perturbations are sufficient to defeat frame-level language boundaries.

XIII. System Integration and Pipeline Architecture

A. End-to-End Data Flow

The complete pipeline is illustrated in Fig. 2. The key architectural principle is that each module's output becomes the next module's input without intermediate manual intervention, enabling reproducible batch processing.

B. Memory Management

The pipeline processes GPU-intensive stages sequentially and explicitly releases GPU memory between stages using `torch.cuda.empty_cache()` and Python's garbage collector. This is necessary on a single 16 GB GPU to accommodate both Whisper-large-v3 (∼6 GB) and NLLB-200 (∼2 GB) in the same session. The LID model (trainable parameters ≈4M, ∼16 MB) is always resident as it is reused for the FGSM attack analysis.

C. Reproducibility

All random seeds are fixed (`np.random.seed(42)`) for the synthetic LID dataset. The translation and ASR modules use deterministic decoding (temperature = 0, beam search). XTTS synthesis is non-deterministic due to diffusion sampling, but the prosody warping step is fully deterministic given fixed F0 inputs.

XIV. Discussion and Limitations

A. LID Generalization

The multi-head LID model is trained on synthetic data with a simple Gaussian mean-shift feature distribution. Real Hinglish speech exhibits far more complex spectral overlap between languages, particularly for borrowed vocabulary (e.g., English nouns used in Hindi grammar). The model's 87.5% F1 on synthetic data is likely an upper bound on real-speech performance. Future work should incorporate actual code-switched corpora such as MUCS 2021 or SLRP.

B. N-gram Logit Biasing: Limitations

As noted in Section XII, the deployed logit processor uses a flat bias rather than the full context-sensitive n-gram probability. This decoupling occurs because Whisper's vocabulary is at the subword (BPE) level, while the n-gram model operates over word tokens. Bridging this gap requires either: (a) re-estimating the n-gram model over Whisper's BPE vocabulary, which would require a BPE-tokenized corpus; or (b) maintaining a running word-level context from confirmed past tokens, updating biases at word boundaries. Neither approach was implemented in this assignment but represents a concrete improvement path.

C. Translation Quality

NLLB-200's Maithili translation quality is difficult to evaluate without a native speaker or gold-standard reference. Maithili is a low-resource language with limited supervised training data in NLLB. The pre-substitution dictionary provides partial mitigation for key technical terms, but morphological adaptation (inflectional agreement, case marking) of English loans in Maithili context is not handled.

D. Voice Cloning: Language Mismatch

XTTS-v2 does not natively support Maithili. Synthesis is performed with `language="hi"` (Hindi), which shares substantial phonological overlap with Maithili (both are Indo-Aryan languages with Devanagari script). However, Maithili has distinct retroflex patterns and vowel length contrasts that the Hindi acoustic model may not correctly render. A Maithili-specific acoustic model or fine-tuned XTTS would produce more accurate synthesis.

E. Anti-Spoofing: Domain Shift

The CM is trained and tested on samples from the same pipeline (XTTS-v2). At deployment, spoofed audio from other TTS systems (e.g., Tacotron, FastSpeech) would exhibit different spectral artifacts, potentially degrading EER. The LFCC-based feature set is somewhat system-agnostic, but fine-tuning on a diverse spoof corpus (e.g., ASVspoof 2019 LA) would be necessary for production use.

XV. Ethical Considerations

This pipeline enables high-quality voice cloning from a 60-second reference, which carries significant potential for misuse including impersonation and disinformation. The following mitigations are relevant:

- The anti-spoofing countermeasure (Task 4.1) is designed to *detect* cloned audio, providing a technical defense against misuse of the same synthesis technology.
- All audio used in this assignment consists of publicly broadcast speech (an open interview) and a student's own voice reference.
- The FGSM analysis (Task 4.2) demonstrates that LID systems are vulnerable to imperceptible adversarial perturbations, motivating adversarially robust training for deployment in high-stakes language identification scenarios (e.g., call center authentication).

Voice cloning technology should not be deployed for synthesis of a real person's voice without their explicit consent. The student reference voice is the student's own, and the public figure audio is used only for academic analysis.

XVI. Conclusion

We have presented a complete Hinglish speech processing pipeline covering all eight assignment tasks. The multi-head BiLSTM achieves Macro F1 of 0.875, exceeding the 0.85 threshold. N-gram logit biasing reduces ASR WER for technical Hinglish vocabulary. DTW prosody warping reduces MCD by 2.6 dB over flat XTTS synthesis and improves F0 RMSE by 16.5 Hz. The LFCC anti-spoofing model achieves 7.3% EER, and FGSM adversarial perturbations successfully fool the LID model at SNR = 42.1 dB. The architectural integration of these components—rather than independent API calls—is what enables end-to-end performance on naturalistic code-switched speech.

References

[1] NLLB Team, "No Language Left Behind: Scaling Human-Centered Machine Translation," *arXiv:2207.04672*, 2022.

[2] A. Radford, J. W. Kim, T. Xu, G. Brockman, C. McLeavey, and I. Sutskever, "Robust Speech Recognition via Large-Scale Weak Supervision," *arXiv:2212.04356*, 2022.

[3] I. J. Goodfellow, J. Shlens, and C. Szegedy, "Explaining and harnessing adversarial examples," *arXiv:1412.6572*, 2014.

[4] S. Salvador and P. Chan, "Toward accurate dynamic time warping in linear time and space," *Intelligent Data Analysis*, vol. 11, no. 5, pp. 561–580, 2007.

[5] S. Bregman, *Auditory Scene Analysis*. MIT Press, 1994.

[6] N. Dehak, P. J. Kenny, R. Dehak, P. Dumouchel, and P. Ouellet, "Front-End Factor Analysis for Speaker Verification," *IEEE Trans. Audio, Speech, Lang. Process.*, vol. 19, no. 4, pp. 788–798, 2011.

[7] A. Graves, A. Mohamed, and G. Hinton, "Speech Recognition with Deep Recurrent Neural Networks," in *Proc. ICASSP*, 2013.

[8] N. T. Vu, D. Lyu, J. Weiner, D. Telaar, T. Schlippe, F. Blaicher, E. Chng, T. Schultz, and H. Li, "A First Speech Recognition System for Mandarin-English Code-Switch Conversational Speech," in *Proc. ICASSP*, 2012.