---CHUNK---

SOURCE: MSC.36(63).pdf
short periods, to supply non-emergency circuits.
Distribution systems should be so arranged that the feeders from the main and emergency sources are separated both vertically and horizontally as widely as practicable.
The emergency source of electrical power may be either a generator or an accumulator battery, which should comply with the following:
.1 Where the emergency source of electrical power is a generator, it should be:
.1.1
.1.2
driven by a suitable prime mover with an independent supply of fuel having a flashpoint which meets the requirements of 7.1.2.2;
started automatically upon failure of the electrical supply from the main source of electrical power and should be automatically connected to the emergency switchboard. Those services referred to in 12.7.5 or 12.8.3 should then be transferred to the emergency gener .ating set. The automatic starting system and the characteristic of the prime mover should be such as to permit the emergency generator to carry its full rated load as quickly as is safe and practicable, subject to a maximum of 45 s; and
W/1687n/pp/EWP
RESOLUTION MSC.36(63)
(adopted on 20 May 1994)

---CHUNK---

SOURCE: MSC.36(63).pdf
permit the emergency generator to carry its full rated load as quickly as is safe and practicable, subject to a maximum of 45 s; and
W/1687n/pp/EWP
RESOLUTION MSC.36(63)
(adopted on 20 May 1994)
ADOPTION OF THE INTERNATIONAL CODE OF SAFETY FOR HIGH SPEED CRAFT 12.3.7
12.3.8
12.3.9
12.3.10
1.2.3.11
12.3.12
MSC 62/23/Add.2
ANNEX 18
Page 113
.1.3 provided with a transitional source of emergency electrical power according to 12.7.5 or 12.8.3 .
. 2 Where the emergency source of electrical power is an accumulator battery, it should be capable of:

.2.1 carrying the emergency electrical load without recharging while maintaining the voltage of the battery throughout the discharge period within 12% above or below its nominal voltage;
.2.2 automatically connecting to the emergency switchboard in the event of failure of the main source of electrical power; and
.2.3 immediately supplying at least those services specified in 12.7.5 or 12.8.3.
The emergency switchboard should be installed as near as is practicable to the emergency source of electrical power.
Where the emergency source of electrical power is a generator, the

---CHUNK---

SOURCE: MSC.36(63).pdf
in 12.7.5 or 12.8.3.
The emergency switchboard should be installed as near as is practicable to the emergency source of electrical power.
Where the emergency source of electrical power is a generator, the emergency switchboard should be located in the same space unless the operation of the emergency switchboard would thereby be impaired.
No accumulator battery fitted in accordance with this section should be installed in the same space as the emergency switchboard. An indicator should be mounted in a suitable space at the craft's operating compartment to indicate when the batteries constituting either the emergency source of electrical power or the transitional source of emergency electrical power referred to in 12.3.6.1.3 are being discharged.
The emergency switchboard should be supplied during normal operation from the main switchboard by an interconnector feeder which should be adequately protected at the main switchboard against overload and short circuit and which should be disconnected automatically at the emergency switchboard upon failure of the main source of electrical power. Where the system is arranged for feedback operation, the

---CHUNK---

SOURCE: MSC.36(63).pdf
short circuit and which should be disconnected automatically at the emergency switchboard upon failure of the main source of electrical power. Where the system is arranged for feedback operation, the interconnector feeder should also be protected at the emergency switchboard at least against short circuit. Failure of the emergency switchboard, when being used in other than an emergency, should not put at risk the operation of the craft.
In order to ensure ready availability of the emergency source of electrical power, arrangements should be made, where necessary, to disconnect automatically non-emergency circuits from the emergency switchboard to ensure that power should be available to the emergency circuits.
The emergency generator and its prime mover and any emergency accumulator battery should be so designed and arranged as to ensure that they will function at full rated power when the craft

is upright and when the craft has a list or trimming accordance with 9.1.12 including any damage cases considered in chapter 2, or is in any combination of angles within those limits.
W/1687n/pp/EWP
RESOLUTION MSC.36(63)
(adopted on 20 May 1994)

---CHUNK---

SOURCE: MSC.36(63).pdf
with 9.1.12 including any damage cases considered in chapter 2, or is in any combination of angles within those limits.
W/1687n/pp/EWP
RESOLUTION MSC.36(63)
(adopted on 20 May 1994)
ADOPTION OF THE INTERNATIONAL CODE OF SAFETY
FOR HIGH SPEED CRAFT MSC 62123/Add.2
ANNEX 18
Page 114
12.3.13
12.4
12.4.1
12.4.2
12.4.3
12.5
12.5.1
Where accumulator batteries are installed to supply emergency services, provisions should be made to charge them in situ from a reliable on-board supply. Charging facilities should be designed to permit the supply of services, regardless of whether battery is on charge or not. Means should be provided to minimize the risk of overcharging or overheating the batteries. Means for efficient air ventilation should be provided.
Starting arrangements for emergency generating sets
Emergency generating sets should be capable of being readily started in their cold condition at a temperature of OOC. If this is impracticable, or if lower temperatures are likely to be encountered, provisions should be made for heating arrangements to ensure ready starting of the generating sets.
Each emergency generating set should be equipped with starting

---CHUNK---

SOURCE: MSC.36(63).pdf
is impracticable, or if lower temperatures are likely to be encountered, provisions should be made for heating arrangements to ensure ready starting of the generating sets.
Each emergency generating set should be equipped with starting devices with a stored energy capability of at least three consecutive starts. The source of stored energy should be protected to preclude critical depletion by the automatic starting system, unless a second independent means of starting is provided. A second source of energy should be provided for an additional three starts within 30 min, unless manual starting can be demonstrated to be

effective.
The stored energy should be maintained at all times, as follows:
.1 electrical and hydraulic starting systems should be maintained from the emergency switchboard;
.2 compressed air starting systems may be maintained by the main or auxiliary compressed air receivers through a suitable nonreturn valve or by an emergency air compressor which, if electrically driven, is supplied from the emergency switchboard;
.3 all of these starting, charging and energy storing devices should be located in the emergency generator space. These

---CHUNK---

SOURCE: MSC.36(63).pdf
nonreturn valve or by an emergency air compressor which, if electrically driven, is supplied from the emergency switchboard;
.3 all of these starting, charging and energy storing devices should be located in the emergency generator space. These devices should not be used for any purpose other than the operation of the emergency generating set. This does not preclude the supply to the air receiver of the emergency