incinerator is in operation with burning of garbage in progress or while the furnace temperature is above 220°C.
W/9096D/ljt/EWP
RESOLUTION MEPC.59(33)
adopted on 30 October 1992

---CHUNK---

SOURCE: MEPC.59(33).pdf
incinerator is in operation with burning of garbage in progress or while the furnace temperature is above 220°C.
W/9096D/ljt/EWP
RESOLUTION MEPC.59(33)
adopted on 30 October 1992
REVISED GUIDELINES FOR THE IMPLEMENTATION OF
ANNEX V OF MARPOL 73/78MEPC 33/20/Add.l
ANNEX 2
Page 7
3.11 Incinerators equipped with a feeding sluice or system should ensure that the material charged will move to the combustion chamber. Such system should be designed such that both operator and environment are protected from hazardous exposu~e.
3.12 Interlocks should be installed to prevent ash removal doors from opening while burning is in progress or while the furnace temperature is above 220°C.
3.13 The incinerator should be provided with a safe observation port of the combustion chamber in order to provide visual control of the burning process and waste accumulation in the combustion chamber. Neither heat, flame, nor particles should be able to pass through the observation port. An example of a safe observation port is high-temperature glass with a metal closure.
3.14 Electrical requirements
3.14.1 International Electrotechnical Commission (IEC) Standards,

---CHUNK---

SOURCE: MEPC.59(33).pdf
particles should be able to pass through the observation port. An example of a safe observation port is high-temperature glass with a metal closure.
3.14 Electrical requirements
3.14.1 International Electrotechnical Commission (IEC) Standards,
particularly IEC Publication 92 - Electrical Installations in Ships and Mobile and Fixed Offshore Units, are applicable for this equipment.
3.14.2 Electrical installation requirements should apply to all electrical equipment, including controls, safety devices, cables, and burners and incinerators.
3.14.2.1 A disconnecting means capable of being locked in the open position should be installed at an accessible location at the incinerator so that the incinerator can be disconnected from all sources of potential. This disconnecting means should be an integral part of the incinerator or adjacent to it. (See 5.1)
3.14.2.2 All uninsulated live metal parts should be guarded to avoid accidental contact.
3.14.2.3 The electrical equipment should be so arranged so that failure of this equipment will cause the fuel supply to be shut off.
3.14.2.4 All electrical contacts of every safety device installed in the

---CHUNK---

SOURCE: MEPC.59(33).pdf
accidental contact.
3.14.2.3 The electrical equipment should be so arranged so that failure of this equipment will cause the fuel supply to be shut off.
3.14.2.4 All electrical contacts of every safety device installed in the control circuit should be electrically connected in series. However, special consideration should be given to arrangements when certain devices are wired in parallel.
3.14.2.5 All electrical components and devices should have a voltage rating commensurate with the supply voltage of the control system.
3.14.2.6 All electrical devices and electric equipment exposed to the weather should be according to IEC Publication 92.201, Table V.
3.14.2.7 All electrical and mechanical control devices should be of a type tested and accepted by a nationally recognized testing agency, according to international standards.
3 . 14.2.8 The design of the control circuits should be such that limit and primary safety controls should directly open a circuit that functions to interrupt the supply of fuel to combustion units.
W/9096D/ljt/EWP
RESOLUTION MEPC.59(33)
adopted on 30 October 1992
REVISED GUIDELINES FOR THE IMPLEMENTATION OF

---CHUNK---

SOURCE: MEPC.59(33).pdf
primary safety controls should directly open a circuit that functions to interrupt the supply of fuel to combustion units.
W/9096D/ljt/EWP
RESOLUTION MEPC.59(33)
adopted on 30 October 1992
REVISED GUIDELINES FOR THE IMPLEMENTATION OF
ANNEX V OF MARPOL 73/78MEPC 33/20/Add.1
ANNEX 2
Page 8
3.14.3 Overcurrent protection
3.14.3.1 Conductors for interconnecting wiring that is smaller than the supply conductors should be provided with overcurrent protection based on the size of the smallest interconnecting conductors external to any control box, according to IEC's rules.
3.14.3.2 Overcurrent protection for interconnecting wiring should be located at the point where the smaller conductors connect to the larger conductors. However, overall overcurrent protection is acceptable if it is sized on the basis of the smallest conductors of the interconnecting wiring, or according to IEC's requirements.
3.14.3.3 Overcurrent protection devices should be accessible and their function should be identified.
3.14.4 Motors
3.14.4.1 All electric motors should have enclosures corresponding to the environment where they are located, at least IP 44, according to

---CHUNK---

SOURCE: MEPC.59(33).pdf
function should be identified.
3.14.4 Motors
3.14.4.1 All electric motors should have enclosures corresponding to the environment where they are located, at least IP 44, according to IEC Publication 529.
3.14.4.2 Motors should be provided with a corrosion-resistant nameplate specifying information in accordance with IEC Publication 92-301.
3.14.4.3 Motors should be provided with running protection by means of integral thermal protection, by overcurrent devices, or a combination of both in accordance with manufacturer's instruction that should be in accordance with IEC Publication 92-202.
3.14.4.4. Motors should be rated for continuous duty and should be designed for an ambient temperature of 45°C or higher.
3.14.4.5 All motors should be provided with terminal leads or terminal screws in terminal boxes integral with, or secured to, the motor frames.
3.14.5 Ignition system
3.14.5.1 When automatic electric ignition is provided, it should be accomplished by means of either a high-voltage electric spark, a high-energy electric spark, or a glow coil.
3.14.5.2 Ignition transformers should have an enclosure corresponding to the

---CHUNK---

SOURCE: MEPC.59(33).pdf
accomplished by means of either a high-voltage electric spark, a high-energy electric spark, or a glow coil.
3.14.5.2 Ignition transformers should have an enclosure corresponding to the environment where they are located, at least IP 44 according to IEC Publication 529.
3.14.5.3 Ignition cable should conform to the requirements of IEC Publication 92-503.
3.14.6 Wiring
3.14.6.1 All wiring for incinerators should be rated and selected in accordance with IEC Publication 92-352.
W/9096D/ljt/EWP
RESOLUTION MEPC.59(33)
adopted on 30 October 1992
REVISED GUIDELINES FOR THE IMPLEMENTATION OF
ANNEX V OF MARPOL 73/783.14.7 Bonding and grounding
MEPe 33/20/Add.1
ANNEX 2
Page 9
3.14.7.1 Means should be provided for grounding the major metallic frame or assembly of the incinerators.
3.14.7.2 Noncurrent carrying enclosures, frames and similar parts of all electrical components and devices should be bonded to the main frame or assembly of the incinerator. Electrical components that are bonded by their installation do not require a separate bonding conductor.
3.14.7.3 When an insulated conductor is used to bond electrical components

---CHUNK---

SOURCE: MEPC.59(33).pdf
assembly of the incinerator. Electrical components that are bonded by their installation do not require a separate bonding conductor.
3.14.7.3 When an insulated conductor is used to bond electrical components and devices, it should show a continuous green colour, with or without a yellow stripe.
4 Operating requirements:
4.1 The incinerator system should be designed and constructed for operation with the following conditions:
Maximum Gombustion chamber
flue gas outlet temperature
Minimum combustion chamber
flue gas outlet temperature
Preheat temperature of
combustion chamber
For Batch Loaded Incinerators, there are no preheating requirements. However, the incinerator should be designed that the temperature in the actual combustion space should reach 600 0 e within 5 minutes after start.
Prepurge, before ignition:
Time between restarts:
Postpurge, after shut-off
fuel oil: