

# Switchmode/High Frequency Common Mode Inductors

# **CMT908-V2**

## **Description:**

Highly dependable Triad common mode EMI suppression inductors are used in various types of power supplies to eliminate noise common to all lines. These units also provide effective differential mode filtering. Meeting VDE, IEC, UL and CSA requirements, they minimize AC line transmitted interference often created by high frequency switching power supplies.

#### Construction:

Constructed with UL rated 130°C materials.



Min.	Amps	Max. DC (Ω)	Min.
Inductance*	RMS	Resistance	Leakage
4 mH	5.20	.04	45µH

<sup>\*</sup>inductance per winding.


## **Dimensions:**

А	В	С	D	Е
1.5 Max	.9 Nom	1.45 Max	.6 nom	.8 Max

Note: 1. Pin diameter: 0.036 2. Pin length: 0.092-0.187

3. Units in inches.

### **Schematic:**




**RoHS Compliance:** As of manufacturing date February 2005, all standard products meet the requirements of 2011/65/EU, known as the RoHS initiative.

\*Upon printing, this document is considered "uncontrolled". Please contact Triad Magnetics website for the most current version. For soldering and washing information please see http://www.triadmagnetics.com/faq.html

Web: www.TriadMagnetics.com Phone 951-277-0757 Fax 951-277-2757

460 Harley Knox Blvd. Perris, California 92571





Publish Date: June 8, 2016

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Triad Magnetics: CMT908-V2