



**K - PLUG** adalah Personal silent practicer box, yang dilengkapi fitur audio link untuk merekam direct langsung ke smartphones. Latihan dimanapun kapanpun langsung di rekam ke smartphones anda.

#### Fungsi dan kegunaan :

1. Silent practicer sekaligus alat rekam untuk smartphones.
2. Alat rekam dari mixer langsung ke smartphones.
3. Simple praktis dan ekonomis
4. Support ke semua tipe Smartphones, Tidak harus hp OTG.
5. Bisa untuk live streaming langsung ke media sosial seperti facebook / Instagram / Youtube \* agar suara menjadi lebih jelas.

#### Fitur K - plug versi 1c :

1. Personal Silent practicer dengan dua input pasive , bisa untuk alat musik dan backing track input.
2. Sebagai audio link , latihan sekalian bisa direkam langsung ke smartphone anda , membuat video cover dengan mudah dan cepat , video + audio mix langsung jadi satu.
3. Bisa juga langsung live stream medsos ig fb youtube dll\* . ( beberapa tipe hp mungkin tidak mendukung fitur ini )
3. Bisa digunakan sebagai personal ear monitor amplifier.
4. Fitur loopback record untuk latihan play backingtrack sekaligus merekam video dari 1 hp yang sama. Di android menggunakan aplikasi open camera.
5. Autovoltage 5-9 v yang memudahkan anda mendapat kan suply dc input dari mulai otg powerbank charger hp\* (beberapa tipe yg original)\*. untuk rekomendasi memakai adaptor efek stompbox 9v negativ center,
6. Monitor out sebagai pasif out selain bisa untuk ke amplifier luar juga bisa sebagai link input ke kamera dsrl / mirrorless menggunakan kabel aux 3,5 mm.

#### Cara penggunaan :

1. Buka play store download aplikasi Open Camera
2. Setting di pengaturan Video setting, pilih audio source pada external mic, atau beberapa tipe hp pilih unprosesed ( seperti Xiaomi atau Azus )
3. Sesuaikan level input agar tidak peak atau tidak terlalu kecil, Untuk beberapa tipe hp plug n play ( samsung iphone sony ) bisa cek grafik audio level input pada aplikasi perekam audio bawaan hp.
4. cek hasil rekam melalui galery atau file explorer.
5. Tipe 1c Untuk merekam dari mixer saat live bisa menggunakan pasif mode, kplug tidak perlu di power suply.

#### Tanya Jawab :

1. Q : Apakah K-PLUG bisa dijadikan soundcard recordnya pake laptop ?  
A : Tidak bisa , K-PLUG hanya khusus ke smartphone tidak bisa ke laptop
2. Q : Apakah ada garansi ?  
A : Garansi jika barang diterima dan terjadi masalah saat pemakaian awal bisa di garansi.
3. Q : Hasil rekam noise ?  
A : cek adaptor powersuply, beberapa type charger kurang bersih recommended pakai adaptor efek stombox 9 v negativ center, pilihan lain powerbank ketiga charger tipe ori, atau bila rekam di stage melalui mixer sebaiknya memakai pasif mode ( kplug tidak di suply agar perbedaan grounding dari mixer dan device bisa di minimalkan.
4. Q : Hasil rekam kecil ?  
A : Cek sinyal input yang masuk ke hp perekam, untuk hp yang plug n play ( samsung iphone sony ) bisa cek grafik audio input di aplikasi perekam audio bawaan. Beberapa tipe dan masing masing merk Hp mungkin bisa berbeda sensitivitas hasil rekamnya, jika kurang bisa di mastering volume saat potong atau edit video dengan aplikasi seperti kinemaster. Setting input Kplug 1c setara musik mixing, untuk beberapa alat musik pasif mungkin harus menggunakan efek pedal atau preamp external.
5. Q : Apakah bisa untuk mic record ?  
A : Untuk Kplug tipe 1c fitur 2 pasif mono input tidak memungkinkan menggunakan mic dinamic maupun kondenser secara direct langsung. Untuk menggunakan mic harus melalui mixer atau efek vokal terlebih dahulu sebelum masuk kplug tipe 1c.



**K - PLUG** is a personal tool box can use as silent practicer and has a recording device directly to your smartphones. Easy to use, anytime and anywhere

#### Funtional :

1. Silent practicer and Box recorder for smartphones
2. Tool for recorder from mixer to smartphones
3. Simple, practical, economical. easy to use anytime anywhere
4. Support almost type smartphones, It doesn't must a OTG phone usb required.
5. Able to live on Facebook / Instagram / Youtube streaming so the sound is clearer.

#### Feature of K - plug v.1c :

1. Personal Silent practicer with two pasive input ( line ), can use for headset amplifier. Mix musical instrument and backingtrack input.
2. With audio link , practice at home and directly record to smartphones , make a video cover very simple and fast, audio video mix directly into one file
3. Able to live on Facebook / Instagram / Youtube streaming so the sound is clearer\*.( some cellphone types may not support this feature )
3. Can be used as a personal ear monitor amplifier.
4. Loopback record feature for play mp3 backingtrack exercises while recording video from the same -

- cellphone. on android using the open camera application.
5. Autovoltage 5-9 volt. it's better to use the 9v stompbox effect adapter, polarity is negative center.
  6. Monitor out as passive outs in addition to being able to External amplifier can also be used as an input link to the DSLR camera / mirrorless using a 3.5 mm aux cable.

#### Steps For Use :

1. Open the play store download the Open Camera application.
2. Settings in the Video setting, select the audio source on an external mic, or several types of cellphones, select unprocessed ( like Xiaomi or Azus )
3. Adjust the input level so it doesn't peak or isn't too small, for some types of smartphones can plug n play (Samsung Iphone Sony) can check the input level audio graph on default audio recording application.
4. Check the results of the record through the gallery or file explorer.
5. kplug v.1c For recording from a mixer when live it can be use as passive mode, kplug doesn't need to be supplied power.

#### Question and answer :

1. Q : Is K-PLUG can be used as a soundcard the record using a laptop?  
A : It can't be, K-PLUG is only specific to smartphones
  2. Q : Is there a guaranteed?  
A : Guarantee if the item is received and a problem occurs the initial use can be guaranteed.
- \* The warranty only applies to Indonesia market.
3. Q : The results of the record there is noise?  
A : check the powersuply adapter, several types of chargers less clean recommended use effect adapter stombox 9 v negativ center, other options Powerbank, third options is original charger, or if recorded on the stage through the mixer should use passive mode, (Kplug is not supplied so that the grounding difference from the mixer and the device can be minimized.
  4. Q : Record level, small ?  
A : Check the input signal that goes to the cellphone recorder, For mobile phones that plug n play (Samsung iPhone Sony) can check the audio input graph in the default audio recorder application. Several types and respective brands of cellphones might be different sensitivity of the results of the record, if less, can be mastering volume when cutting or editing videos with applications like kinemaster.

The Kplug 1c input setting is equivalent to music mixing, for some passive musical instruments may have to use external pedal or preamp effect.

5. Q : Is it possible to record microphones?

A : For Kplug v.1c features 2 passive mono inputs, no allows using dynamic mic or condenser mic, directly. To use the microphones must go through a mixer or vocal effect first before connect to the kplug v.1c input.

Produced by AUB tech  
Kudus Indonesia  
ig : @kplug\_official