Project: Worked examples
Title: Voltage drop and I²R loss
Status: DRAFT Author: TempestOS (2026-10-23) Checker: — (—) Issued: —

1. Scope and method

Voltage drop along a circuit in volts and per cent of the nominal voltage, the conductor power loss, and an estimate of the conductor operating temperature, for DC, single-phase and three-phase AC, from resistivity and cross-section (with temperature correction), from tabulated R and X per kilometre, or from a mV/A/m figure; parallel conductors per phase; the drop limit is a user input (the regulatory limits live in BS 7671 Appendix 4 and Regulation 525 and are not embedded).
$R = \rho_T L/(A\,n)$ with $\rho_T = \rho_{20}[1 + \alpha(T_c - 20)]$, or $R = R' L/n$, $X = X' L/n$. DC: $\Delta V = 2 I R$; single-phase: $\Delta V = 2 I (R\cos\varphi + X\sin\varphi)$; three-phase: $\Delta V = \sqrt{3} I (R\cos\varphi + X\sin\varphi)$; mV/A/m: $\Delta V = (mV/A/m)\, I\, L / 1000$ (the figure already carries the 2 or √3 by convention). Loss: $2 I^2 R$ (DC, 1φ), $3 I^2 R$ (3φ). Conductor temperature: $T_{c,est} = T_{amb} + (T_{rated} - T_{amb})(I/I_z)^2$.
Ref: BS 7671 525 — Voltage drop in consumers' installations
Ref: BS 7671 Appendix 4, section 6 — Voltage drop (mV/A/m tables and the temperature-correction method)
Ref: Hughes, Electrical and Electronic Technology Ch. on DC and AC circuits — Resistance, resistivity and temperature coefficient

2. Inputs

SYMBOL	DESCRIPTION	VALUE	UNIT	SOURCE	VALID RANGE
system	System	DC		assumption: Design convention.	any
V_n	Nominal voltage (line-to-line for three-phase)	48	V	assumption: Design convention.	12 … 1000 V
I	Design current	20	A	spec: Load schedule DC-02: 20 A	0.1 … 5000 A
L	Route length (one way)	30	m	drawing: DRG-E-301 rev A	0.1 … 5000 m
cos_phi	Power factor (AC)	0.85		default	0.5 … 1
n_par	Parallel conductors per phase	1		assumption: Design convention.	1 … 6
data	Conductor data from	resistivity and area		assumption: Design convention.	any
rho_20	Resistivity at 20 °C (copper 0.01724, aluminium 0.0282 Ω·mm²/m)	0.01724	ohm*mm^2/m	reference: Reference record: annealed copper (Hughes)	0.01 … 0.05 ohm*mm^2/m
alpha	Temperature coefficient of resistance	0.00393		reference: Reference record: annealed copper (Hughes)	0.003 … 0.0045
A_c	Conductor cross-section	6	mm^2	spec: Cable schedule CS-02: 6 mm² Cu	1 … 1000 mm^2
T_c	Conductor operating temperature for the resistance	70	degC	assumption: Design convention.	20 … 90 degC

SYMBOL	DESCRIPTION	VALUE	UNIT	SOURCE	VALID RANGE
X_km	Reactance per km per conductor	0	ohm/km	assumption: Design convention.	0 … 1 ohm/km
dv_limit	Voltage-drop limit	5		spec: Battery system spec BS-1: 5 % at the load	1 … 10
T_rated	Conductor rated temperature	70	degC	default	60 … 90 degC
T_amb	Ambient temperature	30	degC	default	0 … 60 degC

3. Assumptions

A1. Balanced load; conductor reactance from the stated X′ (zero when using resistivity alone unless X_km is given); the drop is the arithmetic (R cos φ + X sin φ) form. (Standard engineering approximation.)
A2. A mV/A/m figure is used as tabulated, with its own temperature and system convention. (Cable table convention.)
A3. The conductor temperature estimate scales the rated rise with (I/I_z)²; I_z is the user's tabulated value for the installation method and corrections. (BS 7671 Appendix 4 approach, formula only.)
A4. system (System) is taken as DC. (Design convention.)
A5. V_n (Nominal voltage (line-to-line for three-phase)) is taken as 48 V. (Design convention.)
A6. n_par (Parallel conductors per phase) is taken as 1. (Design convention.)
A7. data (Conductor data from) is taken as resistivity and area. (Design convention.)
A8. T_c (Conductor operating temperature for the resistance) is taken as 70 degC. (Design convention.)
A9. X_km (Reactance per km per conductor) is taken as 0 ohm/km. (Design convention.)

4. Working

```
[9] sin_phi = 0
= 0
```
sin φ
```
[15] rho_T = rho_20 * (1 + alpha * (T_c - 20 degC) / (1 K))
= 0.01724 ohm·mm²/m × (1 + 0.00393 × (70 degC - 20 degC) / 1 K)
= 0.020628 ohm·mm²/m
```
Resistivity at the operating temperature
```
[16] R = rho_T * L / (A_c * n_par)
= 0.020628 ohm·mm²/m × 30 m / (6 mm² × 1)
= 0.10314 ohm
```
Conductor resistance (one conductor, parallel paths combined)
```
[17] X = X_km * L / n_par
= 0 ohm/km × 30 m / 1
= 0 ohm
```
Conductor reactance
```
[18] dV = 2 * I * R
= 2 × 20 A × 0.10314 ohm
= 4.1255 V
```
Voltage drop
```
[19] dV_pct = 100 * dV / V_n
= 100 × 4.1255 V / 48 V
= 8.5949
```
Voltage drop, per cent
```
[20] P_loss = 2 * I^2 * R
= 2 × (20 A)^2 × 0.10314 ohm
= 82.511 W
```
Conductor power loss

```
[21] u_dv = dV_pct / dv_limit
= 8.5949 / 5
= 1.719
```
Drop utilisation against the limit

5. Results

SYMBOL	VALUE	DESCRIPTION
R	0.10314 ohm	Resistance
X	0 ohm	Reactance
dV	4.1255 V	Voltage drop
dV_pct	8.5949	Voltage drop (%)
P_loss	82.511 W	Power loss

6. Checks (governing first)

RESULT	CHECK	DEMAND	CAPACITY	UTILISATION	REF
FAIL	Voltage drop ≤ limit	u_dv = 1.719	u_dv ≤ 1	1.72	BS 7671 525

7. Applicability

WARNING — input.cos_phi: cos_phi (Power factor (AC)) was not entered; the template default 0.85 is used.
WARNING — input.T_rated: T_rated (Conductor rated temperature) was not entered; the template default 70 degC is used.
WARNING — input.T_amb: T_amb (Ambient temperature) was not entered; the template default 30 degC is used.

8. Verification

Template elec.voltage-drop@1.0.0 Content hash 3ed2f07610b34189 Engine calc-engine/1.0.0
Known-answer cases passed 3/3 Test run 2026-10-23 12:00 UTC TempestOS 0.26.0