Solar ESS Co. Ltd.
53 Moo 2 Tambon Nanglae, Amphoe Muang
Chiang Rai 57100, Thailand
Tel 063 151 6694, 089 632 5829
www.solaress.org · LINE: solaress1

Fleet Performance Review

15 DeyeCloud plants not covered by earlier reports · 1 – 24 October 2026

15 plants
Reviewed in this report

12 online
Reporting normally today

3 offline
Comms / commissioning

9.4 MWh
Produced 1–24 Oct (13 plants)

2 urgent
Investigate now

4 settings
Fixable remotely

4.0 MWh
Bought from the grid

389 kWh
Exported unpaid

Summary

Most systems are producing well, but **six plants lose solar every day because of inverter settings** – batteries charged from the grid (Home B, Villa C), battery floors or charge limits set too conservatively (Villa A, the Chiang Mai residence, the Songkhla building) and one site exporting over 40% of its output for free (the office). These can be fixed remotely in DeyeCloud at no cost. **The Trang apartment building** changed behaviour today: the battery was charged from the grid overnight and the hybrid's own panels produced only 7 kWh instead of ≈55 – it needs checking first. Three plants are not reporting: the retreat centre (since 16:09 today), Home E (since May 2025) and the warehouse (never connected). The poultry farm and the Songkhla building are good candidates for battery or system-upgrade proposals.

Priority actions


#	Plant	Action	At stake	Priority
1	**The Trang apartment building**	Find why the battery grid-charged and the hybrid PV dropped on 24 Oct; restore normal mode	≈50 kWh/day	**Urgent**
2	**Home B**	Disable grid charging; battery floor 20%; discharge all evening	≈8–10 kWh/day	**Urgent**
3	**Villa A**	Battery floor 50% → 20%; raise charge current; check zero export	up to 16–35 kWh/day	**Fix settings**
4	**Villa C**	Remove grid charging in the 16:00–19:00 TOU slot	≈4–10 kWh/day	**Fix settings**
5	**The office**	Enable zero export (or confirm export permit); offer battery	≈11 kWh/day exported	**Fix settings**
6	**The Chiang Mai residence**	Raise charge current; fix TOU slot that idles the battery 22:00–24:00	≈2–5 kWh/day	**Fix settings**
7	**The Songkhla building**	Let battery discharge from noon; propose 15–20 kWp upgrade	≈2 kWh/day + upgrade	**Opportunity**
8	**Home D**	Set plant time zone to UTC+07:00; log the 20 Oct fix	schedule accuracy	**Watch**
9	**The retreat centre · Home E · the warehouse**	Restore Wi-Fi / logger, reconnect, or remove empty plants	monitoring	**Check comms**


“At stake” figures are estimates from October data. Three other plants are covered in separate monthly reports.

Solar ESS Co. Ltd.
53 Moo 2 Tambon Nanglae, Amphoe Muang
Chiang Rai 57100, Thailand
Tel 063 151 6694, 089 632 5829
www.solaress.org · LINE: solaress1

1. Fleet overview

Plant	kWp	Battery	Prod. kWh/d	Yield*	Use kWh/d	Grid buy kWh/d	Solar share	Status
On-grid building, Chiang Rai	5	–	18.5	3.69	–	–	–	**Healthy**
Retreat centre (8 kWp)	8	314 Ah (≈16 kWh)	2.0	0.25	1.1	0.0	100%	**Check comms**
Holiday villa A, Koh Samui	20	40.9 kWh	16.4	0.82	21.2	5.4	75%	**Fix settings**
Poultry farm, Chiang Rai	20	–	52.9	2.64	65.3	14.5	78%	**Opportunity**
Holiday villa B, Koh Samui	20	45 kWh	55.1	2.75	69.3	14.2	79%	**Healthy**
Residence, Chiang Mai	6.4	not recorded	27.2	4.26	34.3	8.5	75%	**Fix settings**
Home D, Chiang Mai	10	not recorded	26.8	2.68	36.4	11.2	69%	**Watch**
Villa C (5 kWp)	5	not recorded	10.2	2.04	12.6	2.8	78%	**Fix settings**
Garden home, Myanmar	10	not recorded	35.7	3.57	34.2	0.0	100%	**Healthy**
Apartment building, Trang	12	80 kWh (1,500 Ah)	88.6	7.38	120.1	38.6	68%	**Urgent**
Office (5 kWp)	5	none active	25.7	5.14	19.5	5.1	74%	**Fix settings**
Home B (5 kWp)	5	not recorded	8.5	1.69	24.4	16.8	31%	**Urgent**
Commercial building, Songkhla	5	10.4 kWh	24.8	4.96	73.4	49.5	33%	**Opportunity**
Home E (5.5 kWp)	5.5	–	–	–	–	–	–	**Check comms**
Warehouse (5 kWp)	5	–	–	–	–	–	–	**Check comms**





*Yield = kWh per kWp per day. Averages over the days with data (1–24 Oct; the retreat centre from 8 Oct). Bar colours follow the status. Yields above ≈5 kWh/kWp (the Trang apartment, the office, the Songkhla building) mean the capacity registered in DeyeCloud is lower than the real array, or extra AC-coupled PV is counted; low yields at the retreat centre, Villa A and Home B come from curtailment, not weak panels.


Solar ESS Co. Ltd.
53 Moo 2 Tambon Nanglae, Amphoe Muang
Chiang Rai 57100, Thailand
Tel 063 151 6694, 089 632 5829
www.solaress.org · LINE: solaress1

2. Plant by plant (highest priority first)

Apartment building, Trang

Urgent · Investigate

Trang province · 12 kWp · Hybrid + battery + AC-coupled PV · Battery 80 kWh (1,500 Ah) · Online – abnormal behaviour on 24 Oct



Production/day	Yield	Use/day
88.6 kWh	**7.38 kWh/kWp**	**120.1 kWh**
Grid buy/day	Export/day	Solar share
38.6 kWh	**1.9 kWh**	**68%**


Finding. Normally ≈55 kWh/day from the hybrid's panels plus ≈38 kWh/day from AC-coupled PV, battery cycling 40–60 kWh. On 24 Oct the battery charged from the grid overnight (38% → 99%) and stayed full: hybrid PV fell to 7.2 kWh and 9.1 kWh was exported. Grid Charge reads Disabled and no remote change is logged – a local change or BMS force-charge.

Action. Urgent: check work mode, Time-of-Use and the BMS with the owner or on site; ≈50 kWh/day of solar is at stake. Correct the registered capacity (real PV is larger than 12 kWp).

Home B (5 kWp)

Urgent · Grid charging

Thailand · 5 kWp · Hybrid + battery · Battery not recorded · Online



Production/day	Yield	Use/day
8.5 kWh	**1.69 kWh/kWp**	**24.4 kWh**
Grid buy/day	Export/day	Solar share
16.8 kWh	**0.0 kWh**	**31%**


Finding. Only 5–13 kWh/day from 5 kWp (≈1.7 kWh per kWp – the lowest in the fleet). The battery is charged from the grid in the late evening and stays at 100% all night while the house runs on the grid; in the morning it is already full, so the panels are throttled to the ≈1 kW house load. It only discharges briefly at 14:00–17:00.

Action. Disable grid charging, set the battery floor to 20% and let it discharge all evening and night. Expected: production roughly doubles (≈15–20 kWh/day) and grid purchase drops by ≈8–10 kWh/day.

Holiday villa A, Koh Samui

Fix settings · Settings

Surat Thani province · 20 kWp · Hybrid + battery · Battery 40.9 kWh · Online



Production/day	Yield	Use/day
16.4 kWh	**0.82 kWh/kWp**	**21.2 kWh**
Grid buy/day	Export/day	Solar share
5.4 kWh	**1.0 kWh**	**75%**

Finding. The battery stops discharging at 50% SOC, so only about 12–14 kWh of the 40.9 kWh bank is ever used, and on 24 Oct it never got above 78%. In the morning PV was held to 1–3 kW while the battery charged at only ≈2 kW – a low charge-current limit. On occupied days the villa bought 16–35 kWh from the grid. On empty days ≈2 kWh/day still leaks to the grid.


Action. Lower the battery floor to 20%, raise the battery charge current to the battery's rating, and check zero-export. Expected: most of the 16–35 kWh/day grid purchase on occupied days covered by solar.

Solar ESS Co. Ltd.
53 Moo 2 Tambon Nanglae, Amphoe Muang
Chiang Rai 57100, Thailand
Tel 063 151 6694, 089 632 5829
www.solaress.org · LINE: solaress1

Office (5 kWp)

Fix settings · Exporting

Thailand · 5 kWp · Hybrid, battery not in use · Battery none active · Online



Production/day	Yield	Use/day
25.7 kWh	**5.14 kWh/kWp**	**19.5 kWh**
Grid buy/day	Export/day	Solar share
5.1 kWh	**11.2 kWh**	**74%**


Finding. Good production (≈26 kWh/day) but about 11 kWh/day – over 40% – is exported to the grid, up to 26 kWh on days the office is closed. Export is not paid (no sell-back) and may not be permitted on this connection. No battery activity is recorded.

Action. Enable zero export (or confirm the export permit). Offer a battery so the exported energy covers evening and night use.

Residence, Chiang Mai

Fix settings · Settings

Chiang Mai province · 6.4 kWp · Hybrid + battery · Battery not recorded · Online



Production/day	Yield	Use/day
27.2 kWh	**4.26 kWh/kWp**	**34.3 kWh**
Grid buy/day	Export/day	Solar share
8.5 kWh	**0.0 kWh**	**75%**


Finding. Strong yield (≈4.3 kWh per kWp). But PV is capped flat at ≈4.1 kW from 11:00 to 13:00 while the battery is only half full – the battery charges at a fixed ≈3.2 kW, which suggests a low charge-current limit. At 22:00–24:00 the house runs on the grid with the battery idle at ≈55%, a sign of a Time-of-Use slot floor. Large purchases on 3 and 20 Oct (60 and 33 kWh).

Action. Raise the charge current limit, review the Time-of-Use slots so the battery can discharge all evening, and add the battery size to the plant settings.

Villa C (5 kWp)

Fix settings · Grid charging

Thailand · 5 kWp · Hybrid + battery · Battery not recorded · Online



Production/day	Yield	Use/day
10.2 kWh	**2.04 kWh/kWp**	**12.6 kWh**
Grid buy/day	Export/day	Solar share
2.8 kWh	**0.0 kWh**	**78%**

Finding. From 16:00 to 19:00 the inverter charges the battery from the grid (≈3 kW, SOC 63% → 88%), then discharges it at night – buying grid power only to store it, with conversion losses. 16:00–19:00 is also PEA's on-peak window if a TOU meter is used. Villa was mostly empty until 14 Oct.


Action. Disable grid charging in the 16:00–19:00 Time-of-Use slot. Expected: most of the 4–12 kWh/day purchase disappears on sunny days.

Solar ESS Co. Ltd.
53 Moo 2 Tambon Nanglae, Amphoe Muang
Chiang Rai 57100, Thailand
Tel 063 151 6694, 089 632 5829
www.solaress.org · LINE: solaress1

Commercial building, Songkhla

Opportunity · Undersized

Songkhla province · 5 kWp · Hybrid + battery · Battery 10.4 kWh · Online



Production/day	Yield	Use/day
24.8 kWh	**4.96 kWh/kWp**	**73.4 kWh**
Grid buy/day	Export/day	Solar share
49.5 kWh	**0.0 kWh**	**33%**


Finding. The building uses 65–80 kWh/day (≈3 kW around the clock) against a 5 kWp system, so 60–70% is bought from the grid. The battery is full by noon and then held at 100% until 17:00 while the grid supplies the afternoon load – so midday PV is throttled (peaks of 5.7 kW fall to ≈2.8 kW).

Action. Allow the battery to discharge from noon (Time-of-Use slots) so it can absorb midday PV. Propose a larger system – the load supports ≈15–20 kWp with a bigger inverter and battery.

Poultry farm, Chiang Rai

Opportunity · Curtailment

Chiang Rai province · 20 kWp · On-grid, zero export (no battery) · Online



Production/day	Yield	Use/day
52.9 kWh	**2.64 kWh/kWp**	**65.3 kWh**
Grid buy/day	Export/day	Solar share
14.5 kWh	**2.1 kWh**	**78%**


Finding. Zero export holds the 20 kWp array to the farm's load: on 24 Oct output followed the load all day and peaked at 14 kW only when fans/equipment ran. Production swings from 23 to 89 kWh/day with demand. 1–3.5 kWh/day still flows to the grid, and 7–30 kWh/day is bought, mostly at night.

Action. Schedule pumps, feed and cooling equipment between 10:00 and 15:00; tighten the zero-export setting. A battery (≈20–30 kWh) would capture the curtailed midday energy for night use – a good proposal opportunity.

Home D, Chiang Mai

Watch · Improved

Chiang Mai province · 10 kWp · Hybrid + battery · Battery not recorded · Online (plant time zone set to UTC+06:30)



Production/day	Yield	Use/day
26.8 kWh	**2.68 kWh/kWp**	**36.4 kWh**
Grid buy/day	Export/day	Solar share
11.2 kWh	**0.0 kWh**	**69%**

Finding. Zero production on 11 Oct (a fault or outage). 12–19 Oct bought 12–29 kWh/day with poor battery use. Since 20 Oct no grid power at all and the battery cycles properly (full by 10:00, down to ≈25% by 22:00) – something was corrected. The plant time zone is set to UTC+06:30, not Thailand's UTC+07:00.


Action. Set the plant time zone to UTC+07:00 so schedules line up; confirm what changed on 20 Oct and record it; check the cause of the 11 Oct outage.

Solar ESS Co. Ltd.
53 Moo 2 Tambon Nanglae, Amphoe Muang
Chiang Rai 57100, Thailand
Tel 063 151 6694, 089 632 5829
www.solaress.org · LINE: solaress1

Retreat centre (8 kWp)

Check comms · Offline / comms

Thailand · 8 kWp · Hybrid + battery · Battery 314 Ah (≈16 kWh) · OFFLINE since 24 Oct 16:09; no data 1–7 Oct



Production/day	Yield	Use/day
2.0 kWh	**0.25 kWh/kWp**	**1.1 kWh**
Grid buy/day	Export/day	Solar share
0.0 kWh	**0.0 kWh**	**100%**


Finding. Site load is tiny (50–80 W), so the battery is full by 09:00 and the 8 kWp array produces only 1.5–2.5 kWh/day – demand-limited, not a fault. Monitoring stopped at 16:09 today and there is no data for 1–7 October.

Action. Check the site Wi-Fi/router and the data logger. If the center is used more in future, the system has plenty of spare capacity.

Garden home, Myanmar

Healthy

Myanmar (border area) · 10 kWp · Hybrid + battery, no grid use · Battery not recorded · Online (UTC+06:30, correct for Myanmar)



Production/day	Yield	Use/day
35.7 kWh	**3.57 kWh/kWp**	**34.2 kWh**
Grid buy/day	Export/day	Solar share
0.0 kWh	**0.0 kWh**	**100%**


Finding. Fully self-supplied all month: 25–46 kWh/day produced and used, battery cycling 15–20 kWh a night (full by ≈14:00, ≈38% by morning). Only small afternoon curtailment once the battery is full.

Action. No action needed. Shift any flexible daytime loads to 13:00–16:00 to use the last of the afternoon solar.

Holiday villa B, Koh Samui

Healthy

Surat Thani province · 20 kWp · Hybrid + battery · Battery 45 kWh · Online



Production/day	Yield	Use/day
55.1 kWh	**2.75 kWh/kWp**	**69.3 kWh**
Grid buy/day	Export/day	Solar share
14.2 kWh	**0.0 kWh**	**79%**

Finding. Working well: battery full by about 13:00, discharging through the night (99% → ≈60%), no export. Grid purchases of 20–37 kWh happen on days with 85–90 kWh of use or after cloudy days (18–21 Oct).


Action. No urgent action. If high-use days continue, a battery extension or more PV would cut the remaining purchases.

Solar ESS Co. Ltd.
53 Moo 2 Tambon Nanglae, Amphoe Muang
Chiang Rai 57100, Thailand
Tel 063 151 6694, 089 632 5829
www.solaress.org · LINE: solaress1

On-grid building, Chiang Rai

Healthy

Chiang Rai province · 5 kWp · On-grid (no battery) · Online (inverter sleeps at night)



Production/day	Yield	Use/day
18.5 kWh	**3.69 kWh/kWp**	**–**
Grid buy/day	Export/day	Solar share
–	**–**	**–**

Finding. Grid-tied 5 kWp producing about 18.5 kWh/day (3.7 kWh per kWp) – a good yield for October. Only production is metered, so self-use and export are not visible.

Action. No action needed. Consider adding a CT/meter so consumption and export can be monitored.

3. Plants not reporting

Home E (5.5 kWp)

· 5.5 kWp · OFFLINE since 24 May 2025

Finding. No data for 17 months (last update 24 May 2025). Lifetime production recorded: 6.99 MWh.

Action. Contact the owner: reconnect the logger to Wi-Fi, or remove the plant from the account if the system is no longer ours to monitor.

Warehouse (5 kWp)

· 5 kWp · OFFLINE – never reported

Finding. The plant was created but has never sent any data.

Action. Finish commissioning the logger (Wi-Fi setup and device binding), or delete the empty plant.

The retreat centre also stopped reporting at 16:09 today; its October data up to then is included in section 2.

How this review was made

Daily production, consumption, grid purchase, grid export and battery charge/discharge were taken from each plant's DeyeCloud records for 1–24 October 2026 (24 October up to about 23:40). Today's 5-minute power profiles were used to see when batteries charge, how far they discharge and whether PV is being held back. Inverter settings were read directly only where noted (the Trang apartment). Settings-related findings are inferred from the power profiles and should be confirmed in Device Control before changing anything; estimated gains depend on weather and occupancy. Sites outside Solar ESS's own installations may need the owner's agreement before settings are changed.