

EndtermRenwed\Group5\pyserialEmail.py

```
1 import serial
2 import requests
3 import time
4
5 # --- 1. CONFIGURATION: EDIT THESE TWO LINES ---
6
7 # Replace with the URL you got from Pipedream
8 PIPEDREAM_URL = 'https://eocp8ehbhjt16re.m.pipedream.net'
9
10 # Replace with your Arduino's serial port (e.g., 'COM3' or '/dev/tty.usbmodem...')
11 ARDUINO_PORT = 'COM3'
12
13 # -----
14
15 try:
16     print(f"Attempting to connect to Arduino on {ARDUINO_PORT}...")
17     arduino = serial.Serial(port=ARDUINO_PORT, baudrate=9600, timeout=1)
18     print("--- Successfully connected to Arduino ---")
19     print("--- Listening for serial output... ---")
20
21     while True:
22         # Read a line of text from the Arduino
23         line = arduino.readline().decode('utf-8').strip()
24
25         # If the line is not empty, print it
26         if line:
27             print(f"Arduino: {line}")
28
29             # Check if this line is the trigger command
30             if line == "SEND_EMAIL":
31                 print("\n>>> Email trigger detected! Sending request to Pipedream...")
32
33                 try:
34                     requests.get(PIPEDREAM_URL)
35                     print(">>> Success! Pipedream has been triggered.")
36                 except requests.exceptions.RequestException as e:
37                     print(f">>> Error making web request: {e}")
38                 print("---") # Separator
39
40             time.sleep(0.01)
41
42 except serial.SerialException:
43     print(f"\nError: Could not connect to Arduino on port '{ARDUINO_PORT}'.")
44     print("Please check that the port is correct and the IDE's Serial Monitor is closed.")
45
46
```