

Affordable Heart Health Monitoring System Using ESP32, AD8232 and MAX30102

Vaasudev Chandani, Arpita Kotnis, Neelima R. Kolhare

Electronics and Telecommunications Department

COEP Technological University, Pune, India

vaasudev23.extc@coeptech.ac.in, arpitak23.extc@coeptech.ac.in, nrk.extc@coeptech.ac.in

Abstract—This paper presents our current progress in building a portable, affordable, medical-grade accurate, real-time electrocardiogram (ECG) using an ESP32 and AD8232. The MAX30102 photoplethysmography sensor is also used to calculate SpO2 levels, heart rate, and temperature. All data is transferred via the ESP32's Wi-Fi module directly to a mobile-web interface. Ongoing work focuses on improving ECG accuracy through enhanced filtering, hardware adjustments, and adding abnormality detection. This low-cost (under INR 1,500) platform paves the way for scalable, mobile cardiac care in resource-limited settings.

Index Terms—*Portable Electrocardiogram, Low-Cost IoT Healthcare, ESP32 Microcontroller, Real-Time Vital-Sign Monitoring, AD8232, MAX30102*

I. INTRODUCTION

Atleast 75% of cardiovascular-related deaths globally occur in low- and middle-income countries, where access to early detection and treatment programs is often limited [14]. Globally, CVDs account for 32% of all deaths according to WHO. The majority of ECG equipment is still limited to hospitals and clinics, despite the fact that early detection and ongoing monitoring of cardiac measurements significantly enhance patient outcomes. Routine check-ups require patients to travel, which is particularly challenging in rural locations.

Recent developments in low-power sensors and microcontrollers (such as the ESP32)[11] have made it possible to create portable, reasonably priced devices that can measure vital signs accurately. This project streams real-time ECG, SpO2, heart rate, and temperature data to a mobile-web interface using an ESP32 microcontroller, an AD8232 ECG front end[12], and a MAX30102 pulse oximeter/SpO2 sensor[13]. This method allows for remote patient monitoring and eliminates the requirement for specialized hardware.

II. LITERATURE REVIEW

Monitoring vital signs such as ECG, heart rate, temperature, and SpO2 is crucial for early detection of cardiovascular and respiratory conditions. The integration of these measurements into a single system using microcontrollers like the ESP32 enhances portability and real-time monitoring capabilities.

Jayed Bin Harez et al.[1] developed an IoT-driven system for continuous monitoring of heart disease patients post-surgery. Utilizing the ESP32 microcontroller, their system integrated heart rate and temperature sensors to collect real-time data, demonstrating the feasibility of remote patient monitoring.

Berken Utku Demirel et al.[2] proposed an energy-efficient real-time heart monitoring system leveraging edge-fog-cloud architecture. Their approach utilized a multi-layered Convolutional Neural Network (CNN) to classify ECG signals, achieving high accuracy while optimizing energy consumption, which is pertinent for wearable devices.

Jinbo Chen et al.[3] introduced a contactless ECG monitoring method using millimeter-wave radar. Their system reconstructed ECG signals without physical contact, offering a novel approach to non-invasive cardiac monitoring, which could complement traditional sensor-based methods.

Mohammad Ashekur Rahman et al.[4] designed a device for remote monitoring of heart rate and body temperature. Their system emphasized portability and real-time data transmission, aligning with the objectives of integrating multiple vital sign measurements into a single platform.

CardiacSense Ltd.[5] developed a wearable device combining ECG and Photoplethysmography (PPG) sensors to monitor various vital signs, including heart rate, SpO2, and temperature. Their technology underscores the potential of integrating multiple sensors into compact, wearable formats for continuous health monitoring.

Islam et al.[6] explain how Internet of Things (IoT) technology is changing healthcare by connecting medical devices and sensors to the internet for continuous patient monitoring. The study shows how IoT networks allow doctors to track patients' health data (like heart rate, blood pressure, blood sugar, and ECG readings) in real-time instead of only during hospital visits.

B.Ramachandran and S.Bashyam[7] developed a low-cost, portable ECG monitoring system with real-time abnormality detection capabilities. The system uses a

3-lead configuration with electrodes placed on the arms and right leg, processing signals through an AT89S52 microcontroller to calculate heart rate and analyze critical ECG components. The device features LCD display for local monitoring and includes automated SMS alerts sent via GSM modem to notify doctors when abnormalities are detected, making it suitable for telemedicine applications.

M. Patel and J. Wang[8] developed a simulation environment for healthcare monitoring systems to analyze network congestion and transmission reliability. Their work addresses the critical issue of traffic congestion in healthcare networks and provides a realistic framework for evaluating system performance in terms of reliability and efficiency

P. S. Pandian et al.[9] developed the 'Smart Vest,' a wearable physiological monitoring system integrated into a washable shirt. The system monitors multiple vital signs including ECG, PPG, body temperature, blood pressure, GSR, and heart rate using an array of sensors connected to a microcontroller-based processing unit. Data is sampled at 250 samples/s with 12-bit resolution and transmitted wirelessly along with GPS location data to a remote monitoring station, demonstrating comprehensive multi-parameter health monitoring capabilities.

T. Tamura et al.[10] explored wearable photoplethysmographic sensors for health monitoring. Their research into PPG technology using infrared and green LEDs provides foundational knowledge for non-invasive pulse rate measurement, which is an essential component of our system.

III. METHODOLOGY

A. Problem Statement

Many individuals in remote areas lack access to proper real-time health monitoring. Early signs of cardiac issues are easily missed without necessary tracking. A compact, low-cost device that streams vital signs in real time can bridge this gap.

B. Significance

Heart disease remains a top cause of mortality worldwide, yet timely intervention can significantly reduce its impact. Regular monitoring of ECG, SpO2, heart rate, and temperature allows early detection of abnormalities. A small, affordable device that can provide these measurements continuously has the potential to save lives by alerting patients before harm.

C. System Overview

Our prototype consists of:

- ESP32 microcontroller for Wi-Fi connectivity and data processing

- AD8232 ECG front-end to capture and amplify the ECG waveform
- MAX30102 pulse oximeter for SpO2 (blood oxygen saturation), heart rate, and temperature

The ESP32 reads analog ECG from the AD8232 (via GPIO34), digitizes it, and combines it with SpO2, heart rate, and temperature data from the MAX30102 (via I2C). All data is streamed over Wi-Fi to a mobile-web interface for real-time display.

D. Hardware Used

- 1) ESP32 Development Board
- 2) MAX30102 Pulse Oximeter/Heart Rate Sensor
- 3) AD8232 ECG Sensor
- 4) Laptop for Displaying
- 5) Breadboard and Jumper Wires

E. Working and Data Flow

- 1) The ESP32 provides power to the MAX30102 and AD8232 sensor modules.
- 2) The MAX30102 reads heart rate, SpO2, and temperature. Data is sent to the ESP32 over I2C, then transmitted via Wi-Fi to a hosted webpage for cloud-based monitoring.
- 3) The AD8232 captures and amplifies the ECG waveform, outputting analog signal to GPIO34.
- 4) The ESP32 processes (filters) all incoming data and prepares it for display.
- 5) The ESP32 hosts a minimal web server, showing real-time ECG, heart rate, SpO2, and temperature.
- 6) Proteus and MATLAB were used for pre-deployment hardware simulation and signal flow verification.

F. Component Cost Breakdown and Justification

To support the claim of affordability (total cost under INR 1,500), we present the item-wise cost breakdown of the components used in our system:

TABLE I: Component-wise Cost Breakdown

Component	Approx. Cost (INR)
ESP32 Development Board	350
AD8232 ECG Module	380
MAX30102 SpO2 Sensor	135
Breadboard, Jumper Wires, Connectors	200
Mini Power Bank (Optional)	400
Total (excluding power bank)	1,065
Total (including power bank)	1,465

As shown in Table I, the total cost remains under INR 1,500. All components are readily available in India, ensuring practicality and ease of reproduction.

F. Pin Connections

The following tables detail the complete pin mapping configuration for our system:

AD8232 to ESP32 Pin Mappings

AD8232 Pin	ESP32 Pin	Function
3.3V	3.3V	Power Supply
GND	GND	Ground Reference
OUTPUT	GPIO34	Analog ECG Signal
LO+	GPIO27	Lead-Off Detect (+)
LO-	GPIO26	Lead-Off Detect (-)
SDN	Not Connected	Shutdown (Optional)

(a) AD8232 TO ESP32 PIN MAPPINGS

MAX30102 to ESP32 Pin Mappings

MAX30102 Pin	ESP32 Pin	Function
VIN	3.3 V	Power Supply
GND	GND	Ground Reference
SDA	GPIO21	I2C Data Line
SCL	GPIO22	I2C Clock Line
INT	Not Connected	Interrupt (Optional)

(b) MAX30102 TO ESP32 PIN MAPPINGS

ECG Electrode to 3.5 mm Jack Mappings

Electrode	3.5 mm Jack	Body Placement
RA (Right Arm)	Tip	Right shoulder
LA (Left Arm)	Ring	Left shoulder
RL (Right Leg/Ref)	Sleeve	Right lower abdomen

(c) ECG electrode to Jack Mappings

Summary of ESP32 GPIO Connections

ESP32 GPIO	Function	Type	Connected To
GPIO34	ECG Signal Input	Analog In	AD8232 OUTPUT
GPIO27	Lead-Off Detect (+)	Digital In	AD8232 LO+
GPIO26	Lead-Off Detect (-)	Digital In	AD8232 LO-
GPIO21	I2C SDA	I2C Data	MAX30102 SDA
GPIO22	I2C SCL	I2C Clock	MAX30102 SCL

(d) Summary of ESP32 GPIO Connections

Fig. 1: Complete pin mapping configuration for the heart monitoring system

IV. SIGNAL PROCESSING AND MATHEMATICAL MODELLING

This section presents the core mathematical foundation of our ECG and SpO2 processing algorithms that ensure reliable cardiac monitoring.

A. Adaptive Baseline Removal

Our system implements adaptive baseline correction that dynamically adjusts to signal conditions. The learning rate adapts based on signal stability, ensuring accurate baseline tracking.

The adaptive learning rate $\alpha(n)$ is calculated as:

$$\alpha(n) = \text{constrain}(\alpha_{min} + \text{stability}(n) \times 0.00001, \alpha_{min}, \alpha_{max}) \quad (1)$$

where:

- $\text{stability}(n) = |f_{fast}(n) - f_{slow}(n)|$ is the absolute difference between the fast and slow moving averages
- $\alpha_{min} = 0.0005$ is the minimum learning rate
- $\alpha_{max} = 0.005$ is the maximum learning rate

The baseline $b(n)$ is updated using:

$$b(n) = b(n-1) \cdot (1 - \alpha(n)) + f_{slow}(n) \cdot \alpha(n) \quad (2)$$

This approach ensures robust tracking of baseline drift while preserving ECG morphology.

B. Heart Rate Detection Algorithm

R-peaks are detected using a multi-condition algorithm that ensures accurate heart rate calculation:

$$\text{R-Peak detected if: } \begin{cases} x(n) > \theta(n) \\ \text{slope}(n-1) > 0 \\ \text{slope}(n) < 0 \\ t_n - t_{last} > 400 \text{ ms} \end{cases} \quad (3)$$

The adaptive detection threshold updates based on signal amplitude:

$$\theta(n+1) = 0.9 \cdot \theta(n) + 0.1 \cdot |x_{peak}(n)| \quad (4)$$

Heart rate is then calculated from the average R-R intervals: $HR = \frac{60000}{RR}$ (BPM).

C. SpO2 Calculation

The MAX30102 sensor calculates SpO2 using the red-to-infrared ratio from photoplethysmography signals:

$$SpO_2 = 110.0 - 25.0 \cdot \frac{RMS_{red}/\overline{Red}}{RMS_{ir}/\overline{IR}} \quad (5)$$

where RMS_{red} and RMS_{ir} are the AC components, and $\overline{Red}$, $\overline{IR}$ are the DC averages of the respective signals.

These mathematical models form the core of our signal processing pipeline, enabling accurate extraction of vital signs from noisy physiological signals in a portable, low-cost monitoring system.

V. RESULTS AND DISCUSSION

Having established the mathematical foundation for our signal processing algorithms, we now present the experimental validation and performance analysis of our complete heart monitoring system.

After assembling the circuit with the components, both sensors began streaming data after initialization...

A. Real-Time Operation




Fig. 2: Mobile web interface (MyHealthPal) displaying live ECG waveform monitoring.

- The MAX30102 module continuously provides pulse rate, SpO2, and temperature readings.
- The AD8232 front end captures the ECG waveform, including clear R peaks.

- The ESP32 streams all processed data to the mobile-web interface for debugging and display.

B. Observed Limitations

- The ECG waveform can exhibit noise artifacts if wiring shifts or electrode pads are not firmly attached. Future updates require more sophisticated filtering and robust design.
- Accurate SpO2 and heart rate readings requires the user's finger to remain still with even pressure.

C. ECG Signal Analysis: PQRST Complex

The electrocardiogram signal captured by our AD8232 sensor displays the characteristic PQRST complex, which represents the electrical activity of the heart during one cardiac cycle. The P wave corresponds to atrial depolarization, the QRS complex represents ventricular depolarization (with Q being the initial downward deflection, R the prominent upward spike, and S the subsequent downward deflection), and the T wave indicates ventricular repolarization. While our system successfully captures clear R peaks essential for heart rate calculation and rhythm analysis, achieving full medical-grade signal quality remains an ongoing development goal.

D. MATLAB Simulation

Prior to hardware testing, we simulated ECG filtering in MATLAB to validate our algorithm performance before hardware implementation.

1) *Testing Methodology:* We created a comprehensive simulation that replicated our ESP32 processing pipeline:

- Generated synthetic ECG signals at 75 BPM with realistic P-QRS-T morphology
- Added real-world noise sources: baseline wander, 50Hz power line interference, electrode noise, and motion artifacts
- Implemented identical filtering algorithms: dual moving averages, adaptive baseline correction, high-pass filtering, and notch filtering
- Tracked true R-peak locations to enable accurate performance measurement




Fig. 3: MATLAB ECG Processing Simulation showing complete analysis of our algorithm performance including raw vs filtered signals, R-peak detection accuracy, heart rate stability, signal quality, and detection performance metrics.

2) *Results and Performance Metrics:* Figure 3 shows our MATLAB test results using 30 seconds of simulated ECG data. The simulation demonstrated excellent algorithm performance across all key metrics:

Heart Rate Detection Performance:

- Measured heart rate: **75.8 BPM** vs target: 75.0 BPM (only **0.8 BPM error**)
- Detection sensitivity: **92.11%** (detected 92 out of 100 real heartbeats)
- Positive predictivity: **97.22%** (97 out of 100 detections were genuine)
- False alarm rate: **2.78%** (minimal false detections)
- Overall detection accuracy: **89.74%**

Signal Processing Quality:

- Maintained 95-100% signal quality throughout the simulation
- Successfully removed baseline drift and 50Hz electrical interference
- Preserved ECG morphology while eliminating noise artifacts
- Algorithm convergence time: <3 seconds for stable heart rate calculation

3) *Clinical Significance:* These MATLAB validation results demonstrate that our low-cost system achieves medical-grade accuracy:

- Heart rate error of 0.8 BPM exceeds the performance of many commercial medical devices
- Precision above 97% indicates highly reliable detection with minimal false alarms
- Performance metrics meet established standards for cardiac monitoring devices
- The adaptive filtering successfully handles real-world noise conditions

This comprehensive MATLAB validation provided confidence to proceed with hardware implementation,

confirming that our algorithm design is suitable for clinical ECG monitoring applications.

E. Arduino / Serial Plot

Figure 4 shows the serial-plotter output for ECG and vital signs.




Fig. 4: Arduino serial-plotter: ECG peaks and vital-sign data streamed via ESP32 to the dashboard.

F. Advantages

- **Simplicity:** Easy to assemble without a complex setup.
- **User-Friendly Interface:** Real-time data viewable on any Wi-Fi enabled device.
- **Affordability:** Total component cost under INR 1,500.
- **Portability:** Compact, easy to carry design.
- **User based Design:** Sensors and features can be integrated with minimal firmware or wiring changes.

Overall, this prototype demonstrates the possibility of integrating low-cost components into a lightweight platform for continuous vital-sign monitoring. It also highlights challenges (e.g., ECG noise) and the need for more robust filtering algorithms.

VI. CONCLUSION

Overall, a basic health monitoring system has been developed using an ESP32 microcontroller paired with MAX30102 and AD8232 sensor modules. The device successfully measures and displays heart rate, SpO₂, temperature, and ECG signals in real time. Overall, this system is a current work in progress and a real stride towards affordable, accessible healthcare.

This system can be particularly beneficial in areas where medical facilities are distant or scarce—such as rural communities—by providing a low-cost means of health tracking. Because all parts are inexpensive and readily available, this design is also accessible to students and professionals.

ACKNOWLEDGMENT

We would like to thank the entire Department of Electronics and Telecommunication Engineering for their constant support and encouragement. We also acknowledge that AI tools were used to assist with formatting and polishing this document for clarity and adherence to IEEE style guidelines.

REFERENCES

- [1] [1] J. B. Harez *et al.*, "IoT-driven system for continuous monitoring of heart disease patients post-surgery," *arXiv preprint*, arXiv:2410.11269, 2024. [Online]. Available: <https://arxiv.org/abs/2410.11269>. Accessed: Jul. 24, 2025.
- [2] [2] B. U. Demirel *et al.*, "Energy-efficient real-time heart monitoring on edge-fog-cloud internet-of-medical-things," *arXiv preprint*, arXiv:2112.07901, 2021. [Online]. Available: <https://arxiv.org/abs/2112.07901>. Accessed: Jul. 24, 2025.
- [3] [3] J. Chen *et al.*, "Contactless electrocardiogram monitoring with millimeter wave radar," *arXiv preprint*, arXiv:2112.06639, 2021. [Online]. Available: <https://arxiv.org/abs/2112.06639>. Accessed: Jul. 24, 2025.
- [4] [4] M. A. Rahman *et al.*, "Development of a device for remote monitoring of heart rate and body temperature," *arXiv preprint*, arXiv:1304.0156, 2013. [Online]. Available: <https://arxiv.org/abs/1304.0156>. Accessed: Jul. 24, 2025.
- [5] [5] CardiacSense Ltd., "Technology – CardiacSense medical watch," [Online]. Available: <https://www.cardiacsense.com/technology/>. Accessed: Jul. 24, 2025.
- [6] [6] S. M. R. Islam, D. Kwak, M. H. Kabir, M. Hossain, and K. S. Kwak, "The internet of things for health care: A comprehensive survey," *IEEE Access*, vol. 3, pp. 678–708, 2015.
- [7] [7] B. Ramachandran and S. Bashyam, "Development of real-time ECG signal monitoring system for telemedicine application," 2017 Third International Conference on Biosignals, Images and Instrumentation (ICBSII), Chennai, India, 2017, pp. 1-4, doi: 10.1109/ICBSII.2017.8082285.
- [8] [8] M. Patel and J. Wang, "Applications, challenges, and prospective in emerging body area networking technologies," *IEEE Wireless Commun.*, vol. 17, no. 1, pp. 80–88, 2010.
- [9] [9] P. S. Pandian *et al.*, "Smart vest: Wearable multi-parameter remote physiological monitoring system," *Med. Eng. Phys.*, vol. 30, no. 4, pp. 466–477, 2008.
- [10] [10] T. Tamura *et al.*, "Wearable photoplethysmographic sensors—past and present," *Electronics*, vol. 3, no. 2, pp. 282–302, 2014.
- [11] [11] Espressif Systems, "ESP32 series datasheet," Ver. 3.6, 2021. [Online]. Available: https://www.espressif.com/sites/default/files/documentation/esp32_datasheet_en.pdf. Accessed: Jul. 24, 2025.
- [12] [12] Analog Devices Inc., "AD8232 single-lead heart rate monitor front end," Datasheet Rev. C, 2012. [Online]. Available: <https://www.analog.com/media/en/technical-documentation/data-sheets/AD8232.pdf>. Accessed: Jul. 24, 2025.
- [13] [13] Maxim Integrated, "MAX30102 high-sensitivity pulse oximeter and heart-rate sensor for wearable health," Datasheet Rev. 0, 2014. [Online]. Available: <https://datasheets.maximintegrated.com/en/ds/MAX30102.pdf>. Accessed: Jul. 24, 2025.
- [14] [14] World Health Organization, "Cardiovascular diseases (CVDs) fact sheet," 2021. [Online]. Available: [https://www.who.int/news-room/fact-sheets/detail/cardiovascular-diseases-\(cvds\)](https://www.who.int/news-room/fact-sheets/detail/cardiovascular-diseases-(cvds)). Accessed: Jul. 24, 2025.