


YACC1 memory card v2.0 - standoff option A - 1:1, component side up

Adapter centred (y 36.9-96.9), CF column beside J2, ROM at the top edge

Grid 10 mm, numbers = mm from the BUS-CONNECTOR edge (x, across) and from the JP1 end (y, down) - the same grid as the first fit print (its "JP2 end" = this JP1 end). Shaded = parts, dots = pads, blue = the adapter 15 mm above the card. Lay the adapter on the blue outline, component side up, header toward the bus edge: its two holes must sit on the blue crosses, its header over the blue pin grid, pin 1 at the "PIN 1 END" mark.



Where things land (print grid, mm)

x from the bus edge, y from the JP1 end
H1 (pin-1 end): x 80.7 y 82.8
H2 (power-pad end): x 80.7 y 30.8
holes 52.0 apart, 3.2 mm drill, 7 mm copper keep-out
adapter x 65.4-109.4, y 26.8-86.8
header edge x 65.4, CF slot edge x 109.4
J2 pin 1: x 61.0 y 81.0 (square pad)
J2 pins y 32.7-81.0, odd row x 61.0, even x 58.4
ROM IC13 keep-clear x 154.3-175.9, y 34.8-89.0
(on the board; past an edge it is free air)

Standoffs

M3 hex 15 mm female-female (5.5 AF),
M3 x 6 screws + washers both sides
adapter underside 15 mm above the card


Straight ribbon, pin 1 to pin 1

J2 pin 1 and the adapter's pin 1 at the
SAME end (y max): stripe on that end at
both plugs; the ribbon arches up from J2
and down into the adapter's header.

Trial autoroute (Freerouting, unpolished)

unrouted 0, vias 94, track 13540 mm
DRC copper violations: none

- ① J2 = the IDE header ON THIS BOARD (solid red, pin 1 = square pad); with its ribbon plug it stands ~18 mm; plug envelope dashed red
- ② SHORT 40-WIRE RIBBON, pin 1 to pin 1 (~5-8 cm between the plugs): the grey arrows, J2 -> the adapter's header
- ③ ADAPTER'S IDE HEADER (dashed blue): on the HX-2118P adapter, 15 mm above on standoffs H1 / H2 - the adapter does NOT plug into J2
- ④ CF CARD INSERTS HERE (into the adapter): the thick blue slot edge; the card is pushed in toward the bus



CHECK: this bar must measure exactly 100 mm - print at 100 % / "Actual size", NOT "Fit" / "Shrink to page"

Also check with a ruler: the two blue hole crosses are 52.0 mm apart.

Heights are typical figures, not measured: box header 9, IDC plug on it +9 (~18), plug body ~1.5 wider than the shroud each side, socketed DIP 8.5-9.5, adapter 1.6 thick, CF holder + card ~6-8 on the adapter.

--- ribbon loop ~42 mm above the card

--- adapter's plug top ~35 mm above the card

- the adapter's OWN header (9) + plug, top ~35

CF card in its holder (pushed in from the slot edge, toward the bus)

--- CF card top ~22 mm above the card

plug envelope +1.5 each side

its plug, top ~10

adapter 1.6

M3 standoff 15

socketed DIPs ~9

DIPS ~9
J2 ON THIS BOARD, 9

screw/nut + washer ~3 below

Power: the adapter takes +5 V through its power pads, by a short cable from J3 (+5V, G, G, nc) - pad order to be confirmed on the adapter.

