

Pin	A	A	A	A	A	B	B	B	B	B	C	C			C	C			
	Fixed	Bus Name	Test Chip	Test Port	Test Pin	Old CNTL #	Fixed	Bus Name	Test Chip	Test Port	Test Pin	Old CNTL #	Fixed	Bus Name	Test Chip	Test Port	Test Pin	Old CNTL #	Notes
1	GND	GND					GND	GND					GND	GND					
2	5V	VCC					5V	VCC					5V	VCC					
3	INT ACK ???						ALU FUNCTION SELECT 3	ALU3					BRANCH REGISTER LOAD L	BR-REG-LD-LO					
4	ADDRESS 0	ADDR0	0	0	0		ADDRESS REGISTER CLK	ADDR-REG-CLK	2	0	0	0	INC/DEC REG LD	I/D-REG-LD	3	1	3	27	
5	ADDRESS 1	ADDR1	0	0	1		BOARD ADDRESS REGISTER ID 1	BRD-ADDR-REG1	2	0	1	1	INC/REG DATA OUT	I/D-REG-OUT	3	1	4	28	
6	ADDRESS 2	ADDR2	0	0	2		BOARD ADDRESS REGISTER ID 0	BRD-ADDR-REG0	2	0	2	2	BRANCH REGISTER LOAD HI	BR-REG-LD-HI	3	1	5	29	HI/LO use byte swap ?
7	ADDRESS 3	ADDR3	0	0	3		REGISTER FUNCTION	REG-FUNC	2	0	3	3	BRANCH REGISTER OUT	BR-REG-OUT	3	1	6	30	
8	ADDRESS 4	ADDR4	0	0	4		ADDRESS REGISTER OUT	ADDR-REG-OUT	2	0	4	4	BRANCH CONDITION	BR-COND	3	1	7	31	
9	ADDRESS 5	ADDR5	0	0	5		INC/DEC REG DN	I/D-REG-DN	2	0	5	5	MEMORY WRITE	MEM-WR	4	0	0	32	
10	ADDRESS 6	ADDR6	0	0	6		INC/DEC REG UP	I/D-REG-UP	2	0	6	6	MEMORYREAD	MEM-RD	4	0	1	33	
11	ADDRESS 7	ADDR7	0	0	7		RESET	RESET	2	0	7	7	I/O WRITE	I/O-WR	4	0	2	34	
12	ADDRESS 8	ADDR8	0	1	0		DATA REGISTER OUT ID 0	DATA-REG-OUT-ID0	2	1	0	8	I/O READ	I/O-RD	4	0	3	35	
13	ADDRESS 9	ADDR9	0	1	1		DATA REGISTER OUT ID 1	DATA-REG-OUT-ID1	2	1	1	9	I/O ADDRESS	I/O-ADDR	4	0	4	36	
14	ADDRESS 10	ADDR10	0	1	2		BOARD OUT ID 0	BRD-OUT-ID0	2	1	2	10	INTERRUPT	INT	4	0	5	37	
15	ADDRESS 11	ADDR11	0	1	3		BOARD OUT ID 1	BRD-OUT-ID1	2	1	3	11	SP/PC SELECT	SP/PC-SEL	4	0	6	38	
16	ADDRESS 12	ADDR12	0	1	4		DATA REGISTER IN ID 0	DATA-REG-IN-ID0	2	1	4	12	SP/PC DATA LO OUT	SP/PC-DATA-OUT-LO	4	0	7	39	HI/LO use BYTE SWAP ?
17	ADDRESS 13	ADDR13	0	1	5		DATA REGISTER IN ID 1	DATA-REG-IN-ID1	2	1	5	13	SP/PC DATA HI OUT	SP/PC-DATA-OUT-HI	4	1	0	40	
18	ADDRESS 14	ADDR14	0	1	6		BOARD IN ID 0	BRD-IN-ID0	2	1	6	14	SP/PC ADDRESS OUT	SP/PC-ADDR-OUT	4	1	1	41	
19	ADDRESS 15	ADDR15	0	1	7		BOARD IN ID 1	BRD-IN-ID1	2	1	7	15	SP/PC LOAD LO	SP/PC-LD-LO	4	1	2	42	HI/LO use BYTE SWAP ?
20	DATA 0	DATA0	1	0	0		DATA REGISTER READ LO	DATA-REG-RD-LO	3	0	0	16	SP/PC LOAD HI	SP/PC-LD-HI	4	1	3	43	
21	DATA 1	DATA1	1	0	1		DATA REGISTER WRITE LO	DATA-REG-WR-LO	3	0	1	17	SP/PC DOWN	SP/PC-DN	4	1	4	44	
22	DATA 2	DATA2	1	0	2		DATA REGISTER READ HI	DATA-REG-RD-HI	3	0	2	18	SP/PC UP	SP/PC-UP	4	1	5	45	
23	DATA 3	DATA3	1	0	3		DATA REGISTER WRITE HI	DATA-REG-WR-HI	3	0	3	19	DATA 8	DATA8	1	1	0		
24	DATA 4	DATA4	1	0	4		ALU FUNCTION SELECT 0	ALU0	3	0	4	20	DATA 9	DATA9	1	1	1		
25	DATA 5	DATA5	1	0	5		ALU FUNCTION SELECT 1	ALU1	3	0	5	21	DATA 10	DATA10	1	1	2		
26	DATA 6	DATA6	1	0	6		ALU FUNCTION SELECT 2	ALU2	3	0	6	22	DATA 11	DATA11	1	1	3		
27	DATA 7	DATA7	1	0	7		ALU VALID FUNCTION	ALU-FUNC	3	0	7	23	DATA 12	DATA12	1	1	4		
28	SHIFT REGISTER LOAD	SR-LD					LOAD ACCUMULATOR	LD-AC	3	1	0	24	DATA 13	DATA13	1	1	5		
29	BUS DIRECTION	DIR	4	1	6	46	ACCUMULATOR TO DATA OUT	RD-AC	3	1	1	25	DATA 14	DATA14	1	1	6		
30	HI/LO SWAP	H/L-SWAP	4	1	7	47	ACCUMULATOR IN INVERT	AC-IN-INV	3	1	2	26	DATA 15	DATA15	1	1	7		
31	5V	VCC					5V	VCC					5V	VCC					
32	GND	GND					GND	GND					GND	GND					