

Adapter toward the y = 124 edge (y 63.5-123.5), CF column beside J2, ROM at the top edge


x from the bus edge, y from the JP1 end
H1 (pin-1 end): x 80.7 y 109.5
H2 (power-pad end): x 80.7 y 57.5
holes 52.0 apart, 3.2 mm drill, 7 mm copper keep-out
adapter x 65.4-109.4, y 53.5-113.5
header edge x 65.4, CF slot edge x 109.4
J2 pin 1: x 61.0 y 107.6 (square pad)
J2 pins y 59.4-107.6, odd row x 61.0, even x 58.4
ROM IC13 keep-clear x 154.3-175.9, y 34.8-89.0
(on the board: past an edge it is free air)

M3 hex 15 mm female-female (5.5 AF),
M3 x 6 screws + washers both sides
adapter underside 15 mm above the card

J2 pin 1 and the adapter's pin 1 at the SAME end (y max): stripe on that end at both plugs; the ribbon arches up from J2 and down into the adapter's header.

unrouted 0, vias 100, track 13748 mm
DRC copper violations: none


- ① J2 = the IDE header ON THIS BOARD (solid red, pin 1 = square pad); with its ribbon plug it stands ~18 mm; plug envelope dashed red
- ② SHORT 40-WIRE RIBBON, pin 1 to pin 1 (~5-8 cm between the plugs): the grey arrows, J2 -> the adapter's header
- ③ ADAPTER'S IDE HEADER (dashed blue): on the HX-2118P adapter, 15 mm above on standoffs H1 / H2 - the adapter does NOT plug into J2
- ④ CF CARD INSERTS HERE (into the adapter): the thick blue slot edge; the card is pushed in toward the bus



Also check with a ruler: the two blue hole crosses are 52.0 mm apart.

CHECK: this bar must measure exactly 100 mm - print at 100 % / "Actual size", NOT "Fit" / "Shrink to page"

Side view at 1:1 - the height stack (section along x, seen from the y-max end; card component side up)



J2 is the IDE header ON THIS BOARD. The CF adapter does NOT plug into it: the adapter sits on two 15 mm M3 standoffs and has its OWN IDE header; a short 40-wire ribbon (~5-8 cm) joins the two, pin 1 to pin 1.

and the adapter's pin tails (~2-2.5 mm under it). J2 with its plug stands ~18 mm, taller than the standoffs: its plug envelope stays outside the adapter outline.

Card cage: the slot on this card's component side stays EMPTY (2026-09-25: nothing in front of the memory card), so the ~44 mm stack has the room it needs.

Power: the adapter takes +5 V through its power pads (floppy order +5V, G, G, +12V) by a short straight-through cable from J3 (+5V, G, G, nc): pin 1 to pin 1, so +12 V meets J3's open pin (2026-09-26).

CHECK: this bar must measure exactly 100 mm - print at 100 % / "Actual size", NOT "Fit" / "Shrink to page"