Kube-OVN Document

v1.17.0

Kube-OVN Team

2025 Kube-OVN Team

Table of contents

1. Kube-OVN 5
   1.1 What is Kube-OVN? 5
   1.2 Why Kube-OVN? 5
   1.3 CNI □□□□ 5
   1.4 □□□□□OVN/ovn-kubernetes/Kube-OVN 6
   1.5 □□ 7
2. □□□□ 8
   2.1 □□□□ 8
   2.2 □□□□ 10
   2.3 Underlay □□□□ 12
   2.4 □□ CNI □□ 18
   2.5 Talos □□ 23
   2.6 □□□□□ 24
   2.7 □□ 26
3. □□□□ 27
   3.1 □□□□ 27
   3.2 □□□□□□ 35
   3.3 □□□□ 37
   3.4 IP □□□ 40
   3.5 □□□□□ 42
   3.6 EIP □ SNAT □□ 43
   3.7 □□□□ QoS □□ 46
   3.8 □□□□ 49
   3.9 Webhook □□ 51
   3.10 □□□□ 54
   3.11 LoadBalancer □□ Service 60
   3.12 □□□□□□□ 65
   3.13 □□ 69
4. KubeVirt 82
   4.1 VM □□ IP 82
   4.2 □□□□□ 85
   4.3 □□□□ 87
   4.4 □□□ 89
   4.5 □□□□□ 94
   4.6 DHCP 97

2025 Kube-OVN Team

5. VPC ▯▯ 99
5.1 VPC ▯▯ 99
5.2 VPC Egress Gateway 111
5.3 VPC Egress Gateway ▯▯▯▯ 125
5.4 Egress Gateway BGP ▯ EVPN ▯▯ 128
5.5 VPC QoS 132
5.6 ▯▯▯ VPC ▯▯▯▯▯▯ 135
5.7 ▯▯▯ VPC ▯▯ DNS 140
5.8 SecurityGroup ▯▯ 143
5.9 OVN EIP FIP SNAT DNAT ▯▯ 147
5.10 VPC ▯▯ 156
6. ▯▯▯▯ 158
6.1 kubectl-ko ▯▯ 158
6.2 ▯▯▯▯▯▯ 164
6.3 ▯▯ ovn-central ▯▯ 166
6.4 OVN ▯▯▯▯▯▯▯▯ 170
6.5 ▯▯▯▯ CIDR 173
6.6 ▯▯ Join ▯▯ CIDR 174
6.7 ▯▯▯▯▯▯ 175
6.8 ▯▯▯▯▯▯ 176
7. ▯▯▯▯ 180
7.1 ▯▯▯▯▯ 180
7.2 ▯▯▯▯ 187
7.3 ▯▯▯▯ FastPath ▯▯ 192
7.4 ▯▯ eBPF ▯▯▯▯▯ TCP ▯▯ 194
7.5 ▯▯ OVN-IC ▯▯▯▯▯▯▯ 198
7.6 ▯▯ Submariner ▯▯▯▯▯▯▯ 204
7.7 Overlay ▯▯▯▯▯▯▯▯▯ 206
7.8 Overlay ▯▯▯▯▯▯▯▯ 208
7.9 BGP ▯▯ 211
7.10 ▯▯ MetalLB ▯ Kube-OVN Underlay ▯▯ 218
7.11 Cilium ▯▯ 222
7.12 Cilium NetworkPolicy ▯▯ 225
7.13 Cilium ▯▯▯▯▯▯ 229
7.14 ▯▯▯▯▯▯ 234
7.15 VIP ▯▯ IP 235
7.16 Mellanox ▯▯ Offload ▯▯ 238
7.17 ▯▯▯▯▯ Offload ▯▯ 247

7.18 □□□□□□ Offload □□ 251
7.19 □□□□□□ Offload □□ 255
7.20 DPDK □□ 258
7.21 OpenStack □□ 262
7.22 □□ IPsec □□□□□□□ 266
7.23 OVN □□□□ 268
7.24 □□□□ DNS □□□ Kube-OVN □□ 271
7.25 □□ VPC NAT □□□□ 273
8. □□□□ 274
8.1 □□□□ 274
8.2 What's Next 277
8.3 □□□□□□□ 280
8.4 □□□□ 289
8.5 Underlay □□□□ 291
8.6 □□ Netfilter □□ 298
8.7 □□□□□□□ 304
8.8 □□□ OVS/OVN □□ 306
8.9 □□□□□□ 308
8.10 Kube-OVN □□□□ 310
8.11 Kube-OVN □□□□ 316
8.12 Annotation □□□□ 347
8.13 □□□□ 352
9. □□□□ 355
9.1 □□□□ 355
9.2 □□□□ 355
9.3 □□ 355
9.4 □□ 355

2025 Kube-OVN Team

1. Kube-OVN



1.1 What is Kube-OVN?

Kube-OVN ■■■ CNCF ■■■■■■■■■■■■■■■■■■■■ SDN ■■■■■■■■■■■■■■■■■■■

1.3.1 □□□ eBPF □□□

□□ Cilium □ Calico eBPF□

Kube-OVN □□ Open vSwitch □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□

1.3.2 □□□ CNI, Ingress, Service Mesh □ Observability All in One □□□

□□ Cilium□

Kube-OVN □□□□□ CNI □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□

1.3.3 □□□□ OpenShift □□□

□□ ovn-kubernetes□

□ OpenShift □□□□□□ CNI □□□□ Cluster Network Operator □□□Kube-OVN □□□□□□□□□□□□□□□□□□□□□□□□ RedHat □□□□□□□□□□□□ Kubernetes □□□□□□□□□□□□□□□□□□□□

2026⬚10⬚20⬚

2022⬚5⬚20⬚

GitHub  



1.5 ⬚⬚

2. □□□□

2.1 □□□□

Kube-OVN □□□□□ CNI □□□□□□□□□□□□□□□□ Kubernetes □□□□□□□□□□□□□□□ □□

2.1.1 □□□□

- Kubernetes >= 1.29□
- Docker >= 1.12.6, Containerd >= 1.3.4□
- □□□□: CentOS 7/8, Ubuntu 16.04/18.04/20.04□
- □□ Linux □□□□□□□□□□□□□□□□□□□□□ `geneve`, `openvswitch`, `ip_tables` □ `iptable_nat` □Kube-OVN □□□□□□□□□□□□□

□□□□□

1. □□□□□□□□ 3.10.0-862□□□ `netfilter` □□□□□ bug □□□ Kube-OVN □□□□□□□□□□□□□□□□□□□□□□□□□□□□ CentOS □□□□□□□□□□□□□□□□□□□□□□□□□ bug □□ Floating IPs broken after kernel upgrade to Centos/RHEL 7.5 - DNAT not working□
2. Rocky Linux 8.6 □□□ 4.18.0-372.9.1.el8.x86_64 □□ TCP □□□□ TCP connection failed in Rocky Linux 8.6□□□□□□□□ 4.18.0-372.13.1.el8_6.x86_64 □□□□□□□
3. □□□□□□□□ 4.4□□□□□□□□ `openvswitch` □□□□□□□□□□□□□□□□□□ `openvswitch` □□□□□□□□□□□□□
4. Geneve □□□□□□□□□ IPv6□□□□ `cat /proc/cmdline` □□□□□□□□□□ □□□□□ bug □□□ Geneve tunnels don't work when ipv6 is disabled□

2.1.2 □□□□

- □□□□□□□□□ IPv6□□□□□□□□□□□□□ `ipv6.disable=1` □□□□□□□□ 0□
- `kube-proxy` □□□□□□Kube-OVN □□□□□ Service ClusterIP □□□ `kube-apiserver` □
- □□ kubelet □□□□□□□□ CNI□□□□□□□□□□□□□, kubelet □□□□□□□□□□□□ `--network-plugin=cni --cni-bin-dir=/opt/cni/bin --cni-conf-dir=/etc/cni/net.d` □
- □□□□□□□□□□□□□□□□□□□□

```
#    IPv4 Masquerade
firewall-cmd --add-masquerade --permanent
#   Kube-OVN IPv6/       Masquerade
firewall-cmd --permanent --add-rich-rule 'rule family="ipv6" source address="fd00:10:16::/112" masquerade'

firewall-cmd --reload
```

PDF Slack Support

2025⁄11⁄20⁄

2022⁄5⁄20⁄

GitHub



2.1.4 ⁄⁄

2025 Kube-OVN Team

2.2 ████

Kube-OVN ██████████ Charts ████████████████████████ Kube-OVN ██████████ Overlay ████

██████████ Underlay/Vlan ██████ Underlay ████████████ ████████

██████████████████████████ Kube-OVN ████

2.2.1 ████

██████

████████████ release ████████████████████

```
wget https://raw.githubusercontent.com/kubeovn/kube-ovn/refs/tags/v1.17.0/dist/images/install.sh
```

███ master ████████████████████████████

```
wget https://raw.githubusercontent.com/kubeovn/kube-ovn/master/dist/images/install.sh
```

██████

████████████████

```
REGISTRY="docker.io/kubeovn"           #
VERSION="v1.17.0"                      #     /Tag
POD_CIDR="10.16.0.0/16"                #      CIDR     SVC/NODE/JOIN CIDR
SVC_CIDR="10.96.0.0/12"                #     apiserver   service-cluster-ip-range
JOIN_CIDR="100.64.0.0/16"              # Pod         CIDR     SVC/NODE/POD CIDR
LABEL="node-role.kubernetes.io/control-plane" #    OVN DB
IFACE=""                               #                        Kubernetes    Node IP
TUNNEL_TYPE="geneve"                   #          geneve, vxlan   stt stt        ovs
```

████████████████ `IFACE=enp6s0f0,eth.*` ▯

██████

> ██████ root ▯▯

`bash install.sh`

███████

▯▯

████████ Kube-OVN ██████████

1. ████ `[Step 4/6]` ██████████ Pod▯▯▯

⬚⬚⬚⬚ **label**

```
# kubectl label node -lbeta.kubernetes.io/os=linux kubernetes.io/os=linux --overwrite
node/kube-ovn-control-plane not labeled
node/kube-ovn-worker not labeled

# kubectl label node -lnode-role.kubernetes.io/control-plane kube-ovn/role=master --overwrite
node/kube-ovn-control-plane labeled

#    label    dpdk        dpdk
# kubectl label node -lovn.kubernetes.io/ovs_dp_type!=userspace ovn.kubernetes.io/ovs_dp_type=kernel --overwrite
node/kube-ovn-control-plane labeled
node/kube-ovn-worker labeled
```

⬚⬚ **Helm Repo** ⬚⬚

```
# helm repo add kubeovn https://kubeovn.github.io/kube-ovn/
"kubeovn" has been added to your repositories

# helm repo list
NAME            URL
kubeovn         https://kubeovn.github.io/kube-ovn/

# helm repo update kubeovn
Hang tight while we grab the latest from your chart repositories...
...Successfully got an update from the "kubeovn" chart repository
Update Complete. ⎈Happy Helming!⎈

# helm search repo kubeovn
NAME                    CHART VERSION   APP VERSION     DESCRIPTION
kubeovn/kube-ovn        v1.17.0         v1.17.0         Helm chart for Kube-OVN
```

⬚⬚ **helm install ⬚⬚ Kube-OVN**

Chart ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ `values.yaml` ⬚⬚⬚⬚⬚⬚⬚⬚

```
# helm install kube-ovn kubeovn/kube-ovn --wait -n kube-system --version v1.17.0
NAME: kube-ovn
LAST DEPLOYED: Thu Apr 24 08:30:13 2025
NAMESPACE: kube-system
STATUS: deployed
REVISION: 1
TEST SUITE: None
```

⬚⬚


⬚⬚⬚⬚⬚ ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ **Helm** ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ `values.yaml` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

```
helm upgrade -f values.yaml kube-ovn kubeovn/kube-ovn --wait -n kube-system --version v1.17.0
```

PDF Slack Support

2026⬚4⬚28⬚

2022⬚5⬚20⬚

GitHub 

2025 Kube-OVN Team

2.3 Underlay ▯▯▯▯

▯▯▯▯▯ Kube-OVN ▯▯▯▯▯▯▯ Geneve ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Overlay ▯▯▯

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Kube-OVN ▯▯▯▯▯▯▯▯▯ Underlay ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

6. ■■■■■■■■ Linux Bridge ■■■■■■

■■■■■■■■■■ Kube-OVN Underlay ■■■■■■■■■■

▒▒▒**ProviderNetwork** ▒▒▒▒▒▒▒▒▒▒ **12** ▒▒▒▒

- `defaultInterface` : ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ Bond ▒▒▒▒ Vlan ▒▒▒▒ProviderNetwork ▒▒▒▒▒▒▒▒▒▒▒▒ excludeNodes ▒▒▒▒▒▒▒▒▒ br-net1▒▒▒▒ `br-NAME` ▒▒ OVS ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒
- `customInterfaces` : ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒
- `nodeSelector` : ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ OVS ▒▒▒▒▒▒▒▒▒ `matchLabels` ▒ `matchExpressions` ▒▒▒▒▒▒▒▒
- `excludeNodes` : ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ `net1.provider-network.ovn.kubernetes.io/exclude=true` ▒▒▒▒▒▒▒▒▒▒▒▒▒ **`nodeSelector`** ▒ **`excludeNodes`** ▒▒▒▒▒▒▒▒▒▒▒▒▒ **`nodeSelector`** ▒
- `autoCreateVlanSubinterfaces` : ▒▒▒▒▒▒▒▒ `false` ▒▒▒▒ `true` ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ VLAN ▒▒▒▒▒▒▒ `<interface>.<vlanid>` ▒▒▒▒▒▒▒▒▒

▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

Key	Value	▒▒
net1.provider-network.ovn.kubernetes.io/ready	true	▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ProviderNetwork ▒▒▒▒▒▒▒
net1.provider-network.ovn.kubernetes.io/interface	eth1	▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒
net1.provider-network.ovn.kubernetes.io/mtu	1500	▒▒▒▒▒▒▒▒▒▒▒▒ MTU

> ▒▒▒▒▒▒▒▒▒▒▒▒▒▒ IP▒▒ IP ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ OVS ▒▒▒▒

▒▒▒▒ VLAN ▒▒▒▒

▒ ProviderNetwork ▒▒▒▒ `autoCreateVlanSubinterfaces: true` ▒▒▒▒▒▒▒▒▒▒ VLAN ▒▒▒▒▒▒▒▒ VLAN ▒▒▒▒▒▒▒▒▒▒

▒▒▒▒

```
apiVersion: kubeovn.io/v1
kind: ProviderNetwork
metadata:
  name: vlan-provider
spec:
  defaultInterface: eth0.341
  autoCreateVlanSubinterfaces: true
  customInterfaces:
    - interface: eth2.341
      nodes:
        - worker-node-1
        - worker-node-2
```

▒▒▒▒

▒▒▒▒▒▒▒▒ `<interface>.<vlanid>` ▒▒▒▒ VLAN ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ VLAN ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ ProviderNetwork ▒▒▒▒▒▒▒▒▒▒▒▒▒

▒▒▒▒ VLAN ▒▒

▒▒▒▒▒▒▒▒▒▒▒▒ VLAN ▒▒▒▒▒▒▒▒▒▒ `preserveVlanInterfaces` ▒ `vlanInterfaces` ▒▒▒▒ OVS ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

- `preserveVlanInterfaces` ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ `defaultInterface` ▒ VLAN ▒▒▒▒▒▒▒ `<interface>.<vlanid>` ▒▒▒▒▒▒▒▒▒ OVS ▒▒▒▒▒▒
- `vlanInterfaces` ▒▒▒▒▒▒▒▒▒▒ VLAN ▒▒▒▒▒▒▒▒▒ `eth0.10` ▒ `bond0.20` ▒▒

```
apiVersion: kubeovn.io/v1
kind: ProviderNetwork
metadata:
  name: net1
spec:
  defaultInterface: eth1
  preserveVlanInterfaces: true
  vlanInterfaces:
  - eth1.100
  - eth1.200
```

▒▒ VLAN

Vlan ▒▒▒▒ Vlan Tag ▒ ProviderNetwork ▒▒▒▒▒▒▒▒▒

2025 Kube-OVN Team

▯▯▯▯ VLAN ▯▯▯▯

```
apiVersion: kubeovn.io/v1
kind: Vlan
metadata:
  name: vlan1
spec:
  id: 0
  provider: net1
```

- `id` : ▯ VLAN ID/Tag▯Kube-OVN ▯▯▯▯ Vlan ▯▯▯▯▯▯ Vlan ▯▯▯▯ 0 ▯▯▯▯▯▯▯▯▯vlan ▯▯▯▯▯▯▯ localnet ▯▯▯
- `provider` : ▯▯▯▯▯▯ ProviderNetwork ▯▯▯▯▯▯▯▯ VLAN ▯▯▯▯▯▯▯ ProviderNetwork▯

▯▯ **Subnet**

▯ Vlan ▯▯▯▯▯▯▯▯▯▯▯▯▯▯

```
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: subnet1
spec:
  protocol: IPv4
  cidrBlock: 172.17.0.0/16
  gateway: 172.17.0.1
  vlan: vlan1
  disableGatewayCheck: false
```

- `vlan` ▯▯▯▯▯▯ VLAN ▯▯▯▯▯ Subnet ▯▯▯▯▯▯▯ VLAN▯
- `disableGatewayCheck` ▯▯▯▯ Underlay ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `true` ▯▯▯▯▯▯▯▯

2.3.6 ▯▯▯▯

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ IP ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

▯▯▯▯ IP ▯▯▯▯▯▯ Pod ▯▯ IP ▯ Mac

2.3.7 ▯▯▯▯▯▯▯

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯Kube-OVN ▯▯▯ Underlay ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `spec.logicalGateway` ▯ `true` ▯▯▯

```
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: subnet1
spec:
  protocol: IPv4
  cidrBlock: 172.17.0.0/16
  gateway: 172.17.0.1
  vlan: vlan1
  logicalGateway: true
```

▯▯▯▯▯▯▯▯Pod ▯▯▯▯▯▯▯▯▯▯▯▯▯ Kube-OVN ▯▯▯▯▯▯▯▯▯▯Logical Router▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

2.3.8 Underlay ▯ Overlay ▯▯▯▯

▯▯▯▯▯▯▯▯▯▯▯ Underlay ▯ Overlay ▯▯▯▯▯▯▯▯▯ Overlay ▯▯▯▯ Pod ▯▯▯▯▯▯▯▯ NAT ▯▯▯▯▯▯ Underlay ▯▯▯▯ Pod IP▯ ▯ Underlay ▯▯▯ Pod ▯▯ Overlay ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

□□□□□□ **IP**

□□□□□□□□□□□□ subnet □□□□□ IP □□□□□□□□□□□□□ Underlay Subnet □□□□□□□□□□□□ `u2oInterconnectionIP` □

□□ **Underlay Subnet** □□□□□□ **VPC**

□□□□□ Underlay Subnet □□□□ VPC □□ Overlay Subnet □□□□□□□□□□□□ VPC □□□□ `u2oInterconnection` □□□ `true` □□□□ `subnet.spec.vpc` □□□□ VPC □□□□□

2.3.9 □□□□

□□□□□□□□□□□□□□□ IP □□□□□□□□□□□ Netplan □□□□□□□ Ubuntu□□□□□□□ Netplan □ renderer □□□ NetworkManager□□□□□□□□□□□□ IP □□□□□□ DHCP□□

```
network:
  renderer: NetworkManager
  ethernets:
    eth0:
      dhcp4: no
      addresses:
        - 172.16.143.129/24
  version: 2
```

□□□□□□□□□ IP □□□□□□□□□□□□ netplan □□□□□□□□□□□□

```
netplan generate

nmcli connection reload netplan-eth0
nmcli device set eth0 managed yes
```

□□□□□□□□Kube-OVN □□□□□□□ IP □□□□□□□□□ OVS □□□□

□□□□□□□□□□□□□ NetworkManager □□□□□□□ CentOS□□□□□□□□□□□□□□□□□□□□□□□

```
nmcli connection reload eth0
nmcli device set eth0 managed yes
nmcli -t -f GENERAL.STATE device show eth0 | grep -qw unmanaged || nmcli device reapply eth0
```

□□□□□□□□□□□□□□□□□□□ IP □□□□□□□□ MAC □□□□□□□

2.3.10 □□□□

□□□□□□□ **hairpin** □ **Pod** □□□□□

□□□□□□□□ hairpin □□□□□□□□□□□□□□□ Pod □□□□□□□□□Pod □□□□□□□□□□□□□□□□ OVS □□□□□□ MAC □□□□□□□□□□□□□□□□□

□□□□□□□□□□□□ hairpin□□□□□□□□□□□□□□□□□□□□□□ Kube-OVN □□□□

Pod □□□□□□□□ **Pod** □□□□□□□

□□□□□□□□□□□ Pod □□□□□□□□ 300□□□□□□□□ ARP □□□□□ OVS □□ resubmit □□□□□□□□□□□□□□□□

```
2022-11-13T08:43:46.782Z|00222|ofproto_dpif_upcall(handler5)|WARN|Flow:
arp,in_port=331,vlan_tci=0x0000,dl_src=00:00:00:25:eb:39,dl_dst=ff:ff:ff:ff:ff:ff,arp_spa=10.213.131.240,arp_tpa=10.213.159.254,arp_op=1,arp_sha=00:00:00:25:e
b:39,arp_tha=ff:ff:ff:ff:ff:ff

bridge("br-int")
----------------
 0. No match.
     >>>> received packet on unknown port 331 <<<<
    drop

Final flow: unchanged
Megaflow: recirc_id=0,eth,arp,in_port=331,dl_src=00:00:00:25:eb:39
Datapath actions: drop
2022-11-13T08:44:34.077Z|00224|ofproto_dpif_xlate(handler5)|WARN|over 4096 resubmit actions on bridge br-int while processing
arp,in_port=13483,vlan_tci=0x0000,dl_src=00:00:00:59:ef:13,dl_dst=ff:ff:ff:ff:ff:ff,arp_spa=10.213.152.3,arp_tpa=10.213.159.254,arp_op=1,arp_sha=00:00:00:59:e
f:13,arp_tha=ff:ff:ff:ff:ff:ff
```

□□□□□□□□□□ OVN NB □□ `bcast_arp_req_flood` □ `false` □


```
kubectl ko nbctl set NB_Global . options:bcast_arp_req_flood=false
```


2025 Kube-OVN Team

PDF Slack Support

2026⊠11⊠5⊠

2022⊠5⊠20⊠



GitHub



+2

2.3.11 ⊠⊠

2.4 □□ CNI □□

□□□□□□□□ Kube-OVN □□□□ CNI □□□□ CNI □□□□ Cilium□Calico □ Flannel□□□□□□

2.4.1 □□

□□□ CNI □□□□Kube-OVN □□□□ CNI □□□□ Pod □□□□□□□□□□□□□□□ CNI □□□□□□□□eth0□□□□□□□

- □□□ CNI □□□□□ Kube-OVN □□□□□□□□VPC□□□□□□□□
- □□□□□□□□□□□
- □ Pod □□□□□□□□□□□□□□□□
- □□ Kube-OVN □ VPC NAT □□□□□□□□□□□□□□□□

2.4.2 □□□□

□□□□

1. □ **CNI**□□□□ Kubernetes □□□ CNI□Cilium□Calico□Flannel □□
2. **Multus CNI**□□□□□□□□□□
3. **Kube-OVN**□□□□□□□□□

□□□□

1. □□□□□□□ CNI
2. □□ Multus CNI
3. □□□□□□□□ Kube-OVN

2.4.3 □□

□□ **Helm Chart v2**

```
# values.yaml
cni:
  nonPrimaryCNI: true
```

□□ Helm □□□

```
helm install kube-ovn ./charts/kube-ovn-v2 \
  --namespace kube-system \
  --set cni.nonPrimaryCNI=true
```

□□ **Helm Chart v1**

```
# values.yaml
cni_conf:
  NON_PRIMARY_CNI: true
```

□□ Helm □□□

```
helm install kube-ovn ./charts/kube-ovn \
  --namespace kube-system \
  --set cni_conf.NON_PRIMARY_CNI=true
```

□□□□

□ `kube-ovn-controller` Deployment □ `kube-ovn-cni` DaemonSet □□□□□□□□□□□□□□□□□□□ Pod □□□□□□□□□□□□□□□□□

2025 Kube-OVN Team

```
# kube-ovn-controller Deployment
containers:
- name: kube-ovn-controller
  args:
  - --non-primary-cni-mode=true
```

```
# kube-ovn-cni DaemonSet
containers:
- name: kube-ovn-cni
  args:
  - --non-primary-cni-mode=true
```

2.4.4 ▯▯

▯▯▯▯▯▯▯**NADs**▯

▯▯ NAD ▯▯▯▯▯▯▯▯▯▯▯▯

```
apiVersion: k8s.cni.cncf.io/v1
kind: NetworkAttachmentDefinition
metadata:
  name: kube-ovn-vpc-network
  namespace: default
spec:
  config: |
    {
      "cniVersion": "0.3.1",
      "type": "kube-ovn",
      "server_socket": "/run/openvswitch/kube-ovn-daemon.sock",
      "provider": "kube-ovn-vpc-network.default.ovn"
    }
```

VPC ▯▯▯▯▯

▯▯▯▯▯▯▯ VPC ▯▯▯▯▯▯

```
apiVersion: kubeovn.io/v1
kind: Vpc
metadata:
  name: vpc-secondary
spec:
  namespaces:
  - default
---
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: subnet-secondary
spec:
  vpc: vpc-secondary
  cidr: "10.100.0.0/16"
  gateway: "10.100.0.1"
  provider: kube-ovn-vpc-network.default.ovn
```

Pod ▯▯

▯ Pod ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

```
apiVersion: v1
kind: Pod
metadata:
  name: multi-network-pod
  annotations:
    k8s.v1.cni.cncf.io/networks: default/kube-ovn-vpc-network
spec:
  containers:
  - name: app
    image: nginx
```

2.4.5 ▯▯▯▯▯▯

▯▯▯▯**eth0**▯

- ▯▯ CNI▯Cilium▯Calico ▯▯▯▯
- ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

2025 Kube-OVN Team

- ███ Kubernetes ██████████

██████**net1**、**net2...**、

- ▯ Kube-OVN ▯▯
- ▯▯▯▯▯▯▯▯▯
- ▯▯▯▯▯▯▯▯ VPC ▯▯▯
- ▯▯ Kube-OVN ▯▯▯▯▯▯▯▯QoS ▯ NAT

2.4.6 ▯▯▯▯

1. ▯▯▯▯

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

```
#    Pod
apiVersion: v1
kind: Pod
metadata:
  name: frontend
  annotations:
    k8s.v1.cni.cncf.io/networks: |
      [
        {"name": "default/public-network"},
        {"name": "default/internal-network"}
      ]
```

2. ▯▯▯

▯▯▯▯▯▯▯▯▯▯

```
#    A Pod
apiVersion: v1
kind: Pod
metadata:
  name: tenant-a-app
  annotations:
    k8s.v1.cni.cncf.io/networks: default/tenant-a-network

---
#    B Pod
apiVersion: v1
kind: Pod
metadata:
  name: tenant-b-app
  annotations:
    k8s.v1.cni.cncf.io/networks: default/tenant-b-network
```

3. VPC NAT ▯▯

▯▯▯▯▯▯▯▯▯▯▯▯▯

```
apiVersion: kubeovn.io/v1
kind: VpcNatGateway
metadata:
  name: vpc-nat-gw
spec:
  vpc: vpc-secondary
  subnet: subnet-secondary
  lanIp: "10.100.0.254"
```

2.4.7 ▯▯▯▯

▯▯▯▯▯▯▯

Pod ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

```
metadata:
  annotations:
    k8s.v1.cni.cncf.io/networks: |
      [
```

```
        {"name": "default/kube-ovn-network-1", "interface": "net1"},
        {"name": "default/kube-ovn-network-2", "interface": "net2"}
      ]
```

IP □□□□

□□□□□□□ IP □□□

```
#    IP
metadata:
  annotations:
    k8s.v1.cni.cncf.io/networks: |
      [{
        "name": "default/kube-ovn-network",
        "ips": ["10.100.0.100/16"]
      }]
```

□□□□□**QoS**□

□□□□□□□ QoS □□□

```
metadata:
  annotations:
    ovn.kubernetes.io/ingress_rate: "1000"
    ovn.kubernetes.io/egress_rate: "1000"
```

2.4.8 □□□□

□□□□

1. **Pod** □□□□□□□□ - □□ NAD □□□□□□□□□□□□□□ - □□ kube-ovn-cni □□□□□□ - □□ Multus □□□□□
2. □□□□□□□□ - □□□□□ VPC □□ - □□ Pod □□□□□ - □□□□□□□□□□□□
3. **IP** □□□□ - □□□□ CIDR □□□□□ - □□□□ IP □□ - □□ IPAM □□

□□□□

```
#    Pod
kubectl get pod <pod-name> -o yaml | grep -A 10 "networks-status"

#    Pod
kubectl exec <pod-name> -- ip addr show

#
kubectl exec <pod-name> -- ip route show

#    kube-ovn-cni
kubectl logs -n kube-system daemonset/kube-ovn-cni
```

2.4.9 □□

1. □□□□□□□□□□□□ Kubernetes □□□□
2. □□□□□□□□□□□□□□□□□□□□□□□□□□
3. **DNS**□Pod DNS □□□□□□□□□

2.4.10 □□□□

1. □□□□□□□□□□□□□□□□□ IP □□
2. □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□
3. □□□□□□□□□□□□□□□□□□□□□
4. □□□□□□□□□□□□□□□□
5. □□□□□□□□□□□□□□□□□□□□□

2.4.11 ⬚⬚

- Multus CNI ⬚⬚
- ⬚⬚⬚⬚⬚⬚⬚⬚
- Kube-OVN ⬚⬚

PDF Slack Support

2026⬚4⬚28⬚

2025⬚10⬚30⬚

GitHub 

2.4.12 ⬚⬚

2.5 Talos ⬚⬚

Talos Linux ⬚⬚ Kubernetes ⬚⬚⬚⬚ Linux ⬚⬚⬚

2.5.1 ⬚⬚ Helm Chart ⬚⬚ Kube-OVN

⬚⬚⬚⬚⬚⬚⬚⬚⬚ Talos Linux ⬚⬚⬚⬚ Kube-OVN⬚

```
helm install kube-ovn kubeovn/kube-ovn --wait \
    -n kube-system \
    --version v1.17.0 \
    --set OVN_DIR=/var/lib/ovn \
    --set OPENVSWITCH_DIR=/var/lib/openvswitch \
    --set DISABLE_MODULES_MANAGEMENT=true \
    --set cni_conf.MOUNT_LOCAL_BIN_DIR=false
```

⬚⬚⬚⬚⬚⬚ Underlay ⬚⬚⬚⬚⬚⬚⬚⬚⬚ Helm ⬚⬚⬚⬚⬚⬚ Chart ⬚⬚⬚⬚⬚⬚⬚

```
helm install kubeovn kubeovn/kube-ovn --wait \
    -n kube-system \
    --version v1.17.0 \
    --set OVN_DIR=/var/lib/ovn \
    --set OPENVSWITCH_DIR=/var/lib/openvswitch \
    --set DISABLE_MODULES_MANAGEMENT=true \
    --set cni_conf.MOUNT_LOCAL_BIN_DIR=false \
    --set networking.NETWORK_TYPE=vlan \
    --set networking.vlan.VLAN_INTERFACE_NAME=enp0s5f1 \
    --set networking.vlan.VLAN_ID=0 \    # VLAN_ID=0      VLAN tag    untagged      chart      100
    --set networking.NET_STACK=ipv4 \
    --set-json networking.EXCLUDE_IPS='"172.99.99.11..172.99.99.99"' \
    --set-json ipv4.POD_CIDR='"172.99.99.0/24"' \
    --set-json ipv4.POD_GATEWAY='"172.99.99.1"'
```

Note

VLAN⬚Bond⬚Bridge ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ Underlay ⬚⬚⬚⬚⬚⬚⬚⬚Underlay ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ Talos ⬚⬚⬚⬚⬚⬚ `ignore=true` ⬚⬚⬚⬚⬚⬚

```
machine:
  network:
    interfaces:
      - interface: enp0s5f1
        ignore: true
```

PDF Slack Support

2026⬚4⬚28⬚

2025⬚4⬚16⬚

GitHub

2.5.2 ⬚⬚

2.6 □□□□□

Kube-OVN □□□□□

2025⬚9⬚22⬚

2025⬚8⬚29⬚

GitHub 

2.6.7 ⬚⬚

2.7 ▯▯

▯▯▯▯▯▯ Kube-OVN ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Kube-OVN ▯▯▯▯ OVS ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ ▯▯▯▯ issue ▯▯▯▯▯▯▯▯▯▯ Kube-OVN ▯▯▯▯▯▯▯▯▯▯▯▯

2.7.1 ▯▯▯ Kubernetes ▯▯▯▯▯▯

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

Script Uninstall **Helm Uninstall**

```
wget https://raw.githubusercontent.com/kubeovn/kube-ovn/release-1.16/dist/images/cleanup.sh
bash cleanup.sh

helm uninstall kube-ovn -n kube-system
```

2.7.2 ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ ovsdb ▯▯ openvswitch ▯▯▯▯▯▯▯

```
rm -rf /var/run/openvswitch
rm -rf /var/run/ovn
rm -rf /etc/origin/openvswitch/
rm -rf /etc/origin/ovn/
rm -rf /etc/cni/net.d/01-kube-ovn.conflist
#       v1.10         00-kube-ovn.conflist
rm -rf /etc/cni/net.d/00-kube-ovn.conflist
rm -rf /var/log/openvswitch
rm -rf /var/log/ovn
rm -fr /var/log/kube-ovn
```

2.7.3 ▯▯▯▯

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯iptable/ipset ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯


```
reboot
```

PDF Slack Support

2026▯4▯28▯

2022▯5▯24▯

GitHub



2.7.4 ▯▯

2025 Kube-OVN Team


3. □□□□

3.1 □□□□

□□□ Kube-OVN □□□□□□□□□□□□□□□□Kube-OVN □□□□□□□ IP □□□□□□□□ Namespace □□□□□□□□□□□ Namespace □□ Pod □□□□□□□□□□□□ IP □□□□□□□□□□□□CIDR□□□□□□□□□□□□NAT □□□□□

□□□ CNI □□□□□□□□□□□□□□□□□□□ Kube-OVN □□□

□□□□□ VPC □□□□□□□□□□□□□□□ IP□□□□□ VPC peering □□ VPN □□□□□□□□□□□□□□□□□□□ IP□



Overlay □ Underlay □□□□□□□□□□□□□□□□□□□□

```
  selfLink: /apis/kubeovn.io/v1/subnets/ovn-default
  uid: 7e2451f8-fb44-4f7f-b3e0-cfd27f6fd5d6
spec:
  cidrBlock: 10.16.0.0/16
  default: true
  excludeIps:
  - 10.16.0.1
  gateway: 10.16.0.1
  gatewayType: distributed
  natOutgoing: true
  private: false
  protocol: IPv4
```

3.1.2 Join ⬚⬚


⬚ Kubernetes ⬚⬚⬚⬚⬚⬚⬚⬚ Node ⬚⬚⬚⬚⬚⬚ Pod ⬚⬚⬚⬚⬚ ⬚⬚⬚ Overlay ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ Kube-OVN ⬚⬚⬚⬚⬚ `join` ⬚⬚⬚ ⬚⬚⬚⬚ Node ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ ovn0 ⬚⬚ `join` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ ⬚ Pod ⬚⬚⬚⬚⬚⬚⬚⬚

⬚⬚ Pods ⬚ Nodes ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ ovn0 ⬚⬚⬚⬚⬚Node ⬚⬚ Pod ⬚⬚⬚ ovn0 ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ ovn0 ⬚⬚⬚⬚⬚⬚⬚⬚⬚

⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚


```
  - 10.66.0.1..10.66.0.10
  - 10.66.0.101..10.66.0.151
  gateway: 10.66.0.1
  gatewayType: distributed
  natOutgoing: true
  routeTable: ""
  namespaces:
  - ns1
  - ns2
EOF
```

- `cidrBlock` : ⬚⬚ CIDR ⬚⬚⬚⬚⬚⬚ VPC ⬚⬚⬚⬚ Subnet CIDR ⬚⬚⬚⬚⬚
- `excludeIps` : ⬚⬚⬚⬚⬚⬚



gatewayType distributed

```yaml
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: distributed
spec:
  protocol: IPv4
  cidrBlock: 10.166.0.0/16
  default: false
  excludeIps:
  - 10.166.0.1
  gateway: 10.166.0.1
  gatewayType: distributed
  natOutgoing: true
```



IP Pod ovn0 natOutgoing true Pod IP

gatewayType centralized gatewayNode Kubernetes NodeName gatewayNode

```yaml
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: centralized
spec:
  protocol: IPv4
  cidrBlock: 10.166.0.0/16
  default: false
  excludeIps:
  - 10.166.0.1
  gateway: 10.166.0.1
  gatewayType: centralized
  gatewayNode: "node1,node2"
  natOutgoing: true
```

- gatewayNode kube-ovn-worker:172.18.0.2, kube-ovn-control-plane:172.18.0.3
- ECMP ECMP
- Kube-OVN v1.12.0 subnet crd spec enableEcmp ECMP ECMP kube-ovn-controller Deployment enable-ecmp v1.12.0

>

ECMP kube-ovn-controller ping 5s 5s-10s

Node Ready

gatewayNodeSelectors

2025 Kube-OVN Team

gatewayNodeSelectors ▒▒▒▒

- ▒▒ `gatewayNode` ▒▒▒▒▒▒▒▒▒ gatewayNode ▒ `gatewayNodeSelectors` ▒▒▒▒▒
- ▒▒▒▒▒▒▒▒ OR ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒
- ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

```yaml
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: centralized-selector
spec:
  protocol: IPv4
  cidrBlock: 10.166.0.0/16
  default: false
  excludeIps:
  - 10.166.0.1
  gateway: 10.166.0.1
  gatewayType: centralized
  gatewayNodeSelectors:
    - matchLabels:
        role: gateway
    - matchExpressions:
        - key: node-type
          operator: In
          values: ["gateway", "egress"]
  natOutgoing: true
```

3.1.5 ▒▒ ACL ▒▒

Warning

Kube-OVN ▒▒▒▒ NetworkPolicy▒Network Policy API▒Subnet ACL ▒ Security Group ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ OVN ACL ▒▒▒▒▒▒ NetworkPolicy ▒ NetworkPolicy API ▒▒▒▒ ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

```yaml
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: private
spec:
  protocol: IPv4
  default: false
  namespaces:
  - ns1
  - ns2
  cidrBlock: 10.69.0.0/16
  private: true
  allowSubnets:
  - 10.16.0.0/16
  - 10.18.0.0/16
```

3.1.7 Underlay ▯▯▯▯

> ▯▯▯▯▯▯▯ Underlay ▯▯▯▯▯▯▯

- `vlan`：▯▯▯▯ Underlay ▯▯▯▯▯▯▯▯▯▯▯▯ Subnet ▯▯▯ Vlan CR ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Underlay ▯▯▯
- `logicalGateway`：▯▯ Underlay ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ OVN ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Underlay ▯ Overlay ▯▯▯▯▯▯▯▯▯▯▯ `false` ▯

▯▯▯ **MAC ▯ Underlay ▯▯▯▯▯▯ DHCP▯**

▯▯▯▯▯▯ DHCP ▯▯▯▯▯▯▯▯▯▯▯▯▯ IP ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ CIDR ▯ Underlay ▯▯▯▯▯▯▯▯▯ `vlan` ▯▯▯ `cidrBlock` ▯▯▯Kube-OVN ▯▯▯▯▯▯▯▯▯▯ `Mac` ▯ `ProtocolMac` ▯▯▯▯▯▯ Pod ▯▯▯▯▯ IPAM ▯▯▯▯▯▯ MAC▯▯▯▯▯ IP▯▯▯▯▯▯▯▯▯▯▯ DHCP ▯▯ IP▯

MAC-only ▯▯▯▯▯▯▯▯▯ Pod ▯▯▯▯▯▯▯▯▯▯▯▯ IP ▯▯CRI ▯▯▯▯▯ Pod ▯▯▯Pod ▯▯▯ Pending▯▯▯▯▯▯▯▯▯ Multus ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ KubeVirt VM▯

▯▯▯▯▯▯▯▯▯ `gateway` ▯ `excludeIps` ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ CIDR ▯▯▯▯▯▯▯▯ NAT▯CNI ▯▯▯ MAC ▯▯▯▯▯ IP▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ MAC▯▯▯▯▯▯▯ DHCP ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

`vlan` ▯▯▯▯▯▯▯▯▯▯▯ `ProviderNetwork` ▯ `Vlan` ▯▯▯▯▯

```yaml
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: dhcp-underlay
spec:
  vlan: vlan-dhcp
  provider: dhcp-net.default.ovn
  cidrBlock: ""
  gateway: ""
  excludeIps: []
```

Pod ▯▯▯▯▯ provider ▯ MAC annotation ▯▯▯▯▯ MAC▯▯▯▯▯▯▯ `ovn.kubernetes.io/mac_address` ▯OVN ▯▯▯▯▯▯▯ `<nadName>.<nadNamespace>.ovn.kubernetes.io/mac_address` ▯▯▯▯▯▯ NAD ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `<nadName>.<nadNamespace>.kubernetes.io/mac_address.<interfaceName>` ▯▯▯▯▯▯▯ MAC▯▯▯▯▯ annotation ▯▯▯ provider ▯ annotation▯▯▯▯▯▯▯ IPAM ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

```yaml
metadata:
  annotations:
    k8s.v1.cni.cncf.io/networks: '[{"name":"dhcp-net","namespace":"default","interface":"net1"}]'
    dhcp-net.default.kubernetes.io/mac_address.net1: "02:00:00:00:10:01"
```

MAC-only ▯▯▯ IP CR ▯▯▯ MAC ▯▯ IP▯▯▯ Pod ▯▯▯▯▯▯▯▯IPAM ▯▯▯▯▯▯▯ NIC ▯ MAC ▯▯▯▯▯▯ CIDR ▯▯▯▯▯▯▯▯▯▯▯▯▯ `cidrBlock` ▯MAC-only ▯▯▯▯▯▯▯▯▯ CIDR▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ ▯ Subnet▯

3.1.8 ▯▯▯▯▯▯▯

▯▯▯▯▯▯ `kube-ovn-cni` ▯▯▯ Pod ▯▯▯▯▯ ICMP ▯ ARP ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

3.1.9 Multicast-Snoop ⬚⬚

⬚⬚⬚⬚ subnet ⬚⬚ Pod ⬚⬚⬚⬚⬚⬚⬚⬚OVN ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ Pod⬚⬚⬚⬚⬚ subnet ⬚ multicast snoop ⬚⬚⬚OVN ⬚⬚⬚ `South Database` ⬚⬚⬚⬚⬚ `Multicast_Group` ⬚⬚ ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

```
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: sample1
spec:
  enableMulticastSnoop: true
```

3.1.10 Subnet MTU ⬚⬚

⬚⬚ Subnet ⬚ Pod ⬚ MTU⬚⬚⬚⬚⬚⬚⬚⬚ Subnet ⬚⬚ Pod ⬚⬚⬚

```
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: sample1
spec:
  mtu: 1300
```

3.1.11 ⬚⬚⬚⬚⬚⬚⬚

- IP ⬚⬚⬚
- ⬚⬚ VPC NAT ⬚⬚⬚⬚
- QoS ⬚⬚
- ⬚⬚⬚⬚⬚⬚
- DHCP ⬚⬚
- ⬚⬚⬚⬚⬚⬚⬚
- ⬚⬚⬚⬚⬚⬚⬚
- ⬚⬚ IP ⬚⬚

PDF Slack Support

2026⬚10⬚28⬚

2022⬚5⬚24⬚

GitHub  +5

3.1.12 ⬚⬚

3.2 ▒▒▒▒▒▒▒

▒ `Subnet` ▒▒▒ `spec.routed: true` ▒▒▒▒ Pod ▒▒▒▒▒▒▒▒▒▒IPv4 ▒ `/32` ▒IPv6 ▒ `/128` ▒▒▒▒▒▒▒▒▒▒

2026⊠10⊠28⊠

2026⊠10⊠28⊠

GitHub 

3.2.5 ⊠⊠

3.3 □□□□

Kube-OVN □□□□□ Pod □□ Namespace □□□□□□□□□□ IP □ Mac□ □□□□□□□□□□□□□□□□□Kube-OVN □□□□□□□□□□□□□□□□□□□□□□□□

- □□ Pod □□ IP/Mac□
- □□□□□□□□□□□□□□ IP/MAC□□□□□□□□□□□□□□□□□□□□□□
- Workload □□ IP Pool □□□□□□□□□□□□
- StatefulSet □□□□□□
- KubeVirt VM □□□□□□
- □□ Multus □□□□□□□□□□□□

3.3.1 □□ Pod □□ IP □ Mac

□□□□□ Pod □□□ annotation □□□ Pod □□□□□□□ IP/Mac, `kube-ovn-controller` □□□□□□□□□□□□□□□□□□□□

3.3.3 Workload □□ IP Pool □□□□

Kube-OVN □□□□ annotation `ovn.kubernetes.io/ip_pool` □ Workload□Deployment/StatefulSet/DaemonSet/Job/CronJob□□□□ IP□ `kube-ovn-controller` □□□□□ `ovn.kubernetes.io/ip_pool` □□□□ IP □□□□□□□□

IP Pool □ Annotation □□□□ `template` □□ `annotation` □□□□□ Kubernetes □□□ Workload □□□ □□□□□□□□ Workload □□□□□□□□□□□□□□□□□□□□□□

Deployment □□ IP □□

```
apiVersion: apps/v1
kind: Deployment
metadata:
  name: ippool
  labels:
    app: ippool
spec:
  replicas: 2
  selector:
    matchLabels:
      app: ippool
  template:
    metadata:
      labels:
        app: ippool
      annotations:
        ovn.kubernetes.io/ip_pool: 10.16.0.15,10.16.0.16,10.16.0.17 #
10.16.0.15,fd00:10:16::000E;10.16.0.16,fd00:10:16::000F;10.16.0.17,fd00:10:16::0010
    spec:
      containers:
      - name: ippool
        image: docker.io/library/nginx:alpine
```

□ Workload □□□□ IP □□□□□□□□□

1. `ovn.kubernetes.io/ip_pool` □□ IP □□□□□□□□□ CIDR □□
2. `ovn.kubernetes.io/ip_pool` □□ IP □□□□□□□ IP □□□
3. □ `ovn.kubernetes.io/ip_pool` □□ IP □□□□ replicas □□□□□□□ Pod □□□□□□□□□□□ Workload □□□□□□□□□□□□□□□ `ovn.kubernetes.io/ip_pool` □ IP □□□□

3.3.4 StatefulSet □□□□

StatefulSet □□□□□□ IP□□□□□□ Workload □□□□□□□ `ovn.kubernetes.io/ip_pool` □□□ Pod □□□ IP □□□

□□ StatefulSet □□□□□□□□□□□□□□□□□□□□□□□□□□□Kube-OVN □□□□□□□□□

1. Pod □□□□□□ `ovn.kubernetes.io/ip_pool` □□ IP□□□ StatefulSet □□□□ web□□ web-0 □□□ `ovn.kubernetes.io/ip_pool` □□□□□ IP□ web-1 □□□□□□ IP□□□□□□
2. StatefulSet Pod □□□□□□□□□□ OVN □□ logical_switch_port □□□□□□□□□ Pod □□□□□□ interface □□□□□ Pod □□□□ IP/Mac □□□□□□□□□□□ StatefulSet Volume □□□□□□□□□□
3. □□ 2 □□□□□□□□ `ovn.kubernetes.io/ip_pool` □□□ StatefulSet□Pod □□□□□□□□□□□ IP/Mac□□□□□□ StatefulSet □□□□□□□□□□□□□□□□□□□□

StatefulSet □□

```
apiVersion: apps/v1
kind: StatefulSet
metadata:
  name: web
spec:
  serviceName: "nginx"
  replicas: 2
  selector:
    matchLabels:
      app: nginx
  template:
    metadata:
      labels:
        app: nginx
    spec:
      containers:
      - name: nginx
        image: docker.io/library/nginx:alpine
        ports:
        - containerPort: 80
          name: web
```


2025 Kube-OVN Team

▯▯▯▯▯▯ StatefulSet ▯ Pod ▯▯ Pod IP ▯▯▯▯▯

▯▯ **StatefulSet Pod IP**

▯▯ StatefulSet ▯▯ IP ▯ Pod Name ▯▯▯▯▯▯▯▯▯▯▯ Statefulset ▯ `ovn.kubernetes.io/ip_pool` Annotation ▯▯▯▯ Pod ▯ IP▯

▯▯▯▯▯▯▯▯ StatefulSet Pod IP ▯▯▯▯▯▯ StatefulSet ▯▯▯▯ scale ▯ 0▯▯▯▯▯▯▯ Annotation ▯▯▯ StatefulSet ▯▯▯▯

3.3.5 KubeVirt VM ▯▯▯▯

▯▯ KubeVirt ▯▯▯ VM ▯▯▯ `kube-ovn-controller` ▯▯▯▯▯▯ StatefulSet Pod ▯▯▯▯▯ IP ▯▯▯▯▯▯▯▯ ▯▯▯ VM ▯▯▯▯▯▯▯▯▯▯▯

3.4 IP □□□

IP □□IPPool□□□□□□Subnet□□□□□□ IPAM □□□□□□□□□□ IP □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□Namespace□□□ Workload □□□

3.4.1 □□□□

□□□□□

```
apiVersion: kubeovn.io/v1
kind: IPPool
metadata:
  name: pool-1
spec:
  subnet: ovn-default
  ips:
  - "10.16.0.201"
  - "10.16.0.210/30"
  - "10.16.0.220..10.16.0.230"
  namespaces:
  - ns-1
  enableAddressSet: true
```

□□□□□ Workload□

```
apiVersion: apps/v1
kind: Deployment
metadata:
  name: ippool
  labels:
    app: ippool
spec:
  replicas: 2
  selector:
    matchLabels:
      app: ippool
  template:
    metadata:
      labels:
        app: ippool
      annotations:
        ovn.kubernetes.io/ip_pool: pool-1
    spec:
      containers:
      - name: ippool
        image: docker.io/library/nginx:alpine
```

3.4.2 □□□□ IP □

□ `ovn.kubernetes.io/ip_pool` □□□ IPPool □□□□□ `pool-1` □□□□□□□□ Pod □□□□□ `ovn.kubernetes.io/logical_switch` □□□□□□□ `pool-1.spec.subnet` □□ Pod □□□□ □□□ Pod □ `logical_switch` □ `cidr` □ `gateway` □□□

```
metadata:
  annotations:
    ovn.kubernetes.io/ip_pool: pool-1
```

□□□□□□ `ovn.kubernetes.io/logical_switch` □□□□□□ `IPPool.spec.subnet` □□□ □□□□□□□□□□□□□

□□□□□ Pod□□□□□ `<provider>.kubernetes.io/ip_pool` □□□ provider □□□□ IP □□provider □□□□□□ IPPool □□□□□□□□□□□□□□□□□□ `<provider>.kubernetes.io/logical_switch` □□□□□□□□□□□□□□□□□□□□ IP□ □□□□□ IP □□□□□□ IPv4□IPv6 □□□□□□□□□□□□□□□□□□□□□□□□□ □□□□ IP □□□□□□□□□□ IPPool □□□□□

`spec.namespaces` □□□ IPPool □□□□□□□□□□□□□□□□□□□□□□□□ IPPool □ Pod□ □□□□□□□□□□□□□□□□□ Pod □□□□□□□□□□□□□IPPool □□□□□□□□□□□ StatefulSet □ VM □ Pod □□□□□ □□□□□□ Workload □□□□□

2025 Kube-OVN Team

■■■■■

■■	■■	■■
subnet	■■■■■■■	■■
ips	■■■■■ IP ■■	■■ ■ ■■ .. ■■■■■■■ IPv6■■ ipCount ■■■
ipCount	■■■■■■■■■■	■■■■■ 1-32■■■■■■■■■■

3.5 □□□□□

□□□□□ Pod □□□ Annotations □□□□□□□□□□□□□□□□□□□

```
apiVersion: v1
kind: Pod
metadata:
  name: custom-routes
  annotations:
    ovn.kubernetes.io/routes: |
      [{
        "dst": "192.168.0.101/24",
        "gw": "10.16.0.254"
      }, {
        "gw": "10.16.0.254"
      }]
spec:
  containers:
  - name: nginx
    image: docker.io/library/nginx:alpine
```

> `dst` □□□□□□□□□□□□□□□

□□□□□□□ Deployment□DaemonSet □ StatefulSet□□□□ Annotation □□□□□□□□□ `.spec.template.metadata.annotations` □□□□□□□□

```
apiVersion: apps/v1
kind: Deployment
metadata:
  name: custom-routes
  labels:
    app: nginx
spec:
  replicas: 2
  selector:
    matchLabels:
      app: nginx
  template:
    metadata:
      labels:
        app: nginx
      annotations:
        ovn.kubernetes.io/routes: |
          [{
            "dst": "192.168.0.101/24",
            "gw": "10.16.0.254"
          }, {
            "gw": "10.16.0.254"
          }]
    spec:
      containers:
      - name: nginx
        image: docker.io/library/nginx:alpine
```

PDF Slack Support

2023□9□26□

2023□2□16□

GitHub 

3.5.1 □□

2025 Kube-OVN Team

3.6 EIP 和 SNAT 配置


> 介绍如何在 VPC 网络中使用 VPC 内部的 NAT网关。

- VPC Iptables NAT 网关
- VPC OVN NAT 网关

> 在 VPC 网络中使用浮动公网IP, 访问外部网络。

- 介绍如何在 VPC 内部创建 OVN NAT 网关并通过 pod annotation 进行浮动公网IP
- 介绍如何在 VPC 网络中使用 OVN NAT 网关，通过 provider-network、vlan、subnet CRD 资源对象创建 ovn-eip、ovn-dnat、ovn-fip、ovn-snat CRD 对象 EIP 和 NAT网关，详见VPC OVN NAT 网关
- 介绍如何在 VPC 网络中使用 Iptables NAT 网关，详见VPC Iptables NAT 网关

Kube-OVN 支持 OVN 的 L3 Gateway 功能为 Pod 提供 SNAT 和 EIP 两种 不同的 SNAT机制 Pod 可以共享 IP 地址也可以独享 EIP 两种 Pod、Pod 可以单独 EIP 两种模式



3.6.1 使用场景

- 支持 OVN 的 L3 Gateway 功能，通过 OVS 的隧道 Overlay 和 Underlay 两种 网络模式
- 支持 NAT 模式，使用 Underlay 网络的子网中的固定地址
- 支持 EIP 和 SNAT 共享或独享子网中的地址

3.6.2 配置说明

在 `kube-system` 命名空间 ConfigMap `ovn-external-gw-config` 中

```
apiVersion: v1
kind: ConfigMap
metadata:
  name: ovn-external-gw-config
  namespace: kube-system
data:
  type: "centralized"
  enable-external-gw: "true"
  external-gw-nodes: "kube-ovn-worker"
  external-gw-nic: "eth1"
  external-gw-addr: "172.56.0.1/16"
  nic-ip: "172.56.0.254/16"
  nic-mac: "16:52:f3:13:6a:25"
```

- `enable-external-gw`：是否启用 SNAT 和 EIP 功能
- `type`：`centralized` 或 `distributed`，默认为 `centralized` 模式，`distributed` 模式暂未实现
- `external-gw-nodes`：`centralized` 模式下的网关节点

2025 Kube-OVN Team

- `external-gw-nic` : ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚
- `external-gw-addr` : ⬚⬚⬚⬚⬚⬚⬚ IP ⬚⬚⬚⬚
- `nic-ip`,`nic-mac` : ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ IP ⬚ Mac⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ IP ⬚ Mac⬚

3.6.3 ⬚⬚ OVN ⬚ OVS ⬚⬚⬚⬚⬚⬚⬚⬚

⬚⬚ OVN-NB ⬚⬚⬚⬚⬚ `ovn-external` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ `ovn-cluster-ovn-external` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ chassis⬚

```
# kubectl ko nbctl show
switch 3de4cea7-1a71-43f3-8b62-435a57ef16a6 (external)
    port localnet.external
        type: localnet
        addresses: ["unknown"]
    port external-ovn-cluster
        type: router
        router-port: ovn-cluster-external
router e1eb83ad-34be-4ed5-9a02-fcc8b1d357c4 (ovn-cluster)
    port ovn-cluster-external
        mac: "ac:1f:6b:2d:33:f1"
        networks: ["172.56.0.100/16"]
        gateway chassis: [a5682814-2e2c-46dd-9c1c-6803ef0dab66]
```

⬚⬚ OVS ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ `br-external` ⬚⬚⬚

```
# kubectl ko vsctl ${gateway node name} show
e7d81150-7743-4d6e-9e6f-5c688232e130
    Bridge br-external
        Port br-external
            Interface br-external
                type: internal
        Port eth1
            Interface eth1
        Port patch-localnet.external-to-br-int
            Interface patch-localnet.external-to-br-int
                type: patch
                options: {peer=patch-br-int-to-localnet.external}
```

3.6.4 Pod ⬚⬚ EIP ⬚ SNAT

⬚⬚⬚⬚ Pod ⬚⬚⬚ `ovn.kubernetes.io/snat` ⬚ `ovn.kubernetes.io/eip` annotation ⬚⬚⬚⬚⬚ SNAT ⬚ EIP⬚

```
apiVersion: v1
kind: Pod
metadata:
  name: pod-snat
  annotations:
    ovn.kubernetes.io/snat: 172.56.0.200
spec:
  containers:
  - name: pod-snat
    image: docker.io/library/nginx:alpine
---
apiVersion: v1
kind: Pod
metadata:
  name: pod-eip
  annotations:
    ovn.kubernetes.io/eip: 172.56.0.233
spec:
  containers:
  - name: pod-eip
    image: docker.io/library/nginx:alpine
```

⬚⬚⬚ kubectl ⬚⬚⬚⬚⬚⬚⬚⬚ Pod ⬚⬚⬚⬚ EIP ⬚ SNAT ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ `ovn.kubernetes.io/routed` annotation ⬚⬚⬚⬚⬚⬚⬚⬚

```
kubectl annotate pod pod-eip ovn.kubernetes.io/eip=172.56.0.221 --overwrite
kubectl annotate pod pod-eip ovn.kubernetes.io/routed-
```

⬚ EIP ⬚ SNAT ⬚⬚⬚⬚⬚⬚ `ovn.kubernetes.io/routed` annotation ⬚⬚⬚⬚⬚⬚⬚⬚

3.6.5 ⬚⬚⬚⬚

`kube-ovn-controller` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ SNAT ⬚ EIP ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

- `--external-gateway-config-ns` : Configmap `ovn-external-gw-config` ⬚⬚ Namespace⬚⬚⬚⬚⬚ `kube-system` ⬚

2025 Kube-OVN Team

- `--external-gateway-net` : ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `external` ▯
- `--external-gateway-vlanid` : ▯▯▯▯ Vlan Tag ▯▯▯▯▯ 0▯▯▯▯▯ Vlan▯

PDF Slack Support

2026▯4▯28▯

2022▯5▯24▯

GitHub



3.6.6 ▯▯

2025 Kube-OVN Team

3.7 □□□□ QoS □□

Kube-OVN □□□□□□ Pod □□□□□□□□ QoS□

- □□□□□□ QoS□
- `linux-netem` □□□□□□□□□□□□□□□ QoS□□□□□□□□□□

> □□□□□ Pod □□ QoS □□□ Namespace □ Subnet □□□ QoS □□□

3.7.1 □□□□□□□□□ QoS

□□□□ QoS □□□□ Pod annotation □□□□□□□□□□□ Pod □□□□□□□□□□□ □□□□□□□□ `Mbit/s` □

□□□ `ovn.kubernetes.io/ingress_burst` □ `ovn.kubernetes.io/egress_burst` □□□□□□□□□□□□□□ burst□□□□ `Mbit` □□□□□□□burst □□□□□□□□ 80% □□□□□□ `0` □□□ burst□burst □□□□□□□□□□□□□□□□□□□□ Pod □□□□□□ `<provider>.kubernetes.io/ingress_burst` □ `<provider>.kubernetes.io/egress_burst` □□□ provider □□ □□□ burst□

```
apiVersion: v1
kind: Pod
metadata:
  name: qos
  namespace: ls1
  annotations:
    ovn.kubernetes.io/ingress_rate: "3"
    ovn.kubernetes.io/egress_rate: "1"
    ovn.kubernetes.io/ingress_burst: "2"
    ovn.kubernetes.io/egress_burst: "0"
spec:
  containers:
  - name: qos
    image: docker.io/library/nginx:alpine
```

□□ annotation □□□□ QoS□

```
kubectl annotate --overwrite  pod nginx-74d5899f46-d7qkn ovn.kubernetes.io/ingress_rate=3
#             burst    Mbit
kubectl annotate --overwrite pod nginx-74d5899f46-d7qkn ovn.kubernetes.io/ingress_burst=2 ovn.kubernetes.io/egress_burst=0
```

□□ **QoS** □□

□□□□□□□□□□□□□

```
kind: DaemonSet
apiVersion: apps/v1
metadata:
  name: perf
  namespace: ls1
  labels:
    app: perf
spec:
  selector:
    matchLabels:
      app: perf
  template:
    metadata:
      labels:
        app: perf
    spec:
      containers:
      - name: nginx
        image: docker.io/kubeovn/perf
```

□□□□□□ Pod □□□ iperf3 server□

```
# kubectl exec -it perf-4n4gt -n ls1 sh
# iperf3 -s
-----------------------------------------------------------
Server listening on 5201
-----------------------------------------------------------
```

□□□□□ Pod □□□□□ Pod□

2025 Kube-OVN Team

```
# kubectl exec -it perf-d4mqc -n ls1 sh
# iperf3 -c 10.66.0.12
Connecting to host 10.66.0.12, port 5201
[  4] local 10.66.0.14 port 51544 connected to 10.66.0.12 port 5201
[ ID] Interval           Transfer     Bandwidth       Retr  Cwnd
[  4]   0.00-1.00   sec  86.4 MBytes   725 Mbits/sec    3    350 KBytes
[  4]   1.00-2.00   sec  89.9 MBytes   754 Mbits/sec  118    473 KBytes
[  4]   2.00-3.00   sec   101 MBytes   848 Mbits/sec  184    586 KBytes
[  4]   3.00-4.00   sec   104 MBytes   875 Mbits/sec  217    671 KBytes
[  4]   4.00-5.00   sec   111 MBytes   935 Mbits/sec  175    772 KBytes
[  4]   5.00-6.00   sec   100 MBytes   840 Mbits/sec  658    598 KBytes
[  4]   6.00-7.00   sec   106 MBytes   890 Mbits/sec  742    668 KBytes
[  4]   7.00-8.00   sec   102 MBytes   857 Mbits/sec  764    724 KBytes
[  4]   8.00-9.00   sec  97.4 MBytes   817 Mbits/sec 1175    764 KBytes
[  4]   9.00-10.00  sec   111 MBytes   934 Mbits/sec 1083    838 KBytes
- - - - - - - - - - - - - - - - - - - - - - - - -
[ ID] Interval           Transfer     Bandwidth       Retr
[  4]   0.00-10.00  sec  1010 MBytes   848 Mbits/sec  5119             sender
[  4]   0.00-10.00  sec  1008 MBytes   846 Mbits/sec                  receiver

iperf Done.
```

□□□□□ Pod □□□□□ QoS□

```
kubectl annotate --overwrite  pod perf-4n4gt -n ls1 ovn.kubernetes.io/ingress_rate=30
```

□□□□□□ Pod □□□□□ Pod □□□

```
# iperf3 -c 10.66.0.12
Connecting to host 10.66.0.12, port 5201
[  4] local 10.66.0.14 port 52372 connected to 10.66.0.12 port 5201
[ ID] Interval           Transfer     Bandwidth       Retr  Cwnd
[  4]   0.00-1.00   sec  3.66 MBytes  30.7 Mbits/sec    2   76.1 KBytes
[  4]   1.00-2.00   sec  3.43 MBytes  28.8 Mbits/sec    0    104 KBytes
[  4]   2.00-3.00   sec  3.50 MBytes  29.4 Mbits/sec    0    126 KBytes
[  4]   3.00-4.00   sec  3.50 MBytes  29.3 Mbits/sec    0    144 KBytes
[  4]   4.00-5.00   sec  3.43 MBytes  28.8 Mbits/sec    0    160 KBytes
[  4]   5.00-6.00   sec  3.43 MBytes  28.8 Mbits/sec    0    175 KBytes
[  4]   6.00-7.00   sec  3.50 MBytes  29.3 Mbits/sec    0    212 KBytes
[  4]   7.00-8.00   sec  3.68 MBytes  30.9 Mbits/sec    0    294 KBytes
[  4]   8.00-9.00   sec  3.74 MBytes  31.4 Mbits/sec    0    398 KBytes
[  4]   9.00-10.00  sec  3.80 MBytes  31.9 Mbits/sec    0    526 KBytes
- - - - - - - - - - - - - - - - - - - - - - - - -
[ ID] Interval           Transfer     Bandwidth       Retr
[  4]   0.00-10.00  sec  35.7 MBytes  29.9 Mbits/sec    2             sender
[  4]   0.00-10.00  sec  34.5 MBytes  29.0 Mbits/sec                  receiver

iperf Done.
```

3.7.2 linux-netem QoS

> RHEL □□□□□□□□□□ netem □□□□□ yum install -y kernel-modules-extra && modprobe sch_netem

Pod □□□□□□ annotation □□ `linux-netem` □□ QoS□□□ netem □□□□□□□□□□ QoS □□□ Pod □ Ingress □□□□□□□

- `ovn.kubernetes.io/latency` □□□ Pod □□□□□□□□□□□□□□□ ms□
- `ovn.kubernetes.io/jitter` □□□ Pod □□□□□□□□□□□□□□□□□□ ms□
- `ovn.kubernetes.io/limit` □ □ `qdisc` □□□□□□□□□□□□□□□□□□□□□□□□□□□ 1000□
- `ovn.kubernetes.io/loss` □ □□□□□□□□□□□□□□□ float □□□□□□□□ 20□□□□□ 20% □□□□□□

PDF Slack Support

2026□10□29□

2022□5□24□

GitHub 

3.7.3 ▯▯

3.8 ▒▒▒▒

Kube-OVN ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ IPv4▒IPv6 ▒▒▒▒▒▒▒▒▒▒ ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ Kubernetes ▒▒▒▒▒▒▒▒▒ ▒▒▒▒ Kubernetes ▒▒▒▒▒▒▒▒

3.8.1 ▒▒▒▒▒▒▒

▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ CIDR ▒▒▒▒ `cidr=<IPv4 CIDR>,<IPv6 CIDR>` ▒▒▒▒ CIDR ▒▒▒▒▒ IPv4 ▒▒▒IPv6 ▒▒▒▒▒▒▒▒▒

```
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: ovn-test
spec:
  cidrBlock: 10.16.0.0/16,fd00:10:16::/64
  excludeIps:
  - 10.16.0.1
  - fd00:10:16::1
  gateway: 10.16.0.1,fd00:10:16::1
```

▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

```
  name: attach-ipv6-only
  annotations:
    k8s.v1.cni.cncf.io/networks: default/attachnet
    attachnet.default.ovn.kubernetes.io/ip_family: ipv6
spec:
  containers:
  - name: nginx
    image: docker.io/library/nginx:alpine
```

▯▯▯▯ NetworkAttachmentDefinition ▯▯▯▯▯▯▯▯▯▯▯▯▯ `interface` ▯▯▯▯Kube-OVN ▯▯▯▯▯▯▯▯ provider ▯▯ annotation▯ ▯▯ `net1` ▯▯▯ IPv4▯ `net2` ▯▯▯ IPv6▯

```
apiVersion: v1
kind: Pod
metadata:
  name: attach-mixed-family
  annotations:
    k8s.v1.cni.cncf.io/networks: '[{"name": "attachnet", "namespace": "default", "interface": "net1"}, {"name": "attachnet", "namespace": "default",
"interface": "net2"}]'
    attachnet.default.ovn.net1.kubernetes.io/ip_family: ipv4
    attachnet.default.ovn.net2.kubernetes.io/ip_family: ipv6
spec:
  containers:
  - name: nginx
    image: docker.io/library/nginx:alpine
```

▯▯▯▯▯▯▯▯▯ IP▯▯▯ `ovn.kubernetes.io/ip_address` ▯ `<provider>.kubernetes.io/ip_address` ▯▯▯▯ NetworkAttachmentDefinition ▯▯▯▯▯▯▯ `<nadName>.<nadNamespace>.kubernetes.io/ip_address.<interfaceName>` ▯▯▯ IP ▯▯▯▯▯▯▯ `ip_family` ▯▯▯

PDF Slack Support

2026▯7▯3▯

2022▯5▯24▯



GitHub 



3.8.4 ▯▯

2025 Kube-OVN Team

3.9 Webhook ⬚⬚

⬚⬚ Webhook ⬚⬚⬚ Kube-OVN ⬚⬚ CRD ⬚⬚⬚⬚⬚⬚⬚⬚ Webhook ⬚⬚⬚⬚ ⬚⬚ IP ⬚⬚⬚⬚⬚⬚⬚ Subnet CIDR ⬚⬚⬚⬚⬚⬚⬚⬚

```
    - kube-ovn-webhook.kube-system.svc.cluster.local
  issuerRef:
    group: cert-manager.io
    kind: Issuer
    name: existing-webhook-issuer
```

□ `existing-webhook-issuer` □□□□□□□□□□□□ □□□□ ClusterIssuer□□□□ `issuerRef.kind` □□ `ClusterIssuer` □ □□ Chart □□□□□□□□□ DNS □□□□□□□□□□□□□□□□□□□ □ □□□□□□□□□□□□

□□□□□□□□ `<chart-namespace>` □□□ Chart □□□ `namespace` □□ □□□□□ `webhook-certificate.yaml` □□ `metadata.namespace` □□□

□□□□□□□□□□ Certificate □□□□□□□□□□□□ `validatingWebhook.certificate.create: false` □□ Webhook□

```
kubectl apply -f webhook-certificate.yaml
kubectl wait --for=condition=Ready certificate/kube-ovn-webhook-serving-cert \
  -n "<chart-namespace>" --timeout=120s
```

Webhook □□ `kube-ovn-webhook-secret` □□ `tls.crt` □ `tls.key` □□□□ HTTPS □□□□□□□□□□□□ `ca.crt` □

cert-manager □ CA □□□□□□ Webhook □ `cert-manager.io/inject-ca-from` □□□□□□□ `kube-ovn-webhook-serving-cert` □ Certificate□ □□□□ Certificate □□□ Secret □□ `ca.crt` □□□ Webhook □ `caBundle` □ API server □□□ CA □□□□□ Webhook □□□□□□□□

□□ Webhook Deployment □□□□□ CA □□□□□□□□

```
kubectl rollout status deployment/kube-ovn-webhook -n "<chart-namespace>"
kubectl get validatingwebhookconfiguration kube-ovn-webhook \
  -o jsonpath='{.webhooks[0].clientConfig.caBundle}'
```

□□□□□□

□□ Chart □□□□□□□□□□□□□□□□ Certificate □□□□□□□□ Helm □□□□□□□□□□□□□□□ Certificate □□□□ Issuer□ □□□□□□□ Certificate □□□□□□□□□□ Secret □□□□□□□□□□ cert-manager □ Certificate □□□□□□□□□ □□ Helm □□□□□□□□□□□□□□□□□□□□□□□□ □□□□□□□ Certificate □□□□□□□

3.9.4 □□ Webhook □□

□□□□□ Pod□□□ Pod IP `10.16.0.15` □

```
# kubectl get pod -o wide
NAME                      READY   STATUS    RESTARTS   AGE     IP           NODE              NOMINATED NODE   READINESS GATES
static-7584848b74-fw9dm   1/1     Running   0          2d13h   10.16.0.15   kube-ovn-worker   <none>
```

□□ yaml □□□□ IP □ Pod□

```
apiVersion: v1
kind: Pod
metadata:
  annotations:
    ovn.kubernetes.io/ip_address: 10.16.0.15
    ovn.kubernetes.io/mac_address: 00:00:00:53:6B:B6
  labels:
    app: static
  managedFields:
  name: staticip-pod
  namespace: default
spec:
  containers:
  - image: docker.io/library/nginx:alpine
    imagePullPolicy: IfNotPresent
    name: qatest
```

□□□□ yaml □□□□□□ Pod □□□□□□ IP □□□□□

```
# kubectl apply -f pod-static.yaml
Error from server (annotation static-ip 10.16.0.15 is conflict with ip crd static-7584848b74-fw9dm.default, ip 10.16.0.15): error when creating "pod-
static.yaml": admission webhook "pod-ip-validating.kube-ovn.io" denied the request: annotation static-ip 10.16.0.15 is conflict with ip crd static-7584848b74-
fw9dm.default, ip 10.16.0.15
```

PDF Slack Support

2025 Kube-OVN Team

2026▯10▯25▯

2022▯5▯24▯



GitHub 



3.9.5 ▯▯

3.10 □□□□

□□□

3.10.3 □□□□

□□□□□□□□□□□□□□□□□□□□□□□□□□□□

1. Pod to Pod in the same Nodes

□□□□□□□

Size	TCP Latency	TCP Bandwidth	UDP Latency	UDP Lost Rate	UDP Bandwidth
64	12.7 us	289 Mbits/sec	12.6 us	(1.8%)	77.9 Mbits/sec
128	15.5 us	517 Mbits/sec	12.7 us	(0%)	155 Mbits/sec
512	12.2 us	1.64 Gbits/sec	12.4 us	(0%)	624 Mbits/sec
1k	13 us	2.96 Gbits/sec	11.4 us	(0.53%)	1.22 Gbits/sec
4k	18 us	7.67 Gbits/sec	25.7 us	(0.41%)	1.50 Gbits/sec

□□□□□□□

Size	TCP Latency	TCP Bandwidth	UDP Latency	UDP Lost Rate	UDP Bandwidth
64	11.9 us	324 Mbits/sec	12.2 us	(0.22%)	102 Mbits/sec
128	10.5 us	582 Mbits/sec	9.5 us	(0.21%)	198 Mbits/sec
512	11.6 us	1.84 Gbits/sec	9.32 us	(0.091%)	827 Mbits/sec
1k	10.5 us	3.44 Gbits/sec	10 us	(1.2%)	1.52 Gbits/sec
4k	16.7 us	8.52 Gbits/sec	18.2 us	(1.3%)	2.42 Gbits/sec

2. Pod to Pod in the different Nodes

□□□□□□□

Size	TCP Latency	TCP Bandwidth	UDP Latency	UDP Lost Rate	UDP Bandwidth
64	258 us	143 Mbits/sec	237 us	(61%)	28.5 Mbits/sec
128	240 us	252 Mbits/sec	231 us	(64%)	54.9 Mbits/sec
512	236 us	763 Mbits/sec	256 us	(68%)	194 Mbits/sec
1k	242 us	969 Mbits/sec	225 us	(62%)	449 Mbits/sec
4k	352 us	1.12 Gbits/sec	382 us	(0.71%)	21.4 Mbits/sec

□□□□□□□

Size	TCP Latency	TCP Bandwidth	UDP Latency	UDP Lost Rate	UDP Bandwidth
64	278 us	140 Mbits/sec	227 us	(24%)	59.6 Mbits/sec
128	249 us	265 Mbits/sec	265 us	(23%)	114 Mbits/sec
512	233 us	914 Mbits/sec	235 us	(21%)	468 Mbits/sec
1k	238 us	1.14 Gbits/sec	240 us	(15%)	891 Mbits/sec
4k	370 us	1.25 Gbits/sec	361 us	(0.43%)	7.54 Mbits/sec

2025 Kube-OVN Team

3. Node to Node

▯▯▯▯▯▯▯

Size	TCP Latency	TCP Bandwidth	UDP Latency	UDP Lost Rate	UDP Bandwidth
64	205 us	162 Mbits/sec	183 us	(11%)	74.2 Mbits/sec
128	222 us	280 Mbits/sec	206 us	(6.3%)	155 Mbits/sec
512	220 us	1.04 Gbits/sec	177 us	(20%)	503 Mbits/sec
1k	213 us	2.06 Gbits/sec	201 us	(8.6%)	1.14 Gbits/sec
4k	280 us	5.01 Gbits/sec	315 us	(37%)	1.20 Gbits/sec

▯▯▯▯▯▯▯

Size	TCP Latency	TCP Bandwidth	UDP Latency	UDP Lost Rate	UDP Bandwidth
64	204 us	157 Mbits/sec	204 us	(8.8%)	81.9 Mbits/sec
128	213 us	262 Mbits/sec	225 us	(19%)	136 Mbits/sec
512	220 us	1.02 Gbits/sec	227 us	(21%)	486 Mbits/sec
1k	217 us	1.79 Gbits/sec	218 us	(29%)	845 Mbits/sec
4k	275 us	5.27 Gbits/sec	336 us	(34%)	1.21 Gbits/sec

4. Pod to the Node where the Pod is located

▯▯▯▯▯▯▯

Size	TCP Latency	TCP Bandwidth	UDP Latency	UDP Lost Rate	UDP Bandwidth
64	12.2 us	295 Mbits/sec	12.7 us	(0.27%)	74.1 Mbits/sec
128	14.1 us	549 Mbits/sec	10.6 us	(0.41%)	153 Mbits/sec
512	13.5 us	1.83 Gbits/sec	12.7 us	(0.23%)	586 Mbits/sec
1k	12 us	2.69 Gbits/sec	13 us	(1%)	1.16 Gbits/sec
4k	18.9 us	4.51 Gbits/sec	21.8 us	(0.42%)	1.81 Gbits/sec

▯▯▯▯▯▯▯

Size	TCP Latency	TCP Bandwidth	UDP Latency	UDP Lost Rate	UDP Bandwidth
64	10.4 us	335 Mbits/sec	12.2 us	(0.75%)	95.4 Mbits/sec
128	12.1 us	561 Mbits/sec	11.3 us	(0.25%)	194 Mbits/sec
512	11.6 us	1.87 Gbits/sec	10.7 us	(0.66%)	745 Mbits/sec
1k	12.7 us	3.12 Gbits/sec	10.9 us	(1.2%)	1.46 Gbits/sec
4k	16.5 us	8.23 Gbits/sec	17.9 us	(1.5%)	2.51 Gbits/sec

2025 Kube-OVN Team

5. Pod to the Node where the Pod is not located

□□□□□□□

Size	TCP Latency	TCP Bandwidth	UDP Latency	UDP Lost Rate	UDP Bandwidth
64	234 us	153 Mbits/sec	232 us	(63%)	29.4 Mbits/sec
128	237 us	261 Mbits/sec	238 us	(49%)	76.1 Mbits/sec
512	231 us	701 Mbits/sec	238 us	(57%)	279 Mbits/sec
1k	256 us	1.05 Gbits/sec	228 us	(56%)	524 Mbits/sec
4k	330 us	1.08 Gbits/sec	359 us	(1.5%)	35.7 Mbits/sec

□□□□□□□

Size	TCP Latency	TCP Bandwidth	UDP Latency	UDP Lost Rate	UDP Bandwidth
64	283 us	141 Mbits/sec	230 us	(26%)	55.8 Mbits/sec
128	234 us	255 Mbits/sec	234 us	(25%)	113 Mbits/sec
512	246 us	760 Mbits/sec	234 us	(22%)	458 Mbits/sec
1k	268 us	1.23 Gbits/sec	242 us	(20%)	879 Mbits/sec
4k	326 us	1.20 Gbits/sec	369 us	(0.5%)	7.87 Mbits/sec

6. Pod to the cluster ip service

□□□□□□□

Size	TCP Latency	TCP Bandwidth	UDP Latency	UDP Lost Rate	UDP Bandwidth
64	237 us	133 Mbits/sec	213 us	(65%)	25.5 Mbits/sec
128	232 us	271 Mbits/sec	222 us	(62%)	54.8 Mbits/sec
512	266 us	800 Mbits/sec	234 us	(60%)	232 Mbits/sec
1k	248 us	986 Mbits/sec	239 us	(50%)	511 Mbits/sec
4k	314 us	1.03 Gbits/sec	367 us	(0.6%)	13.2 Mbits/sec

TCP-Conn-Number	QPS	Avg-Resp-Time	Stdev-Resp-Time	Max-Resp-Time
10	14305.17	0.87ms	1.48ms	24.46ms
100	29082.07	3.87ms	4.35ms	102.85ms

□□□□□□

Size	TCP Latency	TCP Bandwidth	UDP Latency	UDP Lost Rate	UDP Bandwidth
64	241 us	145 Mbits/sec	225 us	(19%)	60.2 Mbits/sec
128	245 us	261 Mbits/sec	212 us	(15%)	123 Mbits/sec
512	252 us	821 Mbits/sec	219 us	(14%)	499 Mbits/sec
1k	253 us	1.08 Gbits/sec	242 us	(16%)	852 Mbits/sec
4k	320 us	1.32 Gbits/sec	360 us	(0.47%)	6.70 Mbits/sec

TCP-Conn-Number	QPS	Avg-Resp-Time	Stdev-Resp-Time	Max-Resp-Time
10	13634.07	0.96ms	1.72ms	30.07ms
100	30215.23	3.59ms	3.20ms	77.56ms

7. Host to the Node port service where the Pod is not located on the target Node

□□□□□□

TCP-Conn-Number	QPS	Avg-Resp-Time	Stdev-Resp-Time	Max-Resp-Time
10	14802.73	0.88ms	1.66ms	31.49ms
100	29809.58	3.78ms	4.12ms	105.34ms

□□□□□□

TCP-Conn-Number	QPS	Avg-Resp-Time	Stdev-Resp-Time	Max-Resp-Time
10	14273.33	0.90ms	1.60ms	37.16ms
100	30757.81	3.62ms	3.41ms	59.78ms

8. Host to the Node port service where the Pod is located on the target Node

□□□□□□

TCP-Conn-Number	QPS	Avg-Resp-Time	Stdev-Resp-Time	Max-Resp-Time
10	15402.39	802.50us	1.42ms	30.91ms
100	29424.66	4.05ms	4.31ms	90.60ms

□□□□□□

TCP-Conn-Number	QPS	Avg-Resp-Time	Stdev-Resp-Time	Max-Resp-Time
10	14649.21	0.91ms	1.72ms	43.92ms
100	32143.61	3.66ms	3.76ms	67.02ms

PDF Slack Support

2025□11□20□

2022□5□24□

GitHub 

3.10.4 □□

3.11 LoadBalancer Service

Kube-OVN VPC VPC VPC

VPC VPC VPC VPC `LoadBalancer` Service LoadBalancerIP VPC Service

1. `multus-cni` `macvlan cni`
2. LoadBalancer Service VPC `vpc-nat-gw` macvlan
3. `VPC` VPC LoadBalancer VPC VPC

3.11.1 VPC LoadBalancer Service

kube-system namespace deployment `kube-ovn-controller` `args` `--enable-lb-svc=true` false

```
containers:
- args:
  - /kube-ovn/start-controller.sh
  - --default-cidr=10.16.0.0/16
  - --default-gateway=10.16.0.1
  - --default-gateway-check=true
  - --enable-lb-svc=true                 #       true
```

NetworkAttachmentDefinition CRD

yaml `net-attach-def`

```
apiVersion: "k8s.cni.cncf.io/v1"
kind: NetworkAttachmentDefinition
metadata:
  name: lb-svc-attachment
  namespace: kube-system
spec:
  # master                    eth0 / ens192 / bond0
  config: '{
      "cniVersion": "0.3.0",
      "type": "macvlan",
      "master": "eth0",
      "mode": "bridge"
    }'
```

`eth0` `master`

Subnet

Subnet LoadBalancer Service LoadBalancerIP Underlay Subnet

yaml

```
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: attach-subnet
spec:
  protocol: IPv4
  provider: lb-svc-attachment.kube-system    # provider             net-attach-def     Name.Namespace
  cidrBlock: 172.18.0.0/16
  gateway: 172.18.0.1
  excludeIps:
  - 172.18.0.0..172.18.0.10
```

Subnet `provider` `ovn` `.ovn` Kube-OVN `logical switch`

`provider` `ovn` `.ovn` Kube-OVN IPAM IP

2025 Kube-OVN Team

□□ LoadBalancer Service

□□□□ yaml□□□ LoadBalancer Service□

```
apiVersion: v1
kind: Service
metadata:
  annotations:
    lb-svc-attachment.kube-system.kubernetes.io/logical_switch: attach-subnet   #
    ovn.kubernetes.io/attachmentprovider: lb-svc-attachment.kube-system          #
  labels:
    app: dynamic
  name: test-service
  namespace: default
spec:
  loadBalancerIP: 172.18.0.18                                                    #
  ports:
    - name: test
      protocol: TCP
      port: 80
      targetPort: 80
  selector:
    app: dynamic
  sessionAffinity: None
  type: LoadBalancer
```

□ yaml □□annotation `ovn.kubernetes.io/attachmentprovider` □□□□□□□□□□□□□□□ `net-attach-def` □□□ Name.Namespace □□□□ annotation □□□□□ Pod □□ □□ `net-attach-def` □□□

□□□□ annotation □□□□□□□□□□□□□□□□annotation key □□□ net-attach-def □□□ `Name.Namespace.kubernetes.io/logical_switch` □□□□□ □□ □□□□□□□□ LoadBalancerIP □□□□□□□□□□□□□□□□□□□□□□□□□ LoadBalancerIP □□□

□□□□□□□□ LoadBalancerIP □□□□□□□□ `spec.loadBalancerIP` □□□□□□□□□□□□□□□□□□□□□□□

□□□ yaml □□ Service □□□ Service □ Namespace □□□□□□ Pod □□□□□

```
# kubectl get pod
NAME                                    READY   STATUS    RESTARTS   AGE
lb-svc-test-service-6869d98dd8-cjvll    1/1     Running   0          107m
# kubectl get svc
NAME              TYPE           CLUSTER-IP       EXTERNAL-IP   PORT(S)        AGE
test-service      LoadBalancer   10.109.201.193   172.18.0.18   80:30056/TCP   107m
```

□□ `service.spec.loadBalancerIP` □□□□□□□□□□□□□□□ service external-ip □□□□□□□□□□□□□□□□□□□□□□□□

□□□□ Pod □ yaml □□□□□□□□□□□□□□□□□□□

```
# kubectl get pod -o yaml lb-svc-test-service-6869d98dd8-cjvll
apiVersion: v1
kind: Pod
metadata:
  annotations:
    k8s.v1.cni.cncf.io/network-status: |-
      [{
          "name": "kube-ovn",
          "ips": [
              "10.16.0.2"
          ],
          "default": true,
          "dns": {}
      },{
          "name": "default/test-service",
          "interface": "net1",
          "mac": "ba:85:f7:02:9f:42",
          "dns": {}
      }]
    k8s.v1.cni.cncf.io/networks: default/test-service
    k8s.v1.cni.cncf.io/networks-status: |-
      [{
          "name": "kube-ovn",
          "ips": [
              "10.16.0.2"
          ],
          "default": true,
          "dns": {}
      },{
          "name": "default/test-service",
          "interface": "net1",
          "mac": "ba:85:f7:02:9f:42",
          "dns": {}
      }]
    ovn.kubernetes.io/allocated: "true"
    ovn.kubernetes.io/cidr: 10.16.0.0/16
    ovn.kubernetes.io/gateway: 10.16.0.1
```

```
    ovn.kubernetes.io/ip_address: 10.16.0.2
    ovn.kubernetes.io/logical_router: ovn-cluster
    ovn.kubernetes.io/logical_switch: ovn-default
    ovn.kubernetes.io/mac_address: 00:00:00:45:F4:29
    ovn.kubernetes.io/pod_nic_type: veth-pair
    ovn.kubernetes.io/routed: "true"
    test-service.default.kubernetes.io/allocated: "true"
    test-service.default.kubernetes.io/cidr: 172.18.0.0/16
    test-service.default.kubernetes.io/gateway: 172.18.0.1
    test-service.default.kubernetes.io/ip_address: 172.18.0.18
    test-service.default.kubernetes.io/logical_switch: attach-subnet
    test-service.default.kubernetes.io/mac_address: 00:00:00:AF:AA:BF
    test-service.default.kubernetes.io/pod_nic_type: veth-pair
```

□□ Service □□□□

```
# kubectl get svc -o yaml test-service
apiVersion: v1
kind: Service
metadata:
  annotations:
    ovn.kubernetes.io/vpc: ovn-cluster
    test-service.default.kubernetes.io/logical_switch: attach-subnet
  creationTimestamp: "2022-06-15T09:01:58Z"
  labels:
    app: dynamic
  name: test-service
  namespace: default
  resourceVersion: "38485"
  uid: 161edee1-7f6e-40f5-9e09-5a52c44267d0
spec:
  allocateLoadBalancerNodePorts: true
  clusterIP: 10.109.201.193
  clusterIPs:
  - 10.109.201.193
  externalTrafficPolicy: Cluster
  internalTrafficPolicy: Cluster
  ipFamilies:
  - IPv4
  ipFamilyPolicy: SingleStack
  ports:
  - name: test
    nodePort: 30056
    port: 80
    protocol: TCP
    targetPort: 80
  selector:
    app: dynamic
  sessionAffinity: None
  type: LoadBalancer
status:
  loadBalancer:
    ingress:
    - ip: 172.18.0.18
```

3.11.2 □□ LoadBalancerIP □□

□□□□ yaml, □□□□ Pod□□□ Service □ Endpoints □□□□□

```
apiVersion: apps/v1
kind: Deployment
metadata:
  labels:
    app: dynamic
  name: dynamic
  namespace: default
spec:
  replicas: 2
  selector:
    matchLabels:
      app: dynamic
  strategy:
    rollingUpdate:
      maxSurge: 25%
      maxUnavailable: 25%
    type: RollingUpdate
  template:
    metadata:
      creationTimestamp: null
      labels:
        app: dynamic
    spec:
      containers:
      - image: docker.io/library/nginx:alpine
        imagePullPolicy: IfNotPresent
        name: nginx
      dnsPolicy: ClusterFirst
      restartPolicy: Always
```

▯▯ Service ▯ `LoadBalancerIP:Port` ▯▯▯▯▯▯▯▯▯▯▯▯▯

```
# curl 172.18.0.18:80
<html>
<head>
        <title>Hello World!</title>
        <link href='//fonts.googleapis.com/css?family=Open+Sans:400,700' rel='stylesheet' type='text/css'>
        <style>
        body {
                background-color: white;
                text-align: center;
                padding: 50px;
                font-family: "Open Sans","Helvetica Neue",Helvetica,Arial,sans-serif;
        }
        #logo {
                margin-bottom: 40px;
        }
        </style>
</head>
<body>
                <h1>Hello World!</h1>
                                <h3>Links found</h3>
        <h3>I am on  dynamic-7d8d7874f5-hsgc4</h3>
        <h3>Cookie                  =</h3>
                                    <b>KUBERNETES</b> listening in 443 available at tcp://10.96.0.1:443<br />
                                        <h3>my name is hanhouchao!</h3>
                        <h3> RequestURI='/'</h3>
</body>
</html>
```

▯▯ Service ▯▯▯ Pod▯▯▯▯▯▯▯▯

```
# ip a
4: net1@if62: <BROADCAST,MULTICAST,UP,LOWER_UP> mtu 1500 qdisc noqueue state UP group default
    link/ether ba:85:f7:02:9f:42 brd ff:ff:ff:ff:ff:ff link-netnsid 0
    inet 172.18.0.18/16 scope global net1
       valid_lft forever preferred_lft forever
    inet6 fe80::b885:f7ff:fe02:9f42/64 scope link
       valid_lft forever preferred_lft forever
36: eth0@if37: <BROADCAST,MULTICAST,UP,LOWER_UP> mtu 1400 qdisc noqueue state UP group default
    link/ether 00:00:00:45:f4:29 brd ff:ff:ff:ff:ff:ff link-netnsid 0
    inet 10.16.0.2/16 brd 10.16.255.255 scope global eth0
       valid_lft forever preferred_lft forever
    inet6 fe80::200:ff:fe45:f429/64 scope link
       valid_lft forever preferred_lft forever

# ip rule
0: from all lookup local
32764: from all iif eth0 lookup 100
32765: from all iif net1 lookup 100
32766: from all lookup main
32767: from all lookup default

# ip route show table 100
default via 172.18.0.1 dev net1
10.109.201.193 via 10.16.0.1 dev eth0
172.18.0.0/16 dev net1 scope link

# iptables -t nat -L -n -v
Chain PREROUTING (policy ACCEPT 0 packets, 0 bytes)
 pkts bytes target     prot opt in     out     source               destination
    0     0 DNAT       tcp  --  *      *       0.0.0.0/0            172.18.0.18          tcp dpt:80 to:10.109.201.193:80

Chain INPUT (policy ACCEPT 0 packets, 0 bytes)
 pkts bytes target     prot opt in     out     source               destination

Chain OUTPUT (policy ACCEPT 0 packets, 0 bytes)
 pkts bytes target     prot opt in     out     source               destination

Chain POSTROUTING (policy ACCEPT 0 packets, 0 bytes)
 pkts bytes target     prot opt in     out     source               destination
    0     0 MASQUERADE  all  --  *      *       0.0.0.0/0            10.109.201.193
```

▯▯ lb service Pod ▯ nodeSelector

▯▯▯▯▯▯ `ovn-vpc-nat-config` ConfigMap ▯▯ `nodeSelector` ▯▯▯ LoadBalancer service ▯▯ Pod ▯▯▯▯▯▯

```
apiVersion: v1
data:
  image: docker.io/kubeovn/vpc-nat-gateway:v1.17.0
  nodeSelector: |
    kubernetes.io/hostname: kube-ovn-control-plane
    kubernetes.io/os: linux
kind: ConfigMap
metadata:
  name: ovn-vpc-nat-config
  namespace: kube-system
```

PDF Slack Support

2026⬚11⬚3⬚

2022⬚7⬚19⬚



GitHub 

+3

3.11.3 ⬚⬚

2025 Kube-OVN Team

3.12 ████████

Kube-OVN ████████████████████████████████ Prometheus ████████████

████ kube-prometheus ████ CRD ███████ Prometheus ██████ ████████ kube-prometheus ███████ CRD▯Kube-OVN ████████████████ Kube-OVN ████▯

3.12.1 ▯▯ ServiceMonitor

Kube-OVN ▯▯ `ServiceMonitor` CRD ████████

```
#
kubectl apply -f https://raw.githubusercontent.com/kubeovn/kube-ovn/master/dist/monitoring/pinger-monitor.yaml
# kube-ovn-controller
kubectl apply -f https://raw.githubusercontent.com/kubeovn/kube-ovn/master/dist/monitoring/controller-monitor.yaml
# kube-ovn-cni
kubectl apply -f https://raw.githubusercontent.com/kubeovn/kube-ovn/master/dist/monitoring/cni-monitor.yaml
# ovn
kubectl apply -f https://raw.githubusercontent.com/kubeovn/kube-ovn/master/dist/monitoring/ovn-monitor.yaml
```

Prometheus ████████████ 15s████████████ yaml ▯▯ `interval` ███

3.12.2 ▯▯ kube-ovn-v2 Helm Chart ███████

`kube-ovn-v2` Helm Chart ████████ `PrometheusRule` ▯ Grafana Dashboard ConfigMaps▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Prometheus Operator CRDs▯

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `monitoring` ▯▯▯▯▯

```
prometheusRule:
  enabled: true
  namespace: monitoring
  labels:
    release: kube-prometheus-stack
grafanaDashboards:
  enabled: true
  namespace: monitoring
  datasource: Prometheus
```

`prometheusRule.namespace` ▯ `grafanaDashboards.namespace` ▯▯▯▯▯▯▯▯ `.Values.namespace` ▯▯▯▯▯ `monitoring` ▯▯▯▯▯▯▯▯▯▯▯▯ `helm --namespace kube-system` ▯▯▯ Helm release ▯▯▯▯▯▯▯▯▯▯▯▯▯ override ▯▯▯▯▯▯▯▯▯▯▯ `ServiceMonitor` ▯▯▯▯▯▯▯ Chart ▯▯▯▯▯▯ `.Values.namespace` ▯▯▯▯▯▯

▯▯▯▯▯▯▯▯▯▯▯▯▯

```
helm upgrade --install kube-ovn oci://ghcr.io/kubeovn/charts/kube-ovn-v2 \
  --namespace kube-system \
  --values monitoring-values.yaml
```

`prometheusRule` ▯▯ controller▯pinger▯subnet ▯ OVSDB ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ controller▯OVN monitor▯pinger ▯ agent ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ ServiceMonitor ▯ ▯▯ `controller.serviceMonitor.enabled` ▯ `monitor.serviceMonitor.enabled` ▯ `pinger.serviceMonitor.enabled` ▯ `agent.serviceMonitor.enabled` ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ job ▯ metric labels▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

`KubeOvnControllerAbsent` ▯▯ `absent(up{job="kube-ovn-controller"})` ▯▯▯▯▯▯▯▯ target▯▯▯▯▯▯▯▯ 15m ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Alertmanager ▯ silence/inhibit ▯▯▯▯▯▯▯▯ `prometheusRule.enabled` ▯▯▯▯▯▯▯ `prometheusRule.additionalGroups` ▯▯▯▯▯ `PrometheusRule.spec.groups[]` ▯▯▯▯▯▯▯▯▯▯

`grafanaDashboards.datasource` ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Prometheus ▯▯▯▯▯▯▯▯▯▯▯ `Prometheus` ▯Chart ▯▯▯▯ Dashboard ▯▯▯▯▯ `${DS_PROMETHEUS}` ▯▯▯▯▯▯ ▯▯▯▯▯▯

▯▯ `grafanaDashboards.enabled` ▯▯Helm ▯▯▯▯▯▯ `grafana_dashboard: "1"` ▯▯▯ Dashboard ConfigMaps▯▯▯▯ Grafana sidecar ▯▯▯▯▯▯▯▯▯▯ sidecar ▯▯▯▯▯▯▯▯ ▯▯▯▯▯▯ Dashboard ▯▯▯

3.12.3 ▯▯ Grafana ▯▯

Kube-OVN ▯▯▯▯▯▯▯▯▯▯▯ Grafana Dashboard ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

▯▯▯▯ Dashboard ▯▯▯

2025 Kube-OVN Team

```
#
wget https://raw.githubusercontent.com/kubeovn/kube-ovn/master/dist/monitoring/pinger-grafana.json
# kube-ovn-controller
wget https://raw.githubusercontent.com/kubeovn/kube-ovn/master/dist/monitoring/controller-grafana.json
# kube-ovn-cni
wget https://raw.githubusercontent.com/kubeovn/kube-ovn/master/dist/monitoring/cni-grafana.json
# ovn
wget https://raw.githubusercontent.com/kubeovn/kube-ovn/master/dist/monitoring/ovn-grafana.json
# ovs
wget https://raw.githubusercontent.com/kubeovn/kube-ovn/master/dist/monitoring/ovs-grafana.json
```

▒ Grafana ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ Prometheus ▒▒▒▒▒▒▒ Dashboard▒

`kube-ovn-controller` ▒▒▒▒▒▒▒▒▒▒



`kube-ovn-pinger`



`kube-ovn-cni`



PDF Slack Support

2025 Kube-OVN Team

2026⊠10⊠29⊠

2022⊠5⊠23⊠

GitHub 

3.12.4 ⊠⊠

3.13 ▯▯

3.13.1 NetworkPolicy ▯▯

NetworkPolicy ▯ Kubernetes ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Pod ▯▯▯▯ Pod ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Kube-OVN ▯▯ OVN ▯ ACL ▯▯▯▯▯▯ Kubernetes NetworkPolicy ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

Kube-OVN ▒▒▒▒▒▒ Pod ▒▒▒▒▒▒▒▒▒▒ Named Port▒ ▒▒▒▒▒▒▒▒▒ Pod ▒▒▒▒▒▒ `http` ▒▒▒ TCP 8080 ▒ TCP 8081▒ ▒▒▒▒▒▒▒▒▒▒

⬚⬚⬚⬚⬚⬚⬚

⬚ Kube-OVN v1.13.0 ⬚⬚⬚⬚⬚⬚⬚ `ovn.kubernetes.io/log_acl_actions` annotation ⬚⬚⬚⬚⬚⬚Allow⬚⬚⬚⬚⬚

```yaml
apiVersion: networking.k8s.io/v1
kind: NetworkPolicy
metadata:
  name: allow-from-client
  namespace: default
  annotations:
    ovn.kubernetes.io/enable_log: "true"
    ovn.kubernetes.io/log_acl_actions: "allow"
spec:
  podSelector:
    matchLabels:
      app: web
  policyTypes:
  - Ingress
  ingress:
  - from:
    - podSelector:
        matchLabels:
          app: client
```

`ovn.kubernetes.io/log_acl_actions` ⬚⬚⬚⬚⬚⬚

- `drop` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚
- `allow` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚
- `allow,drop` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

```
# tail -f /var/log/ovn/ovn-controller.log
2024-08-14T09:27:49.590Z|00004|acl_log(ovn_pinctrl0)|INFO|name="np/allow-from-client.default/ingress/IPv4/0", verdict=allow, severity=info, direction=to-
lport:
icmp,vlan_tci=0x0000,dl_src=96:7b:b0:2f:a0:1a,dl_dst=a6:e5:1b:c2:1b:f8,nw_src=10.16.0.7,nw_dst=10.16.0.12,nw_tos=0,nw_ecn=0,nw_ttl=64,nw_frag=no,icmp_type=8,icm
```

⬚⬚⬚⬚⬚⬚

⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ `ovn.kubernetes.io/acl_log_meter_rate` annotation ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

```yaml
apiVersion: networking.k8s.io/v1
kind: NetworkPolicy
metadata:
  name: allow-from-client
  namespace: default
  annotations:
    ovn.kubernetes.io/enable_log: "true"
    ovn.kubernetes.io/log_acl_actions: "allow"
    ovn.kubernetes.io/acl_log_meter_rate: "100"
spec:
  podSelector:
    matchLabels:
      app: web
  policyTypes:
  - Ingress
  ingress:
  - from:
    - podSelector:
        matchLabels:
          app: client
```

`ovn.kubernetes.io/acl_log_meter_rate` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚/⬚⬚⬚⬚⬚⬚⬚ `100` ⬚⬚⬚⬚⬚⬚⬚⬚ 100 ⬚⬚⬚⬚

⬚⬚⬚⬚⬚⬚

⬚ annotation `ovn.kubernetes.io/enable_log` ⬚⬚⬚ `false` ⬚⬚⬚⬚⬚⬚⬚

```
kubectl annotate networkpolicy -n default allow-from-client ovn.kubernetes.io/enable_log=false --overwrite
```

⬚⬚⬚⬚⬚⬚⬚

Kube-OVN ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

- **standard**⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ NetworkPolicy ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ IP ⬚⬚⬚⬚⬚⬚⬚⬚⬚
- **lax**⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

⬚⬚⬚⬚⬚ NetworkPolicy ⬚⬚⬚ annotation ⬚⬚⬚⬚⬚⬚⬚

```yaml
apiVersion: networking.k8s.io/v1
kind: NetworkPolicy
metadata:
  name: example-policy
  namespace: default
  annotations:
    ovn.kubernetes.io/network_policy_enforcement: "lax"
spec:
  podSelector: {}
  policyTypes:
  - Ingress
```

⬚⬚⬚⬚ Kube-OVN ⬚⬚⬚⬚⬚⬚⬚⬚⬚ `--np-enforcement` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

⬚⬚⬚⬚

- ACL ⬚⬚
- ⬚⬚⬚ NetworkPolicy

PDF Slack Support

2026⬚11⬚3⬚

2025⬚10⬚23⬚

GitHub

+1

⬚⬚

3.13.2 Network Policy API

Kube-OVN 通过 `network-policy-api v0.3.0` 引入 `v1beta1` 版本的 `ClusterNetworkPolicy` 和CNP和API，为 ANP/CNP 提供了 DNS 名称匹配 和[illegible]DNS resolver 支持

使用 `protocols` 字段

CNP 支持通过 `protocols` 字段指定协议和端口

```
protocols:
  - tcp:
      destinationPort:
        number: 443
  - udp:
      destinationPort:
        range:
          start: 8000
          end: 9000
```

支持 TCP、UDP 和 SCTP 协议，通过 `destinationNamedPort` 可以匹配 Pod 中定义的命名端口。Pod 可以通过标签选择器、Namespace 标签或Node、Network 标签来选择 peer 范围。Pod[illegible]

如果 `protocols` 字段为空，则匹配 peer 的 DNS resolver[illegible] `Accept` 。

理解 **Tier**

`spec.priority` 字段范围为 `0` 到 `399` 的整数，对应 Tier 内的 CNP 规则。priority、controller 和内置的 ACL、ANP/BANP 的 priority 规则。Network Policy API 的 规则。CNP 内的 priority 规则。

兼容性

使用 `network-policy-api v0.3.0` 的 controller 和 CRD 规则。CNP 中的 `ports` 和 `protocols` 字段。`ports`

v0.3.0 CRD 中的 `v1alpha2` 和 `v1beta1` 中的 `v1beta1` 字段。v0.3.0 的 `protocols` schema 规则。conversion webhook字段。schema 的 `v1alpha2` 字段。`v1beta1` 字段。CRD 中的 `ports` 字段。`protocols` 在v1.16 中的 `ports` 和 CNP 中的 `apiVersion: v1alpha2` 的 字段。

ANP 和 BANP 规则。`v1alpha1` CRD。`network-policy-api v0.3.0` 中的 CNP conformance profile中的 ANP/BANP 测试。

PDF Slack Support

2026年11月7日

2026年11月7日

GitHub 

2025 Kube-OVN Team

3.13.3 ??? NetworkPolicy ACL ??

Kube-OVN ?????? `networking.k8s.io/v1` `NetworkPolicy` ??? OVN ACL ??

??????????

- `allow` ?????????? NetworkPolicy ????????? `allow-related` ACL?
- `default-deny` ???????????????????? ACL?

`default-deny` ??????????? ACL ? NetworkPolicy?????????????????????????? Pod ??????? default-deny ACL ???????????????????? default-deny ???????????

??????

???? ACL ???? OVN 24.09 ??????????????????????????

- OVS 3.4 ???????
- ?? Linux ?? datapath???? userspace ? DPDK datapath?
- ?? OVS datapath ?????? `psample=true` ?
- OVS schema ?? `Flow_Sample_Collector_Set.local_group_id` ?
- Linux ???? `psample` generic-netlink family?

??? Kubernetes NetworkPolicy ?????? NetworkPolicy ???????? Kube-OVN ACL ????????? DHCP ????????? ACL?SecurityGroup?AdminNetworkPolicy? BaselineAdminNetworkPolicy?ClusterNetworkPolicy ???? ACL ????

??????? conntrack???????????????? OVN ??? conntrack ????????????????

????

?? Helm chart ?????? `aclSampling` ??????? v2 chart ??????????

```
aclSampling:
  enabled: true
  setID: 142
  localGroupID: 142
  appIDNew: 102
  appIDEstablished: 103
  collectorIDAllow: 1
  collectorIDDefaultDeny: 2
  allowProbabilityPercent: 1
  defaultDenyProbabilityPercent: 100
```

```
helm upgrade --install kube-ovn ./charts/kube-ovn-v2 \
  --set aclSampling.enabled=true
```

???? classic chart???? `./charts/kube-ovn` ????????????????????? CNI agent ???????????

???? manifest ????????? ACL ?????????????????????????? Helm ??????

```
ENABLE_ACL_SAMPLING=true \
ACL_SAMPLING_SET_ID=142 \
ACL_SAMPLING_LOCAL_GROUP_ID=142 \
ACL_SAMPLING_APP_ID_NEW=102 \
ACL_SAMPLING_APP_ID_ESTABLISHED=103 \
ACL_SAMPLING_COLLECTOR_ID_ALLOW=1 \
ACL_SAMPLING_COLLECTOR_ID_DEFAULT_DENY=2 \
ACL_SAMPLING_ALLOW_PROBABILITY_PERCENT=1 \
ACL_SAMPLING_DEFAULT_DENY_PROBABILITY_PERCENT=100 \
bash dist/images/install.sh
```

?????? `ENABLE_ACL_SAMPLING` ? `ACL_SAMPLING_SET_ID` ? `ACL_SAMPLING_LOCAL_GROUP_ID` ? `ACL_SAMPLING_APP_ID_NEW` ? `ACL_SAMPLING_APP_ID_ESTABLISHED` ? `ACL_SAMPLING_COLLECTOR_ID_ALLOW` ? `ACL_SAMPLING_COLLECTOR_ID_DEFAULT_DENY` ? `ACL_SAMPLING_ALLOW_PROBABILITY_PERCENT` ? `ACL_SAMPLING_DEFAULT_DENY_PROBABILITY_PERCENT` ???????? collector set ????????????????

2025 Kube-OVN Team

▯▯▯▯▯▯▯▯▯▯▯

▯▯	▯▯	▯▯
`enabled`	▯▯▯▯	▯▯▯▯▯▯▯▯▯ACL ▯▯▯▯▯▯▯▯▯▯▯
`setID`	▯▯▯▯▯▯ 32 ▯▯▯▯	▯▯ OVN collector set ▯ OVS collector-set ID▯
`localGroupID`	▯▯▯▯ 32 ▯▯▯▯▯▯▯▯▯	OVS collector set ▯▯▯▯ Linux psample group▯
`appIDNew`	1 ▯ 255 ▯▯▯▯▯▯	`acl-new` ▯▯▯▯ application ▯▯▯▯
`appIDEstablished`	1 ▯ 255 ▯▯▯▯▯▯	`acl-est` ▯▯▯▯ application ▯▯▯▯
`collectorIDAllow`	1 ▯ 255 ▯▯▯▯▯▯	allow ▯▯▯▯▯▯ collector▯
`collectorIDDefaultDeny`	1 ▯ 255 ▯▯▯▯▯▯	default-deny ▯▯▯▯▯▯ collector▯
`allowProbabilityPercent`	0 ▯ 100 ▯▯▯▯	allow ▯▯▯▯▯▯▯▯▯
`defaultDenyProbabilityPercent`	0 ▯ 100 ▯▯▯▯	default-deny ▯▯▯▯▯▯▯▯▯

Kube-OVN ▯▯ `round(percent * 65535 / 100)` ▯▯▯▯▯▯▯▯ OVN ▯ 16 ▯▯▯▯▯▯▯▯▯▯▯

▯▯▯▯▯▯▯▯ controller/daemon warning ▯▯▯

▯▯	▯▯
`acl_sampling_controller_available`	▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ reconcile ▯▯ `1` ▯▯▯▯▯▯▯▯▯▯ `0` ▯
`acl_sampling_controller_failures_total{operation}`	`reconcile` ▯ `prepare` ▯ `attach` ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯
`acl_sampling_node_available{node_name}`	▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `1` ▯▯▯▯ `0` ▯
`acl_sampling_node_failures_total{node_name}`	▯▯ collector-set reconcile ▯▯▯▯▯

▯▯▯▯▯

▯ controller ▯ agent ▯▯ `aclSampling.enabled` ▯▯ `false` ▯▯▯ Kube-OVN ▯▯▯▯▯▯▯▯ NetworkPolicy ▯▯ ACL ▯ sample ▯▯▯▯ OVN ▯▯▯▯▯▯▯▯▯▯ `Sample` ▯▯▯▯▯▯▯▯▯▯ ▯▯▯▯ collector ▯ application▯▯▯▯▯▯▯▯▯▯ collector set▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

PDF Slack Support

2026▯10▯28▯

2026▯10▯28▯

GitHub

▯▯

2025 Kube-OVN Team

3.13.4 ▯▯▯ NetworkPolicy

▯▯

▯▯▯▯▯▯Kube-OVN ▯▯ NetworkPolicy ▯▯▯ `podSelector` ▯▯▯ Pod ▯▯▯▯ OVN ▯▯▯

▯▯▯▯▯ Pod▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Provider▯

- `ovn.kubernetes.io/network_policy_for`

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Pod ▯▯▯▯▯▯▯

▯▯▯▯

▯▯▯▯▯▯▯▯▯▯

```
metadata:
  annotations:
    ovn.kubernetes.io/network_policy_for: "ovn,default/net-a,default/net-b"
```

▯▯▯▯▯▯▯▯▯

- `ovn` ▯▯▯ OVN Provider▯
- `<namespace>/<net-attach-def>`

▯▯▯

- `ovn`
- `default/net-a`
- `ovn,default/net-a`

Provider ▯▯▯▯

- ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ OVN Provider▯
- ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯
- ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Provider▯▯▯▯▯▯▯▯▯▯▯▯
- ▯▯▯▯▯▯▯▯▯▯▯▯

`<namespace>/<net-attach-def>` ▯ Kube-OVN ▯▯▯▯▯▯▯ Provider ▯▯▯▯▯

- `<nad-name>.<nad-namespace>.ovn`

▯▯

▯▯ Pod ▯▯▯▯▯▯▯

- ▯▯ OVN Provider▯ `ovn` ▯
- `default/net-a`
- `default/net-b`

▯▯▯▯

- ▯▯▯ `network_policy_for` ▯
- ▯▯▯▯▯▯ `ovn` ▯ `net-a` ▯ `net-b`
- `network_policy_for: default/net-a` ▯
- ▯▯▯▯▯▯▯ `net-a`
- `network_policy_for: ovn,default/net-b` ▯

2025 Kube-OVN Team

- □□□□□ `ovn` □ `net-b`


□□

- □□□□□□□□□□□□□ Provider/□□□□□□□□ Kubernetes NetworkPolicy □□□□□
- □□□□□□□□□□□□□□□□□□□□□□□□□□□

PDF Slack Support

2026□4□28□

2026□2□24□

GitHub 

□□

3.13.5 ■■■■■■■■■■

Kubernetes ■■■ NetworkPolicy ■■■■■ L3 ■ L4 ■■■■■■■■■■■■■■■ AdminNetworkPolicy (ANP) ■■■■■■■■■■■■■■■

[illegible]

[illegible]

```
apiVersion: policy.networking.k8s.io/v1alpha1
kind: AdminNetworkPolicy
metadata:
  name: deny-external-domains
spec:
  priority: 55
  subject:
    namespaces:
      matchLabels:
        kubernetes.io/metadata.name: kube-system
  egress:
  - action: Deny
    name: deny-baidu-google
    to:
    - domainNames:
      - '*.baidu.com.'
      - '*.google.com.'
```

[illegible]

[illegible]	[illegible]
`priority`	[illegible]
`subject`	[illegible]Pod [illegible]
`egress`	[illegible]
`action`	[illegible] `Allow` / `Deny` / `Pass`
`domainNames`	[illegible] `.` [illegible]

[illegible]

[illegible] kube-ovn-pinger [illegible]

```
#
kubectl exec -it -n kube-system kube-ovn-pinger-xxxxx -- ping baidu.com
```

> [illegible] DNS [illegible] ACL [illegible]

[illegible] DNSNameResolver [illegible]

```
# kubectl get dnsnameresolver
NAME                                DNS NAME        RESOLVED IPS
anp-deny-external-domains-88dc32ab  *.google.com.
anp-deny-external-domains-fb3029ce  *.baidu.com.    220.181.7.203
```

PDF Slack Support

2026-4-28

2025-9-17

GitHub 

[illegible]

2025 Kube-OVN Team

3.13.6 □□□□

□□□□□□□□□□ Pod □□□□□□□□□□□□□□□□□□□□□Pod □□□□□□ Kube-OVN IPAM □□□□ MAC □□□□ IP □□□□□□□□□□□□□□□□□□□□

4. KubeVirt

4.1 VM □□ IP

□□□□□□□□□□ IP □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□ VM □□□□□□□□□□ VM □ IP □□□□□□□□□□□□□□□□□□□□□□□□

□□□□□□□□ CNI □□□□□□□□□□

- □□□ IP □□□ VM □□□□□□□□VM □□□□□□□ IP □□□□□□□
- IP □□□ Node □□□VM □□□□□□□□□□□□□□□□□ IP□
- □□□□□□□□ IP □□□□□□□□□□□□ VM □ IP □□□

□□□□□□□□ KubeVirt □ `masquerade` □□□□□□□□ iptables □ VM □□□□□□□□□□□□□□□□□□□ VM □ IP □□□□□ `masquerade` □□ `bridge` □□□□□□□□

- Pod IP □ VM IP □□□□□□□□□□□□□□□□□□□□□□□□□□□ Pod IP □□□□□□□□□□□□□□□□□□□□□□□□
- `masquerade` □□ iptables □□□□□□□□□□□□□ `bridge` □□□□□□
- `masquerade` □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□
- `masquerade` □□□□□ conntrack □□□□□□□□□□□□□□□□□□□□□□□□□□□

Kube-OVN □□□ KubeVirt □ `bridge` □ `managedTap` □□□□□□□ IP □ VM □□□□□□□□□ IP □□□ VM □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□ annotation □□□□□ VM □□□□□ IP □□□□□□□□□□□□ Kube-OVN □□□□□ Multus □□□□□□□□□□□□□□□□□□□□

```
          cloudInitNoCloud:
            userDataBase64: SGkuXG4=
```

1. ⬚⬚ VM ⬚⬚

```
kubectl get vmi testvm
```

1. ⬚⬚ VM

```
virtctl restart testvm
```

1. ⬚⬚⬚ VM

```
virtctl migrate testvm
```

⬚⬚⬚⬚⬚ bridge ⬚⬚⬚ VM ⬚⬚⬚⬚⬚⬚⬚IP ⬚⬚⬚⬚⬚⬚⬚

4.1.2 ⬚⬚ IP/Mac ⬚⬚

⬚⬚⬚⬚⬚⬚ VM ⬚ IP/Mac ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ VM ⬚⬚⬚ annotation ⬚⬚⬚⬚ VM ⬚⬚ IP ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ KubeVirt ⬚⬚⬚⬚ VM ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

4.1.3 VM □□ IP

Kube-OVN □□□□□□□□□ VM IP□□□□ IP □□□□□ VM □□□□□□

□□□□□□□□□ VM IP□

1. □□ VM Annotation□□□□□□□□ IP □□□
2. □□ `virtctl restart <vm name>` □□ VM□□□□ IP □□□□□

4.1.4 □□□□

□□□□□ VM □□□□□□□ IP□□□□□□□□ VM □□□□□□□□□□□□ `ovn.kubernetes.io/logical_switch` □□□□

```yaml
apiVersion: kubevirt.io/v1
kind: VirtualMachine
metadata:
  name: testvm
spec:
  runStrategy: Always
  template:
    metadata:
      labels:
        kubevirt.io/size: small
        kubevirt.io/domain: testvm
      annotations:
        ovn.kubernetes.io/logical_switch: subnet1 #(1)
        kubevirt.io/allow-pod-bridge-network-live-migration: "true"
    spec:
      domain:
        devices:
          disks:
            - name: containerdisk
              disk:
                bus: virtio
            - name: cloudinitdisk
              disk:
                bus: virtio
          interfaces:
          - name: default
            bridge: {}
        resources:
          requests:
            memory: 64M
      networks:
      - name: default
        pod: {}
      volumes:
        - name: containerdisk
          containerDisk:
            image: quay.io/kubevirt/cirros-container-disk-demo
        - name: cloudinitdisk
          cloudInitNoCloud:
            userDataBase64: SGkuXG4=
```

1. 🙋 □□□□□ VM □□□□□

PDF Slack Support

2026□2□11□

2025□3□3□

GitHub

4.1.5 □□

4.2 ▯▯▯▯▯

KubeVirt ▯ Clone ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Label ▯ Annotation▯▯▯▯▯▯▯▯▯ Kube-OVN ▯ Annotation ▯▯▯ IP▯MAC ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

2025⬚9⬚10⬚

2025⬚8⬚13⬚



GitHub 

4.2.3 ⬚⬚

4.3 ▒▒▒▒

▒ KubeVirt ▒ Bridge ▒▒▒▒▒▒DHCP ▒▒▒ virt-launcher ▒▒▒▒▒▒▒▒ KubeVirt ▒▒▒▒ IPv4 ▒▒▒ DHCP▒▒▒ Bridge ▒▒▒ KubeVirt VM ▒▒▒▒ RA ▒▒▒▒▒▒ IPv6 ▒▒▒▒▒ Kube-OVN ▒▒▒ DHCP ▒ RA ▒▒▒▒▒▒ KubeVirt ▒▒▒▒▒ DHCP/RA ▒▒▒▒▒▒▒▒▒▒▒▒▒

▒ KubeVirt 1.4.0 ▒▒▒▒▒▒▒▒ Network Binding Plugin ▒▒▒▒▒ Bridge ▒▒▒▒▒ `managedTap` ▒▒▒▒▒ KubeVirt ▒▒▒ DHCP ▒▒▒▒▒▒▒▒▒▒ `managedTap` ▒▒▒ Kube-OVN ▒ DHCP/RA ▒▒▒▒▒▒▒▒ VM ▒▒▒▒▒▒▒▒▒▒▒▒▒

4.3.1 ▒▒▒▒ DHCP

▒ Kube-OVN ▒ Subnet ▒▒▒ DHCP ▒ IPv6 RA ▒▒▒▒▒▒▒▒ YAML ▒▒▒▒▒

```yaml
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: dual-stack-subnet
spec:
  cidrBlock: "10.244.0.0/16,fd00:10:244::/64"
  enableDHCP: true
  enableIPv6RA: true
```

4.3.2 ▒▒ `managedTap` ▒▒▒▒

▒ KubeVirt ▒▒▒ `managedTap` ▒ Network Binding Plugin:

```
# kubectl patch kubevirts -n kubevirt kubevirt --type=json -p=\
'[{"op": "add", "path": "/spec/configuration/network",    "value": {
    "binding": {
        "managedtap": {
            "domainAttachmentType": "managedTap"
        }
    }
}}]'
```

4.3.3 ▒▒▒▒▒▒▒▒▒▒ `managedTap` ▒▒▒▒

```yaml
apiVersion: kubevirt.io/v1
kind: VirtualMachine
metadata:
  name: dual-stack-vm
  namespace: default
spec:
  running: false
  template:
    spec:
      domain:
        devices:
          interfaces:
            - name: default
              binding:
                name: managedtap
      networks:
      - name: default
        pod: {}
```

▒▒▒▒▒▒▒▒▒▒▒▒ VM ▒▒ DHCP ▒ IPv6 RA ▒▒▒▒▒▒▒▒▒ IPv4/IPv6 ▒▒▒

PDF Slack Support

2025▒9▒10▒

2025▒3▒3▒

GitHub

4.3.4 ▯▯

4.4 ...

...

KubeVirt ...

- KubeVirt ... Bridge ...
- KubeVirt ...
- ... IP ...
- ...

Kube-OVN ... 0.5 ... TCP ...

4.4.1 ...

... VM Spec ... `kubevirt.io/allow-pod-bridge-network-live-migration: "true"` ... annotation...Kube-OVN ...

1. ... VM

```
kubectl apply -f - <<EOF
apiVersion: kubevirt.io/v1
kind: VirtualMachine
metadata:
  name: testvm
spec:
  runStrategy: Always
  template:
    metadata:
      labels:
        kubevirt.io/size: small
        kubevirt.io/domain: testvm
      annotations:
        kubevirt.io/allow-pod-bridge-network-live-migration: "true"
    spec:
      domain:
        devices:
          disks:
            - name: containerdisk
              disk:
                bus: virtio
            - name: cloudinitdisk
              disk:
                bus: virtio
          interfaces:
          - name: default
            bridge: {}
        resources:
          requests:
            memory: 64M
      networks:
      - name: default
        pod: {}
      volumes:
        - name: containerdisk
          containerDisk:
            image: quay.io/kubevirt/cirros-container-disk-demo
        - name: cloudinitdisk
          cloudInitNoCloud:
            userDataBase64: SGkuXG4=
EOF
```

1. SSH ...

```
# password: gocubsgo
virtctl ssh cirros@testvm
ping 8.8.8.8
```

1. ...

```
virtctl migrate testvm
```


... VM ... SSH ... ping ...

2025 Kube-OVN Team


4.4.2 □□□□□

Kube-OVN □□□□□□□□□□□□□□□□□□□Live migration - Reducing downtime with multchassis port bindings□


□□□□□□□□□□□□□□□□□□




1. KubeVirt □□ VM □□□□□



1. KubeVirt □□□□□□□□□□□ Pod□□□□ Pod □□□□□□□□□□□




1. KubeVirt □□□□ Pod□□□ libvirt □□□ RARP □□□□□□ Pod □□□□□□□□ Pod □□□□□□□



1. KubeVirt □□□ Pod□□□□□□□Kube-OVN □□ Watch Migration CR □□□□□□□□□□□□□□□□□□□□□□□□□

2025 Kube-OVN Team



⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ 5 ⬚⬚⬚ 6 ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ libvirt ⬚ RARP ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ 0.5 ⬚⬚⬚⬚⬚ TCP ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

PDF Slack Support

2025⬚9⬚10⬚

2025⬚3⬚3⬚

GitHub

4.4.3 ⬚⬚

4.5 □□□□□

Kube-OVN □ Multus Dynamic Networks Controller □□□□□□□ KubeVirt □ v1.4.0 □□□□□□□□□□□□□□□ VM □□□□□□□□□□□□□□□□□□□

4.5.1 □□□□

□ Thick □□□□ Multus□

```
kubectl apply -f https://raw.githubusercontent.com/k8snetworkplumbingwg/multus-cni/refs/heads/master/deployments/multus-daemonset-thick.yml
```

□□ Multus Dynamic Networks Controller□

```
kubectl apply -f https://raw.githubusercontent.com/k8snetworkplumbingwg/multus-dynamic-networks-controller/refs/heads/main/manifests/dynamic-networks-controller.yaml
```

4.5.2 □□□□□□□

□□ NetworkAttachmentDefinition

□ `provider` □□□□□□ `ovn` □

```
apiVersion: "k8s.cni.cncf.io/v1"
kind: NetworkAttachmentDefinition
metadata:
  name: attachnet
  namespace: default
spec:
  config: '{
      "cniVersion": "0.3.0",
      "type": "kube-ovn",
      "server_socket": "/run/openvswitch/kube-ovn-daemon.sock",
      "provider": "attachnet.default.ovn"
    }'
```

- `spec.config.type` : □□□ `kube-ovn` □□□ CNI □□□□ Kube-OVN □□□
- `server_socket` : Kube-OVN □□□□□ socket □□□ □□□□□ `/run/openvswitch/kube-ovn-daemon.sock` □
- `provider` : □□ NetworkAttachmentDefinition □ `<name>.<namespace>.ovn` , Kube-OVN □□□□□□□□□□□□□ Subnet □□□□□□□□□□□□□ ovn□

□□□□ Kube-OVN Subnet

□□□ Kube-OVN □□□□□□□□□ `provider` □□□□□□□□ NetworkAttachmentDefinition □ `<name>.<namespace>.ovn` □□□□ `ovn` □□□□□□□ □ Kube-OVN □□□□□□□□□□ Subnet □□□□□

```
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: attachnet
spec:
  protocol: IPv4
  provider: attachnet.default.ovn
  cidrBlock: 172.17.0.0/16
  gateway: 172.17.0.1
  excludeIps:
  - 172.17.0.0..172.17.0.10
```

4.5.3 □□ VM □□

□□□□□ yaml □□ VM□

```
apiVersion: kubevirt.io/v1
kind: VirtualMachine
metadata:
  name: vm-fedora
spec:
  runStrategy: Always
  template:
    spec:
      domain:
```

```
        devices:
          disks:
          - disk:
              bus: virtio
            name: containerdisk
          interfaces:
          - masquerade: {}
            name: defaultnetwork
          rng: {}
        resources:
          requests:
            memory: 1024M
      networks:
      - name: defaultnetwork
        pod: {}
      terminationGracePeriodSeconds: 0
      volumes:
      - containerDisk:
          image: quay.io/kubevirt/fedora-with-test-tooling-container-disk:devel
        name: containerdisk
```

▒▒▒▒

▒▒ VM ▒ Spec ▒▒▒▒▒▒▒▒▒▒

```
apiVersion: kubevirt.io/v1
kind: VirtualMachine
metadata:
  name: vm-fedora
template:
  spec:
    domain:
      devices:
        interfaces:
        - name: defaultnetwork
          masquerade: {}
          # new interface
        - name: dyniface1
          bridge: {}
    networks:
    - name: defaultnetwork
      pod: {}
      # new network
    - name: dyniface1
      multus:
        networkName: attachnet
```

▒▒▒▒

▒▒▒ `interface` ▒ `state` ▒▒▒ `absent` ▒▒▒▒▒▒▒▒▒▒

```
apiVersion: kubevirt.io/v1
kind: VirtualMachine
metadata:
  name: vm-fedora
template:
  spec:
    domain:
      devices:
        interfaces:
          - name: defaultnetwork
            masquerade: {}
          # set the interface state to absent
          - name: dyniface1
            state: absent
            bridge: {}
    networks:
      - name: defaultnetwork
        pod: {}
      - name: dyniface1
        multus:
          networkName: attachnet
```

PDF Slack Support

2025 Kube-OVN Team

2025⊠11⊠18⊠

2025⊠11⊠18⊠

GitHub 

4.5.4 ⊠⊠

4.6 DHCP

□□□ `managedTap` □ `SR-IOV` □ `DPDK` □□□□□□KubeVirt □□□ DHCP □□□□□□□□□□□□□Kube-OVN □□□□ OVN □ DHCP □□□□□□□□ Pod □□□□ DHCP □□□□□□□□□□□□□□ KubeVirt □□□□□□ DHCP □□□□□ IP □□□□□□ Kube-OVN □ DHCP □□□□ DHCPv6, IPv6RA, DNS□TFTP □ DHCP □□□□□□□□□□□□□□□□□□□□ DHCP □□□□□□□□□

> **Warning**
>
> □□ `bridge` □□□□□□KubeVirt □ DHCP □□□ Kube-OVN □□□□□ DHCP □□□□□ Kube-OVN □□□ DHCP □□□□□□□□□□□□□ Kube-OVN □□□□□ DHCP □□□ □□□□`managedTap` □□□□□□ `bridge` □□□□□`managedTap` □□□□□□□□□□□□ managedTap □□□□□

4.6.1 □□□□ DHCP □□

□□ DHCP □□□□□□

```yaml
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: sn-dual
spec:
  cidrBlock: "10.0.0.0/24,240e::a00/120"
  default: false
  disableGatewayCheck: true
  disableInterConnection: false
  excludeIps:
    - 10.0.0.1
    - 240e::a01
  gateway: 10.0.0.1,240e::a01
  gatewayNode: ''
  gatewayType: distributed
  natOutgoing: false
  private: false
  protocol: Dual
  provider: ovn
  vpc: vpc-test
  enableDHCP: true
  dhcpV4Options: "lease_time=3600,router=10.0.0.1,server_id=169.254.0.254,server_mac=00:00:00:2E:2F:B8"
  dhcpV6Options: "server_id=00:00:00:2E:2F:C5"
  enableIPv6RA: true
  ipv6RAConfigs: "address_mode=dhcpv6_stateful,max_interval=30,min_interval=5,send_periodic=true"
```

- `enableDHCP` : □□□□□□□ DHCP □□□
- `dhcpV4Options` , `dhcpV6Options` : □□□□□□□ ovn-nb □ DHCP □□□□□□□□ DHCP Options□ □□□□□□□ `"lease_time=3600, router=$ipv4_gateway, server_id=169.254.0.254, server_mac=$random_mac"` □ `server_id=$random_mac` □
- `enableIPv6RA` : □□□□ DHCPv6 □□□□□□□□
- `ipv6RAConfigs` □□□□□□□□ ovn-nb □ Logical_Router_Port □□□□□□□□ Logical Router Port□□□□□□ `address_mode=dhcpv6_stateful, max_interval=30, min_interval=5, send_periodic=true` □

4.6.2 Pod □□ DHCP □□

□□□□□□□ DHCP □□□□Kube-OVN □□□□□□ Pod □□□□□□ Pod □□□□□□□□□□ DHCP □□□Pod □□□ DHCP □□□□□□□□□□□□□□□□□□□□ DHCP □□□□□□□□□□ `enableDHCP` □□□□□□□

□□□□□

```yaml
#     provider   "ovn"
ovn.kubernetes.io/dhcp-v4-options: "lease_time=3600,router=10.0.0.1,dns_server=8.8.8.8"
ovn.kubernetes.io/dhcp-v6-options: "server_id=00:00:00:00:00:01"

#      provider   "net1.ns1.ovn"
net1.ns1.ovn.kubernetes.io/dhcp-v4-options: "lease_time=7200"
```

□□□ key □□□ `<provider>.kubernetes.io/dhcp-v4-options` □ `<provider>.kubernetes.io/dhcp-v6-options` □□□ `<provider>` □□□□□□□□□□□□□□□□□□□□ provider □ `ovn` □□□□□□ Multus □□□□□□□□□provider □□□ `<net-attach-def-name>.<namespace>.ovn` □

2025 Kube-OVN Team

▯▯▯▯

▯▯▯▯ Pod ▯▯▯▯▯▯ DHCPv4 ▯▯▯

```
apiVersion: v1
kind: Pod
metadata:
  name: dhcp-pod
  annotations:
    ovn.kubernetes.io/dhcp-v4-options: "lease_time=3600,router=10.0.0.1,dns_server=8.8.8.8"
    ovn.kubernetes.io/dhcp-v6-options: "server_id=00:00:00:00:00:01"
spec:
  containers:
    - name: test
      image: docker.io/library/nginx:alpine
```

▯▯ Multus ▯▯▯▯▯▯▯▯▯ provider ▯▯▯▯▯▯▯▯▯▯▯▯ DHCP ▯▯▯

```
apiVersion: v1
kind: Pod
metadata:
  name: multi-nic-dhcp-pod
  annotations:
    k8s.v1.cni.cncf.io/networks: '[{"name": "net1", "namespace": "ns1"}]'
    ovn.kubernetes.io/dhcp-v4-options: "lease_time=3600,router=10.0.0.1"
    net1.ns1.ovn.kubernetes.io/dhcp-v4-options: "lease_time=7200,router=10.0.1.1"
spec:
  containers:
    - name: test
      image: docker.io/library/nginx:alpine
```

▯▯▯▯▯

DHCP ▯▯▯▯▯▯▯▯▯▯▯▯▯

1. **Pod** ▯▯▯▯▯ `<provider>.kubernetes.io/dhcp-v4-options` ▯ `<provider>.kubernetes.io/dhcp-v6-options` ▯▯▯ Pod ▯▯ DHCP ▯▯▯
2. ▯▯▯▯▯▯▯ Subnet CRD ▯ `dhcpV4Options` ▯ `dhcpV6Options` ▯▯▯▯▯▯▯▯▯ DHCP ▯▯▯

▯ Pod ▯▯▯ DHCP ▯▯▯▯▯▯▯▯▯ Pod ▯▯▯▯ DHCP ▯▯▯▯▯▯▯▯▯▯▯▯▯

> **Note**
>
> ▯▯▯▯▯▯▯ Pod ▯▯ DHCP ▯▯▯▯▯▯▯▯ DHCP ▯▯▯▯▯▯▯ Pod ▯▯▯▯▯

PDF Slack Support

2026▯3▯30▯

2022▯5▯24▯

GitHub

5. VPC ⊠⊠

5.1 VPC ⊠⊠

Kube-OVN ⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠ VPC ⊠⊠⊠⊠⊠ VPC ⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠ Subnet ⊠⊠⊠ ⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠EIP ⊠⊠⊠⊠

> VPC ⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠ Kubernetes ⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠ ⊠⊠⊠⊠⊠⊠ Pod ⊠⊠⊠NodePort ⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠ DNS ⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠ ⊠⊠⊠⊠⊠⊠⊠ Kubernetes ⊠⊠⊠⊠⊠⊠⊠ Kube-OVN ⊠⊠ VPC ⊠⊠⊠⊠⊠⊠⊠⊠⊠ VPC ⊠⊠ Subnet ⊠⊠⊠⊠⊠ Kubernetes ⊠⊠⊠⊠⊠⊠⊠⊠⊠ VPC ⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠EIP ⊠ NAT ⊠⊠⊠⊠⊠⊠⊠ ⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠ VPC ⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠ ACL ⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠ VPC ⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠ VPC ⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠⊠

□□□□□□□□□□□□□□□ VPC □□□□□ CIDR:

```
kind: Subnet
apiVersion: kubeovn.io/v1
metadata:
  name: net1
spec:
  vpc: test-vpc-1
  cidrBlock: 10.0.1.0/24
  protocol: IPv4
  namespaces:
    - ns1
---
kind: Subnet
apiVersion: kubeovn.io/v1
metadata:
  name: net2
spec:
  vpc: test-vpc-2
  cidrBlock: 10.0.1.0/24
  protocol: IPv4
  namespaces:
    - ns2
```

□□□□□ Namespace □□□ Pod:

```
apiVersion: v1
kind: Pod
metadata:
  namespace: ns1
  name: vpc1-pod
spec:
  containers:
    - name: vpc1-pod
      image: docker.io/library/nginx:alpine
---
apiVersion: v1
kind: Pod
metadata:
  namespace: ns2
  name: vpc2-pod
spec:
  containers:
    - name: vpc2-pod
      image: docker.io/library/nginx:alpine
```

□□□□□□□□□□ Pod □□□□□□□ CIDR□□□□□□□□□□□□□ VPC□□□ Pod □□□□□□□

5.1.3 □□ VPC □□

VPC □□□□□□□□□□□□□ VPC □□□VPC □□□□□□□□□□□□□□□□□□□□□□ □□ IP□SNAT □ DNAT □□□

VPC □□□□□□ Multus-CNI □□□□□□□□□□□□□ multus-cni□

> **Note**
>
> □□□ VPC □□□□□□□□□ VPC □□□□□□□□□□□□□□□
>
> □□□□□ VPC □□□□□□□□□□□□□□VPC NAT □□□OVN □□□ Egress Gateway□□□ VPC NAT □□□ Kube-OVN □□□□□□□□□□□□□□ VPC NAT □□□□□□□□□□ Pod□□□□□□□□□□□ VPC □□□□□□□□□□□ Macvlan □□□□□□□□□□□□ Pod □□ iptables □□□□□□□□□□□□□□□□□□□□

```
  - 192.168.0.1..192.168.0.10
---
apiVersion: "k8s.cni.cncf.io/v1"
kind: NetworkAttachmentDefinition
metadata:
  name: ovn-vpc-external-network
  namespace: kube-system
spec:
  config: '{
      "cniVersion": "0.3.0",
      "type": "macvlan",
      "master": "eth1",
      "mode": "bridge",
      "ipam": {
        "type": "kube-ovn",
        "server_socket": "/run/openvswitch/kube-ovn-daemon.sock",
        "provider": "ovn-vpc-external-network.kube-system"
      }
    }'

        `ipam`        VPC     net1     Kube-OVN    IP
---
apiVersion: "k8s.cni.cncf.io/v1"
kind: NetworkAttachmentDefinition
metadata:
  name: ovn-vpc-external-network
  namespace: kube-system
spec:
  config: '{
      "cniVersion": "0.3.0",
      "type": "macvlan",
      "master": "eth1",
      "mode": "bridge"
    }'
```

- □ Subnet □□□□□□□□□□□□□□□□□□□□□□□□□ Macvlan □□□ VPC □□□□□□□□□□□□□□□□□□□□□□□□ IP□
- VPC □□□□ Macvlan □□□□□□□□ `NetworkAttachmentDefinition` □ `master` □□□□□□□□□□□□□□□□□
- `name` □□□□□□□□

□ Macvlan □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□L2/L3 □□□□□□□□□□□□□□□□□□□□ □□□□□□□□□□□□□□□□□□□□□□□□Vlan □□□□□□□□□□

1. □□ OpenStack □ VM □□□□□□□□□□□□□□□ `PortSecurity` □□□□
2. □□ VMware □ vSwitch □□□□□□□ `MAC Address Changes`, `Forged Transmits` □ `Promiscuous Mode Operation` □□□□ `allow` □
3. □□ Hyper-V □□□□□□□□□□□□□□□□□□□□□□ `MAC Address Spoofing` □
4. □□□□□□□ AWS□GCE□□□□□□□□□□□□□□□□□□ Mac □□□□ Macvlan □□□□□
5. □□ Macvlan □□□□□□□Macvlan □□□□□□□□□□□□□□□□□□□□□□□□□ VpcNATGateway Pod □□□□□□□□□□□□□□□□ Pod□
6. □□□□□□□□□□□□□□□□ Trunk □□□□□□□□□□□□□□□□□□□□□□□□ Macvlan □□□□

□□ **VPC** □□□□

VPC □□□□□□□□□ `kube-system` □□□□□□□ `ovn-vpc-nat-gw-config` □□□□□□□□□ `ovn-vpc-nat-config` ConfigMap □□□□□□ `image` □□□ Pod □□□□□□□□□ `imagePullSecret` □□□□□□□□□□□□□ `nodeSelector` □□□□□□ `nodeSelector` □□□□ `LoadBalancer` □□ Service □ lb-svc □□□VpcNATGateway Pod □□□□ `VpcNatGateway.spec.selector` □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□ NAT □□ workload □□□□□□□□□□ Docker registry Secret□□□□ ConfigMap □□□ Secret □□□□□□ workload □□□□□□ `kube-system` □□□□□□□ `spec.namespace` □□□□□□□□□□□□□□□□□

```
---
kind: ConfigMap
apiVersion: v1
metadata:
  name: ovn-vpc-nat-config
  namespace: kube-system
data:
  image: 'docker.io/kubeovn/vpc-nat-gateway:v1.17.0'
  imagePullSecret: vpc-nat-registry
  nodeSelector: |
    kubernetes.io/hostname: kube-ovn-control-plane
---
kind: ConfigMap
apiVersion: v1
metadata:
  name: ovn-vpc-nat-gw-config
  namespace: kube-system
data:
  enable-vpc-nat-gw: 'true'
```

- `image`: □□ Pod □□□□□□□□

- `imagePullSecret` ▯▯▯▯ Docker registry Secret ▯▯▯Secret ▯▯▯▯▯▯ NAT ▯▯ workload ▯▯▯▯▯▯▯▯▯▯ StatefulSet/Deployment ▯▯▯▯▯▯▯▯▯▯▯▯▯
- `enable-vpc-nat-gw` ▯▯▯▯▯▯▯ VPC ▯▯▯▯▯

▯▯

```
kubectl create secret docker-registry vpc-nat-registry \
  --namespace kube-system \
  --docker-server=registry.example.com \
  --docker-username='<username>' \
  --docker-password='<password>'
```

▯▯ **VPC** ▯▯

```
kind: VpcNatGateway
apiVersion: kubeovn.io/v1
metadata:
  name: gw1
spec:
  vpc: test-vpc-1
  subnet: net1
  lanIp: 10.0.1.254
  selector:
    - "kubernetes.io/hostname: kube-ovn-worker"
    - "kubernetes.io/os: linux"
  externalSubnets:
    - ovn-vpc-external-network
  noDefaultEIP: false
```

- `vpc` ▯▯ VpcNatGateway ▯▯▯ VPC▯
- `subnet` ▯▯ VPC ▯▯▯ Subnet ▯▯VPC ▯▯ Pod ▯▯▯▯▯▯▯ `lanIp` ▯▯▯▯▯▯▯▯
- `namespace` ▯▯▯▯VPC ▯▯▯▯▯▯▯Deployment ▯ StatefulSet▯▯▯ Pod ▯▯▯ Namespace▯▯▯▯▯▯▯ kube-ovn-controller ▯▯▯ Namespace▯▯▯▯ `kube-system` ▯▯ `VpcNatGateway` ▯▯▯▯▯▯▯▯▯▯▯▯ `VpcNatGateway` ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `spec` ▯▯▯ `metadata.namespace` ▯
- `lanIp` ▯ `subnet` ▯▯▯▯▯▯▯▯ IP▯VPC ▯▯ Pod ▯▯▯▯▯▯▯ IP▯▯ VPC ▯▯▯▯▯▯▯▯▯▯▯ VpcNatGateway ▯ `nextHopIP` ▯▯▯▯▯▯▯▯ `lanIp` ▯
- `selector` ▯VpcNatGateway Pod ▯▯▯▯▯▯▯▯▯▯▯ Kubernetes ▯▯ NodeSelector ▯▯▯▯▯▯
- `externalSubnets` ▯VPC ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `ovn-vpc-external-network` ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯
- `noDefaultEIP` ▯VPC ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ EIP▯▯▯▯▯ `false` ▯▯ v1.15 ▯▯▯▯▯▯▯▯▯ BGP ▯▯▯▯▯▯▯▯▯▯▯▯ `true` ▯▯▯ Underlay ▯▯▯

▯▯▯▯▯▯▯▯

- `tolerations` ▯▯ VPC ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ ▯▯▯▯▯▯▯▯
- `affinity` ▯▯ VPC ▯▯ Pod ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ ▯▯▯▯▯▯▯▯▯▯

▯▯▯ VPC ▯▯ Pod ▯▯▯▯▯▯ Namespace ▯▯▯ `spec.namespace` ▯▯▯▯▯▯▯▯ Namespace▯

```
kind: VpcNatGateway
apiVersion: kubeovn.io/v1
metadata:
  name: gw1
spec:
  namespace: tenant-network
  vpc: test-vpc-1
  subnet: net1
  externalSubnets:
    - ovn-vpc-external-network
```

▯▯▯ VPC-NAT-GW ▯▯▯▯▯▯▯

1. nat gw pod ▯▯▯▯▯▯net1 arp ▯▯▯▯▯▯ping ▯▯▯▯▯▯▯▯▯▯ eip ▯▯▯▯▯▯▯ arp▯▯▯ ping ▯▯

▯▯ **LAN IP** ▯▯▯▯

`spec.lanIp` ▯▯▯▯▯▯▯▯▯▯▯▯ `replicas` ▯ 1 ▯▯▯▯▯▯▯▯controller ▯▯▯▯▯▯▯▯▯ LAN IP▯▯▯▯▯▯▯▯▯ `spec.lanIp` ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ StatefulSet▯

▯ `spec.replicas` ▯▯ 1 ▯▯▯▯▯▯▯ Deployment ▯▯▯▯▯▯▯▯▯▯▯ Pod ▯▯▯▯▯▯▯▯ LAN IP▯▯▯ `spec.lanIp` ▯▯▯▯▯▯▯▯▯▯controller ▯▯▯▯▯▯▯▯▯▯▯▯ OVN ▯▯▯▯▯▯ BFD ▯▯▯ `status.lanIp` ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

LAN IP

```
spec:
  replicas: 2
  # lanIp      controller
```

BFD

VPC NAT BFDBidirectional Forwarding Detection VPC `spec.bfd.enabled` true

```
spec:
  vpc: test-vpc-1
  subnet: net1
  replicas: 2
  bfd:
    enabled: true
    minRX: 500
    minTX: 500
    multiplier: 3
```

`bfd.enabled`	boolean	false	BFD
`bfd.minRX`	int32	1000	BFDms
`bfd.minTX`	int32	1000	BFDms
`bfd.multiplier`	int32	3	BFD = minRX × multiplier

`internalSubnets` `internalCIDRs` CIDR NAT

```
spec:
  vpc: test-vpc-1
  subnet: net1
  internalSubnets:
  - subnet-a
  - subnet-b
  internalCIDRs:
  - 10.0.2.0/24
```

EIP

EIP IP VPC DNATSNAT IP

EIP

```
kind: IptablesEIP
apiVersion: kubeovn.io/v1
metadata:
  name: eip-random
spec:
  natGwDp: gw1
```

EIP

```
kind: IptablesEIP
apiVersion: kubeovn.io/v1
metadata:
  name: eip-static
spec:
  natGwDp: gw1
  v4ip: 192.168.0.100
```

EIP

```
kind: IptablesEIP
apiVersion: kubeovn.io/v1
metadata:
  name: eip-random
spec:
```

```
  natGwDp: gw1
  externalSubnet: ovn-vpc-external-network
```

- `externalSubnet` ▒EIP ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ `ovn-vpc-external-network` ▒IptablesEIP ▒▒▒▒▒▒▒ VpcNatGateway ▒ `externalSubnets` ▒▒▒▒▒▒▒▒EIP ▒▒▒▒▒▒▒▒ ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒
- `namespace` ▒▒▒▒EIP ▒▒▒▒▒ NAT ▒▒▒▒▒▒▒▒ Pod ▒▒ Namespace▒▒▒▒▒▒▒ `natGwDp` ▒▒▒▒ VpcNatGateway ▒▒▒▒▒▒▒ `spec.namespace` ▒▒▒▒▒▒ controller ▒▒▒▒ Namespace▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ Namespace ▒▒▒▒ `IptablesEIP` ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ `spec` ▒▒▒▒ `metadata.namespace` ▒

▒▒▒▒▒▒▒ EIP ▒ NAT ▒▒▒▒▒▒▒ Namespace ▒▒▒▒ `spec.namespace` ▒▒▒▒▒▒▒▒ VpcNatGateway ▒▒▒▒ Namespace▒

```
kind: IptablesEIP
apiVersion: kubeovn.io/v1
metadata:
  name: eip-tenant
spec:
  natGwDp: gw1
  namespace: tenant-network
```

▒▒ DNAT ▒▒

▒▒ DNAT ▒▒▒▒▒▒▒▒▒▒▒▒ EIP ▒▒▒▒▒▒▒▒▒▒ VPC ▒▒▒▒▒ IP ▒▒▒▒▒

```
kind: IptablesEIP
apiVersion: kubeovn.io/v1
metadata:
  name: eipd01
spec:
  natGwDp: gw1

---
kind: IptablesDnatRule
apiVersion: kubeovn.io/v1
metadata:
  name: dnat01
spec:
  eip: eipd01
  externalPort: '8888'
  internalIp: 10.0.1.10
  internalPort: '80'
  protocol: tcp
```

DNAT ▒▒▒▒▒▒▒SHARE ▒▒▒

`type: share` ▒▒ **VPC NAT** ▒▒▒▒▒ **Kubernetes Service** ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ Pod▒

share ▒▒▒ **IptablesDnatRule** ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ ▒▒▒▒▒▒▒▒▒VPC NAT ▒▒▒▒▒ Kubernetes Service▒▒▒▒

▒▒▒▒▒▒

- `type` ▒ `exclusive` ▒▒▒▒▒▒▒▒▒▒▒▒▒ EIP:Port ▒▒▒▒▒▒ DNAT ▒▒▒▒▒▒ `share` ▒▒▒▒▒▒ Service ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ EIP:Port▒
- `sessionAffinity` ▒▒ `share` ▒▒▒▒▒▒▒▒▒ `ClientIP` ▒▒▒▒▒▒▒▒ IP ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ 10800 ▒▒3 ▒▒▒▒▒▒▒▒ `sessionAffinityTimeoutSeconds` ▒▒▒▒

▒▒ SNAT ▒▒

▒▒ SNAT ▒▒▒VPC ▒▒ Pod ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ EIP ▒▒ SNAT▒

```
---
kind: IptablesEIP
apiVersion: kubeovn.io/v1
metadata:
  name: eips01
spec:
  natGwDp: gw1
---
kind: IptablesSnatRule
apiVersion: kubeovn.io/v1
metadata:
  name: snat01
spec:
  eip: eips01
  internalCIDR: 10.0.1.0/24
```


2025 Kube-OVN Team

□□□□ **IP**

□□□□ IP □□□VPC □□□□ IP □□ EIP □□□□□□□□□□□□□□□□ EIP □□ VPC □□ IP□VPC □□□□ IP □□□□□□□□□□ SNAT □□□ EIP□

```
---
kind: IptablesEIP
apiVersion: kubeovn.io/v1
metadata:
  name: eipf01
spec:
  natGwDp: gw1

---
kind: IptablesFIPRule
apiVersion: kubeovn.io/v1
metadata:
  name: fip01
spec:
  eip: eipf01
  internalIp: 10.0.1.5
```

VPC NAT □□□□ Kubernetes Service

□□□□□□□□□□□□□□□□□□

□□	□□□□	□□
`--enable-lb`	true	OVN □□□□□□□□ ClusterIP / NodePort / LoadBalancer □□ Service □□□□□
`--enable-gw-nftable-lb-svc`	false	VPC NAT □□□□ LoadBalancer □□ Service□□□□□ nftables □□□□□□□□□□ `ovn.kubernetes.io/eip` annotation
`--enable-gw-nftable-svc-cluster-ip`	false	□ Service ClusterIP □□□□□ nftables□□□□□□ ClusterIP □□□□
`--enable-lb-svc`	false	Pod □□ LoadBalancer□□□ LoadBalancer Service □□□□ Pod□DNAT EIP □ ClusterIP□□ `--enable-gw-nftable-lb-svc` □□□□□□ `--enable-lb` □ `--enable-gw-nftable-svc-cluster-ip` □□ ClusterIP □□□

□□□□□□□□

□□	□□□□
□ `--enable-lb` □□□□	OVN □□□□□□□□□ Service □□
`--enable-lb` + `--enable-gw-nftable-lb-svc`	OVN □□ ClusterIP□□□□□ LoadBalancer □ EIP □□□□
`--enable-gw-nftable-lb-svc` + `--enable-gw-nftable-svc-cluster-ip`	□□□□□□ EIP □ ClusterIP□OVN LB □□□
□ `--enable-gw-nftable-svc-cluster-ip`	□□□□□ ClusterIP□□ EIP□□□□ `--enable-lb` □□
`--enable-lb-svc` + `--enable-lb`	Pod □□□□ EIP□OVN □□□□□□□ ClusterIP
`--enable-lb-svc` + `--enable-gw-nftable-svc-cluster-ip`	Pod □□□□ EIP□□□□□ ClusterIP

□□□□□

- `--enable-lb-svc` □ `--enable-gw-nftable-lb-svc` □□□□□□ LoadBalancer Service □ EIP □□□□
- □□ Service □□□□□□ `ovn.kubernetes.io/vpc-nat-gw` □ `ovn.kubernetes.io/service_external_ip_from_subnet` annotation□webhook □□□□□□□□□□□□□□ LoadBalancer ingress IP□

□□□□□ □ Service □□ annotation `ovn.kubernetes.io/vpc-nat-gw` □□□□□□□□LoadBalancer □□□ Service □□□□ `ovn.kubernetes.io/eip` □□ EIP □□□□□□□□

```
apiVersion: v1
kind: Service
metadata:
  name: my-app
  annotations:
    ovn.kubernetes.io/vpc-nat-gw: gw1
    ovn.kubernetes.io/eip: eipd01
```

```
spec:
  type: LoadBalancer
  selector:
    app: my-app
  ports:
  - port: 80
    targetPort: 8080
    protocol: TCP
```

□□□□□□□□ Service □□□□□□□□□□□□ `IptablesDnatRule` □ `type: share` □□□□□□ Pod □□□ nftables □□□Service □□□□□□□□

□□□□□

- □□□□ `LoadBalancer` □ `ClusterIP` □□□ Service
- □□□□□□ClusterIP□□□□□□□EIP□□□□□□□□□
- □□□ `ExternalTrafficPolicy: Cluster` □□□□ Local □□
- share DNAT □□□ IPv4
- □□□□□□ EndpointSlice □□□□

5.1.4 □□□□□

□□□□ VPC □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□ Kube-OVN □□□□□□□□□□□□□□□□□□□

□□□□

```
kind: Vpc
apiVersion: kubeovn.io/v1
metadata:
  name: test-vpc-1
spec:
  staticRoutes:
    - cidr: 0.0.0.0/0
      nextHopIP: 10.0.1.254
      policy: policyDst
    - cidr: 172.31.0.0/24
      nextHopIP: 10.0.1.253
      policy: policySrc
      routeTable: "rtb1"
```

- `policy`：□□□□□□□□ `policyDst` □□□□□□□ `policySrc` □
- □□□□□□□□□□□□CIDR □□□□□□□□□□□□□□□□□□□□

▯▯ `SwitchLBRule` ▯▯▯▯▯

```
apiVersion: kubeovn.io/v1
kind: SwitchLBRule
metadata:
  name:  cjh-slr-nginx
spec:
  vip: 1.1.1.1
  sessionAffinity: ClientIP
  namespace: default
  selector:
    - app: nginx
  ports:
  - name: dns
    port: 8888
    targetPort: 80
    protocol: TCP
```

- `vip` ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯
- `namespace` ▯▯▯▯▯▯▯▯ Pod ▯▯▯ Namespace▯
- `sessionAffinity` ▯▯ Service ▯ `sessionAffinity` ▯▯▯▯▯
- `selector` ▯▯ Service ▯ `selector` ▯▯▯▯▯
- `ports` ▯▯ Service ▯ `port` ▯▯▯▯▯

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

```
# kubectl get slr
NAME               VIP         PORT(S)                 SERVICE                            AGE
vpc-dns-test-cjh2  10.96.0.3   53/UDP,53/TCP,9153/TCP  kube-system/slr-vpc-dns-test-cjh2  88m
```

5.1.6 ▯▯▯ vpc-dns

▯▯▯▯▯ VPC ▯▯▯ VPC ▯▯▯▯▯▯▯VPC ▯ Pod ▯▯▯▯▯▯▯ coredns ▯▯▯▯▯▯▯▯▯ ▯▯▯▯▯▯▯▯▯ VPC ▯▯▯ CoreDNS ▯▯▯▯▯ Service ▯▯▯▯▯▯▯ Kube-OVN ▯▯▯ vpc-dns ▯▯▯▯▯▯

▯▯▯▯▯▯▯

```
apiVersion: "k8s.cni.cncf.io/v1"
kind: NetworkAttachmentDefinition
metadata:
  name: ovn-nad
  namespace: default
spec:
  config: '{
      "cniVersion": "0.3.0",
      "type": "kube-ovn",
      "server_socket": "/run/openvswitch/kube-ovn-daemon.sock",
      "provider": "ovn-nad.default.ovn"
    }'
```

▯▯ **vpc-dns ▯ ConfigMap**

▯ kube-system ▯▯▯▯▯▯▯ configmap▯▯▯ vpc-dns ▯▯▯▯▯▯▯▯▯▯▯▯ vpc-dns ▯▯▯

```
apiVersion: v1
kind: ConfigMap
metadata:
  name: vpc-dns-config
  namespace: kube-system
data:
  coredns-vip: 10.96.0.3
  enable-vpc-dns: "true"
  nad-name: ovn-nad
  nad-provider: ovn-nad.default.ovn
```

- `enable-vpc-dns` ▯▯▯▯▯▯ `true` ▯▯▯▯▯ `false` ▯▯▯▯▯▯▯ `true` ▯
- `coredns-image` ▯▯▯▯▯▯▯dns ▯▯▯▯▯▯▯▯▯▯▯ coredns ▯▯▯▯▯
- `coredns-vip` ▯▯ coredns ▯▯ lb ▯▯▯ vip▯
- `nad-name` ▯▯▯▯ `network-attachment-definitions` ▯▯▯▯▯
- `nad-provider` ▯▯▯▯ provider ▯▯▯

2025 Kube-OVN Team

- `k8s-service-host` □□□□□□□□ coredns □□ k8s apiserver □□□ ip□
- `k8s-service-port` □□□□□□□□ coredns □□ k8s apiserver □□□ port□

□□ **vpc-dns** □□□□

```yaml
apiVersion: rbac.authorization.k8s.io/v1
kind: ClusterRole
metadata:
  labels:
    kubernetes.io/bootstrapping: rbac-defaults
  name: system:vpc-dns
rules:
  - apiGroups:
    - ""
    resources:
    - endpoints
    - services
    - pods
    - namespaces
    verbs:
    - list
    - watch
  - apiGroups:
    - discovery.k8s.io
    resources:
    - endpointslices
    verbs:
    - list
    - watch
---
apiVersion: rbac.authorization.k8s.io/v1
kind: ClusterRoleBinding
metadata:
  annotations:
    rbac.authorization.kubernetes.io/autoupdate: "true"
  labels:
    kubernetes.io/bootstrapping: rbac-defaults
  name: vpc-dns
roleRef:
  apiGroup: rbac.authorization.k8s.io
  kind: ClusterRole
  name: system:vpc-dns
subjects:
- kind: ServiceAccount
  name: vpc-dns
  namespace: kube-system
---
apiVersion: v1
kind: ServiceAccount
metadata:
  name: vpc-dns
  namespace: kube-system
---
apiVersion: v1
kind: ConfigMap
metadata:
  name: vpc-dns-corefile
  namespace: kube-system
data:
  Corefile: |
    .:53 {
        errors
        health {
          lameduck 5s
        }
        ready
        kubernetes cluster.local in-addr.arpa ip6.arpa {
          pods insecure
          fallthrough in-addr.arpa ip6.arpa
        }
        prometheus :9153
        forward . /etc/resolv.conf {
          prefer_udp
        }
        cache 30
        loop
        reload
        loadbalance
    }
```

□□ **vpc-dns**

```yaml
kind: VpcDns
apiVersion: kubeovn.io/v1
metadata:
  name: test-cjh1
spec:
```

```
  vpc: cjh-vpc-1
  subnet: cjh-subnet-1
```

- `vpc` ▯▯▯▯▯ dns ▯▯▯ vpc ▯▯▯
- `subnet` ▯▯▯▯▯ dns ▯▯▯▯▯▯▯▯

▯▯▯▯▯▯▯

```
[root@hci-dev-mst-1 kubeovn]# kubectl get vpc-dns
NAME        ACTIVE   VPC         SUBNET
test-cjh1   false    cjh-vpc-1   cjh-subnet-1
test-cjh2   true     cjh-vpc-1   cjh-subnet-2
```

- `ACTIVE`：`true` ▯▯▯▯▯▯▯▯ dns ▯▯▯ `false` ▯▯▯

▯▯

- ▯▯ VPC ▯▯▯▯▯▯▯▯▯▯ DNS ▯▯▯
- ▯▯▯ VPC ▯▯▯▯▯ vpc-dns ▯▯▯▯▯▯▯ VPC ▯▯▯ subnet▯▯▯▯▯▯ vpc-dns ▯▯▯▯▯ `true` ▯▯▯▯ `false` ▯
- ▯ `true` ▯ vpc-dns ▯▯▯▯▯▯▯▯▯▯ `false` ▯ vpc-dns ▯▯▯▯▯

5.1.7 ▯▯▯▯

▯▯▯▯▯ VPC ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ VPC ▯▯▯▯▯▯▯▯

```
kind: Vpc
apiVersion: kubeovn.io/v1
metadata:
  name: test-vpc-1
spec:
  namespaces:
  - ns1
  defaultSubnet: test
```

- `defaultSubnet` ▯VPC ▯▯▯▯▯▯▯▯▯▯

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Namespace ▯▯ `ovn.kubernetes.io/logical_switch` ▯▯▯▯▯▯▯▯▯▯▯▯ `ovn.kubernetes.io/logical_switch` ▯▯▯ Pod ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

▯▯▯ VPC Pod ▯▯ livenessProbe ▯ readinessProbe

▯▯▯▯▯▯▯▯▯▯▯▯ VPC ▯▯ Pod ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ kubelet ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ VPC ▯▯ Pod▯Kube-OVN ▯▯ TProxy ▯ kubelet ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ VPC ▯▯ Pod▯▯▯▯▯▯▯▯▯▯▯▯

▯▯▯▯▯▯▯▯▯ DaemonSet `kube-ovn-cni` ▯▯▯▯▯▯ `--enable-tproxy=true` ▯

```
spec:
  template:
    spec:
      containers:
      - args:
        - --enable-tproxy=true
```

▯▯▯▯▯▯▯▯▯

1. ▯▯▯▯▯▯▯▯▯▯▯▯▯ VPC ▯▯ Pod ▯▯▯▯▯▯ IP▯▯▯▯▯▯▯▯▯
2. ▯▯▯▯▯▯▯▯ `tcpSocket` ▯ `httpGet` ▯▯▯▯▯▯▯▯

PDF Slack Support

2025 Kube-OVN Team

2026⬚11⬚5⬚

2022⬚5⬚24⬚

GitHub 


5.1.8 ⬚⬚

5.2 VPC Egress Gateway


Note

□□□ VPC □□□□□□□□□ VPC □□□□□□□□□□□□□□□


□□□□□ VPC □□□□□□□□□□□□□□VPC NAT □□□OVN □□□ Egress Gateway□□□ VPC NAT □□□ Kube-OVN □□□□□□□□□□□□□□ VPC NAT □□□□□□□□□ Pod□□□□□□□□□□ VPC □□□□□□□□□□ Macvlan □□□□□□□□□□□ Pod □□ iptables □□□□□□□□□□□□□□□



□□ Egress Gateway □□□□□□□□□□□□□ OVN □□□□□□ VPC □ Pod □□□□□□□□□□□OVN □□□□□□□□□□□□□□□□□□□ Egress Gateway □□□□□□□□□□□□□□□□□□□ Egress Gateway □□□□□□□□□□ □□□□□□□□□□□□□□



OVN ■■ BFD ■■■■■ Egress Gateway ■■■■■■■■■■ Egress Gateway ■■■■■■OVN ■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■



5.2.2 ▯▯▯▯

VPC Egress Gateway ▯ VPC NAT Gateway ▯▯▯▯▯▯▯▯▯▯▯ ▯▯ Multus-CNI▯

> ▯▯ VPC Egress Gateway ▯▯▯▯▯▯ ConfigMap▯

▯ Kube-OVN ▯▯▯▯▯ CNI ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ NetworkAttachmentDefinition ▯▯▯ Kube-OVN ▯▯▯▯▯▯▯▯ provider ▯▯▯▯ `<nad-name>.<nad-namespace>.ovn` ▯▯▯▯▯▯ ▯▯ NetworkAttachmentDefinition ▯▯▯▯▯▯▯▯▯▯

```yaml
apiVersion: k8s.cni.cncf.io/v1
kind: NetworkAttachmentDefinition
metadata:
  name: veg-internal
  namespace: default
spec:
  config: |
    {
      "cniVersion": "0.3.1",
      "type": "kube-ovn",
      "server_socket": "/run/openvswitch/kube-ovn-daemon.sock",
      "provider": "veg-internal.default.ovn"
    }
---
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: veg-internal-subnet
spec:
  vpc: vpc1
  provider: veg-internal.default.ovn
  protocol: IPv4
  cidrBlock: 192.168.0.0/24
  gateway: 192.168.0.1
```

█ VPC Egress Gateway ███ `internalSubnet` ████████████████Multus ████ NetworkAttachmentDefinition ██ Pod ██████████ Pod ██████████ `eth0` █ `externalSubnet` ██████ NetworkAttachmentDefinition ██ `net1` ████████████████ CNI `eth0` ██████████ Pod██████████ `policies` ████████████ CNI ███████ `selectors` ███ provider ████████ NetworkAttachmentDefinition████████████████ reconcile█

5.2.3 ████

██ NetworkAttachmentDefinition

VPC Egress Gateway ██████████ VPC ████████████████ NetworkAttachmentDefinition ████████████ `macvlan` ████ Kube-OVN ██ IPAM ███████

```yaml
apiVersion: k8s.cni.cncf.io/v1
kind: NetworkAttachmentDefinition
metadata:
  name: eth1
  namespace: default
spec:
  config: '{
      "cniVersion": "0.3.0",
      "type": "macvlan",
      "master": "eth1",
      "mode": "bridge",
      "ipam": {
        "type": "kube-ovn",
        "server_socket": "/run/openvswitch/kube-ovn-daemon.sock",
        "provider": "eth1.default"
      }
    }'
---
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: macvlan1
spec:
  protocol: IPv4
  provider: eth1.default
  cidrBlock: 172.17.0.0/16
  gateway: 172.17.0.1
  excludeIps:
    - 172.17.0.0..172.17.0.10
```

> ███████ CNI ████ NetworkAttachmentDefinition █ VPC Egress Gateway ██████████

████████████████████ ██████

██ VPC Egress Gateway

██ VPC Egress Gateway ████████

```yaml
apiVersion: kubeovn.io/v1
kind: VpcEgressGateway
metadata:
  name: gateway1
  namespace: default
spec:
  vpc: ovn-cluster
  replicas: 1
  externalSubnet: macvlan1
  policies:
    - snat: true
      subnets:
        - ovn-default
```

███████ default ███████ VPC `ovn-cluster` ███████ gateway1 ████ VPC Egress Gateway█ `ovn-cluster` █ `ovn-default` ███10.16.0.0/16██████ Pod ███ `macvlan1` ███ SNAT ████████████

████████ CNI ████████████████████████████████████

```yaml
apiVersion: kubeovn.io/v1
kind: VpcEgressGateway
metadata:
  name: gateway-nonprimary
  namespace: default
spec:
  vpc: vpc1
  replicas: 1
  internalSubnet: veg-internal-subnet
  externalSubnet: macvlan1
  policies:
    - snat: true
```


2025 Kube-OVN Team

```
      subnets:
        - veg-internal-subnet
```

▯▯▯▯▯▯▯▯ VPC Egress Gateway▯

```
$ kubectl get veg gateway1
NAME       VPC           REPLICAS   BFD ENABLED   EXTERNAL SUBNET   PHASE       READY   AGE
gateway1   ovn-cluster   1          false         macvlan1          Completed   true    13s
```

▯▯▯▯▯▯▯▯

```
kubectl get veg gateway1 -o wide
NAME       VPC           REPLICAS   BFD ENABLED   EXTERNAL SUBNET   PHASE       READY   INTERNAL IPS     EXTERNAL IPS      WORKING NODES         AGE
gateway1   ovn-cluster   1          false         macvlan1          Completed   true    ["10.16.0.12"]   ["172.17.0.11"]   ["kube-ovn-worker"]   82s
```

▯▯▯▯▯▯▯▯

```
$ kubectl get deployment -l ovn.kubernetes.io/vpc-egress-gateway=gateway1
NAME       READY   UP-TO-DATE   AVAILABLE   AGE
gateway1   1/1     1            1           4m40s

$ kubectl get pod -l ovn.kubernetes.io/vpc-egress-gateway=gateway1 -o wide
NAME                        READY   STATUS    RESTARTS   AGE     IP           NODE              NOMINATED NODE   READINESS GATES
gateway1-b9f8b4448-76lhm   1/1     Running   0          4m48s   10.16.0.12   kube-ovn-worker   <none>           <none>
```

▯▯ Pod ▯▯ IP▯▯▯▯ iptables ▯▯▯

```
$ kubectl exec gateway1-b9f8b4448-76lhm -c gateway -- ip address show
1: lo: <LOOPBACK,UP,LOWER_UP> mtu 65536 qdisc noqueue state UNKNOWN group default qlen 1000
    link/loopback 00:00:00:00:00:00 brd 00:00:00:00:00:00
    inet 127.0.0.1/8 scope host lo
       valid_lft forever preferred_lft forever
    inet6 ::1/128 scope host
       valid_lft forever preferred_lft forever
2: net1@if13: <BROADCAST,MULTICAST,UP,LOWER_UP> mtu 1500 qdisc noqueue state UP group default qlen 1000
    link/ether 62:d8:71:90:7b:86 brd ff:ff:ff:ff:ff:ff link-netnsid 0
    inet 172.17.0.11/16 brd 172.17.255.255 scope global net1
       valid_lft forever preferred_lft forever
    inet6 fe80::60d8:71ff:fe90:7b86/64 scope link
       valid_lft forever preferred_lft forever
17: eth0@if18: <BROADCAST,MULTICAST,UP,LOWER_UP> mtu 1400 qdisc noqueue state UP group default
    link/ether 36:7c:6b:c7:82:6b brd ff:ff:ff:ff:ff:ff link-netnsid 0
    inet 10.16.0.12/16 brd 10.16.255.255 scope global eth0
       valid_lft forever preferred_lft forever
    inet6 fe80::347c:6bff:fec7:826b/64 scope link
       valid_lft forever preferred_lft forever

$ kubectl exec gateway1-b9f8b4448-76lhm -c gateway -- ip route show
default via 172.17.0.1 dev net1
10.16.0.0/16 dev eth0 proto kernel scope link src 10.16.0.12
172.17.0.0/16 dev net1 proto kernel scope link src 172.17.0.11

$ kubectl exec gateway1-b9f8b4448-76lhm -c gateway -- iptables -t nat -S
-P PREROUTING ACCEPT
-P INPUT ACCEPT
-P OUTPUT ACCEPT
-P POSTROUTING ACCEPT
-A POSTROUTING -s 10.16.0.0/16 -j MASQUERADE --random-fully
```

▯ Gateway Pod ▯▯▯▯▯▯▯▯▯▯

```
$ kubectl exec -ti gateway1-b9f8b4448-76lhm -c gateway -- bash
nobody@gateway1-b9f8b4448-76lhm:/kube-ovn$ tcpdump -i any -nnve icmp and host 172.17.0.1
tcpdump: data link type LINUX_SLL2
tcpdump: listening on any, link-type LINUX_SLL2 (Linux cooked v2), snapshot length 262144 bytes
06:50:58.936528 eth0  In  ifindex 17 92:26:b8:9e:f2:1c ethertype IPv4 (0x0800), length 104: (tos 0x0, ttl 63, id 30481, offset 0, flags [DF], proto ICMP (1),
length 84)
    10.16.0.9 > 172.17.0.1: ICMP echo request, id 37989, seq 0, length 64
06:50:58.936574 net1  Out ifindex 2 62:d8:71:90:7b:86 ethertype IPv4 (0x0800), length 104: (tos 0x0, ttl 62, id 30481, offset 0, flags [DF], proto ICMP (1),
length 84)
    172.17.0.11 > 172.17.0.1: ICMP echo request, id 39449, seq 0, length 64
06:50:58.936613 net1  In  ifindex 2 02:42:39:79:7f:08 ethertype IPv4 (0x0800), length 104: (tos 0x0, ttl 64, id 26701, offset 0, flags [none], proto ICMP
(1), length 84)
    172.17.0.1 > 172.17.0.11: ICMP echo reply, id 39449, seq 0, length 64
06:50:58.936621 eth0  Out ifindex 17 36:7c:6b:c7:82:6b ethertype IPv4 (0x0800), length 104: (tos 0x0, ttl 63, id 26701, offset 0, flags [none], proto ICMP
(1), length 84)
    172.17.0.1 > 10.16.0.9: ICMP echo reply, id 37989, seq 0, length 64
```

OVN Logical Router ▯▯▯▯▯▯▯▯▯▯▯

```
$ kubectl ko nbctl lr-policy-list ovn-cluster
Routing Policies
     31000                           ip4.dst == 10.16.0.0/16           allow
```

```
     31000                          ip4.dst == 100.64.0.0/16           allow
     30000                             ip4.dst == 172.18.0.2         reroute               100.64.0.3
     30000                             ip4.dst == 172.18.0.3         reroute               100.64.0.2
     30000                             ip4.dst == 172.18.0.4         reroute               100.64.0.4
     29100                           ip4.src == 10.16.0.0/16         reroute               10.16.0.12
     29000 ip4.src == $ovn.default.kube.ovn.control.plane_ip4         reroute               100.64.0.2
     29000       ip4.src == $ovn.default.kube.ovn.worker2_ip4         reroute               100.64.0.4
     29000        ip4.src == $ovn.default.kube.ovn.worker_ip4         reroute               100.64.0.3
```

... `.spec.replicas` ...

```
$ kubectl scale veg gateway1 --replicas=2
vpcegressgateway.kubeovn.io/gateway1 scaled

$ kubectl get veg gateway1
NAME       VPC           REPLICAS   BFD ENABLED   EXTERNAL SUBNET   PHASE       READY   AGE
gateway1   ovn-cluster   2          false         macvlan           Completed   true    39m

$ kubectl get pod -l ovn.kubernetes.io/vpc-egress-gateway=gateway1 -o wide
NAME                        READY   STATUS    RESTARTS   AGE   IP           NODE               NOMINATED NODE   READINESS GATES
gateway1-b9f8b4448-76lhm   1/1     Running   0          40m   10.16.0.12   kube-ovn-worker    <none>           <none>
gateway1-b9f8b4448-zd4dl   1/1     Running   0          64s   10.16.0.13   kube-ovn-worker2   <none>           <none>

$ kubectl ko nbctl lr-policy-list ovn-cluster
Routing Policies
     31000                            ip4.dst == 10.16.0.0/16           allow
     31000                          ip4.dst == 100.64.0.0/16           allow
     30000                             ip4.dst == 172.18.0.2         reroute               100.64.0.3
     30000                             ip4.dst == 172.18.0.3         reroute               100.64.0.2
     30000                             ip4.dst == 172.18.0.4         reroute               100.64.0.4
     29100                           ip4.src == 10.16.0.0/16         reroute               10.16.0.12, 10.16.0.13
     29000 ip4.src == $ovn.default.kube.ovn.control.plane_ip4         reroute               100.64.0.2
     29000       ip4.src == $ovn.default.kube.ovn.worker2_ip4         reroute               100.64.0.4
     29000        ip4.src == $ovn.default.kube.ovn.worker_ip4         reroute               100.64.0.3
```

... Egress Gateway IP ...

... `externalIPs` ... `nodeSelector` ... Egress Gateway Pods ... Egress IP ...

```yaml
apiVersion: kubeovn.io/v1
kind: VpcEgressGateway
metadata:
  name: gateway1
  namespace: default
spec:
  vpc: ovn-cluster
  replicas: 2
  externalSubnet: macvlan1
  policies:
    - snat: true
      subnets:
        - ovn-default
  externalIPs:
    - 172.17.0.10
    - 172.17.0.11
  nodeSelector:
    - matchLabels:
        kubernetes.io/hostname: kube-ovn-worker
```

... IP ... `internalIPPool` ... `externalIPPool` ... `IPPool` ...IPPool ... `internalSubnet` ... `externalSubnet` ... `internalIPs` ... `externalIPs` ...

```yaml
spec:
  internalIPPool: veg-internal
  externalIPPool: veg-external
```

... BFD ...

BFD ... VPC ... BFD LRP ... VPC ... BFD Port...

```yaml
apiVersion: kubeovn.io/v1
kind: Vpc
metadata:
  name: vpc1
spec:
  bfdPort:
    enabled: true
    ip: 10.255.255.255
---
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
```

```
  name: subnet1
spec:
  vpc: vpc1
  protocol: IPv4
  cidrBlock: 192.168.0.0/24
```

██ BFD Port ██████ OVN LR ████████████ BFD ▯ LRP▯

```
$ kubectl ko nbctl show vpc1
router 0c1d1e8f-4c86-4d96-88b2-c4171c7ff824 (vpc1)
    port bfd@vpc1
        mac: "8e:51:4b:16:3c:90"
        networks: ["10.255.255.255"]
    port vpc1-subnet1
        mac: "de:c9:5c:38:7a:61"
        networks: ["192.168.0.1/24"]
```

██████ VPC Egress Gateway ▯ `.spec.bfd.enabled` ███ `true` ████████

```
apiVersion: kubeovn.io/v1
kind: VpcEgressGateway
metadata:
  name: gateway2
  namespace: default
spec:
  vpc: vpc1
  replicas: 2
  internalSubnet: subnet1
  externalSubnet: macvlan
  bfd:
    enabled: true
  policies:
    - snat: true
      ipBlocks:
        - 192.168.0.0/24
```

██ VPC Egress Gateway ███

```
$ kubectl get veg gateway2 -o wide
NAME       VPC    REPLICAS   BFD ENABLED   EXTERNAL SUBNET   PHASE       READY   INTERNAL IPS                    EXTERNAL IPS                    WORKING
NODES                            AGE
gateway2   vpc1   2          true          macvlan           Completed   true    ["192.168.0.2","192.168.0.3"]   ["172.17.0.13","172.17.0.14"]   ["kube-ovn-
worker","kube-ovn-worker2"]   58s

$ kubectl get pod -l ovn.kubernetes.io/vpc-egress-gateway=gateway2 -o wide
NAME                        READY   STATUS    RESTARTS   AGE     IP            NODE               NOMINATED NODE   READINESS GATES
gateway2-fcc6b8b87-8lgvx    1/1     Running   0          2m18s   192.168.0.3   kube-ovn-worker2   <none>           <none>
gateway2-fcc6b8b87-wmww6    1/1     Running   0          2m18s   192.168.0.2   kube-ovn-worker    <none>           <none>

$ kubectl ko nbctl lr-policy-list vpc1
Routing Policies
     29100                       ip4.src == 192.168.0.0/24         reroute                192.168.0.2, 192.168.0.3
     29090                       ip4.src == 192.168.0.0/24            drop

$ kubectl ko nbctl list bfd
_uuid               : 223ede10-9169-4c7d-9524-a546e24bfab5
detect_mult         : 3
dst_ip              : "192.168.0.2"
external_ids        : {af="4", vendor=kube-ovn, vpc-egress-gateway="default/gateway2"}
logical_port        : "bfd@vpc1"
min_rx              : 1000
min_tx              : 1000
options             : {}
status              : up

_uuid               : b050c75e-2462-470b-b89c-7bd38889b758
detect_mult         : 3
dst_ip              : "192.168.0.3"
external_ids        : {af="4", vendor=kube-ovn, vpc-egress-gateway="default/gateway2"}
logical_port        : "bfd@vpc1"
min_rx              : 1000
min_tx              : 1000
options             : {}
status              : up
```

██ Pod ██ BFD ███

```
$ kubectl exec gateway2-fcc6b8b87-8lgvx -c bfdd -- bfdd-control status
There are 1 sessions:
Session 1
 id=1 local=192.168.0.3 (p) remote=10.255.255.255 state=Up

$ kubectl exec gateway2-fcc6b8b87-wmww6 -c bfdd -- bfdd-control status
There are 1 sessions:
Session 1
 id=1 local=192.168.0.2 (p) remote=10.255.255.255 state=Up
```

□□□□

VPC BFD PORT

□□	□□	□□	□□□	□□	□□
`enabled`	`boolean`	□	`false`	□□□□ BFD Port□	`true`
`ip`	`string`	□	-	BFD Port □□□ IP □□□ □□□□□□□□□□□□ IPv6 □ □□□	`169.255.255.2` `fdff::1` / `169.255.255.2`
`nodeSelector`	`object`	□	-	□□□□□□ BFD Port □□□ □□□□□□□□BFD Port □ □□□□□□□□□□□□□□□□ OVN HA Chassis Group□□□ Active/ Backup □□□□□□ Active □□□□□□□□□□ nodeSelector□ Kube-OVN □□□□□□□□□ □□□□□□□□□□ `kubectl ko nbctl list ha_chassis_group` □□□□□□□ OVN HA Chassis Group □□□	-
`nodeSelector.matchLabels`	`dict/map`	□	-	□□□□□□□□□□□□□	-
`nodeSelector.matchExpressions`	`object array`	□	-	□□□□□□□□□□□□□	-

2025 Kube-OVN Team

VPC EGRESS GATEWAY

Spec▯

...	...	...	...	...	...
`vpc`	`string`	...	... VPC ...ovn-cluster...	VPC ...	`vpc1`
`replicas`	`integer/int32`	...	`1`	...	`2`
`prefix`	`string`	...	-	... Deployment ...	`veg-`
`image`	`string`	...	-	... Deployment ...	`docker.io/kubeovn/kube-ovn:v1.14.0-debug`
`internalSubnet`	`string`	...	VPC ...	... VPC ...	`subnet1`
`externalSubnet`	`string`	...	-	...	`ext1`
`externalNetworkMode`	`string`	...	`Attachment`	... `Attachment` ... externalSubnet ... `PrimaryCNI` ... Pod ...PrimaryCNI ... externalIP/externalIPPool/BGP/EVPN/selectors/bandwidth/observability... CNI ...	`PrimaryCNI`
`internalIPs`	`string array`	...	-	... VPC ... IP ... IPv6 ... IP ... `<replicas> + 1` ... Pod ...	`10.16.0.101` / `fd00::11` / `10.16.0.101,fd00::11`
`externalIPs`	`string array`	...	-	... IP ... IPv6 ... IP ... `<replicas> + 1` ... Pod ...	`10.16.0.101` / `fd00::11` / `10.16.0.101,fd00::11`
`internalIPPool`	`string`	...	-	... `IPPool` ...IPPool ... `internalSubnet` ... `internalIPs` ...	`veg-internal`
`externalIPPool`	`string`	...	-	... `IPPool` ...IPPool ... `externalSubnet` ... `externalIPs` ...	`veg-external`
`bfd`	`object`	...	-	BFD ...	-

2025 Kube-OVN Team

...	...	...	...	...	...
`policies`	`object array`	...	-	Egress ... `selectors` ...	-
`selectors`	`object array`	...	-	... Namespace Selector ... Pod Selector ... Egress ... Pod ... SNAT/ MASQUERADE... ... `policies` ...	-
`nodeSelector`	`object array`	...	-	...Deployment/ Pod...	-
`trafficPolicy`	`string`	...	`Cluster`	... `Cluster` / `Local` ... **BFD** ... ... `Local` ... Egress ... ... VPC Egress Gateway ... ... VPC Egress Gateway ... Egress ...	`Local`
`podAntiAffinity`	`string`	...	`Required`	Pod ... `Required` ... ... `Preferred` ... ... `Preferred` ... `Required` ... Pod ...	`Preferred`
`priorityClassName`	`string`	...	-	... Pod ... PriorityClass ... ... Pod ...	`high-priority`
`bandwidth`	`object`	...	-	...	-
`bandwidth.ingress`	`integer` `string`	...	-	... VPC ...	`1024` / `1Gi`
`bandwidth.egress`	`integer` `string`	...	-	... VPC ...	`1024` / `1Gi`

...

... Mbps ... `M` ... `Mi` ... `G` ... `Gi` ... quantity ... bit/s... Mbps... `100M` ... `100Mi` ... `1G` ... `1Gi` ... 100...105...1000 ... 1074 Mbps...

... 9223372036854 Mbps... `ingress` ... `egress` ...

```yaml
spec:
  bandwidth:
    ingress: 1024
    egress: 1Gi
```


2025 Kube-OVN Team

> ⚠ ████████

████0 ▯ 9223372036854 ████████████████ Mbps ██████ Kube-OVN ████████ `vpc-egress-gateways.kubeovn.io` CRD ██████████ `x-kubernetes-int-or-string: true` ██████████████

Helm ████ Chart ▯ `crds/` ████ CRD███ `kube-ovn-v2` Chart ██████ `KUBE_OVN_VERSION` ██████████ Kube-OVN ████████████████████████ CRD bundle▯

```
kubectl apply -f "https://raw.githubusercontent.com/kubeovn/kube-ovn/${KUBE_OVN_VERSION}/charts/kube-ovn-v2/crds/kube-ovn-crd.yaml"
```

████████████████████████████████ quantity ████████████ Mbps ▯▯

BFD ▯▯▯

▯▯	▯▯	▯▯	▯▯▯	▯▯	▯▯
`enabled`	`boolean`	▯	`false`	████ BFD▯	`true`
`minRX`	`integer/int32`	▯	`1000`	BFD minRX ▯ ▯ms▯▯	`500`
`minTX`	`integer/int32`	▯	`1000`	BFD minTX ▯ ▯ms▯▯	`500`
`multiplier`	`integer/int32`	▯	`3`	BFD multiplier ▯▯	`1`

Egress ▯▯▯

▯▯	▯▯	▯▯	▯▯▯	▯▯	▯▯
`snat`	`boolean`	▯	`false`	████ SNAT/ MASQUERADE▯	`true`
`ipBlocks`	`string array`	▯	-	████ Gateway ▯ IP ██████ IPv6▯	`192.168.0.1` / `192.168.0.0/24`
`subnets`	`string array`	▯	-	████ Gateway ▯ VPC ███████ IPv6 ████████	`subnet1`

Selectors▯

▯▯	▯▯	▯▯	▯▯▯	▯▯	▯▯
`namespaceSelector`	`object`	▯	-	Namespace ████ ███████ Namespace▯	-
`namespaceSelector.matchLabels`	`dict/map`	▯	-	████████████	-
`namespaceSelector.matchExpressions`	`object array`	▯	-	████████████	-
`podSelector`	`object`	▯	-	Pod ████████████ Pod▯	-
`podSelector.matchLabels`	`dict/map`	▯	-	████████████	-
`podSelector.matchExpressions`	`object array`	▯	-	████████████	-

2025 Kube-OVN Team

⬚⬚⬚⬚⬚⬚

⬚⬚	⬚⬚	⬚⬚	⬚⬚⬚	⬚⬚	⬚⬚
matchLabels	dict/map	⬚	-	⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚	-
matchExpressions	object array	⬚	-	⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚	-
matchFields	object array	⬚	-	⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚	-

Status⬚

⬚⬚	⬚⬚	⬚⬚	⬚⬚
ready	boolean	Gateway ⬚⬚⬚⬚⬚	true
phase	string	Gateway ⬚⬚⬚⬚⬚	Pending / Processing / Completed
internalIPs	string array	⬚⬚ VPC ⬚⬚⬚⬚⬚ IP ⬚⬚⬚	-
externalIPs	string array	⬚⬚⬚⬚⬚⬚⬚⬚⬚ IP ⬚⬚⬚	-
workload	object	⬚⬚⬚⬚⬚⬚⬚⬚	-
workload.apiVersion	string	⬚⬚⬚⬚ API ⬚⬚⬚	apps/v1
workload.kind	string	⬚⬚⬚⬚⬚⬚⬚⬚	Deployment
workload.name	string	⬚⬚⬚⬚⬚⬚⬚⬚	gateway1
workload.nodes	string array	⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚	-
conditions	object array	-	-

PDF Slack Support

2026⬚11⬚5⬚

2024⬚12⬚12⬚

GitHub

+1

5.2.4 ⬚⬚

2025 Kube-OVN Team

5.3 VPC Egress Gateway ▯▯▯▯

VPC Egress Gateway ▯▯▯▯▯▯▯ Pod ▯▯▯▯▯▯▯▯▯▯▯▯ sidecar▯▯ sidecar ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ conntrack NAT ▯▯▯▯▯▯▯▯ NAT ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

...ConfigMap ... Service ... condition... observer ...volume ... Pod...

... `/kube-ovn/vpc-egress-gateway-observer` ...launcher ... `sleep infinity` ... binary ... observer ... `CAP_NET_ADMIN` file capability... conntrack ...

5.3.3 ...

observer ... TCP ... `10666` ... `/metrics` ... `/healthz` ...observer ... Prometheus registry... `go_*` ... `process_*` ... `promhttp_*` ... `namespace` ... `name` ... `pod` ... `node` ...

...liveness probe ... observer binary... loopback ... `/healthz` ... observer ... Pod ... observer binary ... `sleep infinity` ...

...

... scrape ... `/proc/net/dev` ...observer ... scrape ... Pod `network-status` annotation ... Multus ...

...	...	...
`kube_ovn_vpc_egress_gateway_interface_rx_bytes_total`	`interface` ... `type`	...
`kube_ovn_vpc_egress_gateway_interface_tx_bytes_total`	`interface` ... `type`	...
`kube_ovn_vpc_egress_gateway_interface_rx_packets_total`	`interface` ... `type`	...
`kube_ovn_vpc_egress_gateway_interface_tx_packets_total`	`interface` ... `type`	...
`kube_ovn_vpc_egress_gateway_interface_drops_total`	`interface` ... `type` ... `direction`	...
`kube_ovn_vpc_egress_gateway_interface_errors_total`	`interface` ... `type` ... `direction`	...

`type` ... `internal` ... `external` ... `direction` ... `rx` ... `tx` ...

Conntrack ...

Conntrack ... IP ...

...	...	...
`kube_ovn_vpc_egress_gateway_conntrack_nat_flows_active`	`address_family` ... `protocol` ... `nat_type`	... NAT ... conntrack table dump ...
`kube_ovn_vpc_egress_gateway_conntrack_nat_flows_started_total`	`address_family` ... `protocol` ... `nat_type`	observer ... NAT ...
`kube_ovn_vpc_egress_gateway_conntrack_nat_flows_ended_total`	`address_family` ... `protocol` ... `nat_type`	... NAT ...
`kube_ovn_vpc_egress_gateway_conntrack_nat_packets_total`	`address_family` ... `protocol` ... `nat_type` ... `direction`	conntrack accounting ...
`kube_ovn_vpc_egress_gateway_conntrack_nat_bytes_total`	`address_family` ... `protocol` ... `nat_type` ... `direction`	conntrack accounting ...

`address_family` ... `ipv4` ... `ipv6` ... `protocol` ... `tcp` ... `udp` ... `sctp` ... `icmp` ... `icmpv6` ... `other` ... `nat_type` ... `snat` ... `dnat` ... `snat_dnat` ... `direction` ... `original` ... `reply` ...

... `kube_ovn_vpc_egress_gateway_observability_*` ...conntrack ...cache ... conntrack accounting ... `/metrics` ...

2025 Kube-OVN Team

5.3.4 ServiceMonitor ⬚⬚

⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ `publishNotReadyAddresses: true` ⬚ headless Service⬚⬚⬚⬚ `targetPort` ⬚ `10666` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ ServiceMonitor⬚ `observability.serviceMonitor` ⬚⬚⬚⬚ label ⬚ annotation ⬚⬚⬚⬚ ServiceMonitor ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ selector label⬚

⬚⬚ ServiceMonitor CRD ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ `ServiceMonitorReady=False` ⬚⬚⬚⬚⬚⬚CRD ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ ServiceMonitor⬚⬚ condition ⬚⬚⬚⬚⬚ `Ready` condition ⬚⬚⬚⬚⬚

5.3.5 JSON ⬚⬚⬚

⬚⬚⬚⬚ JSON Lines ⬚⬚⬚⬚⬚ `observability` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

5.4 Egress Gateway BGP 和 EVPN 支持

⚠ 实验功能

BGP 和 EVPN 支持为集群出口流量提供了更灵活的路由控制能力。

主要特性：

- 支持 L3VPN（基于 L2VPN
- 基于 FRR 实现动态路由配置 Pod
- 支持 BGP BFD

5.4.1 概述

VPC Egress Gateway 支持通过 BGP 和 EVPN/VXLAN 将出口流量从 Egress Gateway Pod 中的 FRR（Free Range Routing）转发到 BGP 和 EVPN 对等体。Gateway 的 init 容器会根据 BgpConf 和 EvpnConf 自动生成 FRR 配置

在 BGP 模式（Egress Gateway 会通过 BGP 协议将本地路由宣告给对等体。EVPN 模式（init 容器会为 Pod 创建 Linux VRF、bridge 和 VXLAN 设备，以支持 L2VPN EVPN 功能。数据通过 VXLAN 隧道从 Egress Gateway Pod 发送（Kubernetes 节点网络可以是 Geneve）

> 注意：为了使 BGP 会话能够建立，kube-ovn-speaker 会将 Pod/节点/Service 路由宣告

5.4.2 使用场景

在 BGP/EVPN 网络环境中，与 VPC Egress Gateway 结合使用 Multus-CNI 可以

在传统的 BGP（数据中心 EVPN（网络中，通过 BGP

5.4.3 使用方法

创建 **BgpConf** 资源

BgpConf 资源用于配置 BGP 会话参数

```
apiVersion: kubeovn.io/v1
kind: BgpConf
metadata:
  name: bgp-conf-6502
spec:
  localASN: 65002
  peerASN: 65001
  neighbours:
    - 10.0.1.1
  holdTime: 90s
  keepaliveTime: 30s
  connectTime: 10s
  ebgpMultiHop: true
```

本地使用 AS 号 65002，与 AS 号 65001 的 BGP 对等体 10.0.1.1，启用 EBGP Multi-Hop。

创建 **EvpnConf** 资源

EvpnConf 资源用于配置 EVPN 参数，EvpnConf 与 BgpConf 共享相同的会话参数

```
apiVersion: kubeovn.io/v1
kind: EvpnConf
metadata:
  name: evpn-conf-1016
spec:
  vni: 1016
  routeTargets:
    - "65000:1016"
```


2025 Kube-OVN Team

■■■■■■■■■■ VNI ■ 1016 ■ EVPN ■■■Route Target ■ `65000:1016` ■

■■■■ BGP/EVPN ■ VPC Egress Gateway

■■■■ VPC Egress Gateway ■■■■ NetworkAttachmentDefinition ■■■■■■■■

■■■ VpcEgressGateway ■ `.spec` ■■■ `bgpConf` ■ `evpnConf` ■■■■■■■■■■■■■■■■■■■■

```yaml
apiVersion: kubeovn.io/v1
kind: VpcEgressGateway
metadata:
  name: gateway1
  namespace: default
spec:
  vpc: ovn-cluster
  replicas: 1
  externalIPs:
    - 10.0.1.13
  internalIPs:
    - 10.16.0.13
  externalSubnet: macvlan1
  bgpConf: bgp-conf-6502
  evpnConf: evpn-conf-1016
  policies:
    - snat: false
      subnets:
        - ovn-default
    - snat: false
      ipBlocks:
        - 10.17.0.0/16
```

■■■■■■■■■■■■■ BGP ■ EVPN ■ VPC Egress Gateway■Gateway Pod ■■■■ FRR ■■■■■ BGP EVPN ■■■■■■■■■■■■■■■■■■ VXLAN ■■■■■■■■■■■■■ BGP/EVPN ■■■■■■■■ `snat` ■■■ `false` ■

■■■ BGP■■■■ EVPN■

■■■■■■ BGP ■■■■■■■■■■■ EVPN/VXLAN■■■■■■ `bgpConf` ■■■■■■■ `evpnConf` ■■■■■■■■ FRR ■■■■ BGP IPv4 Unicast ■■■■■■■■■■

```yaml
apiVersion: kubeovn.io/v1
kind: VpcEgressGateway
metadata:
  name: gateway-bgp-only
  namespace: default
spec:
  vpc: ovn-cluster
  replicas: 1
  externalSubnet: macvlan1
  bgpConf: bgp-conf-6502
  policies:
    - snat: true
      subnets:
        - ovn-default
```


2025 Kube-OVN Team

5.4.4 □□□□

BgpConf

□□	□□	□□	□□□	□□	□□
`localASN`	`uint32`	□	-	□□ AS □□	`65002`
`peerASN`	`uint32`	□	-	□□ AS □□	`65001`
`routerId`	`string`	□	Pod IP	BGP Router ID□	`10.0.1.13`
`neighbours`	`string array`	□	-	BGP □□ IP □□□□□	`10.0.1.1`
`password`	`string`	□	-	BGP □□□□□	`secret`
`holdTime`	`string (duration)`	□	-	BGP Hold □□□	`90s`
`keepaliveTime`	`string (duration)`	□	-	BGP Keepalive □ □□	`30s`
`connectTime`	`string (duration)`	□	-	BGP □□□□□□	`10s`
`ebgpMultiHop`	`boolean`	□	`false`	□□□□ EBGP Multi-Hop□	`true`

EvpnConf

□□	□□	□□	□□□	□□	□□
`vni`	`uint32`	□	-	VXLAN Network Identifier□	`1016`
`routeTargets`	`string array`	□	-	□□□□□□□□ Route Target □□□	`65000:1016`

VpcEgressGateway □□□□

□□□□□ VpcEgressGateway `.spec` □□□□ BGP/EVPN □□□□□□□□ VpcEgressGateway □□□□□□□ Egress Gateway □□□□□□□□□□□□

□□	□□	□□	□□□	□□	□□
`bgpConf`	`string`	□	-	□□□ BgpConf □□□ □□□□□□□ Egress Gateway □□□ BGP□	`bgp-conf-6502`
`evpnConf`	`string`	□	-	□□□ EvpnConf □□□ □□□□□□□□ `bgpConf` □□□□□□ Egress Gateway □ □□ EVPN/VXLAN□	`evpn-conf-1016`

PDF Slack Support

2025 Kube-OVN Team

2026□4□8□

2026□4□8□

GitHub 

5.4.5 □□

5.5 VPC QoS

Kube-OVN [illegible] QoSPolicy CRD [illegible] VPC [illegible]

5.5.1 [illegible]

QoSPolicy [illegible] `priority` [illegible] QoS [illegible]

[illegible]

[illegible]	[illegible]	[illegible]
EIP QoS	1	[illegible] EIP [illegible]
NATGW [illegible] QoS	2	[illegible] NATGW [illegible] IP [illegible]
NATGW net1 [illegible] QoS	3	[illegible]

[illegible]

- `shared=false` [illegible] QoS [illegible] `shared=true` [illegible]
- EIP [illegible] QoS [illegible] NATGW [illegible] QoS

5.5.2 EIP QoS

[illegible] EIP [illegible] 1Mbps[illegible] 1[illegible] `shared=false` [illegible] QoSPolicy [illegible] EIP [illegible] QoSPolicy [illegible] QoS [illegible]

QoSPolicy [illegible]

```yaml
apiVersion: kubeovn.io/v1
kind: QoSPolicy
metadata:
  name: qos-eip-example
spec:
  shared: false
  bindingType: EIP
  bandwidthLimitRules:
  - name: eip-ingress
    rateMax: "1" # Mbps
    burstMax: "1" # Mbps
    priority: 1
    direction: ingress
  - name: eip-egress
    rateMax: "1" # Mbps
    burstMax: "1" # Mbps
    priority: 1
    direction: egress
```

IptablesEIP [illegible]

```yaml
kind: IptablesEIP
apiVersion: kubeovn.io/v1
metadata:
  name: eip-1
spec:
  natGwDp: gw1
  qosPolicy: qos-eip-example
```

`.spec.qosPolicy` [illegible]

5.5.3 [illegible] QoS [illegible] EIP

[illegible] `label` [illegible] qos [illegible] eip[illegible]

```
# kubectl get eip  -l ovn.kubernetes.io/qos=qos-eip-example
NAME    IP            MAC               NAT   NATGWDP   READY
eip-1   172.18.11.24   00:00:00:34:41:0B   fip   gw1       true
```


2025 Kube-OVN Team

5.5.4 VPC NATGW net1 □□ QoS

□ VPC NATGW □ net1 □□□□□□□□□□□□□□ 10Mbps□□□□□ 3□□□ `shared=true` □□□□□ QoSPolicy □□□□□□□□□□□□□□□□□□□□□□□□ QoSPolicy □□□□

QoSPolicy □□□□□

```yaml
apiVersion: kubeovn.io/v1
kind: QoSPolicy
metadata:
  name: qos-natgw-example
spec:
  shared: true
  bindingType: NATGW
  bandwidthLimitRules:
  - name: net1-ingress
    interface: net1
    rateMax: "10" # Mbps
    burstMax: "10" # Mbps
    priority: 3
    direction: ingress
  - name: net1-egress
    interface: net1
    rateMax: "10" # Mbps
    burstMax: "10" # Mbps
    priority: 3
    direction: egress
```

VpcNatGateway □□□□□

```yaml
kind: VpcNatGateway
apiVersion: kubeovn.io/v1
metadata:
  name: gw1
spec:
  vpc: test-vpc-1
  subnet: net1
  lanIp: 10.0.1.254
  qosPolicy: qos-natgw-example
  selector:
    - "kubernetes.io/hostname: kube-ovn-worker"
    - "kubernetes.io/os: linux"
```

`.spec.qosPolicy` □□□□□□□□□□□□□□□□□□□

5.5.5 net1 □□□□□□ QoS

□ net1 □□□□□□□□□□□□□□□□□ 5Mbps□□□□□ 2□□□ `shared=true` □□□□□ QoSPolicy □□□□□□□□□□□□□□□□□□□□□ QoSPolicy □□□□

QoSPolicy □□□□□

```yaml
apiVersion: kubeovn.io/v1
kind: QoSPolicy
metadata:
  name: qos-natgw-example
spec:
  shared: true
  bindingType: NATGW
  bandwidthLimitRules:
  - name: net1-extip-ingress
    interface: net1
    rateMax: "5" # Mbps
    burstMax: "5" # Mbps
    priority: 2
    direction: ingress
    matchType: ip
    matchValue: src 172.18.11.22/32
  - name: net1-extip-egress
    interface: net1
    rateMax: "5" # Mbps
    burstMax: "5" # Mbps
    priority: 2
    direction: egress
    matchType: ip
    matchValue: dst 172.18.11.23/32
```

VpcNatGateway □□□□□

```yaml
kind: VpcNatGateway
apiVersion: kubeovn.io/v1
metadata:
  name: gw1
spec:
```

```
  vpc: test-vpc-1
  subnet: net1
  lanIp: 10.0.1.254
  qosPolicy: qos-natgw-example
  selector:
    - "kubernetes.io/hostname: kube-ovn-worker"
    - "kubernetes.io/os: linux"
```

5.5.6 □□□□□ QoS □ NATGW

□□ `label` □□□□□□□□ qos □ eip□

```
# kubectl get vpc-nat-gw  -l ovn.kubernetes.io/qos=qos-natgw-example
NAME   VPC          SUBNET   LANIP
gw1    test-vpc-1   net1     10.0.1.254
```

5.5.7 □□ qos □□

```
# kubectl get qos -A
NAME               SHARED   BINDINGTYPE
qos-eip-example    false    EIP
qos-natgw-example  true     NATGW
```

5.5.8 □□

- □□□□□□□□□□□ QoS □□□□□□□□□ QoS □□□□□□□□□□□□□ QoS □ EIP □ NATGW□□□□□□□ `spec.qosPolicy` □□□

PDF Slack Support

2026□1□29□

2023□5□9□

GitHub

5.5.9 □□

5.6 ▯▯▯ VPC ▯▯▯▯▯▯

Kubernetes ▯▯▯ Service ▯▯▯▯▯▯▯▯▯▯▯▯▯ ▯▯▯▯▯▯ VPC ▯▯▯▯ ▯▯ Service ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

1. Service IP ▯▯▯▯▯▯▯▯▯▯▯▯▯ VPC ▯▯▯▯▯▯▯▯▯
2. ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ IP ▯▯▯

▯▯▯▯▯▯▯▯▯Kube-OVN ▯ 1.11 ▯▯ `SwitchLBRule` CRD▯▯▯▯▯▯▯▯▯▯▯ VPC ▯▯▯▯▯▯▯▯▯▯▯▯

`SwitchLBRule` ▯▯▯▯▯▯▯▯▯▯▯▯▯ VPC ▯▯▯▯▯▯▯▯▯▯▯▯

5.6.1 `Selector` ▯▯▯▯▯▯▯▯▯▯▯

▯▯ `selector` ▯▯▯▯▯ `label` ▯▯▯▯▯ `pod` ▯▯▯▯▯▯▯▯▯▯▯▯

`SwitchLBRule` ▯▯▯▯▯▯

```
apiVersion: kubeovn.io/v1
kind: SwitchLBRule
metadata:
  name:  cjh-slr-nginx
spec:
  vip: 1.1.1.1
  sessionAffinity: ClientIP
  namespace: default
  selector:
    - app: nginx
  ports:
  - name: dns
    port: 8888
    targetPort: 80
    protocol: TCP
```

- `selector`, `sessionAffinity` ▯ `port` ▯▯▯▯▯▯ Kubernetes Service▯
- `vip` ▯▯▯▯▯▯▯▯▯▯ IP ▯▯▯
- `namespace` ▯ `selector` ▯▯▯ Pod ▯▯▯▯▯▯▯▯

Kube-OVN ▯▯▯ `SwitchLBRule` ▯▯▯▯▯▯ Pod ▯▯ Pod ▯▯ VPC ▯▯▯▯▯▯▯ L2 LB▯

5.6.2 `Endpoints` ▯▯▯▯▯▯▯▯▯▯▯

▯▯ `endpoints` ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `selector` ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

████████ selector ▯ endpoints,██████ selector ████

5.6.3 ████

OVN ▯▯ IPv4 ████████████████████ ██

[Health Checks](https://www.ovn.org/support/dist-docs/ovn-nb.5.html)

▯▯ ovn ████████████████ SwitchLBRule ████████████ SwitchLBRule ████████ VPC ▯ subnet ██████████ vip ████████████████ ip_port_mappings ▯ load_balancer_health_check ██████████████

- ████ vip ████████ subnet ██████████████ subnet ████████████████████████████ SwitchLBRule ████████████
- ████████ Selector ██████████████

█████████

```
root@server:~# kubectl get po -o wide -n vulpecula
NAME                      READY   STATUS    RESTARTS   AGE     IP          NODE     NOMINATED NODE   READINESS GATES
nginx-78d9578975-f4qn4    1/1     Running   3          4d16h   10.16.0.4   worker   <none>           <none>
nginx-78d9578975-t8tm5    1/1     Running   3          4d16h   10.16.0.6   worker   <none>           <none>

#    slr
root@server:~# cat << END > slr.yaml
apiVersion: kubeovn.io/v1
kind: SwitchLBRule
metadata:
  name:  nginx
  namespace:  vulpecula
spec:
  vip: 1.1.1.1
  sessionAffinity: ClientIP
  namespace: default
  selector:
    - app: nginx
  ports:
  - name: dns
    port: 8888
    targetPort: 80
    protocol: TCP
END
root@server:~# kubectl apply -f slr.yaml
root@server:~# kubectl get slr
NAME              VIP       PORT(S)    SERVICE                       AGE
vulpecula-nginx   1.1.1.1   8888/TCP   default/slr-vulpecula-nginx   3d21h
```

██████ subnet ████ vip ███████

```
#       vip

root@server:~# kubectl get vip
NAME          NS    V4IP        MAC                V6IP    PMAC   SUBNET        READY   TYPE
vulpecula-subnet    10.16.0.2   00:00:00:39:95:C1   <nil>          vulpecula-subnet   true
```

████████████ Load_Balancer_Health_Check ▯ Service_Monitor ▯

```
root@server:~# kubectl ko nbctl list Load_Balancer
_uuid               : 3cbb6d43-44aa-4028-962f-30d2dba9f0b8
external_ids        : {}
health_check        : [5bee3f12-6b54-411c-9cc8-c9def8f67356]
ip_port_mappings    : {"10.16.0.4"="nginx-78d9578975-f4qn4.default:10.16.0.2", "10.16.0.6"="nginx-78d9578975-t8tm5.default:10.16.0.2"}
name                : cluster-tcp-session-loadbalancer
options             : {affinity_timeout="10800"}
protocol            : tcp
selection_fields    : [ip_src]
vips                : {"1.1.1.1:8888"="10.16.0.4:80,10.16.0.6:80"}

root@server:~# kubectl ko nbctl list Load_Balancer_Health_Check
_uuid               : 5bee3f12-6b54-411c-9cc8-c9def8f67356
external_ids        : {switch_lb_subnet=vulpecula-subnet}
options             : {failure_count="3", interval="5", success_count="3", timeout="20"}
vip                 : "1.1.1.1:8888"

root@server:~# kubectl ko sbctl list Service_Monitor
_uuid               : 1bddc541-cc49-44ea-9935-a4208f627a91
external_ids        : {}
ip                  : "10.16.0.4"
logical_port        : nginx-78d9578975-f4qn4.default
options             : {failure_count="3", interval="5", success_count="3", timeout="20"}
port                : 80
protocol            : tcp
```

```
src_ip              : "10.16.0.2"
src_mac             : "c6:d4:b8:08:54:e7"
status              : online

_uuid               : 84dd24c5-e1b4-4e97-9daa-13687ed59785
external_ids        : {}
ip                  : "10.16.0.6"
logical_port        : nginx-78d9578975-t8tm5.default
options             : {failure_count="3", interval="5", success_count="3", timeout="20"}
port                : 80
protocol            : tcp
src_ip              : "10.16.0.2"
src_mac             : "c6:d4:b8:08:54:e7"
status              : online
```

... `vip` ...

```
root@server:~# kubectl exec -it -n vulpecula nginx-78d9578975-t8tm5 -- curl 1.1.1.1:8888
<!DOCTYPE html>
<html>
<head>
<title>Welcome to nginx!</title>
<p><em>Thank you for using nginx.</em></p>
</body>
</html>
```

...

... `pod` ...

```
kubectl delete po nginx-78d9578975-f4qn4
kubectl get po -o wide -n vulpecula
NAME                     READY   STATUS    RESTARTS   AGE     IP          NODE     NOMINATED NODE   READINESS GATES
nginx-78d9578975-lxmvh   1/1     Running   0          31s     10.16.0.8   worker   <none>           <none>
nginx-78d9578975-t8tm5   1/1     Running   3          4d16h   10.16.0.6   worker   <none>           <none>
```

... `Load_Balancer_Health_Check` ... `Service_Monitor` ...

```
root@server:~# kubectl ko nbctl list Load_Balancer
_uuid               : 3cbb6d43-44aa-4028-962f-30d2dba9f0b8
external_ids        : {}
health_check        : [5bee3f12-6b54-411c-9cc8-c9def8f67356]
ip_port_mappings    : {"10.16.0.4"="nginx-78d9578975-f4qn4.default:10.16.0.2", "10.16.0.6"="nginx-78d9578975-t8tm5.default:10.16.0.2",
"10.16.0.8"="nginx-78d9578975-lxmvh.default:10.16.0.2"}
name                : cluster-tcp-session-loadbalancer
options             : {affinity_timeout="10800"}
protocol            : tcp
selection_fields    : [ip_src]
vips                : {"1.1.1.1:8888"="10.16.0.6:80,10.16.0.8:80"}

root@server:~# kubectl ko nbctl list Load_Balancer_Health_Check
_uuid               : 5bee3f12-6b54-411c-9cc8-c9def8f67356
external_ids        : {switch_lb_subnet=vulpecula-subnet}
options             : {failure_count="3", interval="5", success_count="3", timeout="20"}
vip                 : "1.1.1.1:8888"

root@server:~# kubectl ko sbctl list Service_Monitor
_uuid               : 84dd24c5-e1b4-4e97-9daa-13687ed59785
external_ids        : {}
ip                  : "10.16.0.6"
logical_port        : nginx-78d9578975-t8tm5.default
options             : {failure_count="3", interval="5", success_count="3", timeout="20"}
port                : 80
protocol            : tcp
src_ip              : "10.16.0.2"
src_mac             : "c6:d4:b8:08:54:e7"
status              : online

_uuid               : 5917b7b7-a999-49f2-a42d-da81f1eeb28f
external_ids        : {}
ip                  : "10.16.0.8"
logical_port        : nginx-78d9578975-lxmvh.default
options             : {failure_count="3", interval="5", success_count="3", timeout="20"}
port                : 80
protocol            : tcp
src_ip              : "10.16.0.2"
src_mac             : "c6:d4:b8:08:54:e7"
status              : online
```

... `SwitchLBRule` ... `Load_Balancer_Health_Check` ... `Service_Monitor` ... `vip` ...

```
root@server:~# kubectl delete -f slr.yaml
switchlbrule.kubeovn.io "vulpecula-nginx" deleted
root@server:~# kubectl get vip
No resources found
```

```
root@server:~# kubectl ko sbctl list Service_Monitor
root@server:~#
root@server:~# kubectl ko nbctl list Load_Balancer_Health_Check
root@server:~#
```

5.6.4 ... VPC ...

> `RouterLBRule` ... OVN EIP ... OVN EIP FIP SNAT DNAT ... OVN ...

... `SwitchLBRule` ... `RouterLBRule` ... VPC ... OVN ... Load Balancer ... OVN EIP ...

`RouterLBRule` ...

```yaml
apiVersion: kubeovn.io/v1
kind: RouterLBRule
metadata:
  name: rlr-nginx
spec:
  ovnEip: eip-1
  vpc: vpc-1
  namespace: default
  selector:
    - app: nginx
  sessionAffinity: ClientIP
  ports:
  - name: http
    port: 80
    targetPort: 8080
    protocol: TCP
```

...

...	...
ovnEip	... OVN EIP ...
vpc	... VPC ...
namespace	... Pod ...
selector	... Pod ...
endpoints	... IP ... selector ... selector...
sessionAffinity	... Kubernetes Service
ports	... name / port / targetPort / protocol

...

```yaml
apiVersion: kubeovn.io/v1
kind: RouterLBRule
metadata:
  name: rlr-example
spec:
  ovnEip: eip-1
  vpc: vpc-1
  namespace: default
  endpoints:
    - 10.0.1.10
    - 10.0.1.11
    - 10.0.1.12
  ports:
  - name: web
    port: 443
    targetPort: 8443
    protocol: TCP
```

... `kubectl get rlr` ...

```
# kubectl get rlr
NAME           OVNEIP   VPC    PORT(S)     SERVICE                   AGE
rlr-example    eip-1    vpc-1  443/TCP     default/rlr-rlr-example   10s
```

PDF Slack Support

2025 Kube-OVN Team

2026□11□5□

2022□12□15□



GitHub 



5.6.5 □□

5.7 □□□ VPC □□ DNS

□□□□□□□ VPC □□□ VPC □□□□□□□□□□ VPC □□□□□□□□□□□□ VPC □□ coredns□ □□□□□□□□□□ VPC □□□ Kubernetes □□□□□□□□□□□□□□□□□□□□□□□□□□□□ `vpc-dns` CRD □□□□

□ CRD □□□□□□□ coredns□□ Pod □□□□□□□□□□□□□□□□□□ VPC□□□□□□□□□□ VPC □□□□□□□□□□□□□□□□□□□ VPC □□□□□□□□□□□□□□□□□□□□

```
        loop
        reload
        loadbalance
    }
```

□□□□□□□□□□□□□□ nat-gw-pod □□□□□□□□□□

5.7.2 □□□□□□□

```
apiVersion: "k8s.cni.cncf.io/v1"
kind: NetworkAttachmentDefinition
metadata:
  name: ovn-nad
  namespace: default
spec:
  config: '{
      "cniVersion": "0.3.0",
      "type": "kube-ovn",
      "server_socket": "/run/openvswitch/kube-ovn-daemon.sock",
      "provider": "ovn-nad.default.ovn"
    }'
```

5.7.3 □□ vpc-dns □ Configmap

□ kube-system □□□□□□□ configmap□□□ vpc-dns □□□□□□□□□□□ vpc-dns □□□

```
apiVersion: v1
kind: ConfigMap
metadata:
  name: vpc-dns-config
  namespace: kube-system
data:
  coredns-vip: 10.96.0.3
  enable-vpc-dns: "true"
  nad-name: ovn-nad
  nad-provider: ovn-nad.default.ovn
```

- `enable-vpc-dns` □□□□□□□□□□□ `true` □
- `coredns-image` □dns □□□□□□□□□□□ coredns □□□□□
- `coredns-vip` □□ coredns □□ lb □□□ vip□
- `nad-name` □□□□ `network-attachment-definitions` □□□□□
- `nad-provider` □□□□ provider □□□
- `k8s-service-host` □□□ coredns □□ k8s apiserver □□□ ip□□□□□□□ apiserver □□□
- `k8s-service-port` □□□ coredns □□ k8s apiserver □□□ port□□□□□□□ apiserver □□□

5.7.4 □□ vpc-dns

□□ vpc-dns yaml□

```
kind: VpcDns
apiVersion: kubeovn.io/v1
metadata:
  name: test-cjh1
spec:
  vpc: cjh-vpc-1
  subnet: cjh-subnet-1
  replicas: 2
```

- `vpc` □ □□□□ dns □□□ vpc □□□
- `subnet` □□□□□ dns □□□□□□□□
- `replicas` : vpc dns deployment replicas

□□□□□□□□□□

```
# kubectl get vpc-dns
NAME        ACTIVE   VPC         SUBNET
test-cjh1   false    cjh-vpc-1   cjh-subnet-1
test-cjh2   true     cjh-vpc-1   cjh-subnet-2
```

`ACTIVE` : `true` ⬚⬚⬚⬚⬚⬚ dns ⬚⬚⬚ `false` ⬚⬚⬚⬚

⬚⬚⬚⬚⬚ VPC ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ DNS ⬚⬚⬚

- ⬚⬚⬚ VPC ⬚⬚⬚⬚⬚ vpc-dns ⬚⬚⬚⬚⬚⬚⬚ VPC ⬚⬚⬚ subnet⬚⬚⬚⬚⬚⬚ vpc-dns ⬚⬚⬚⬚ `true` ⬚⬚⬚⬚ `false` ⬚
- ⬚ `true` ⬚ vpc-dns ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ `false` ⬚ vpc-dns ⬚⬚⬚⬚⬚

5.7.5 ⬚⬚⬚⬚⬚⬚⬚

⬚⬚ vpc-dns Pod ⬚⬚⬚⬚⬚ label `app=vpc-dns` ⬚⬚⬚⬚⬚⬚⬚⬚ vpc-dns Pod ⬚⬚⬚

```
# kubectl -n kube-system get pods -l app=vpc-dns
NAME                                READY   STATUS    RESTARTS   AGE
vpc-dns-test-cjh1-7b878d96b4-g5979   1/1     Running   0          28s
vpc-dns-test-cjh1-7b878d96b4-ltmf9   1/1     Running   0          28s
```

⬚⬚ slr ⬚⬚⬚⬚⬚

```
# kubectl -n kube-system get slr
NAME               VIP          PORT(S)                 SERVICE                             AGE
vpc-dns-test-cjh1   10.96.0.3   53/UDP,53/TCP,9153/TCP   kube-system/slr-vpc-dns-test-cjh1   113s
```

⬚⬚⬚ VPC ⬚⬚ Pod⬚⬚⬚ dns ⬚⬚:

```
nslookup kubernetes.default.svc.cluster.local 10.96.0.3
```

⬚ VPC ⬚⬚ switch lb rule ⬚⬚⬚⬚⬚⬚⬚⬚ VPC ⬚⬚⬚⬚⬚⬚⬚ Pod ⬚⬚⬚⬚⬚⬚

PDF Slack Support

2026⬚4⬚28⬚

2022⬚12⬚26⬚

GitHub



5.7.6 ⬚⬚

5.8 SecurityGroup ⬚⬚

Kube-OVN ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ Pod ⬚⬚⬚⬚⬚⬚⬚⬚

> **Warning**
>
> Kube-OVN ⬚⬚⬚⬚ NetworkPolicy⬚Network Policy API⬚Subnet ACL ⬚ Security Group ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ OVN ACL ⬚⬚⬚⬚⬚⬚ NetworkPolicy ⬚ NetworkPolicy API ⬚⬚⬚⬚ ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

```
    remoteType: address
  - ipVersion: ipv4
    policy: deny
    priority: 2
    protocol: all
    remoteAddress: 0.0.0.0/0
    remoteType: address
---
apiVersion: kubeovn.io/v1
kind: SecurityGroup
metadata:
  name: sg-tier1
spec:
  tier: 1
  allowSameGroupTraffic: true
  ingressRules:
  - ipVersion: ipv4
    policy: allow
    priority: 1
    protocol: tcp
    remoteAddress: 10.16.0.0/16
    remoteType: address
    portRangeMin: 80
    portRangeMax: 443
```

... `sg-tier0` ... `10.16.0.0/16` ... TCP ... tier 1... `sg-tier1` ... 80-443 ... TCP ...

... Pod... annotation ...

```
apiVersion: v1
kind: Pod
metadata:
  labels:
    app: web
  annotations:
    ovn.kubernetes.io/security_groups: 'sg-tier0,sg-tier1'
  name: multi-tier-pod
  namespace: default
spec:
  nodeName: kube-ovn-worker
  containers:
  - image: docker.io/library/nginx:alpine
    imagePullPolicy: IfNotPresent
    name: nginx
```

5.8.3 ...

... `localAddress` ...

- **`localAddress`** ... IP ... CIDR...
- **`sourcePortRangeMin`** / **`sourcePortRangeMax`** ...1-65535... TCP ... UDP ...

...

```
apiVersion: kubeovn.io/v1
kind: SecurityGroup
metadata:
  name: sg-local-filter
spec:
  allowSameGroupTraffic: true
  ingressRules:
  - ipVersion: ipv4
    policy: allow
    priority: 1
    protocol: tcp
    remoteAddress: 10.16.0.0/16
    remoteType: address
    portRangeMin: 8080
    portRangeMax: 8080
    localAddress: 10.16.0.100
    sourcePortRangeMin: 1024
    sourcePortRangeMax: 65535
```

... `10.16.0.0/16` ... `10.16.0.100` ... 8080 ... TCP ... 1024-65535...

5.8.4 ...

- ... ACL ...OVN ... ACL ... ACL ...

2025 Kube-OVN Team

- ██████ `priority` ██████ 1-16384████████████████ ACL ████████████████ ACL ████████████ `ACL = 18484 -` ████████████ ACL ███
- `tier` ████ `0` ▯ `1` ▯ `policy: pass` ████ tier `0` ████ tier `1` ██████████
- ████████████████████████Kube-OVN ▯▯ CNI███ Pod ████ Pod ████████████████████ Pod ████ ContainerCreating ██████████ Running ███

5.8.5 ████

████ YAML ▯▯ Pod▯▯ annotation ████████████

```
apiVersion: v1
kind: Pod
metadata:
  labels:
    app: static
  annotations:
    ovn.kubernetes.io/security_groups: 'sg-example'
  name: sg-test-pod
  namespace: default
spec:
  nodeName: kube-ovn-worker
  containers:
  - image: docker.io/library/nginx:alpine
    imagePullPolicy: IfNotPresent
    name: qatest
```

██████████

```
# kubectl get pod -o wide
NAME                   READY   STATUS              RESTARTS   AGE     IP           NODE                  NOMINATED NODE   READINESS GATES
sg-test-pod            0/1     ContainerCreating   0          5h32m   <none>       kube-ovn-worker       <none>           <none>
test-99fff7f86-52h9r   1/1     Running             0          5h41m   10.16.0.14   kube-ovn-control-plane   <none>           <none>
test-99fff7f86-qcgjw   1/1     Running             0          5h43m   10.16.0.13   kube-ovn-worker       <none>           <none>
```

▯▯ kubectl describe pod ▯▯ Pod ████████████

```
# kubectl describe pod sg-test-pod
Name:         sg-test-pod
Namespace:    default
Priority:     0
Node:         kube-ovn-worker/172.18.0.2
Start Time:   Tue, 28 Feb 2023 10:29:36 +0800
Labels:       app=static
Annotations:  ovn.kubernetes.io/allocated: true
              ovn.kubernetes.io/cidr: 10.16.0.0/16
              ovn.kubernetes.io/gateway: 10.16.0.1
              ovn.kubernetes.io/ip_address: 10.16.0.15
              ovn.kubernetes.io/logical_router: ovn-cluster
              ovn.kubernetes.io/logical_switch: ovn-default
              ovn.kubernetes.io/mac_address: 00:00:00:FA:17:97
              ovn.kubernetes.io/pod_nic_type: veth-pair
              ovn.kubernetes.io/port_security: true
              ovn.kubernetes.io/routed: true
              ovn.kubernetes.io/security_groups: sg-allow-reject
Status:       Pending
IP:
IPs:          <none>
.
.
.
Events:
  Type     Reason                  Age                   From     Message
  ----     ------                  ----                  ----     -------
  Warning  FailedCreatePodSandBox  5m3s (x70 over 4h59m)  kubelet  (combined from similar events): Failed to create pod sandbox: rpc error: code = Unknown
desc = failed to setup network for sandbox "40636e0c7f1ade5500fa958486163d74f2e2300051a71522a9afd7ba0538afb6": plugin type="kube-ovn" failed (add): RPC
failed; request ip return 500 configure nic failed 10.16.0.15 network not ready after 200 ping 10.16.0.1
```

████████████████████████████████

```
apiVersion: kubeovn.io/v1
kind: SecurityGroup
metadata:
  name: sg-gw-both
spec:
  allowSameGroupTraffic: true
  egressRules:
  - ipVersion: ipv4
    policy: allow
    priority: 2
    protocol: all
    remoteAddress: 10.16.0.13
    remoteType: address
```


2025 Kube-OVN Team

```
  - ipVersion: ipv4
    policy: allow
    priority: 1
    protocol: all
    remoteAddress: 10.16.0.1
    remoteType: address
  ingressRules:
  - ipVersion: ipv4
    policy: deny
    priority: 2
    protocol: icmp
    remoteAddress: 10.16.0.14
    remoteType: address
  - ipVersion: ipv4
    policy: allow
    priority: 1
    protocol: icmp
    remoteAddress: 10.16.0.1
    remoteType: address
```

⬚⬚⬚

5.9 OVN EIP FIP SNAT DNAT ⬚⬚

Note

⬚⬚⬚ VPC ⬚⬚⬚⬚⬚⬚⬚ VPC ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

⬚⬚⬚⬚⬚ VPC ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚VPC NAT ⬚⬚⬚OVN ⬚⬚⬚ Egress Gateway⬚⬚⬚ VPC NAT ⬚⬚⬚ Kube-OVN ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ VPC NAT ⬚⬚⬚⬚⬚⬚⬚⬚ Pod⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ VPC ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ Macvlan ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ Pod ⬚⬚ iptables ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

```
###               vlan id                  underlay
```

⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

- ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ provider network⬚vlan⬚subnet ⬚⬚⬚⬚
- ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ VPC enable_eip_snat ⬚⬚⬚⬚⬚⬚⬚⬚ vlan⬚subnet ⬚⬚⬚⬚⬚⬚⬚⬚⬚ ip ⬚ ipam⬚
- ⬚⬚⬚⬚⬚⬚⬚ VPC ⬚ enable_eip_snat ⬚⬚, ⬚⬚⬚⬚⬚⬚⬚⬚ pod annotation ⬚ fip snat⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚
- ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ VPC ⬚ enable_eip_snat ⬚⬚⬚⬚⬚⬚⬚⬚⬚ vlan⬚subnet ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ VPC ⬚⬚ eip snat ⬚⬚⬚⬚

1.1 ⬚⬚ **underlay** ⬚⬚⬚⬚

```
#    provider-network  vlan  subnet
# cat 01-provider-network.yaml

apiVersion: kubeovn.io/v1
kind: ProviderNetwork
metadata:
  name: external204
spec:
  defaultInterface: vlan

# cat 02-vlan.yaml

apiVersion: kubeovn.io/v1
kind: Vlan
metadata:
  name: vlan204
spec:
  id: 204
  provider: external204

# cat 03-vlan-subnet.yaml

apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: external204
spec:
  protocol: IPv4
  cidrBlock: 10.5.204.0/24
  gateway: 10.5.204.254
  vlan: vlan204
  excludeIps:
  - 10.5.204.1..10.5.204.100
```

1.2 ⬚⬚ **VPC** ⬚⬚ **eip_snat**

```
#      VPC     underlay    provider subnet
# cat 00-centralized-external-gw-no-ip.yaml

apiVersion: v1
kind: ConfigMap
metadata:
  name: ovn-external-gw-config
  namespace: kube-system
data:
  enable-external-gw: "true"
  external-gw-nodes: "pc-node-1,pc-node-2,pc-node-3"
  type: "centralized"
  external-gw-nic: "vlan" #      ovs
  external-gw-addr: "10.5.204.254/24" # underlay       ip
```

⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ logical router port (lrp) ip ⬚ mac⬚⬚⬚⬚⬚ underlay ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ lrp ⬚⬚⬚ ovn eip ⬚⬚⬚

⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ ip ⬚⬚⬚⬚⬚⬚⬚ lrp ⬚⬚⬚ ovn-eip⬚ ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ lrp ⬚⬚⬚ ovn eip⬚

1.3 ⬚⬚⬚ **VPC** ⬚⬚ **eip snat fip** ⬚⬚

```
# cat 00-ns.yml

apiVersion: v1
kind: Namespace
metadata:
  name: vpc1

# cat 01-vpc-external.yml
```

```
kind: Vpc
apiVersion: kubeovn.io/v1
metadata:
  name: vpc1
spec:
  namespaces:
  - vpc1
  enableExternal: true
  staticRoutes:
    - cidr: 0.0.0.0/0
      nextHopIP: 10.5.204.254
      policy: policyDst

# VPC    enableExternal      lrp

# cat 02-subnet.yml

apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: vpc1-subnet1
spec:
  cidrBlock: 192.168.0.0/24
  default: false
  disableGatewayCheck: false
  disableInterConnection: true
  gatewayNode: ""
  gatewayType: distributed
  #gatewayType: centralized
  natOutgoing: false
  private: false
  protocol: IPv4
  provider: ovn
  vpc: vpc1
  namespaces:
  - vpc1

#                  subnet
```

▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

```
# kubectl ko nbctl show vpc1

router 87ad06fd-71d5-4ff8-a1f0-54fa3bba1a7f (vpc1)
    port vpc1-vpc1-subnet1
        mac: "00:00:00:ED:8E:C7"
        networks: ["192.168.0.1/24"]
    port vpc1-external204
        mac: "00:00:00:EF:05:C7"
        networks: ["10.5.204.105/24"]
        gateway chassis: [7cedd14f-265b-42e5-ac17-e03e7a1f2342 276baccb-fe9c-4476-b41d-05872a94976d fd9f140c-c45d-43db-a6c0-0d4f8ea298dd]
    nat 21d853b0-f7b4-40bd-9a53-31d2e2745739
        external ip: "10.5.204.115"
        logical ip: "192.168.0.0/24"
        type: "snat"
```

```
# kubectl ko nbctl lr-route-list vpc1

IPv4 Routes
Route Table <main>:
               0.0.0.0/0             10.5.204.254 dst-ip
#    VPC CRD
```

> ▒▒▒▒▒▒ enableExternal ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

```
# cat 03-extra-vlan-subnet.yaml
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: extra
spec:
  protocol: IPv4
  cidrBlock: 10.10.204.0/24
  gateway: 10.10.204.254
  vlan: vlan0
  excludeIps:
  - 10.10.204.1..10.10.204.100
```

1.4.2 ▒▒▒ VPC ▒▒

```
apiVersion: kubeovn.io/v1
kind: Vpc
metadata:
  name: vpc1
spec:
  namespaces:
  - vpc1
  enableExternal: true  #    enableExternal   VPC               external   ls
  extraExternalSubnets: #    extraExternalSubnets
  - extra
```

▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

```
# kubectl ko nbctl show vpc1
router 87ad06fd-71d5-4ff8-a1f0-54fa3bba1a7f (vpc1)
    port vpc1-vpc1-subnet1
        mac: "00:00:00:ED:8E:C7"
        networks: ["192.168.0.1/24"]
    port vpc1-external204
        mac: "00:00:00:EF:05:C7"
        networks: ["10.5.204.105/24"]
        gateway chassis: [7cedd14f-265b-42e5-ac17-e03e7a1f2342 276baccb-fe9c-4476-b41d-05872a94976d fd9f140c-c45d-43db-a6c0-0d4f8ea298dd]
    port vpc1-extra
        mac: "00:00:00:EF:6A:C7"
        networks: ["10.10.204.105/24"]
        gateway chassis: [7cedd14f-265b-42e5-ac17-e03e7a1f2342 276baccb-fe9c-4476-b41d-05872a94976d fd9f140c-c45d-43db-a6c0-0d4f8ea298dd]
```

5.9.3 2. ovn-eip

▒▒▒▒ iptables-eip ▒▒▒▒▒▒▒▒▒▒▒▒▒ovn-eip ▒▒▒▒▒▒ type

- nat: ▒▒ ovn dnat▒fip, snat ▒▒▒ nat ▒▒▒▒▒
- lrp: ▒▒▒▒▒▒▒▒▒▒ underlay ▒▒▒▒▒▒▒ lrp ▒▒▒▒ ip ▒▒▒▒▒▒ dnat snat ▒▒
- lsp: ▒▒▒▒▒▒▒▒▒▒▒▒LSP▒▒ EIP

```
---
kind: OvnEip
apiVersion: kubeovn.io/v1
metadata:
  name: eip-static
spec:
  externalSubnet: external204
  type: nat

#       eip           fip
```

externalSubnet ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

```
metadata:
  name: eip-static
spec:
  externalSubnet: external204
  type: nat

---
kind: OvnFip
apiVersion: kubeovn.io/v1
metadata:
  name: eip-static
spec:
  ovnEip: eip-static
  ipName: vpc-1-busybox01.vpc1  #       ip crd
  type: "centralized"           # centralized    distributed

--
#         VPC       ip

kind: OvnFip
apiVersion: kubeovn.io/v1
metadata:
  name: eip-static
spec:
  ovnEip: eip-static
  vpc: vpc1
  v4Ip: 192.168.0.2
  type: "centralized"           # centralized    distributed
```

```
# kubectl get ofip
NAME          VPC    V4EIP          V4IP          READY   IPTYPE   IPNAME
eip-for-vip   vpc1   10.5.204.106   192.168.0.3   true    vip      test-fip-vip
eip-static    vpc1   10.5.204.101   192.168.0.2   true             vpc-1-busybox01.vpc1
# kubectl get ofip eip-static
NAME          VPC    V4EIP          V4IP          READY   IPTYPE   IPNAME
eip-static    vpc1   10.5.204.101   192.168.0.2   true             vpc-1-busybox01.vpc1

[root@pc-node-1 03-cust-vpc]# ping 10.5.204.101
PING 10.5.204.101 (10.5.204.101) 56(84) bytes of data.
64 bytes from 10.5.204.101: icmp_seq=2 ttl=62 time=1.21 ms
64 bytes from 10.5.204.101: icmp_seq=3 ttl=62 time=0.624 ms
64 bytes from 10.5.204.101: icmp_seq=4 ttl=62 time=0.368 ms
^C
--- 10.5.204.101 ping statistics ---
4 packets transmitted, 3 received, 25% packet loss, time 3049ms
rtt min/avg/max/mdev = 0.368/0.734/1.210/0.352 ms
[root@pc-node-1 03-cust-vpc]#

#       node ping    VPC    pod     ip
```

```
#     ip
# kubectl ko nbctl show vpc1
router 87ad06fd-71d5-4ff8-a1f0-54fa3bba1a7f (vpc1)
    port vpc1-vpc1-subnet1
        mac: "00:00:00:ED:8E:C7"
        networks: ["192.168.0.1/24"]
    port vpc1-external204
        mac: "00:00:00:EF:05:C7"
        networks: ["10.5.204.105/24"]
        gateway chassis: [7cedd14f-265b-42e5-ac17-e03e7a1f2342 276baccb-fe9c-4476-b41d-05872a94976d fd9f140c-c45d-43db-a6c0-0d4f8ea298dd]
    nat 813523e7-c68c-408f-bd8c-cba30cb2e4f4
        external ip: "10.5.204.101"
        logical ip: "192.168.0.2"
        type: "dnat_and_snat"
```

2.2 ovn-fip vip fip

 vip kubevirt vip keepalived kube-vip

 fip VPC vip vip

```
#     vip eip    eip     vip
# cat vip.yaml

apiVersion: kubeovn.io/v1
kind: Vip
metadata:
  name: test-fip-vip
spec:
  subnet: vpc1-subnet1

# cat 04-fip.yaml

---
kind: OvnEip
apiVersion: kubeovn.io/v1
metadata:
  name: eip-for-vip
```

```
spec:
  externalSubnet: external204
  type: nat

---
kind: OvnFip
apiVersion: kubeovn.io/v1
metadata:
  name: eip-for-vip
spec:
  ovnEip: eip-for-vip
  ipType: vip         #       fip     pod ip              vip
  ipName: test-fip-vip

---
#         VPC       ip

kind: OvnFip
apiVersion: kubeovn.io/v1
metadata:
  name: eip-for-vip
spec:
  ovnEip: eip-for-vip
  ipType: vip         #       fip     pod ip              vip
  vpc: vpc1
  v4Ip: 192.168.0.3
```

```
# kubectl get ofip
NAME          VPC    V4EIP          V4IP          READY   IPTYPE   IPNAME
eip-for-vip   vpc1   10.5.204.106   192.168.0.3   true    vip      test-fip-vip


[root@pc-node-1 fip-vip]# ping  10.5.204.106
PING 10.5.204.106 (10.5.204.106) 56(84) bytes of data.
64 bytes from 10.5.204.106: icmp_seq=1 ttl=62 time=0.694 ms
64 bytes from 10.5.204.106: icmp_seq=2 ttl=62 time=0.436 ms

#   node    ping


# pod     ip

[root@pc-node-1 fip-vip]# kubectl -n vpc1 exec -it vpc-1-busybox03 -- bash
[root@vpc-1-busybox03 /]#
[root@vpc-1-busybox03 /]#
[root@vpc-1-busybox03 /]# ip a
1: lo: <LOOPBACK,UP,LOWER_UP> mtu 65536 qdisc noqueue state UNKNOWN group default qlen 1000
    link/loopback 00:00:00:00:00:00 brd 00:00:00:00:00:00
    inet 127.0.0.1/8 scope host lo
       valid_lft forever preferred_lft forever
    inet6 ::1/128 scope host
       valid_lft forever preferred_lft forever
1568: eth0@if1569: <BROADCAST,MULTICAST,UP,LOWER_UP> mtu 1500 qdisc noqueue state UP group default
    link/ether 00:00:00:56:40:e5 brd ff:ff:ff:ff:ff:ff link-netnsid 0
    inet 192.168.0.5/24 brd 192.168.0.255 scope global eth0
       valid_lft forever preferred_lft forever
    inet 192.168.0.3/24 scope global secondary eth0  #      vip
       valid_lft forever preferred_lft forever
    inet6 fe80::200:ff:fe56:40e5/64 scope link
       valid_lft forever preferred_lft forever

[root@vpc-1-busybox03 /]# tcpdump -i eth0 host  192.168.0.3 -netvv
tcpdump: listening on eth0, link-type EN10MB (Ethernet), capture size 262144 bytes
00:00:00:ed:8e:c7 > 00:00:00:56:40:e5, ethertype IPv4 (0x0800), length 98: (tos 0x0, ttl 62, id 44830, offset 0, flags [DF], proto ICMP (1), length 84)
    10.5.32.51 > 192.168.0.3: ICMP echo request, id 177, seq 1, length 64
00:00:00:56:40:e5 > 00:00:00:ed:8e:c7, ethertype IPv4 (0x0800), length 98: (tos 0x0, ttl 64, id 43962, offset 0, flags [none], proto ICMP (1), length 84)
    192.168.0.3 > 10.5.32.51: ICMP echo reply, id 177, seq 1, length 64

# pod        fip     icmp
```

5.9.4 3. ovn-snat

3.1 ovn-snat [] subnet [] cidr

[] iptables-snat []

```
# cat 03-subnet-snat.yaml

---
kind: OvnEip
apiVersion: kubeovn.io/v1
metadata:
  name: snat-for-subnet-in-vpc
spec:
  externalSubnet: external204
  type: nat

---
kind: OvnSnatRule
```

```
apiVersion: kubeovn.io/v1
metadata:
  name: snat-for-subnet-in-vpc
spec:
  ovnEip: snat-for-subnet-in-vpc
  vpcSubnet: vpc1-subnet1 # eip

---
#         VPC       subnet cidr

kind: OvnSnatRule
apiVersion: kubeovn.io/v1
metadata:
  name: snat-for-subnet-in-vpc
spec:
  ovnEip: snat-for-subnet-in-vpc
  vpc: vpc1
  v4IpCidr: 192.168.0.0/24 #        cidr      ip
```

□□□□□□□□□□□□□□□□□ externalSubnet □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□ extra□

3.2 ovn-snat □□□□□ pod ip

□□□□ iptables-snat □□□□□□□□□□□□

```
# cat 03-pod-snat.yaml

---
kind: OvnEip
apiVersion: kubeovn.io/v1
metadata:
  name: snat-for-pod-vpc-ip
spec:
  externalSubnet: external204
  type: nat

---
kind: OvnSnatRule
apiVersion: kubeovn.io/v1
metadata:
  name: snat01
spec:
  ovnEip: snat-for-pod-vpc-ip
  ipName: vpc-1-busybox02.vpc1 # eip      pod ip

---
#         VPC       ip

kind: OvnSnatRule
apiVersion: kubeovn.io/v1
metadata:
  name: snat-for-subnet-in-vpc
spec:
  ovnEip: snat-for-subnet-in-vpc
  vpc: vpc1
  v4IpCidr: 192.168.0.4
```

□□□□□□□□□□□□□□□□□ externalSubnet □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□ extra□

□□□□□□□□□□□□□ snat □□□□□□□□□□□□□

```
# kubectl ko nbctl show vpc1
router 87ad06fd-71d5-4ff8-a1f0-54fa3bba1a7f (vpc1)
    port vpc1-vpc1-subnet1
        mac: "00:00:00:ED:8E:C7"
        networks: ["192.168.0.1/24"]
    port vpc1-external204
        mac: "00:00:00:EF:05:C7"
        networks: ["10.5.204.105/24"]
        gateway chassis: [7cedd14f-265b-42e5-ac17-e03e7a1f2342 276baccb-fe9c-4476-b41d-05872a94976d fd9f140c-c45d-43db-a6c0-0d4f8ea298dd]
    nat 21d853b0-f7b4-40bd-9a53-31d2e2745739
        external ip: "10.5.204.115"
        logical ip: "192.168.0.0/24"
        type: "snat"
    nat da77a11f-c523-439c-b1d1-72c664196a0f
        external ip: "10.5.204.116"
        logical ip: "192.168.0.4"
        type: "snat"
```

```
[root@pc-node-1 03-cust-vpc]# kubectl get po -A -o wide  | grep busy
vpc1            vpc-1-busybox01                              1/1     Running   0               3d15h   192.168.0.2   pc-node-2   <none>           <none>
vpc1            vpc-1-busybox02                              1/1     Running   0               17h     192.168.0.4   pc-node-1   <none>           <none>
vpc1            vpc-1-busybox03                              1/1     Running   0               17h     192.168.0.5   pc-node-1   <none>           <none>
vpc1            vpc-1-busybox04                              1/1     Running   0               17h     192.168.0.6   pc-node-3   <none>           <none>
vpc1            vpc-1-busybox05                              1/1     Running   0               17h     192.168.0.7   pc-node-1   <none>           <none>
```

```
# kubectl exec -it -n vpc1            vpc-1-busybox04   bash
kubectl exec [POD] [COMMAND] is DEPRECATED and will be removed in a future version. Use kubectl exec [POD] -- [COMMAND] instead.
[root@vpc-1-busybox04 /]#
[root@vpc-1-busybox04 /]#
[root@vpc-1-busybox04 /]# ip a
1: lo: <LOOPBACK,UP,LOWER_UP> mtu 65536 qdisc noqueue state UNKNOWN group default qlen 1000
    link/loopback 00:00:00:00:00:00 brd 00:00:00:00:00:00
    inet 127.0.0.1/8 scope host lo
       valid_lft forever preferred_lft forever
    inet6 ::1/128 scope host
       valid_lft forever preferred_lft forever
17095: eth0@if17096: <BROADCAST,MULTICAST,UP,LOWER_UP> mtu 1500 qdisc noqueue state UP group default
    link/ether 00:00:00:76:94:55 brd ff:ff:ff:ff:ff:ff link-netnsid 0
    inet 192.168.0.6/24 brd 192.168.0.255 scope global eth0
       valid_lft forever preferred_lft forever
    inet6 fe80::200:ff:fe76:9455/64 scope link
       valid_lft forever preferred_lft forever
[root@vpc-1-busybox04 /]# ping 223.5.5.5
PING 223.5.5.5 (223.5.5.5) 56(84) bytes of data.
64 bytes from 223.5.5.5: icmp_seq=1 ttl=114 time=22.2 ms
64 bytes from 223.5.5.5: icmp_seq=2 ttl=114 time=21.8 ms

[root@pc-node-1 03-cust-vpc]# kubectl exec -it -n vpc1            vpc-1-busybox02   bash
kubectl exec [POD] [COMMAND] is DEPRECATED and will be removed in a future version. Use kubectl exec [POD] -- [COMMAND] instead.
[root@vpc-1-busybox02 /]#
[root@vpc-1-busybox02 /]#
[root@vpc-1-busybox02 /]#
[root@vpc-1-busybox02 /]# ip a
1: lo: <LOOPBACK,UP,LOWER_UP> mtu 65536 qdisc noqueue state UNKNOWN group default qlen 1000
    link/loopback 00:00:00:00:00:00 brd 00:00:00:00:00:00
    inet 127.0.0.1/8 scope host lo
       valid_lft forever preferred_lft forever
    inet6 ::1/128 scope host
       valid_lft forever preferred_lft forever
1566: eth0@if1567: <BROADCAST,MULTICAST,UP,LOWER_UP> mtu 1500 qdisc noqueue state UP group default
    link/ether 00:00:00:0b:e9:d0 brd ff:ff:ff:ff:ff:ff link-netnsid 0
    inet 192.168.0.4/24 brd 192.168.0.255 scope global eth0
       valid_lft forever preferred_lft forever
    inet6 fe80::200:ff:fe0b:e9d0/64 scope link
       valid_lft forever preferred_lft forever
[root@vpc-1-busybox02 /]# ping 223.5.5.5
PING 223.5.5.5 (223.5.5.5) 56(84) bytes of data.
64 bytes from 223.5.5.5: icmp_seq=2 ttl=114 time=22.7 ms
64 bytes from 223.5.5.5: icmp_seq=3 ttl=114 time=22.6 ms
64 bytes from 223.5.5.5: icmp_seq=4 ttl=114 time=22.1 ms
^C
--- 223.5.5.5 ping statistics ---
4 packets transmitted, 3 received, 25% packet loss, time 3064ms
rtt min/avg/max/mdev = 22.126/22.518/22.741/0.278 ms

#       pod          snat
```

5.9.5 4. ovn-dnat

4.1 ovn-dnat pod dnat

```yaml
kind: OvnEip
apiVersion: kubeovn.io/v1
metadata:
  name: eip-dnat
spec:
  externalSubnet: underlay

---
kind: OvnDnatRule
apiVersion: kubeovn.io/v1
metadata:
  name: eip-dnat
spec:
  ovnEip: eip-dnat
  ipName: vpc-1-busybox01.vpc1 #      pod ip crd
  protocol: tcp
  internalPort: "22"
  externalPort: "22"


---
#         VPC      ip

kind: OvnDnatRule
apiVersion: kubeovn.io/v1
metadata:
  name: eip-dnat
spec:
  ovnEip: eip-dnat
  protocol: tcp
  internalPort: "22"
  externalPort: "22"
  vpc: vpc1
  v4Ip: 192.168.0.3
```

⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ externalSubnet ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ extra⬚

OvnDnatRule ⬚⬚⬚⬚ IptablesDnatRule ⬚⬚

```
# kubectl get oeip eip-dnat
NAME       V4IP         V6IP   MAC                TYPE   READY
eip-dnat   10.5.49.4           00:00:00:4D:CE:49  dnat   true

# kubectl get odnat
NAME                EIP                 PROTOCOL   V4EIP       V4IP          INTERNALPORT   EXTERNALPORT   IPNAME                          READY
eip-dnat            eip-dnat            tcp        10.5.49.4   192.168.0.3   22             22             vpc-1-busybox01.vpc1            true
```

4.2 ovn-dnat ⬚ vip ⬚⬚⬚⬚ dnat

```
kind: OvnDnatRule
apiVersion: kubeovn.io/v1
metadata:
  name: eip-dnat
spec:
  ipType: vip  #       dnat     pod ip              vip
  ovnEip: eip-dnat
  ipName: test-dnat-vip
  protocol: tcp
  internalPort: "22"
  externalPort: "22"

---
#          VPC       ip

kind: OvnDnatRule
apiVersion: kubeovn.io/v1
metadata:
  name: eip-dnat
spec:
  ipType: vip  #       dnat     pod ip              vip
  ovnEip: eip-dnat
  ipName: test-dnat-vip
  protocol: tcp
  internalPort: "22"
  externalPort: "22"
  vpc: vpc1
  v4Ip: 192.168.0.4
```

OvnDnatRule ⬚⬚⬚⬚ IptablesDnatRule ⬚⬚

```
# kubectl get vip test-dnat-vip
NAME            V4IP          PV4IP   MAC                PMAC   V6IP   PV6IP   SUBNET         READY
test-dnat-vip   192.168.0.4           00:00:00:D0:C0:B5                        vpc1-subnet1   true

# kubectl get oeip eip-dnat
NAME       V4IP         V6IP   MAC                TYPE   READY
eip-dnat   10.5.49.4           00:00:00:4D:CE:49  dnat   true

# kubectl get odnat eip-dnat
NAME       EIP        PROTOCOL   V4EIP       V4IP          INTERNALPORT   EXTERNALPORT   IPNAME          READY
eip-dnat   eip-dnat   tcp        10.5.49.4   192.168.0.4   22             22             test-dnat-vip   true
```

PDF Slack Support

2026⬚10⬚20⬚

2023⬚3⬚3⬚

GitHub

5.10 VPC ⬚⬚

VPC ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ VPC ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ VPC ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ NAT ⬚⬚⬚

5.10.1 ⬚⬚⬚⬚

1. ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ VPC⬚
2. ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ VPC ⬚⬚⬚⬚ CIDR ⬚⬚⬚⬚⬚
3. ⬚⬚⬚⬚⬚⬚⬚ VPC ⬚⬚⬚⬚⬚⬚⬚ VPC ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚
4. ⬚⬚ `vpcPeerings` ⬚⬚⬚⬚⬚⬚⬚⬚ `localConnectIP` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ IP ⬚⬚⬚⬚ CIDR⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ `169.254.0.1/30` ⬚ `169.254.0.1/30,fd00::1/64` ⬚⬚⬚⬚⬚⬚⬚⬚ CIDR ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

- `cidr` ▯▯▯▯ Subnet ▯ CIDR▯
- `nextHopIP` ▯▯▯ VPC ▯▯▯▯ `localConnectIP` ▯

▯▯▯▯

▯▯▯▯▯ VPC ▯▯admission webhook ▯▯▯▯▯ peering ▯▯▯ `localConnectIP` ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

```
localConnectIP is required for vpc peering with vpc-2, e.g. 169.254.0.1/30
```

▯▯▯▯▯▯▯▯▯▯ CIDR▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ admission webhook ▯▯▯▯VPC controller ▯ reconcile ▯▯▯▯▯▯▯▯▯▯ CIDR ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

6. □□□□

6.1 kubectl-ko □□

`kubectl-ko` □□□□□□□□ Kube-OVN □ Go □□□ kubectl □□□□□□ Kubernetes API □□□□□□□□□□□□□□□□□□□□□□□□ `kubectl-ko-node-agent` DaemonSet□□□ agent □□ `kube-ovn-cni` □ `ovs` □ `ovs-ovn` □ `ovn-central` □□□□□□□□□□□□□□□ shell□OVN/OVS □□□ `tcpdump` □□□□□□□□ Bash□OVN/OVS□tar □□□□□□ kubectl □□□□□□□ `kubectl ko` □□□□□□□□□□□□ `kubectl` □

6.1.1 □□

Kube-OVN □□□ CNI □□□□□□□□□□□□□□□□ `/usr/local/bin/kubectl-ko` □□□□□□□□□□□□□□□□ Kube-OVN □□□ GitHub Release □□ `kubectl-ko-<os>-<arch>.tar.gz` □Linux/macOS□□ `kubectl-ko-windows-<arch>.zip` □□□□□□ `kubectl-ko-checksums.txt` □□ SHA256□□□□□□□□ `PATH` □□□□□□□□□□□□□□□□□□□□□□□□□□ □□ OVN/OVS □□□□□□□□ Linux □□□□□□Linux□macOS□Windows □□□ amd64 □ arm64 □□□□□□□ Linux Pod □□□□□□□□□□□□□□□□□□□□

Windows □□□□□□□□□ ZIP □□□□□ `Get-FileHash` □□ SHA256□□□□ `Expand-Archive` □□□□□ `kubectl-ko.exe` □□□ `kubectl.exe` □□□□□□ `PATH` □□□□□□□□□□□□ PowerShell □□□□

```
Get-FileHash .\kubectl-ko-windows-arm64.zip -Algorithm SHA256
Expand-Archive .\kubectl-ko-windows-arm64.zip .\kubectl-ko-windows-arm64
.\kubectl-ko-windows-arm64\kubectl-ko.exe version
.\kubectl-ko-windows-arm64\kubectl-ko.exe --context staging exec nbctl -- show
```

x64 Windows □□□ amd64 □□□□□□□ stdout □□□□□□□ `kubectl ko capture --pod web -- -w -` □ □□□ PowerShell 7.4 □□□□□□□□ `cmd.exe` □□□ PowerShell □□□□□ pcap □□□□Windows □□□□□ WSL□

□□□□□□□□□□□□ `kubectl-ko-node-agent` DaemonSet□□□ Helm Chart □□ Kube-OVN □□□□ DaemonSet □□□□□□□□□□□□□□□□ Kubernetes `pods/exec` □□ agent helper□agent □□□□□□□□□□ socket □□□□□□□□ □□□□□□□□□□ Kube-OVN □□□□□ □□□□□□□□□ agent DaemonSet □□□□□□ `agent` □□□□□□□□□□ CNI □ OVS/OVN □□ Pod □□□□□□ Helm Chart □□□□□□ agent□□□□ `global.registry.imagePullSecrets` □□□□□□□□□□ Chart □ `full` □ `controlPlaneOnly` □ `dataPlaneOnly` □□□□□□ agent□v2 Chart □□□□□ □□□□□□□□□□□□ `ovsOvn.ovnDirectory` □ `logging.directory` □ `cni.configDirectory` □□□□□□□□□agent □□□□□ Linux □□□

□□□□□□□□□ `make build-kubectl-ko` □□□□ `dist/images/kubectl-ko` □□□□□□ Linux □ `dist/images/kubectl-ko-node-agent` □□□□□□□ Go `replace` □□□□□□□□□ Release □□□□□□□□□□□□ `go install ...@version` □ Windows □□□□□□□ `go build -o kubectl-ko.exe ./cmd/kubectl-ko` □□□□□□ □□ `GOOS=windows GOARCH=amd64 make build-kubectl-ko` □ARM □□□□□□□ □□ `arm64` □

□□□□□□□□□□□□□□□□□□□□

```
kubectl ko version
kubectl plugin list
```

`kubectl plugin list` □□□□□□□□□□□□□□□□□□□□

6.1.2 □□□□□□□□

Go CLI □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□

```
kubectl ko
  exec
    (POD | TYPE/NAME) [-c CONTAINER] [flags] -- COMMAND [args...]
    -l SELECTOR -- COMMAND [args...]
    nbctl | sbctl | ic-nbctl | ic-sbctl -- [TOOL_ARGS...]
    vsctl | ofctl | dpctl | appctl --node NODE -- [TOOL_ARGS...]
  db
    health
    nb
      status | backup | kick SERVER_ID | restore
    sb
      status | backup | kick SERVER_ID
  trace --pod POD|--node NODE --dst-ip IP [OPTIONS]
  capture (--pod POD | --vm VM | --vmi VMI) -- [TCPDUMP_ARGS...]
  network inspect --pod POD [--output table|json]
  diagnose
    cluster | node NODE | subnet SUBNET
    connectivity --target PROTOCOL://IP:PORT [--target ...]
    environment
  logs [OPTIONS]
  restart
  perf run [OPTIONS] | recovery --yes
```


2025 Kube-OVN Team

```
acl decode COOKIE | listen --node NODE
version | completion bash|zsh|fish|powershell
```

██	███████
`exec POD -- COMMAND` ▯ `exec deploy/NAME -- COMMAND` ▯ `exec svc/NAME -- COMMAND`	▯ Pod ███ workload selector ████ Running Pod███ Kubernetes `pods/exec` ███████ `po` ▯ `deploy` ▯ `svc` ▯ `ds` ▯ `sts` ▯ `rs` ▯ `rc` ▯ `job` ████Workload ████████████████████ Pod▯
`exec -l SELECTOR -- COMMAND`	▯ Kubernetes label selector ████ Running Pod▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯
`exec nbctl` ▯ `exec sbctl` ▯ `exec ic-nbctl` ▯ `exec ic-sbctl`	████ OVN ▯ interconnection ███ leader███ agent ████ socket ████████████████████████
`exec vsctl/ofctl/dpctl/appctl --node NODE`	███████ agent ▯▯ OVS ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯
`db nb/sb status` ▯ `db health`	██████ leader ▯ RAFT ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Running central ███ NB/SB ▯▯▯▯▯▯▯▯ leader▯▯▯▯▯▯▯▯▯▯▯▯
`db nb/sb backup`	▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ SHA256███ JSON ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯
`db nb/sb kick SERVER_ID`	████ RAFT ███ `--dry-run` ███ leader Pod ▯▯▯▯▯▯▯▯ agent▯▯▯▯▯▯ leader ███ agent▯
`db nb restore`	▯▯▯▯▯▯ bootstrap ▯▯▯▯▯▯ NB ▯▯▯▯▯ central NB/SB ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ SB▯▯▯▯▯▯ central▯▯▯▯▯▯▯▯ RAFT header▯▯▯▯▯▯▯▯▯▯▯▯▯▯ OVS▯▯▯▯▯▯▯▯▯▯
`trace`	▯▯ Pod/▯▯▯▯▯MAC ▯▯▯▯▯▯▯▯ OVN▯OVS trace▯▯▯ IPv4/IPv6▯ICMP/TCP/UDP▯IPv4 ARP▯ hostNetwork▯Underlay/U2O ▯ VM ▯▯▯ `--engine ovn` ▯▯▯ OVN trace▯
`capture`	▯ Pod ▯ KubeVirt launcher ▯▯▯▯▯▯▯▯▯ `--pod` ▯ `--vm` ▯ `--vmi` ▯▯▯▯ `-w -` ▯ pcap ▯▯▯▯▯ stdout▯
`network inspect`	▯▯ Pod ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯MAC▯MTU▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ veth ▯▯▯▯▯▯▯ `macvlan` / `ipvlan` ▯▯▯▯▯▯▯▯ `--output=json` ▯▯▯▯▯▯▯▯▯▯
`diagnose cluster` ▯ `diagnose node NODE`	▯▯▯▯▯▯▯▯▯▯ rollout ▯ leader▯▯▯▯▯▯▯▯▯▯▯ NodePort Service▯▯▯▯▯▯▯▯ Pod ▯▯ pinger ▯▯▯▯▯▯▯▯▯▯▯▯node ▯▯▯▯▯▯▯▯▯▯▯
`diagnose subnet SUBNET`	▯▯▯▯▯▯▯▯ DaemonSet ▯ NodePort Service▯▯▯▯▯ Pod ▯▯▯▯▯▯ TCP/UDP▯▯▯ ICMP ▯ NodePort ▯▯▯▯▯▯▯ ▯▯▯ CNI ▯▯ TCP/UDP listener▯
`diagnose connectivity`	▯▯▯ pinger ▯▯▯▯▯▯▯▯▯▯▯▯ Pod ▯▯▯▯▯▯ TCP/UDP IP endpoint▯▯▯▯▯ NodePort Service ▯▯▯ DaemonSet▯
`diagnose environment`	▯▯ Kubernetes API ▯▯▯▯▯ Linux ▯▯▯▯▯▯▯▯▯▯▯▯ agent ▯▯▯▯▯▯▯▯▯▯ CNI Pod ▯▯▯▯▯
`logs`	▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Linux ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ manifest ▯▯▯▯▯▯▯ `netstat.log` ▯▯▯▯▯ `/proc/net/{tcp,tcp6,udp,udp6,unix}` ▯▯▯▯▯▯▯▯ PID/▯▯▯
`restart`	▯▯▯▯▯▯▯▯▯▯▯▯ central▯OVS▯controller▯CNI▯pinger ▯ monitor▯
`perf run`	▯▯▯▯▯▯▯▯ Pod/Service▯▯▯ Pod▯▯▯▯Service ▯▯▯▯▯▯▯▯▯▯▯▯ OVN LB ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ central leader▯
`perf recovery --yes`	▯▯▯▯▯ NB▯SB ▯ northd leader Pod ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯
`acl decode COOKIE` ▯ `acl listen --node NODE`	▯▯ sample cookie▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ cookie▯▯▯▯▯▯▯▯▯
`version` ▯ `help` ▯ `completion`	▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ shell ▯▯▯

6.1.3 ████████

██ Kubernetes ████████████████████████████ `--` ███kubeconfig ██████ `--kubeconfig` ▯ `KUBECONFIG` ▯context▯TLS▯ ██████ impersonation▯Workload `exec` ██ ████ `-n/--namespace` ▯ kubeconfig ██████ `default` ██████ `TYPE/NAME` ████████████ ████████████ `capture` ▯ `trace` ███ Pod▯VM ▯ VMI ██████ ███ `namespace/name` ████████Kube-OVN ████████ `--kube-ovn-namespace` ▯ `KUBE_OVN_NS` ▯ `kube-system` ██████

██	███████
██	`--timeout=0` ████████████████ `--discovery-timeout=10s` ████████Kubernetes `--request-timeout` ████████ exec ██
Kubernetes exec	██ `POD` ▯ `TYPE/NAME` ▯ `-c/--container` ▯ `-l/--selector` ▯ `-i/--stdin` ▯ `-t/--tty` ▯ `-q/--quiet` ▯ `--pod-running-timeout=1m` ████████ `--` ██
████████	OVS ████ `--node` ██████████ `--pod` ▯ `--vm` ▯ `--vmi` ████████ `--` ██
████	`network inspect` ██ `--pod` ███ `--output=table` ███████ `--output=json` ▯
Trace	`--pod` ▯ `--node` ████████ `--dst-ip` ███ `--protocol=icmp` ▯ `--engine=all` ███ `--dst-mac` ▯TCP/UDP ██ `--dst-port=1..65535` ▯IPv4 ARP ██ `--arp-op=request` ▯ `--arp-op=reply` ▯
████████	██████ `--output FILE` ████████████████████ `--source-node NODE` ████ `--yes` ▯ `--dry-run` ▯
██	cluster/node/subnet ██ `--read-only` ████████████/██████ `--skip-kube-proxy` ██████ `WITHOUT_KUBE_PROXY=true` ▯subnet ▯ `--tcp-port` ▯ `--udp-port` ████ `TCP_CONN_CHECK_PORT` ▯ `UDP_CONN_CHECK_PORT` ██████ 8100▯8101████████connectivity ███████ `--target tcp://IP:PORT` ▯ `udp://IP:PORT` ▯IPv6 ████████
██	`--component=all` ███ `all` ▯ `kube-ovn` ▯ `ovn` ▯ `ovs` ▯ `linux` ▯ `--output-dir=kubectl-ko-log` ▯ `--concurrency=4` ▯ `--item-timeout=30s` ███ `--max-bytes=268435456` ███ `--strict` ▯
██	`perf run` ██ `--image=docker.io/kubeovn/test:v1.13.0` ▯ `--duration=5s` ▯ `--bandwidth=1G` ████████████ 1 ██ 5 ████████████ ██████████ leader ████ `perf recovery --yes` ███

██ NodePort ██████ `PreferDualStack` ████ Service ██████████ ██ ████████████

```
kubectl ko exec -n app pod/web -- date
kubectl ko exec nbctl --context staging -- --format=json show
kubectl ko exec nbctl -- -- ls-add example -- lsp-add example example-port
kubectl ko trace --pod app/web --dst-ip 10.0.0.8 --protocol tcp --dst-port 443
kubectl ko trace --node worker-a --dst-ip 2001:db8::8 --engine ovn
kubectl ko network inspect --pod app/web --output json
kubectl ko diagnose subnet ovn-default --tcp-port 8100 --udp-port 8101
kubectl ko diagnose connectivity --target tcp://10.0.0.8:8100 --target 'udp://[2001:db8::8]:8101'
kubectl ko db nb backup --output northbound.backup
kubectl ko logs --component ovn --output-dir ./support --strict
kubectl ko perf run --image registry.example/test:v1.13.0 --duration 2s
```

6.1.4 Workload exec

`exec` ██████████ Pod ███ Kubernetes workload ███workload ████ selector ████ Running Pod████████████████ Pod▯ `-l/--selector` ████████████████████ ██ ▯ Pod ████ `-n/--namespace` ████████████████ kubeconfig ████████ `default` ▯ ████ leader ████████████████████

███ Kubernetes ███████ `-c/--container` ▯ `-i/--stdin` ▯ `-t/--tty` ▯ `-q/--quiet` ▯ `--pod-running-timeout` ▯ `-n/--namespace` ▯ ████████████████ `--` ████ ████████████████ `--help` ▯ `--timeout` ▯ `-n` ▯ `-c` ████████████████

```
kubectl ko exec deploy/web -- date
kubectl ko exec -n app pod/web -- date
kubectl ko exec svc/web -c app -- sh -c 'echo ready'
kubectl ko exec -n app -l app=web -- curl http://localhost:8080/healthz
kubectl ko exec nbctl -- --format=json show
kubectl ko exec vsctl --node worker-a -- --timeout=5 show
```

`exec nbctl --help` ██████████ `exec nbctl -- --help` ███████ `ovn-nbctl` ████████████████████████████ ████████████████ `--` ████████████████████ ██████ ████████████████████████ TTY ███

6.1.5 Pod/VM 和 VMI 抓包

`capture` 支持通过 `--pod` 和 `--vm` 或 `--vmi` 指定目标，并把 `-D` 及其后的 `-i`、`-c`、`-s`、`-nn` 和 `-w -` 传给 pcap 工具；stdout/stderr 会

```
kubectl ko capture --namespace app --pod web -- -w - > capture.pcap
kubectl ko capture --vm app/database -- -w - > vm.pcap
kubectl ko capture --namespace app --vmi database -- -c 10
```

在 agent 中创建 Linux `AF_PACKET` socket 并 `setns(2)` 进入 `tcpdump` 或 `nsenter` 的 shell，捕获 Ethernet 帧并写出 pcap 流。

KubeVirt 虚拟机抓包

- `--vm` 会先把 VMI 切换为 VM，`--vmi` 则直接使用 VMI。
- 读取 VMI controller UID，定位 launcher Pod。
- 进入 launcher 容器，在 launcher 容器内执行 launcher 命令。
- launcher 不是 Running 时，会报告 launcher、VMI/Pod 状态和可用的 `--pod` 参数。

对于 VMI，launcher Pod 会先 `--vm` 启动 VM，`network inspect` 会从 OVSDB 和 Pod 网络命名空间 OVS 接口、Pod UID 匹配的 cgroup 路径和 Pod 内接口 RX/TX 计数，并以 JSON 输出 64 位 `stats64` 计数和 `stats`。

6.1.6 连通性诊断

connectivity 对 UDP 端口使用 `health check` 协议，发送 echo 请求和 DNS 查询，UDP 端口使用 subnet 中的 listener。

cluster/node/subnet 目标会额外检查 Internet，并发送 ICMP 探测；`--external-address IP` 可

```
kubectl ko diagnose cluster --external-address 1.1.1.1 --external-address 2606:4700:4700::1111
```

诊断会为每个 Pod 选择 IP 族匹配的地址，并为每次探测生成唯一 UID，cluster/node/connectivity 使用 pinger 和 service account，Pod 使用 pinger UID 和 Ready 探针，Pod 使用 host PID 和 `SYS_ADMIN` 能力，agent 使用 service-account token。subnet 使用 DaemonSet 在 Pod 内执行，Pod 使用

`logs` 将 `kubectl-ko-log/<node>/{kube-ovn,ovn,openvswitch,linux}` 下的 central 文件 `ovn/central-<pod>` 和 `manifest.json` 复制到

`--strict` 会把 Unix 文件和Windows 文件的 ACL 和Unix 文件的 Windows ACL 与 NTFS

Linux 使用 Kubernetes API 读取 Linux 节点 CNI Pod/agent 的XFRM 状态和 `nokeys` 的IPsec 状态，并把 CNI Pod UID 传给 charon 和 agent 的 strongSwan 管理 socket。`ipsec.conf` 会在 CNI 容器和 Pod 内/的IPsec 状态和 daemon 状态

`db nb restore` 会把 NB 数据库和 SB 数据库 `--source-node` 传给 `NODE_IPS` 参数，bootstrap 节点 `NODE_IPS` 会在central hostPath 和 central Deployment 上 OVS 数据库和 hostNetwork helper 使用 hostPath。节点 OVS 数据库 hostPath 和 central 的helper 和 central 的 security context 的 UID 一致

`--dry-run` 只打印 `--yes` 的helper 命令，和 central 会把 central Pod 的 RAFT header 和 JSON 输出 `/etc/ovn/.kubectl-ko-recovery-<id>` 和 central 的 glob 模式

`perf run` 在 Service 后端 30 秒内对 OVN LB 和 chassis 节点 qperf 流量，并对 LB 和 `restart` 节点 OVN/OVS 守护进程 `perf recovery --yes` 恢复

6.1.7 通过 agent 执行

命令通过 Kubernetes `pods/exec` 进入 agent helper 子命令，并通过 gRPC 连接 agent。agent 使用 socket 目录和 service-account token。`kube-ovn-cni`、`ovs-ovn` 和 `ovn-central` 等命令会在 Pod 内通过 Kubernetes 执行，workload exec 使用 WebSocket 和 SPDY 协议。helper 会把 stdin 传给 exec 会话，并在 agent 侧使用 Linux 伪终端和 130 字节缓冲区转发 session 输出。

对于不能通过 agent 和 `pods/exec` 访问 workload 的环境，get/list 和 agent 使用 `pods/exec` 权限，pods/log 使用 create/delete 和 rollout 权限对 workload patch/scale 和 `pods/exec` 权限，使用 Kube-OVN 的

6.1.8 □□□□□

Go CLI □□□□□□□□□ Bash □□□□□□□□□□□□□□□CI □□□□□ □□□□□□□□□ `logs --component COMPONENT --output-dir DIR` □

□□□	□□□
`nbctl ARGS` □ `sbctl ARGS`	`exec nbctl -- ARGS` □ `exec sbctl -- ARGS`
`icnbctl ARGS` □ `icsbctl ARGS`	`exec ic-nbctl -- ARGS` □ `exec ic-sbctl -- ARGS`
`vsctl/ofctl/dpctl/appctl NODE ARGS`	`exec TOOL --node NODE -- ARGS`
`nb/sb status` □ `nb/sb backup` □ `nb/sb kick ID`	`db nb/sb status` □ `db nb/sb backup` □ `db nb/sb kick ID`
`nb dbstatus` □ `sb dbstatus`	`db health`
`nb restore`	□□□ `db nb restore --source-node NODE --dry-run` □□□□□□ `--yes` □
`trace POD IP [MAC] PROTOCOL [PORT/OP]`	`trace --pod POD --dst-ip IP [--dst-mac MAC] --protocol PROTOCOL [--dst-port PORT/--arp-op OP]`
`trace node//NODE ...`	`trace --node NODE ...`
`ovn-trace ...`	`trace --engine ovn ...`
`tcpdump POD ARGS`	`capture --pod POD -- ARGS`
`diagnose [all]`	`diagnose cluster`
`diagnose node NODE` □ `diagnose subnet SUBNET`	□□□□□□□□□□□□□□□□□□□□□□□□□□□
`diagnose IPPorts tcp-IP-PORT,udp-IP-PORT`	`diagnose connectivity --target tcp://IP:PORT --target udp://IP:PORT`
`env-check`	`diagnose environment`
`log COMPONENT --output DIR`	`logs --component COMPONENT --output-dir DIR`
`reload`	`restart`
`perf IMAGE --duration 5`	`perf run --image IMAGE --duration 5s`
□□□□ leader □ `perf --include-disruption`	□□□□ `perf recovery --yes` □
`acl-sample decode/listen ...`	`acl decode/listen ...`

□□□□□□□□ `tcpdump` □ `ncat` / `netcat` □ `net-tools` □□□ `kubectl ko capture` □□□□□ `kubectl ko diagnose connectivity` □□ TCP/UDP endpoint□□□ `network inspect` □ `trace` □ `logs` □ `perf` □□□□□ □□□□□□□□□□□□□□□□□ DEBUG □□□DEBUG □□□□□□□ `gdb` □ `valgrind` □□□□□□□

□□ □ `kubectl ko` □□□□□ Helm values □□□ □ Bash □□□□□□□□□□□□□□□□□□□□□□□□□□ E2E fixture □□□□

PDF Slack Support

2025 Kube-OVN Team

2026⊠10⊠28⊠

2022⊠5⊠24⊠

GitHub 

6.1.9 ⊠⊠

6.2 ▒▒▒▒▒▒▒

▒▒▒▒▒▒▒ Kubernetes ▒▒▒▒▒▒▒▒▒▒▒▒ `ovs-ovn` ▒▒▒▒▒ `ovn-controller` ▒▒▒▒▒▒▒▒▒▒▒▒ `ovn-central` ▒▒▒▒▒▒▒▒▒▒ ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ ▒▒▒▒▒ Kubernetes ▒▒▒▒▒▒▒▒▒ ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ `ovn-central` ▒▒▒▒▒▒▒▒▒▒▒▒ ovn-central ▒▒▒

6.2.1 ▒▒▒▒▒▒▒▒▒▒▒

```
 # kubectl drain kube-ovn-worker --ignore-daemonsets --force
 node/kube-ovn-worker cordoned
 WARNING: ignoring DaemonSet-managed Pods: kube-system/kube-ovn-cni-zt74b, kube-system/kube-ovn-pinger-5rxfs, kube-system/kube-proxy-jpmnm, kube-system/ovs-
ovn-v2kll
 evicting pod kube-system/coredns-64897985d-qsgpt
 evicting pod local-path-storage/local-path-provisioner-5ddd94ff66-llss6
 evicting pod kube-system/kube-ovn-controller-8459db5ff4-94lxb
 pod/kube-ovn-controller-8459db5ff4-94lxb evicted
 pod/coredns-64897985d-qsgpt evicted
 pod/local-path-provisioner-5ddd94ff66-llss6 evicted
 node/kube-ovn-worker drained
```

6.2.2 ▒▒ kubelet ▒ docker

▒▒▒▒▒▒▒ `ovs-ovn` ▒▒▒▒▒▒▒▒ `ovn-central` ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

```
systemctl stop kubelet
systemctl stop docker
```

Containerd

> ▒▒ containerd ▒▒ CRI ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ Pod/▒▒▒▒▒▒▒▒▒▒▒ `ovs-ovn` ▒

▒▒ containerd ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ `ovs-ovn` ▒▒▒▒

1. ▒▒ kubelet

   ```
   systemctl stop kubelet
   ```

2. ▒▒ ovs-ovn Pod

   ```
   crictl rm -f $(crictl ps | grep openvswitch | awk '{print $1}')
   ```

3. ▒▒ containerd

   ```
   systemctl stop containerd
   ```

6.2.3 ▒▒ Node ▒▒▒▒▒▒▒

```
rm -rf /var/run/openvswitch
rm -rf /var/run/ovn
rm -rf /etc/origin/openvswitch/
rm -rf /etc/origin/ovn/
rm -rf /etc/cni/net.d/00-kube-ovn.conflist
rm -rf /etc/cni/net.d/01-kube-ovn.conflist
rm -rf /var/log/openvswitch
rm -rf /var/log/ovn
```

6.2.4 ▒▒ kubectl ▒▒▒▒

```
kubectl delete no kube-ovn-01
```


2025 Kube-OVN Team

6.2.5 □□□□□□□□□□ ovn-sb □□□

□□□□□□ kube-ovn-worker □□□□□□□□

```
# kubectl ko sbctl show
Chassis "b0564934-5a0d-4804-a4c0-476c93596a17"
  hostname: kube-ovn-worker
  Encap geneve
      ip: "172.18.0.2"
      options: {csum="true"}
  Port_Binding kube-ovn-pinger-5rxfs.kube-system
Chassis "6a29de7e-d731-4eaf-bacd-2f239ee52b28"
  hostname: kube-ovn-control-plane
  Encap geneve
      ip: "172.18.0.3"
      options: {csum="true"}
  Port_Binding coredns-64897985d-nbfln.kube-system
  Port_Binding node-kube-ovn-control-plane
  Port_Binding local-path-provisioner-5ddd94ff66-h4tn9.local-path-storage
  Port_Binding kube-ovn-pinger-hf2p6.kube-system
  Port_Binding coredns-64897985d-fhwlw.kube-system
```

6.2.6 □□□□□□ chassis □□□□□□□□□□□□

uuid □□□□□□□□□□ Chassis □□ id□

```
# kubectl ko sbctl chassis-del b0564934-5a0d-4804-a4c0-476c93596a17
# kubectl ko sbctl show
Chassis "6a29de7e-d731-4eaf-bacd-2f239ee52b28"
  hostname: kube-ovn-control-plane
  Encap geneve
      ip: "172.18.0.3"
      options: {csum="true"}
  Port_Binding coredns-64897985d-nbfln.kube-system
  Port_Binding node-kube-ovn-control-plane
  Port_Binding local-path-provisioner-5ddd94ff66-h4tn9.local-path-storage
  Port_Binding kube-ovn-pinger-hf2p6.kube-system
  Port_Binding coredns-64897985d-fhwlw.kube-system
```

PDF Slack Support

2026□7□3□

2022□6□3□

GitHub






6.2.7 □□

6.3 ▯▯ ovn-central ▯▯

▯▯ `ovn-central` ▯▯ `ovn-nb` ▯ `ovn-sb` ▯▯▯▯▯▯▯ etcd ▯ Raft ▯▯▯▯▯▯▯ `ovn-central` ▯▯▯▯▯▯▯

从 ovn-sb 中踢出节点

查看当前 ovn-sb 集群状态，记录待踢出节点的 ID：

```
kubectl ko sb status
3722
Name: OVN_Southbound
Cluster ID: d4bd (d4bd37a4-0400-499f-b4df-b4fd389780f0)
Server ID: 3722 (3722d5ae-2ced-4820-a6b2-8b744d11fb3e)
Address: tcp:[172.18.0.3]:6644
Status: cluster member
Role: leader
Term: 1
Leader: self
Vote: self

Last Election started 2395317 ms ago, reason: timeout
Last Election won: 2395316 ms ago
Election timer: 5000
Log: [130, 130]
Entries not yet committed: 0
Entries not yet applied: 0
Connections: <-e9f7 ->e9f7 <-6e84 ->6e84
Disconnections: 0
Servers:
    e9f7 (e9f7 at tcp:[172.18.0.5]:6644) next_index=130 match_index=129 last msg 1006 ms ago
    6e84 (6e84 at tcp:[172.18.0.4]:6644) next_index=130 match_index=129 last msg 1004 ms ago
    3722 (3722 at tcp:[172.18.0.3]:6644) (self) next_index=2 match_index=129
status: ok
```

`kube-ovn-control-plane2` 节点 IP 为 `172.18.0.5`，其 ID 为 `e9f7`，将其从 ovn-sb 集群中踢出：

```
# kubectl ko sb kick e9f7
started removal
```

查看踢出后状态：

```
# kubectl ko sb status
3722
Name: OVN_Southbound
Cluster ID: d4bd (d4bd37a4-0400-499f-b4df-b4fd389780f0)
Server ID: 3722 (3722d5ae-2ced-4820-a6b2-8b744d11fb3e)
Address: tcp:[172.18.0.3]:6644
Status: cluster member
Role: leader
Term: 1
Leader: self
Vote: self

Last Election started 2481636 ms ago, reason: timeout
Last Election won: 2481635 ms ago
Election timer: 5000
Log: [131, 131]
Entries not yet committed: 0
Entries not yet applied: 0
Connections: <-6e84 ->6e84
Disconnections: 2
Servers:
    6e84 (6e84 at tcp:[172.18.0.4]:6644) next_index=131 match_index=130 last msg 642 ms ago
    3722 (3722 at tcp:[172.18.0.3]:6644) (self) next_index=2 match_index=130
status: ok
```

重新加入节点至 ovn-central

假设 ovn-central 原有 `NODE_IPS` 为两个节点：

```
kubectl label node kube-ovn-control-plane2 kube-ovn/role-
kubectl scale deployment -n kube-system ovn-central --replicas=2
kubectl set env deployment/ovn-central -n kube-system NODE_IPS="172.18.0.3,172.18.0.4"
kubectl rollout status deployment/ovn-central -n kube-system
```

重新加入节点至 ovn-central 集群

重启 `ovs-ovn` 以刷新其连接的数据库节点：

```
# kubectl set env daemonset/ovs-ovn -n kube-system OVN_DB_IPS="172.18.0.3,172.18.0.4"
daemonset.apps/ovs-ovn env updated
# kubectl delete pod -n kube-system -lapp=ovs
pod "ovs-ovn-4f6jc" deleted
```

```
pod "ovs-ovn-csn2w" deleted
pod "ovs-ovn-mpbmb" deleted
```

... `kube-ovn-controller` ...

```
# kubectl set env deployment/kube-ovn-controller -n kube-system OVN_DB_IPS="172.18.0.3,172.18.0.4"
deployment.apps/kube-ovn-controller env updated

# kubectl rollout status deployment/kube-ovn-controller -n kube-system
Waiting for deployment "kube-ovn-controller" rollout to finish: 1 of 3 updated replicas are available...
Waiting for deployment "kube-ovn-controller" rollout to finish: 2 of 3 updated replicas are available...
deployment "kube-ovn-controller" successfully rolled out
```

...

... `kube-ovn-control-plane2` ...

```
rm -rf /etc/origin/ovn
```

... Kubernetes ...

6.3.2 ovn-central ...

... Kubernetes ... `ovn-central` ...

...

... `/etc/origin/ovn` ... `ovnnb_db.db` ... `ovnsb_db.db` ...

```
rm -rf /etc/origin/ovn
```

... **ovn-central** ...

... `ovn-central` ...

```
# kubectl ko nb status
1b9a
Name: OVN_Northbound
Cluster ID: 32ca (32ca07fb-739b-4257-b510-12fa18e7cce8)
Server ID: 1b9a (1b9a5d76-e69b-410c-8085-39943d0cd38c)
Address: tcp:[172.18.0.3]:6643
Status: cluster member
Role: leader
Term: 44
Leader: self
Vote: self

Last Election started 1855739 ms ago, reason: timeout
Last Election won: 1855729 ms ago
Election timer: 5000
Log: [147, 147]
Entries not yet committed: 0
Entries not yet applied: 0
Connections: ->4984 <-4984
Disconnections: 0
Servers:
    4984 (4984 at tcp:[172.18.0.4]:6643) next_index=147 match_index=146 last msg 367 ms ago
    1b9a (1b9a at tcp:[172.18.0.3]:6643) (self) next_index=140 match_index=146
status: ok

# kubectl ko sb status
3722
Name: OVN_Southbound
Cluster ID: d4bd (d4bd37a4-0400-499f-b4df-b4fd389780f0)
Server ID: 3722 (3722d5ae-2ced-4820-a6b2-8b744d11fb3e)
Address: tcp:[172.18.0.3]:6644
Status: cluster member
Role: leader
Term: 33
Leader: self
Vote: self

Last Election started 1868589 ms ago, reason: timeout
Last Election won: 1868579 ms ago
Election timer: 5000
Log: [142, 142]
Entries not yet committed: 0
```

```
Entries not yet applied: 0
Connections: ->6e84 <-6e84
Disconnections: 0
Servers:
    6e84 (6e84 at tcp:[172.18.0.4]:6644) next_index=142 match_index=141 last msg 728 ms ago
    3722 (3722 at tcp:[172.18.0.3]:6644) (self) next_index=134 match_index=141
status: ok
```

⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

⬚⬚⬚⬚ ovn-central ⬚⬚⬚⬚ `NODE_IPS` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

```
kubectl label node kube-ovn-control-plane2 kube-ovn/role=master
kubectl scale deployment -n kube-system ovn-central --replicas=3
kubectl set env deployment/ovn-central -n kube-system NODE_IPS="172.18.0.3,172.18.0.4,172.18.0.5"
kubectl rollout status deployment/ovn-central -n kube-system
```

⬚⬚⬚⬚⬚⬚⬚⬚ **ovn-central** ⬚⬚

⬚⬚ `ovs-ovn` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

```
# kubectl set env daemonset/ovs-ovn -n kube-system OVN_DB_IPS="172.18.0.3,172.18.0.4,172.18.0.5"
daemonset.apps/ovs-ovn env updated
# kubectl delete pod -n kube-system -lapp=ovs
pod "ovs-ovn-4f6jc" deleted
pod "ovs-ovn-csn2w" deleted
pod "ovs-ovn-mpbmb" deleted
```

⬚⬚ `kube-ovn-controller` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

```
# kubectl set env deployment/kube-ovn-controller -n kube-system OVN_DB_IPS="172.18.0.3,172.18.0.4,172.18.0.5"
deployment.apps/kube-ovn-controller env updated

# kubectl rollout status deployment/kube-ovn-controller -n kube-system
Waiting for deployment "kube-ovn-controller" rollout to finish: 1 of 3 updated replicas are available...
Waiting for deployment "kube-ovn-controller" rollout to finish: 2 of 3 updated replicas are available...
deployment "kube-ovn-controller" successfully rolled out
```

PDF Slack Support

2025⬚9⬚10⬚

2022⬚5⬚24⬚

GitHub



6.3.3 ⬚⬚

6.4 OVN □□□□□□□□

□□□

6.4.1 □□□□□

□□ kubectl □□□ backup □□□□□□□□□□□□□□□□□□□□□□□□□□□□

```
# kubectl ko nb backup
tar: Removing leading `/' from member names
backup ovn-nb db to /root/ovnnb_db.060223191654183154.backup

# kubectl ko sb backup
tar: Removing leading `/' from member names
backup ovn-sb db to /root/ovnsb_db.060223191654183154.backup
```

6.4.2 □□□□□□□□□

□□□□□□□□□□□□□□□□□□□

6.4.3 [illegible]

[illegible] leader[illegible]

[illegible] ovn-central

[illegible] `ovn-central` [illegible] `ovn-central` [illegible]

```
kubectl scale deployment -n kube-system ovn-central --replicas=0
```

[illegible]

[illegible] [illegible] [illegible]

> [illegible] [illegible] `ovsdb-tool cluster-to-standalone` [illegible]

[illegible] `ovn-central` [illegible] `NODE_IPS` [illegible] [illegible] `/etc/origin/ovn` [illegible] [illegible]

[illegible] `docker` [illegible]

```
docker run -it -v /etc/origin/ovn:/etc/ovn kubeovn/kube-ovn:v1.17.0 bash
cd /etc/ovn/
ovsdb-tool cluster-to-standalone ovnnb_db_standalone.db ovnnb_db.db
ovsdb-tool cluster-to-standalone ovnsb_db_standalone.db ovnsb_db.db
```

[illegible] containerd[illegible] docker[illegible] `ctr` [illegible]

```
ctr -n k8s.io image pull docker.io/kubeovn/kube-ovn:v1.17.0
ctr -n k8s.io run --rm -t \
  --mount type=bind,src=/etc/origin/ovn,dst=/etc/ovn,options=rbind:rw \
  docker.io/kubeovn/kube-ovn:v1.17.0 ovn-recover bash
cd /etc/ovn/
ovsdb-tool cluster-to-standalone ovnnb_db_standalone.db ovnnb_db.db
ovsdb-tool cluster-to-standalone ovnsb_db_standalone.db ovnsb_db.db
exit
```

[illegible] `ovn-central` Pod [illegible] `ovsdb-tool cluster-to-standalone` [illegible] `kubectl cp` [illegible]

[illegible] ovn-central [illegible]

[illegible]

```
mv /etc/origin/ovn/ovnnb_db.db /tmp
mv /etc/origin/ovn/ovnsb_db.db /tmp
```

[illegible]

[illegible] `ovnnb_db.db` [illegible] `ovnsb_db.db` [illegible] `ovn-central` [illegible] `NODE_IPS` [illegible] `/etc/origin/ovn/` [illegible]

```
mv /etc/origin/ovn/ovnnb_db_standalone.db /etc/origin/ovn/ovnnb_db.db
mv /etc/origin/ovn/ovnsb_db_standalone.db /etc/origin/ovn/ovnsb_db.db
```

[illegible] `ovn-central` [illegible]

```
kubectl scale deployment -n kube-system ovn-central --replicas=3
kubectl rollout status deployment/ovn-central -n kube-system
```

PDF Slack Support

2026⬚4⬚28⬚

2022⬚5⬚24⬚

GitHub 

6.4.4 ⬚⬚

6.5 ▯▯▯▯ CIDR

▯▯▯▯▯▯▯ CIDR ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

> ▯▯▯▯ CIDR ▯▯▯▯▯▯▯ Pod ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ CIDR ▯▯▯▯▯▯▯▯▯▯ ▯▯ Join ▯▯ CIDR ▯▯▯▯▯▯ Join ▯▯ CIDR▯

6.5.1 ▯▯▯▯

▯▯ `kubectl edit` ▯▯▯▯ `cidrBlock` ▯ `gateway` ▯ `excludeIps` ▯

```
kubectl edit subnet test-subnet
```

6.5.2 ▯▯▯▯▯▯▯▯▯ Namespace ▯▯▯ Pod

▯▯▯▯▯ `test` Namespace ▯▯▯

```
for pod in $(kubectl get pod --no-headers -n test --field-selector spec.restartPolicy=Always -o custom-columns=NAME:.metadata.name,HOST:spec.hostNetwork |
awk '{if ($2!="true") print $1}'); do
  kubectl delete pod "$pod" -n test --ignore-not-found
done
```

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ host ▯▯▯▯▯ Pod▯

```
for ns in $(kubectl get ns --no-headers -o custom-columns=NAME:.metadata.name); do
  for pod in $(kubectl get pod --no-headers -n "$ns" --field-selector spec.restartPolicy=Always -o custom-columns=NAME:.metadata.name,HOST:spec.hostNetwork |
awk '{if ($2!="true") print $1}'); do
    kubectl delete pod "$pod" -n "$ns" --ignore-not-found
  done
done
```

6.5.3 ▯▯▯▯▯▯▯▯▯

▯▯▯▯▯▯▯▯▯▯ CIDR ▯▯▯▯▯ `kube-ovn-controller` Deployment ▯▯▯▯▯▯

```
args:
- --default-cidr=10.17.0.0/16
- --default-gateway=10.17.0.1
- --default-exclude-ips=10.17.0.1
```

PDF Slack Support

2026▯4▯28▯

2022▯5▯24▯

GitHub 

6.5.4 ▯▯

2025 Kube-OVN Team

6.6 □□ Join □□ CIDR

□□□□□□ Join □□ CIDR □□□□□□□□□□□□□□□□□□□□□□□□

> □□ Join □□ CIDR □□□□□□□□ Pod □□□□□□□□□□□□□□□□□□□□□□□□ □□□□□□□□□□□

6.6.1 □□ Join □□

```
kubectl patch subnet join --type='json' -p '[{"op": "replace", "path": "/metadata/finalizers", "value": []}]'
kubectl delete subnet join
```

6.6.2 □□□□□□□□□

```
kubectl annotate node ovn.kubernetes.io/allocated=false --all --overwrite
```

6.6.3 □□ Join □□□□□□□

□□ `kube-ovn-controller` □ Join □□□□□□□

```
kubectl edit deployment -n kube-system kube-ovn-controller
```

□□□□□□□

```
args:
- --node-switch-cidr=100.51.0.0/16
```

□□ `kube-ovn-controller` □□ `join` □□□

```
kubectl delete pod -n kube-system -lapp=kube-ovn-controller
```

□□□□ Join □□□□□

```
# kubectl get subnet
NAME          PROVIDER   VPC           PROTOCOL   CIDR            PRIVATE   NAT     DEFAULT   GATEWAYTYPE   V4USED   V4AVAILABLE   V6USED   V6AVAILABLE
EXCLUDEIPS
join          ovn        ovn-cluster   IPv4       100.51.0.0/16   false     false   false     distributed   2        65531         0        0
["100.51.0.1"]
ovn-default   ovn        ovn-cluster   IPv4       10.17.0.0/16    false     true    true      distributed   5        65528         0        0
["10.17.0.1"]
```

6.6.4 □□□□ ovn0 □□□□

□□□□□ `ovn0` □□□□□□□□□□□□□□□□ `kube-ovn-cni` □□□□

```
kubectl delete pod -n kube-system -l app=kube-ovn-cni
```

PDF Slack Support

2025□9□10□

2022□5□24□

GitHub 

6.6.5 □□

2025 Kube-OVN Team

6.7 □□□□□□□

□□ kube-ovn.yaml □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□

```
vi kube-ovn.yaml
# ...
        - name: kube-ovn-controller
          image: "docker.io/kubeovn/kube-ovn:v1.17.0"
          imagePullPolicy: IfNotPresent
          args:
          - /kube-ovn/start-controller.sh
          - --v=3
# ...
#
```

PDF Slack Support

2025□9□10□

2023□4□4□

GitHub 

6.7.1 □□

2025 Kube-OVN Team

6.8 ■■■■■■■

■■■■■■■■■■■■■■■■ ■■■■■ ■■ Kube-OVN ■■■■■■■■■■■■■■■

6.8.1 ■■■■■■■

1. ■■■■■■■■■■
    - ■■ Pod ■ Pod ■■■■■■■
    - ■■ Pod ■■■■■■■■■■■■
    - ■■ Pod ■■ Service ■■■■■
    - ■■ Pod ■■■■■■■■■
    - ■■ Pod ■■■■■■■■■■■■
    - ■■■■■■■■ `kube-ovn-pinger` ■■■■■■■■■■■■■■■■■■■■■■■■
2. ■■■■■■■■■■■■■■■■■■■■■■■■■■
    - ■■ Pod ■■■■■■■■■■■■■■■■■■■■■■■
    - ■■■■■ kube-ovn-cni ■■■■■■ CNI ■■■■■■■■■
    - ■■■■■ ovs-ovn ■■■■■■■■■■ OVS ■■■■■
    - ■■ kube-ovn-controller ■■■■■■■■■■■■■■■■■■■■
    - ■■ ovn-central ■■■■■■■■■■ OVN ■■■■■
    - ■■■■■ dmesg ■■■■■■■■■■■■■■■■■■■
    - ■■■■■ `netstat -s` ■■■■■■■■■■■■■■■■
3. ■■■■■■■■■■■■■■■■■■■■ CPU, ■■■■ IO ■■■■■■■■

■■■■■■■■■■■■■ `kubectl ko logs` ■■■■■■■

6.8.2 Pod ■■■■■■■■■■ IP ■■

■■

Pod ■■■■■ Running ■■■kubectl describe Pod ■■■■■ `duplicate IPv4 address <ip> found on logical switch port <port>`

■■■■■

1. ■■■■■ Pod ■■■■■ IP Pod■■■■■■ IP ■■■■ IP ■■■■■■■■■■ IP ■■■■■■■ IP Pod
2. ■■ kube-ovn-controller ■■■■■■■■ IP ■■■■■■■■■
3. ■■■■■■■ kube-ovn-controller ■■■■■■■■■■■■ IP ■■■■■
4. `kubectl ko nbctl show` ■■ OVN ■■■■■■■■■■■■■ IP ■■
5. ■ OVN ■■■■■■■■■■ Kubernetes ■■■■■■■■■■■■ IP ■■■■■■■■■■ `kubectl ko nbctl lsp-del <port>` ■■■■■

6.8.3 Pod ■■■■■■■■■■ ping gateway failed

■■

Pod ■■■■■ Running ■■■kubectl describe Pod ■■■■■ `network <ip> with gateway <gw ip> is not ready for interface eth0 after 30 checks`

■■■■■

1. `kubectl ko sbctl show` ■■ Pod ■■■■■■■■■■■■
2. ■■■■■■■■■■ ovn-central ■ ovs-ovn ■■■■■■■■■■■■■■■■■■■■ ovn-central ■ ovs-ovn ■■■■■

2025 Kube-OVN Team

3. □□□□□□□□□□□□□□□□□□□□ Pod □□□□□
4. □□ Underlay □□□□□□□□□□□□□□□□□□□□□□□□□□□□ Underlay □□□□ □□

6.8.4 Pod □□□□□□□□□

□□

□□ VPC □ Pod □□□□□□□□□□□□□□□□□□□□□□□□

□□□□

1. □□ `kubectl ko trace` □□ OVN □□□□□□□□□□□□ ACL □□
2. □□□ ACL □□□□□□ ACL □□
3. □□□□ ACL □□□□□□ Subnet stats □□□□□□□□□□□□□□□□□□□□□□□□□□□□
4. □□□□□□□□□□□□□□□□□□□□□□□□□□□□ Subnet Spec □□□□□□□□□□
5. □□ `kube-ovn-controller` □□□□□□□□□□□□□□□□□□□□□□

6.8.5 Pod IP □□□□□□ CIDR □

□□

Pod □□□□□□□□ IP □□□□□□ CIDR □□

□□□□

1. □□□□□□□□ `/etc/cni/net.d/` □□□□□□□□□□□□ Kube-OVN □ CNI □□□□
2. □□□□□□□□□□□□□□□□□□□□□□
3. □□ kubelet □□□□□□□□□□□□ Pod

6.8.6 Debug Pod □□□□□□□

□□

kubectl debug □□□ Pod □□□□□ ContainerCreating □□□Pod Event □□ network not ready □ no address allocated

□□□□

□□ debug Pod □□□□□□ yaml □□□□□□ yaml □□ Annotation□

```
ovn.kubernetes.io/ip_address
ovn.kubernetes.io/mac_address
ovn.kubernetes.io/allocated
ovn.kubernetes.io/routed
```

□□ debug Pod□□□□□□□□ yaml □□□□ debug Pod□

6.8.7 ARM □□□□□□□□□□□□□□□□

□□

ARM □□□□□□□□ Offload □□□□□□□□□□□□□□□□□□□□□□□□

□□ `netstat` □□□□□□

```
# netstat -us
IcmpMsg:
    InType0: 22
    InType3: 24
    InType8: 117852
    OutType0: 117852
```

```
    OutType3: 29
    OutType8: 22
Udp:
    3040636 packets received
    0 packets to unknown port received.
    4 packet receive errors
    602 packets sent
    0 receive buffer errors
    0 send buffer errors
    InCsumErrors: 4
UdpLite:
IpExt:
    InBcastPkts: 10244
    InOctets: 4446320361
    OutOctets: 1496815600
    InBcastOctets: 3095950
    InNoECTPkts: 7683903
```

□□□ `InCsumErrors` □□□□□□□□□□□□□□□□□□□□□□

□□□□

□□ □□□ `tx offload` □□□□□ TCP □□□□□□□□□

```
ethtool -K eth0 tx off
```

□□□□□□□□CentOS 7 □□□□□□□□□□□□□□□□□□□□□□□□□□□□□ `4.19.90-25.16.v2101` □□□□□□□□□□□□

6.8.8 Pod □□ Service □□

□□

Pod □□□□□ Service □□□□□□ `dmesg` □□□□□

```
netlink: Unknown conntrack attr (type=6, max=5)
openvswitch: netlink: Flow actions may not be safe on all matching packets.
```

□□□□□□□□ OVS □□□□□□□□□□ NAT □□□

□□□□

1. □□□□□□□□□□□□ OVS □□□□□
2. □□□□ Overlay □□□□□□□ `kube-ovn-controller` □□□□□□□ `--enable-lb=false` □□ OVN LB □□ kube-proxy □□ Service □□□

6.8.9 ovn-central □□□□□□□

□□

□ v1.11.x □□□□□1 □□ Pod □□□□□□□□ OVN NB □□ SB □□□□□□□□□□□□□□□□ Kube-OVN □□□□□ ovsdb-server/compact □□□□□□□□□□□□

□□□□

□□□□□□□□ v1.13 □ `ENABLE_COMPACT` □□□□□ `false` □□□ `dist/images/install.sh` □ `start-db.sh` □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□ ovn-central □□□□□□□□□□□□□□□ `true` □

```
- name: ENABLE_COMPACT
  value: "false"
```

PDF Slack Support

2025 Kube-OVN Team

2026▯4▯28▯

2022▯5▯24▯



GitHub 



6.8.10 ▯▯

7. □□□□

7.1 □□□□□


Kube-OVN □□□□□ CNI □□□□□□ macvlan□vlan□host-device □□□□□□□□□ IPAM □□□ □□□□□□□□□□□ Kube-OVN □□□□□□ IP □□□

Kube-OVN □□□□□□□□□□ Kube-OVN □□□□□□□□□□

7.1.1 □□□□

□□□□□□


□□□□ Multus CNI □□□□□□ pod □□□□□□□□□□□□□ pod □□□□□□□eth0□net0 □ net1□ eth0 □□ kubernetes □□□□□□□□□ kubernetes □□□□□ kubernetes api-server□kubelet □□□ net0 □ net1 □□□□□□□□□□□□□□□ CNI □□□□ vlan/vxlan/ptp□□□□□□□□



IPAM□

□□□□ Multus CNI□□□□□□□□ Pod □□□□□□□□□□□□□ □□□□□□□□□□□□□□□□□□□□□ IP □□□□□□□□□□□□ Kube-OVN □□□□□□□□□□□ Subnet □ IP □ CRD □□□ IP □□□□□□□ □□□□□□□□IP □□□□□□□ □□□□□□□□□□□□□□□□□□□□

⬚⬚⬚⬚



⬚⬚⬚⬚⬚⬚⬚⬚ Kube-OVN ⬚⬚⬚⬚⬚⬚⬚⬚⬚ IP ⬚⬚⬚⬚⬚⬚⬚ eth0 ⬚⬚⬚⬚ OVN ⬚⬚⬚net1 ⬚⬚⬚⬚⬚⬚ CNI ⬚⬚⬚ net1 ⬚⬚⬚⬚⬚⬚⬚⬚⬚ multus-cni ⬚⬚ NetworkAttachmentDefinition ⬚⬚⬚⬚⬚

⬚ Pod ⬚⬚⬚⬚ `kube-ovn-controller` ⬚⬚⬚⬚ Pod ⬚⬚⬚⬚⬚⬚⬚ Pod ⬚⬚ annotation ⬚⬚⬚⬚⬚⬚ Subnet ⬚⬚⬚⬚⬚ IP ⬚⬚⬚⬚⬚⬚ ⬚⬚ Pod ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ Pod annotation ⬚⬚

⬚⬚⬚⬚⬚⬚⬚⬚CNI ⬚⬚⬚⬚⬚⬚⬚⬚⬚ `kube-ovn-cni` ⬚⬚⬚ ipam ⬚⬚⬚ `kube-ovn-cni` ⬚⬚⬚⬚ Pod annotation ⬚⬚⬚⬚⬚⬚⬚⬚ CNI ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ CNI ⬚⬚⬚

7.1.2 ⬚⬚⬚⬚⬚

`NetworkAttachmentDefinition` ⬚⬚ `spec` ⬚⬚⬚multus ⬚⬚⬚⬚ `defaultConfDir` ⬚⬚⬚⬚⬚ CNI ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

```
apiVersion: "k8s.cni.cncf.io/v1"
kind: NetworkAttachmentDefinition
metadata:
  name: macvlan-conf-2
```

⬚⬚ `kube-ovn-controller` ⬚⬚⬚⬚⬚⬚⬚⬚ `NetworkAttachmentDefinition` ⬚⬚ `provider` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ `spec` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ `kube-ovn-controller` ⬚⬚⬚⬚⬚⬚⬚⬚ `provider` ⬚⬚⬚⬚⬚⬚ `spec` ⬚⬚⬚⬚⬚⬚⬚ Kube-OVN ⬚ IPAM ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

7.1.3 ⬚⬚⬚⬚⬚

⬚⬚ Kube-OVN ⬚ Multus

⬚⬚⬚ Kube-OVN ⬚⬚⬚⬚⬚ ⬚ Multus how to use ⬚⬚⬚ Kube-OVN ⬚ Multus-CNI⬚

⬚⬚⬚⬚ CNI ⬚⬚ IPAM

⬚⬚⬚⬚⬚⬚⬚ Kube-OVN ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ CNI⬚

⬚⬚ NETWORKATTACHMENTDEFINITION

⬚⬚⬚⬚⬚⬚⬚ macvlan ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

```
apiVersion: "k8s.cni.cncf.io/v1"
kind: NetworkAttachmentDefinition
metadata:
  name: macvlan
  namespace: default
spec:
  config: '{
      "cniVersion": "0.3.0",
      "type": "macvlan",
      "master": "eth0",
      "mode": "bridge",
      "ipam": {
        "type": "kube-ovn",
        "server_socket": "/run/openvswitch/kube-ovn-daemon.sock",
        "provider": "macvlan.default"
      }
    }'
```

- `spec.config.ipam.type` : ▯▯▯▯▯ `kube-ovn` ▯▯▯ kube-ovn ▯▯▯▯▯▯▯▯▯▯
- `server_socket` : Kube-OVN ▯▯▯▯▯ socket ▯▯▯▯▯▯▯▯ `/run/openvswitch/kube-ovn-daemon.sock` ▯
- `provider` : ▯▯ NetworkAttachmentDefinition ▯ `<name>.<namespace>` ▯Kube-OVN ▯▯▯▯▯▯▯▯▯▯▯▯▯ Subnet ▯▯▯
- `master` : ▯▯▯▯▯▯▯▯▯

> **Info**
>
> ▯▯▯ `provider` ▯ Underlay ▯▯ `ProviderNetwork` ▯▯▯▯▯▯▯▯▯▯▯▯▯

```
    macvlan.default.kubernetes.io/ip_address: 172.17.0.100
    macvlan.default.kubernetes.io/mac_address: 00:00:00:53:6B:BB
spec:
  containers:
  - name: static-ip
    image: docker.io/library/nginx:alpine
```

... IP ...

... ippool ... `<networkAttachmentName>.<networkAttachmentNamespace>.kubernetes.io/ip_pool` annotation...

```
apiVersion: apps/v1
kind: Deployment
metadata:
  namespace: default
  name: static-workload
  labels:
    app: static-workload
spec:
  replicas: 2
  selector:
    matchLabels:
      app: static-workload
  template:
    metadata:
      labels:
        app: static-workload
      annotations:
        k8s.v1.cni.cncf.io/networks: default/macvlan
        ovn.kubernetes.io/ip_pool: 10.16.0.15,10.16.0.16,10.16.0.17
        macvlan.default.kubernetes.io/ip_pool: 172.17.0.200,172.17.0.201,172.17.0.202
    spec:
      containers:
      - name: static-workload
        image: docker.io/library/nginx:alpine
```

... macvlan ... Pod

... macvlan ... Pod...Pod ... annotation... `default-route` ...

```
apiVersion: v1
kind: Pod
metadata:
  name: samplepod-route
  namespace: default
  annotations:
    k8s.v1.cni.cncf.io/networks: '[{
      "name": "macvlan",
      "namespace": "default",
      "default-route": ["172.17.0.1"]
    }]'
spec:
  containers:
  - name: samplepod-route
    command: ["/bin/ash", "-c", "trap : TERM INT; sleep infinity & wait"]
    image: docker.io/library/alpine:edge
```

... macvlan ... Pod

... macvlan ... Pod... annotation `v1.multus-cni.io/default-network` ... NetworkAttachmentDefinition ... `<namespace>/<name>` ...

```
apiVersion: v1
kind: Pod
metadata:
  name: samplepod-macvlan
  namespace: default
  annotations:
    v1.multus-cni.io/default-network: default/macvlan
spec:
  containers:
  - name: samplepod-macvlan
    command: ["/bin/ash", "-c", "trap : TERM INT; sleep infinity & wait"]
    image: docker.io/library/alpine:edge
```

... KUBE-OVN SUBNET...PROVIDER OVN...

... `provider` ... ovn ... subnet ... IP ... `provider` ... ovn ... Kube-OVN Subnet... `cidrBlock` ... `exclude_ips` ... Subnet ...

```
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: macvlan
spec:
  protocol: IPv4
  provider: ovn
```


2025 Kube-OVN Team

```
  cidrBlock: 172.17.0.0/16
  gateway: 172.17.0.1
  excludeIps:
  - 172.17.0.0..172.17.0.10
```

▯▯▯▯▯▯▯▯ Pod

▯▯▯▯▯ `provider` ▯▯▯ ovn ▯ subnet ▯▯▯ IP ▯ Pod▯▯▯ annotation `k8s.v1.cni.cncf.io/networks` ▯ `<networkAttachmentName>.<networkAttachmentNamespace>.kubernetes.io/logical_switch` ▯▯▯▯▯

```
apiVersion: v1
kind: Pod
metadata:
  name: samplepod
  namespace: default
  annotations:
    k8s.v1.cni.cncf.io/networks: default/macvlan
    macvlan.default.kubernetes.io/logical_switch: macvlan
spec:
  containers:
  - name: samplepod
    command: ["/bin/ash", "-c", "trap : TERM INT; sleep infinity & wait"]
    image: docker.io/library/alpine:edge
```

- `k8s.v1.cni.cncf.io/networks` : ▯▯▯▯▯▯ NetworkAttachmentDefinition ▯ `<namespace>/<name>`
- `macvlan.default.kubernetes.io/logical_switch` : ▯▯▯▯▯▯

> ▯▯▯
>
> - ▯▯ `<networkAttachmentName>.<networkAttachmentNamespace>.kubernetes.io/logical_switch` ▯▯▯▯▯▯▯▯▯▯▯▯ provider ▯▯▯▯▯
> - ▯▯ ovn ▯▯▯ subnet ▯▯ ipam ▯▯▯▯▯▯▯▯ IP ▯ Pod▯▯▯▯▯▯▯ IP ▯▯▯▯▯▯▯▯▯▯▯▯▯▯ macvlan ▯ Pod▯
> - ▯▯▯▯▯▯▯▯▯▯▯ macvlan ▯ Pod▯

▯▯▯▯▯ Kube-OVN ▯▯▯▯

▯▯▯▯▯▯▯▯ Kube-OVN ▯▯▯▯▯

▯▯ NETWORKATTACHMENTDEFINITION

▯ `provider` ▯▯▯▯▯▯ `ovn` ▯

```
apiVersion: "k8s.cni.cncf.io/v1"
kind: NetworkAttachmentDefinition
metadata:
  name: attachnet
  namespace: default
spec:
  config: '{
      "cniVersion": "0.3.0",
      "type": "kube-ovn",
      "server_socket": "/run/openvswitch/kube-ovn-daemon.sock",
      "provider": "attachnet.default.ovn"
    }'
```

- `spec.config.type` : ▯▯▯ `kube-ovn` ▯▯▯ CNI ▯▯▯▯ Kube-OVN ▯▯▯
- `server_socket` : Kube-OVN ▯▯▯▯▯ socket ▯▯▯▯▯▯▯▯ `/run/openvswitch/kube-ovn-daemon.sock` ▯
- `provider` : ▯▯ NetworkAttachmentDefinition ▯ `<name>.<namespace>.ovn` ▯Kube-OVN ▯▯▯▯▯▯▯▯▯▯▯▯▯ Subnet ▯▯▯▯▯▯▯▯▯▯▯▯ ovn▯

▯▯▯▯ KUBE-OVN SUBNET

▯▯▯ Kube-OVN ▯▯▯▯▯▯▯▯ `provider` ▯▯▯▯▯▯▯▯ NetworkAttachmentDefinition ▯ `<name>.<namespace>.ovn` ▯▯▯▯ `ovn` ▯▯▯▯▯▯▯ ▯ Kube-OVN ▯▯▯▯▯▯▯▯▯▯ Subnet ▯▯▯▯▯

```
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: attachnet
spec:
  protocol: IPv4
  provider: attachnet.default.ovn
  cidrBlock: 172.17.0.0/16
  gateway: 172.17.0.1
  excludeIps:
  - 172.17.0.0..172.17.0.10
```

[illegible] Pod

[illegible] Pod[illegible] annotation `k8s.v1.cni.cncf.io/networks` [illegible] NetworkAttachmentDefinition [illegible] `<namespace>/<name>` [illegible]

```
apiVersion: v1
kind: Pod
metadata:
  name: samplepod
  namespace: default
  annotations:
    k8s.v1.cni.cncf.io/networks: default/attachnet
spec:
  containers:
  - name: samplepod
    command: ["/bin/ash", "-c", "trap : TERM INT; sleep infinity & wait"]
    image: docker.io/library/alpine:edge
```

[illegible] IP/MAC

[illegible] NetworkAttachmentDefinition [illegible] IP/MAC[illegible] `k8s.v1.cni.cncf.io/networks` [illegible] `interface` [illegible] annotation[illegible] `<nadName>.<nadNamespace>.kubernetes.io/ip_address.<interfaceName>` [illegible] `<nadName>.<nadNamespace>.kubernetes.io/mac_address.<interfaceName>` [illegible] - [illegible] IP/MAC[illegible]

[illegible]

[illegible] Kube-OVN [illegible] Pod[illegible] `<networkAttachmentName>.<networkAttachmentNamespace>.ovn.kubernetes.io/routes` annotation [illegible]

```
apiVersion: v1
kind: Pod
metadata:
  name: custom-routes-attach
  namespace: default
  annotations:
    k8s.v1.cni.cncf.io/networks: default/attachnet
    attachnet.default.ovn.kubernetes.io/routes: |
      [{
        "dst": "192.168.0.101/24",
        "gw": "172.17.0.254"
      }, {
        "gw": "172.17.0.254"
      }]
spec:
  containers:
  - name: custom-routes-attach
    command: ["/bin/ash", "-c", "trap : TERM INT; sleep infinity & wait"]
    image: docker.io/library/alpine:edge
```

> `dst` [illegible]

[illegible] Deployment[illegible]DaemonSet [illegible] StatefulSet[illegible] Annotation [illegible] `.spec.template.metadata.annotations` [illegible]

```
apiVersion: apps/v1
kind: Deployment
metadata:
  name: custom-routes-attach
  labels:
    app: nginx
spec:
  replicas: 2
  selector:
    matchLabels:
      app: nginx
  template:
    metadata:
      labels:
        app: nginx
      annotations:
        k8s.v1.cni.cncf.io/networks: default/attachnet
        attachnet.default.ovn.kubernetes.io/routes: |
          [{
            "dst": "192.168.0.101/24",
            "gw": "172.17.0.254"
          }, {
            "gw": "172.17.0.254"
          }]
    spec:
      containers:
      - name: nginx
        image: docker.io/library/nginx:alpine
```

[illegible] KUBE-OVN SUBNET[illegible]PROVIDER OVN[illegible]

[illegible] `provider` [illegible] ovn [illegible] subnet [illegible] IP [illegible] `provider` [illegible] ovn [illegible] Kube-OVN Subnet[illegible] `cidrBlock` [illegible] `exclude_ips` [illegible] Subnet [illegible]

2025 Kube-OVN Team

```
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: attachnet
spec:
  protocol: IPv4
  provider: ovn
  cidrBlock: 172.17.0.0/16
  gateway: 172.17.0.1
  excludeIps:
  - 172.17.0.0..172.17.0.10
```

▯▯▯▯▯▯▯▯ **Pod**

▯▯▯▯▯ `provider` ▯▯▯ ovn ▯ subnet ▯▯▯ IP ▯ Pod▯▯▯ annotation `k8s.v1.cni.cncf.io/networks` ▯ `<networkAttachmentName>.<networkAttachmentNamespace>.ovn.kubernetes.io/logical_switch` ▯▯▯▯▯

```
apiVersion: v1
kind: Pod
metadata:
  name: samplepod
  namespace: default
  annotations:
    k8s.v1.cni.cncf.io/networks: default/attachnet
    attachnet.default.ovn.kubernetes.io/logical_switch: attachnet
spec:
  containers:
  - name: samplepod
    command: ["/bin/ash", "-c", "trap : TERM INT; sleep infinity & wait"]
    image: docker.io/library/alpine:edge
```

- `k8s.v1.cni.cncf.io/networks` : ▯▯▯▯▯▯ NetworkAttachmentDefinition ▯ `<namespace>/<name>`
- `attachnet.default.ovn.kubernetes.io/logical_switch` : ▯▯▯▯▯▯

> ▯▯▯
>
> - ▯▯ `<networkAttachmentName>.<networkAttachmentNamespace>.ovn.kubernetes.io/logical_switch` ▯▯▯▯▯▯▯▯▯▯▯▯ provider ▯▯▯▯▯
> - ▯▯▯▯▯▯▯ Kube-OVN ▯▯▯ Pod▯▯▯▯▯▯▯ IP ▯ Pod▯▯▯▯▯▯▯ IP ▯▯▯▯▯▯▯▯▯▯▯▯▯ macvlan ▯ Pod▯▯▯▯▯▯▯▯▯▯▯▯▯ Kube-OVN ▯▯▯ Pod▯▯▯▯▯▯▯▯▯▯▯▯▯
> - ▯▯▯▯▯▯▯ Kube-OVN ▯▯▯ Pod▯▯▯▯▯▯▯ `<networkAttachmentName>.<networkAttachmentNamespace>.ovn.kubernetes.io/routes` annotation ▯▯▯▯▯ ▯▯▯

PDF Slack Support

2026▯2▯11▯

2022▯5▯20▯

GitHub



7.1.4 ▯▯

2025 Kube-OVN Team

7.2 ...

...Kube-OVN ...

...

...Kube-OVN ...

7.2.1 ...

...

1. CNI ... CNI ...
2. ... 10ns ... 20ns...
3. ... CPU... CPU ...
4. ... Macvlan ... SR-IOV ...

7.2.2 ...

> ... ...

Overlay ...

...

- Kubernetes: 1.22.0
- OS: CentOS 7
- Kube-OVN: 1.8.0 *Overlay* ...
- CPU: Intel(R) Xeon(R) E-2278G
- Network: 2*10Gbps, xmit_hash_policy=layer3+4

... `qperf -t 60 <server ip> -ub -oo msg_size:1 -vu tcp_lat tcp_bw udp_lat udp_bw` ... 1 ... tcp/udp ...

Type	tcp_lat (us)	udp_lat (us)	tcp_bw (Mb/s)	udp_bw(Mb/s)
Kube-OVN Default	25.7	22.9	27.1	1.59
Kube-OVN Optimized	13.9	12.9	27.6	5.57
HOST Network	13.1	12.4	28.2	6.02

Overlay Underlay ...

... Kube-OVN ... Overlay ... Underlay ...

Environment:

- Kubernetes: 1.22.0
- OS: CentOS 7
- Kube-OVN: 1.8.0
- CPU: AMD EPYC 7402P 24-Core Processor
- Network: Intel Corporation Ethernet Controller XXV710 for 25GbE SFP28

2025 Kube-OVN Team

`qperf -t 60 <server ip> -ub -oo msg_size:1 -vu tcp_lat tcp_bw udp_lat udp_bw`

Type	tcp_lat (us)	udp_lat (us)	tcp_bw (Mb/s)	udp_bw(Mb/s)
Kube-OVN Overlay	15.2	14.6	23.6	2.65
Kube-OVN Underlay	14.3	13.8	24.2	3.46
HOST Network	16.6	15.4	24.8	2.64

`qperf -t 60 <server ip> -ub -oo msg_size:1K -vu tcp_lat tcp_bw udp_lat udp_bw`

Type	tcp_lat (us)	udp_lat (us)	tcp_bw (Gb/s)	udp_bw(Gb/s)
Kube-OVN Overlay	16.5	15.8	10.2	2.77
Kube-OVN Underlay	15.9	14.5	9.6	3.22
HOST Network	18.1	16.6	9.32	2.66

`qperf -t 60 <server ip> -ub -oo msg_size:4K -vu tcp_lat tcp_bw udp_lat udp_bw`

Type	tcp_lat (us)	udp_lat (us)	tcp_bw (Gb/s)	udp_bw(Gb/s)
Kube-OVN Overlay	34.7	41.6	16.0	9.23
Kube-OVN Underlay	32.6	44	15.1	6.71
HOST Network	35.9	45.9	14.6	5.59

> [illegible] netfilter [illegible] `kube-proxy` [illegible] netfilter[illegible] [illegible]

7.2.3 [illegible]

[illegible]

CPU [illegible]

[illegible] CPU [illegible] CPU [illegible]

```
cpupower frequency-set -g performance
```

[illegible]

[illegible]

[illegible]

```
# ethtool -g eno1
 Ring parameters for eno1:
 Pre-set maximums:
 RX:             4096
 RX Mini:        0
 RX Jumbo:       0
 TX:             4096
 Current hardware settings:
 RX:             255
 RX Mini:        0
 RX Jumbo:       0
 TX:             255
```

[illegible]

```
ethtool -G eno1 rx 4096
ethtool -G eno1 tx 4096
```

[illegible] **tuned** [illegible]

tuned [illegible] profile [illegible]

[illegible]

```
tuned-adm profile network-latency
```

[illegible]

```
tuned-adm profile network-throughput
```

[illegible]

[illegible] `irqbalance` [illegible] CPU [illegible] CPU [illegible]

[illegible] **OVN LB**

OVN [illegible] L2 LB [illegible] `conntrack` [illegible] recirculate [illegible] CPU [illegible] 20% [illegible] CPU [illegible] [illegible] Overlay [illegible] `kube-proxy` [illegible] Service [illegible] [illegible] Pod-to-Pod [illegible] `kube-ovn-controller` [illegible]

```
command:
- /kube-ovn/start-controller.sh
args:
...
- --enable-lb=false
...
```

> Underlay [illegible] `kube-proxy` [illegible] iptables [illegible] ipvs [illegible] LB [illegible] Service [illegible]

[illegible] **conntrack** [illegible]

[illegible] OVN LB [illegible] Service [illegible] Service [illegible] NetworkPolicy [illegible] Subnet A [illegible] Pod [illegible] Subnet B [illegible] Service[illegible] [illegible] kube-ovn-controller [illegible] `--skip-conntrack-dst-cidrs` [illegible] conntrack [illegible]

```
    --skip-conntrack-dst-cidrs="10.17.0.0/16,169.254.169.245/32"
```

[illegible] **FastPath** [illegible]

[illegible] network ns[illegible] netfilter [illegible] 20% [illegible] CPU [illegible] [illegible] netfilter [illegible] `FastPath` [illegible] netfilter [illegible] CPU [illegible] [illegible]

> [illegible] netfilter [illegible] iptables[illegible]ipvs[illegible]nftables [illegible]

[illegible]

[illegible] FastPath [illegible]

[illegible] `insmod kube_ovn_fastpath.ko` [illegible] `FastPath` [illegible] `dmesg` [illegible]

```
# dmesg
...
[619631.323788] init_module,kube_ovn_fastpath_local_out
[619631.323798] init_module,kube_ovn_fastpath_post_routing
[619631.323800] init_module,kube_ovn_fastpath_pre_routing
[619631.323801] init_module,kube_ovn_fastpath_local_in
...
```

OVS [illegible]

OVS [illegible] flow [illegible] 10% [illegible] CPU [illegible] x86 CPU [illegible] `popcnt` [illegible] `sse4.2` [illegible] [illegible]flow [illegible] CPU [illegible] [illegible] 5% [illegible]

[illegible] `FastPath` [illegible]

2025 Kube-OVN Team

[illegible] CPU [illegible]

```
cat /proc/cpuinfo  | grep popcnt
cat /proc/cpuinfo  | grep sse4_2
```

CENTOS [illegible]

[illegible]

```
yum install -y gcc kernel-devel-$(uname -r) python3 autoconf automake libtool rpm-build openssl-devel
```

[illegible] OVS [illegible] RPM [illegible]:

```
git clone -b branch-3.5 --depth=1 https://github.com/openvswitch/ovs.git
cd ovs
curl -s  https://github.com/kubeovn/ovs/commit/2d2c83c26d4217446918f39d5cd5838e9ac27b32.patch |  git apply
./boot.sh
./configure --with-linux=/lib/modules/$(uname -r)/build CFLAGS="-g -O2 -mpopcnt -msse4.2"
make rpm-fedora-kmod
cd rpm/rpmbuild/RPMS/x86_64/
```

[illegible] RPM [illegible]

```
rpm -i openvswitch-kmod-3.5.1-1.el7.x86_64.rpm
```

[illegible] Kube-OVN[illegible] OVS [illegible]

UBUNTU [illegible]

[illegible]

```
apt install -y autoconf automake libtool gcc build-essential libssl-dev
```

[illegible] OVS [illegible]

```
apt install -y autoconf automake libtool gcc build-essential libssl-dev

git clone -b branch-3.5 --depth=1 https://github.com/openvswitch/ovs.git
cd ovs
curl -s  https://github.com/kubeovn/ovs/commit/2d2c83c26d4217446918f39d5cd5838e9ac27b32.patch |  git apply
./boot.sh
./configure --prefix=/usr/ --localstatedir=/var --enable-ssl --with-linux=/lib/modules/$(uname -r)/build
make -j `nproc`
make install
make modules_install

cat > /etc/depmod.d/openvswitch.conf << EOF
override openvswitch * extra
override vport-* * extra
EOF

depmod -a
cp debian/openvswitch-switch.init /etc/init.d/openvswitch-switch
/etc/init.d/openvswitch-switch force-reload-kmod
```

[illegible] Kube-OVN[illegible] OVS [illegible]

[illegible] STT [illegible]

> **Warning**
>
> OpenVswitch [illegible] 3.6 [illegible] STT [illegible] Tunnel [illegible]

[illegible] Geneve [illegible] Vxlan [illegible] UDP [illegible] UDP [illegible] TCP [illegible] TCP [illegible] offload [illegible] TCP [illegible] CPU [illegible] TCP [illegible]

STT [illegible] TCP [illegible] TCP [illegible] TCP [illegible] TCP [illegible] TCP [illegible]

STT [illegible] OVS [illegible]OVS [illegible]

2025 Kube-OVN Team

STT ⬚⬚⬚⬚⬚

```
kubectl set env daemonset/ovs-ovn -n kube-system TUNNEL_TYPE=stt

kubectl delete pod -n kube-system -lapp=ovs
```

PDF Slack Support

2025⬚10⬚28⬚

2022⬚5⬚24⬚

GitHub







7.2.4 ⬚⬚

7.3 ▯▯▯▯ FastPath ▯▯

▯▯▯▯▯▯▯▯▯ Profile▯ `Netfilter` ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ 20% ▯▯▯ CPU ▯▯▯FastPath ▯▯▯▯▯▯▯ `Netfilter` ▯▯ ▯▯ CPU ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

2026⬚2⬚11⬚

2022⬚5⬚24⬚



GitHub 




7.3.5 ⬚⬚

7.4 □□ eBPF □□□□□ TCP □□


□□□□□□ 5G □□□□□□□□□□ Pod □□□□□□□□ TCP □□□□□□□ Intel □□□ istio-tcpip-bypass □□□Pod □□□□ eBPF □□□□□□□□ TCP/IP □□□□□□□□ socket □□□□□□□□□□□□□□□□□□□□

7.4.1 □□□□

□□□□□□□□□□□□□□□ Pod □□ TCP □□□□□□□□□□□□□□□□ TCP/IP, netfilter□OVS □□□□□□□



istio-tcpip-bypass ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ TCP ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ socket ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯



▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ TCP ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ Service Mesh ▒▒▒▒▒▒▒▒▒▒▒▒▒ Service Mesh ▒▒▒▒▒▒▒

▒▒▒▒▒▒▒▒▒▒▒▒▒ Tanzu Service Mesh Acceleration using eBPF▒

7.4.2 ▒▒▒▒

eBPF ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ Ubuntu 20.04 ▒ Linux 5.4.0-74-generic ▒▒▒▒▒▒▒▒▒▒

7.4.3 ▒▒▒▒

▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ Pod▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ `nodeSelector` ▒

```
# kubectl create deployment perf --image=kubeovn/perf:dev --replicas=2
deployment.apps/perf created
# kubectl get pod -o wide
NAME                    READY   STATUS    RESTARTS   AGE   IP           NODE     NOMINATED NODE   READINESS GATES
perf-7697bc6ddf-b2cpv   1/1     Running   0          28s   100.64.0.3   sealos   <none>           <none>
perf-7697bc6ddf-p2xpt   1/1     Running   0          28s   100.64.0.2   sealos   <none>           <none>
```

▒▒▒▒▒▒ Pod ▒▒ qperf server▒▒▒▒▒▒ Pod ▒▒▒ qperf client ▒▒▒▒▒▒▒▒

```
# kubectl exec -it perf-7697bc6ddf-b2cpv sh
/ # qperf

# kubectl exec -it perf-7697bc6ddf-p2xpt sh
/ # qperf -t 60 100.64.0.3 -ub -oo msg_size:1:16K:*4 -vu tcp_lat tcp_bw
```

▒▒ istio-tcpip-bypass ▒▒▒

```
kubectl apply -f https://raw.githubusercontent.com/intel/istio-tcpip-bypass/main/bypass-tcpip-daemonset.yaml
```

▯▯▯▯ perf client ▯▯▯▯▯▯▯▯▯▯

```
# kubectl exec -it perf-7697bc6ddf-p2xpt sh
/ # qperf -t 60 100.64.0.3 -ub -oo msg_size:1:16K:*4 -vu tcp_lat tcp_bw
```

7.4.4 ▯▯▯▯

▯▯▯▯▯▯ TCP ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ 40% ~ 60% ▯▯▯▯▯▯▯▯▯▯▯▯▯ 1024 ▯▯▯▯▯▯▯▯▯ 40% ~ 80% ▯▯▯

Packet Size (byte)	eBPF tcp_lat (us)	Default tcp_lat (us)	eBPF tcp_bw (Mb/s)	Default tcp_bw(Mb/s)
1	20.2	44.5	1.36	4.27
4	20.2	48.7	5.48	16.7
16	19.6	41.6	21.7	63.5
64	18.8	41.3	96.8	201
256	19.2	36	395	539
1024	18.3	42.4	1360	846
4096	16.5	62.6	4460	2430
16384	20.2	58.8	9600	6900

> ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ 512 ▯▯▯▯▯▯▯ eBPF ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ TCP ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ ▯▯▯▯▯▯▯▯▯▯▯▯ eBPF ▯▯▯▯▯▯▯▯▯▯▯▯ eBPF TCP ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

7.4.5 ▯▯▯▯

1. istio-tcpip-bypass
2. Deep Dive TCP/IP Bypass with eBPF in Service Mesh
3. Tanzu Service Mesh Acceleration using eBPF

PDF Slack Support

2025▯9▯10▯

2022▯9▯27▯


GitHub 

7.4.6 ▯▯

7.5 ▒▒ OVN-IC ▒▒▒▒▒▒▒

Kube-OVN ▒▒▒▒ OVN-IC ▒▒▒ Kubernetes ▒▒ Pod ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ Pod ▒▒▒▒ Pod IP ▒▒▒▒▒▒▒ Kube-OVN ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ IP ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

> ▒▒▒▒▒▒▒▒▒▒▒ Overlay ▒▒▒▒▒Underlay ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒



> **Limitation**
>
> OVN-IC ▒▒▒▒▒▒▒ Pod IP ▒▒▒▒▒▒▒▒▒▒▒▒ Service▒DNS ▒ NetworkPolicy ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ Istio ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

7.5.1 ▒▒▒▒

1. 1.11.16 ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

▒▒▒▒▒ `install-ovn-ic.sh` ▒▒▒▒▒▒▒▒▒

```
wget https://raw.githubusercontent.com/kubeovn/kube-ovn/release-1.16/dist/images/install-ic-server.sh
```

▒▒▒▒▒▒▒▒▒▒ `TS_NUM` ▒▒▒▒▒▒▒▒ ECMP Path ▒▒▒

```
sed 's/VERSION=.*/VERSION=v1.17.0/' dist/images/install-ic-server.sh | TS_NUM=3 bash
```

▒▒▒▒▒▒▒▒▒▒

```
deployment.apps/ovn-ic-server created
Waiting for deployment spec update to be observed...
Waiting for deployment "ovn-ic-server" rollout to finish: 0 out of 3 new replicas have been updated...
Waiting for deployment "ovn-ic-server" rollout to finish: 0 of 3 updated replicas are available...
Waiting for deployment "ovn-ic-server" rollout to finish: 1 of 3 updated replicas are available...
Waiting for deployment "ovn-ic-server" rollout to finish: 2 of 3 updated replicas are available...
deployment "ovn-ic-server" successfully rolled out
OVN IC Server installed Successfully
```

▒▒ `kubectl ko icsbctl show` ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

```
kubectl ko icsbctl show
availability-zone az0
    gateway 059b5c54-c540-4d77-b009-02d65f181a02
        hostname: kube-ovn-worker
        type: geneve
            ip: 172.18.0.3
        port ts-az0
            transit switch: ts
            address: ["00:00:00:B4:8E:BE 169.254.100.97/24"]
    gateway 74ee4b9a-ba48-4a07-861e-1a8e4b9f905f
        hostname: kube-ovn-worker2
        type: geneve
            ip: 172.18.0.2
        port ts1-az0
            transit switch: ts1
            address: ["00:00:00:19:2E:F7 169.254.101.90/24"]
    gateway 7e2428b6-344c-4dd5-a0d5-972c1ccec581
        hostname: kube-ovn-control-plane
        type: geneve
            ip: 172.18.0.4
        port ts2-az0
            transit switch: ts2
            address: ["00:00:00:EA:32:BA 169.254.102.103/24"]
availability-zone az1
    gateway 034da7cb-3826-4318-81ce-6a877a9bf285
        hostname: kube-ovn1-worker
        type: geneve
            ip: 172.18.0.6
        port ts-az1
            transit switch: ts
            address: ["00:00:00:25:3A:B9 169.254.100.51/24"]
    gateway 2531a683-283e-4fb8-a619-bdbcb33539b8
        hostname: kube-ovn1-worker2
        type: geneve
            ip: 172.18.0.5
        port ts1-az1
            transit switch: ts1
            address: ["00:00:00:52:87:F4 169.254.101.118/24"]
    gateway b0efb0be-e5a7-4323-ad4b-317637a757c4
        hostname: kube-ovn1-control-plane
        type: geneve
            ip: 172.18.0.8
        port ts2-az1
            transit switch: ts2
            address: ["00:00:00:F6:93:1A 169.254.102.17/24"]
```

▒▒▒▒▒▒▒ **2**

▒▒▒▒▒ `kube-ovn-controller` ▒▒▒ IP ▒▒▒▒▒▒▒▒▒ `OVN-IC` ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

▒▒ `docker` ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ `OVN-IC` ▒▒▒▒▒

```
docker run --name=ovn-ic-db -d --env "ENABLE_OVN_LEADER_CHECK="false"" --network=host --privileged  -v /etc/ovn/:/etc/ovn -v /var/run/ovn:/var/run/ovn -v /
var/log/ovn:/var/log/ovn kubeovn/kube-ovn:v1.17.0 bash start-ic-db.sh
```

▒▒▒▒▒ `containerd` ▒▒ `docker` ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

2025 Kube-OVN Team

```
ctr -n k8s.io run -d --env "ENABLE_OVN_LEADER_CHECK="false"" --net-host --privileged --mount="type=bind,src=/etc/ovn/,dst=/etc/ovn,options=rbind:rw" --
mount="type=bind,src=/var/run/ovn,dst=/var/run/ovn,options=rbind:rw" --mount="type=bind,src=/var/log/ovn,dst=/var/log/ovn,options=rbind:rw" docker.io/kubeovn/
kube-ovn:v1.17.0 ovn-ic-db bash start-ic-db.sh
```

7.5.3 ■■■■■■■

■■■■■■■■■■■■■■■■■■■■■■ VPC ■ Subnet ■ CIDR ■■■■■■ `OVN-IC` ■■■■■■■■■■■■■ Subnet CIDR ■■■■■■■

■ `kube-system` Namespace ■■■ `ovn-ic-config` ConfigMap■

```
apiVersion: v1
kind: ConfigMap
metadata:
  name: ovn-ic-config
  namespace: kube-system
data:
  enable-ic: "true"
  az-name: "az1"
  ic-db-host: "192.168.65.3"
  ic-nb-port: "6645"
  ic-sb-port: "6646"
  gw-nodes: "az1-gw"
  auto-route: "true"
```

- `enable-ic`：■■■■■■■■■■
- `az-name`：■■■■■■■■■■■■■■■■■■■■■■■■■■■■
- `ic-db-host`：■■ `OVN-IC` ■■■■■■■■■■
- `ic-nb-port`：`OVN-IC` ■■■■■■■■■■■■■ 6645■
- `ic-sb-port`：`OVN-IC` ■■■■■■■■■■■■■ 6646■
- `gw-nodes`：■■■■■■■■■■■■■■■■■■■■■■■■■■■■
- `auto-route`：■■■■■■■■■■■■■■■■■

■■■ ■■■■■■■■■■■■■ `ovn-ic-config` ■■ ConfigMap ■■■■■■■■■■■■■■■■■■■■■■ ConfigMap■■■■■■■■■ ConfigMap■

■ `ovn-ic` ■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■ `ts` ■

```
# ovn-ic-sbctl show
availability-zone az1
    gateway deee03e0-af16-4f45-91e9-b50c3960f809
        hostname: az1-gw
        type: geneve
            ip: 192.168.42.145
        port ts-az1
            transit switch: ts
            address: ["00:00:00:50:AC:8C 169.254.100.45/24"]
availability-zone az2
    gateway e94cc831-8143-40e3-a478-90352773327b
        hostname: az2-gw
        type: geneve
            ip: 192.168.42.149
        port ts-az2
            transit switch: ts
            address: ["00:00:00:07:4A:59 169.254.100.63/24"]
```

■■■■■■■■■■■■■■■■■■■■■■■■■■■■■

```
# kubectl ko nbctl lr-route-list ovn-cluster
IPv4 Routes
                10.42.1.1            169.254.100.45 dst-ip (learned)
                10.42.1.3                100.64.0.2 dst-ip
                10.16.0.2                100.64.0.2 src-ip
                10.16.0.3                100.64.0.2 src-ip
                10.16.0.4                100.64.0.2 src-ip
                10.16.0.6                100.64.0.2 src-ip
             10.17.0.0/16            169.254.100.45 dst-ip (learned)
            100.65.0.0/16            169.254.100.45 dst-ip (learned)
```

■■■■■■■■■■■ 1 ■■■■■ Pod ■■■ `ping` ■■ 2 ■■■■■ Pod IP ■■■■■■■■■■

■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■ Subnet ■■ `disableInterConnection` ■■■■■■■■■

```
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
```


2025 Kube-OVN Team

```
    name: no-advertise
  spec:
    cidrBlock: 10.199.0.0/16
    disableInterConnection: true
```

7.5.4 ⬚⬚⬚⬚⬚⬚

⬚⬚⬚⬚⬚⬚⬚⬚ CIDR ⬚⬚⬚⬚⬚⬚⬚⬚

```
docker run --name=ovn-ic-db -d --env "ENABLE_OVN_LEADER_CHECK="false"" --network=host --privileged -v /etc/ovn/:/etc/ovn -v /var/run/ovn:/var/run/ovn -v /var/
log/ovn:/var/log/ovn -e LOCAL_IP="192.168.65.3"  -e NODE_IPS="192.168.65.3,192.168.65.2,192.168.65.1"   kubeovn/kube-ovn:v1.17.0 bash start-ic-db.sh
```

 `containerd`

```
ctr -n k8s.io run -d --env "ENABLE_OVN_LEADER_CHECK="false"" --net-host --privileged --mount="type=bind,src=/etc/ovn/,dst=/etc/ovn,options=rbind:rw" --
mount="type=bind,src=/var/run/ovn,dst=/var/run/ovn,options=rbind:rw" --mount="type=bind,src=/var/log/ovn,dst=/var/log/ovn,options=rbind:rw"  --
env="NODE_IPS="192.168.65.3,192.168.65.2,192.168.65.1"" --env="LOCAL_IP="192.168.65.3"" docker.io/kubeovn/kube-ovn:v1.17.0 ovn-ic-db bash start-ic-db.sh
```

- `LOCAL_IP` IP
- `NODE_IPS` `OVN-IC` IP

 `OVN-IC` follower

 `docker`

```
docker run --name=ovn-ic-db -d --network=host --privileged -v /etc/ovn/:/etc/ovn -v /var/run/ovn:/var/run/ovn -v /var/log/ovn:/var/log/ovn -e
LOCAL_IP="192.168.65.2"  -e NODE_IPS="192.168.65.3,192.168.65.2,192.168.65.1" -e LEADER_IP="192.168.65.3"  kubeovn/kube-ovn:v1.17.0 bash start-ic-db.sh
```

 `containerd`

```
ctr -n k8s.io run -d --net-host --privileged --mount="type=bind,src=/etc/ovn/,dst=/etc/ovn,options=rbind:rw" --mount="type=bind,src=/var/run/ovn,dst=/var/run/
ovn,options=rbind:rw" --mount="type=bind,src=/var/log/ovn,dst=/var/log/ovn,options=rbind:rw"  --env="NODE_IPS="192.168.65.3,192.168.65.2,192.168.65.1"" --
env="LOCAL_IP="192.168.65.2"" --env="LEADER_IP="192.168.65.3"" docker.io/kubeovn/kube-ovn:v1.17.0 ovn-ic-db bash start-ic-db.sh
```

- `LOCAL_IP` IP
- `NODE_IPS` `OVN-IC` IP
- `LEADER_IP` : `OVN-IC` leader IP

 `ovn-ic-config` `OVN-IC`

```yaml
apiVersion: v1
kind: ConfigMap
metadata:
  name: ovn-ic-config
  namespace: kube-system
data:
  enable-ic: "true"
  az-name: "az1"
  ic-db-host: "192.168.65.3,192.168.65.2,192.168.65.1"
  ic-nb-port: "6645"
  ic-sb-port: "6646"
  gw-nodes: "az1-gw"
  auto-route: "true"
```

7.5.6 ECMP

1

ECMPECMP path 3 ECMP path

```
kubectl edit deployment ovn-ic-server -n kube-system
```

'TS_NUM' `TS_NUM` ECMP Path

7.5.7

Configmap

```
kubectl -n kube-system delete cm ovn-ic-config
```

 `ts`

```
kubectl ko nbctl ls-del ts
```

[illegible]

7.5.8 az-name

[illegible] `kubectl edit` [illegible] `ovn-ic-config` configmap `az-name` [illegible] ovn-cni pod [illegible] 10 [illegible]

```
ovn-appctl -t ovn-controller inc-engine/recompute
```

7.5.9 [illegible]

[illegible] `ovn-ic-config` Configmap

```
kubectl -n kube-system delete cm ovn-ic-config
```

[illegible] `ts` [illegible]

```
kubectl ko nbctl ls-del ts
```

[illegible] OVN-IC [illegible]

[illegible] `docker` [illegible]

```
docker stop ovn-ic-db
docker rm ovn-ic-db
```

[illegible] `containerd` [illegible]

```
ctr -n k8s.io task kill ovn-ic-db
ctr -n k8s.io containers rm ovn-ic-db
```

[illegible] deployment `ovn-ic-server` [illegible]

```
kubectl delete deployment ovn-ic-server -n kube-system
```

[illegible] master [illegible] DB[illegible]

```
rm -f /etc/origin/ovn/ovn_ic_nb_db.db
rm -f /etc/origin/ovn/ovn_ic_sb_db.db
```

PDF Slack Support

2025[illegible]6[illegible]19[illegible]

2022[illegible]5[illegible]24[illegible]

GitHub 

7.5.10 [illegible]

7.6 ▯▯ Submariner ▯▯▯▯▯▯▯

Submariner ▯▯▯▯▯▯▯ Kubernetes ▯▯ Pod ▯ Service ▯▯▯▯▯▯▯▯▯▯▯▯▯ Kube-OVN ▯▯▯▯▯▯▯

▯▯▯▯ OVN-IC ▯▯▯▯▯▯▯▯▯▯▯▯Submariner ▯▯▯▯ Kube-OVN ▯▯ Kube-OVN ▯▯▯▯▯▯▯ ▯▯▯ Service ▯▯▯▯▯▯▯▯▯ Submariner ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

7.6.1 ▯▯▯▯

- ▯▯▯▯▯ Service CIDR ▯▯▯▯▯▯ CIDR ▯▯▯▯▯

7.6.2 ▯▯ Submariner

> **Note**
>
> Submariner ▯ v0.22.0 ▯▯▯ nftables ▯▯▯▯▯▯▯▯▯▯▯▯ Kube-OVN ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Submariner▯
>
> ```
> kubectl create namespace submariner-operator
> kubectl create configmap submariner-global --namespace=submariner-operator --from-literal=use-nftables=false
> ```

▯▯ `subctl` ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

```
curl -Ls https://get.submariner.io | bash
export PATH=$PATH:~/.local/bin
echo export PATH=\$PATH:~/.local/bin >> ~/.profile
```

▯▯ `kubeconfig` ▯▯▯▯▯▯ `submariner-broker` ▯▯▯▯▯▯▯▯▯

```
subctl deploy-broker
```

▯▯▯▯▯▯ `cluster0` ▯▯▯▯▯▯ CIDR ▯ `10.16.0.0/16` ▯join ▯▯ CIDR ▯ `100.64.0.0/16` ▯ `cluster1` ▯▯▯▯▯▯ CIDR ▯ `11.16.0.0/16` ▯join ▯▯ CIDR ▯ `100.68.0.0/16` ▯

▯▯ `kubeconfig` ▯ `cluster0` ▯▯▯▯▯▯ broker▯▯▯▯▯▯▯▯▯:

```
subctl  join broker-info.subm --clusterid  cluster0 --clustercidr 100.64.0.0/16,10.16.0.0/16  --natt=false --cable-driver vxlan --health-check=false
kubectl label nodes cluster0 submariner.io/gateway=true
```

▯▯ `kubeconfig` ▯ `cluster1` ▯▯▯▯▯▯ broker▯▯▯▯▯▯▯▯▯:

```
subctl  join broker-info.subm --clusterid  cluster1 --clustercidr 100.68.0.0/16,11.16.0.0/16  --natt=false --cable-driver vxlan --health-check=false
kubectl label nodes cluster1 submariner.io/gateway=true
```

▯▯▯▯ `join` ▯▯▯▯▯▯▯▯ `gateway, routeagent` pod ▯▯▯▯▯, ▯▯ `submariner-operator` ▯▯ `clusterrole` ▯▯▯▯▯▯▯:

```
- apiGroups:
  - "apps"
  resources:
  - daemonsets
  verbs:
  - create
  - get
  - list
  - watch
  - update
```

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `subnet` `ovn-default` ▯▯▯▯▯▯▯▯ `centralized` ▯▯▯▯▯▯▯ `gatewayNode` ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

```
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: ovn-default
spec:
  gatewayType: centralized
  gatewayNode: "node1,node2"   #   submariner     gateway
```

▯ submariner ▯▯▯▯ `gateway` ▯▯▯▯▯▯ `gatewayNode` ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

2025 Kube-OVN Team

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Pod ▯▯▯▯▯ IP ▯▯▯▯▯▯▯▯

▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `subctl` ▯▯▯▯▯▯▯▯


```
subctl show all
subctl diagnose all
```

▯▯ Submariner ▯▯▯▯▯▯▯▯ Submariner ▯▯▯▯▯

PDF Slack Support

2026▯4▯28▯

2022▯5▯24▯

GitHub 

7.6.3 ▯▯

7.7 Overlay

Underlay Pod IP

> VPC Overlay Pod IP IP

7.7.1

- `ip_forward`
- iptables forward Drop
- ct `INVALID`

7.7.2

`natOutgoing` `false` nat Pod IP

```yaml
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: routed
spec:
  protocol: IPv4
  cidrBlock: 10.166.0.0/16
  default: false
  excludeIps:
  - 10.166.0.1
  gateway: 10.166.0.1
  gatewayType: distributed
  natOutgoing: false
```

Pod

Kubernetes

```
ip route add 10.166.0.0/16 via 192.168.2.10 dev eth0
```

`10.166.0.0/16` `192.168.2.10` Kubernetes

IP Keepalived VIP VIP

Subnet `gatewayType` `centralized` `gatewayNode` IP

```yaml
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: routed
spec:
  protocol: IPv4
  cidrBlock: 10.166.0.0/16
  default: false
  excludeIps:
  - 10.166.0.1
  gateway: 10.166.0.1
  gatewayType: centralized
  gatewayNode: "node1"
  natOutgoing: false
```

nat VPC NAT

PDF Slack Support

2025 Kube-OVN Team

2023⊠12⊠25⊠

2022⊠7⊠6⊠

GitHub 

7.7.3 ⊠⊠

2025 Kube-OVN Team

7.8 Overlay □□□□□□□□

□□□□□□□□□□□□□□ Overlay □□□□□□□□□□□□□□□ tunnel □□□□□□□□□

- □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□
- □□□
- □□

7.8.1 □□□□□□□□□

□□□□□□□□□□□□□□□Kube-OVN □□□□□ Kubernetes Node IP □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□

□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□

```
IFACE=eth1
```

□□□□□□□□□□□□□□□□□□□□□□ `ens[a-z0-9]*,eth[a-z0-9]*` □

□□□□□□□□□□ `kube-ovn-cni` DaemonSet □□□□□□□□□

```
args:
- --iface=eth1
```

□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□ annotation `ovn.kubernetes.io/tunnel_interface` □□□□□□□□□□□□□□□□□ annotation □□□□□ `iface` □□□□□□□□ annotation□

```
kubectl annotate node no1 ovn.kubernetes.io/tunnel_interface=ethx
```

7.8.2 □□□□□□□□□□□□□

□□□□□□□□□□□□□□□□Kube-OVN □□□□□□□□□□□□□□□□□□□□□□□□ IP □□ tunnel □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□

□□□□□

- □□□□□□□□□□□□□□□□□□□□□□□□ IP □□□□
- □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□
- □□□□□□□ Overlay □□□□□□

□□□□□

1. □□□□ Node □□□□□□□□□□□□□□□□□□□□□□□□ IP□
2. □ Subnet □□□□ `nodeNetwork` □□□□□□□□□□□□□□□□□□□
3. kube-ovn-daemon □□□□□□□□□□□□□□□□ IP □□□□ OVS□
4. □ Pod □□□□□□□□□□□□□□□□□ `nodeNetwork` □□□□□□ Pod □ OVS □□□□□□□□□□ IP□

□□□□□□□

□□□□□□□□□□□□□□□□□□□□□□ `ovn.kubernetes.io/node_networks` □□□□□□□□ JSON □□□key □□□□□□□value □□□□□□□□□□ IP□

```
kubectl annotate node <node-name> ovn.kubernetes.io/node_networks='{"storage": "192.168.100.10", "app": "172.16.0.10"}'
```

□□□□□□□□□□□□□□□□□

- `storage` □□□□ IP `192.168.100.10` □□□□□ IP □□□□□□□□□□□□□
- `app` □□□□ IP `172.16.0.10` □□□□□ IP □□□□□□□□□□□

□□□□□□□□□□□□□□□□□□□

[illegible]

[illegible] `spec.nodeNetwork` [illegible]

```
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: storage-subnet
spec:
  protocol: IPv4
  cidrBlock: 10.100.0.0/16
  gateway: 10.100.0.1
  nodeNetwork: storage
```

[illegible] `storage-subnet` [illegible] Pod [illegible] `storage` [illegible] tunnel [illegible]

[illegible] `nodeNetwork` [illegible] IP[illegible] `IFACE` [illegible] IP[illegible]

[illegible]

[illegible] OVS [illegible] IP [illegible]

[illegible] OVS [illegible] IP[illegible]

```
ovs-vsctl get open . external-ids:ovn-encap-ip
```

[illegible] IP[illegible]

```
"192.168.1.10,192.168.100.10,172.16.0.10"
```

[illegible] IP[illegible]

```
ovs-vsctl get open . external-ids:ovn-encap-ip-default
```

[illegible] POD [illegible] IP

[illegible] Pod [illegible] Pod [illegible] OVS [illegible] IP [illegible]

```
ovs-vsctl --columns=external_ids find interface external-ids:iface-id="<pod-name>.<namespace>"
```

[illegible] `nodeNetwork` [illegible] `encap-ip` [illegible]

```
external_ids        : {encap-ip="192.168.100.10", iface-id="test-pod.default", ...}
```

[illegible]

[illegible]

[illegible]

1. [illegible]

[illegible]

- `eth0` [illegible]IP [illegible] `192.168.1.10` [illegible] `192.168.1.11`
- `eth1` [illegible]IP [illegible] `10.10.10.10` [illegible] `10.10.10.11`

```
kubectl annotate node node1 ovn.kubernetes.io/node_networks='{"storage": "10.10.10.10"}'
kubectl annotate node node2 ovn.kubernetes.io/node_networks='{"storage": "10.10.10.11"}'
```

2. [illegible]

```
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: storage-net
spec:
  protocol: IPv4
  cidrBlock: 10.200.0.0/16
  gateway: 10.200.0.1
  nodeNetwork: storage
```

```
  namespaces:
  - storage-namespace
```

3. ⬚⬚⬚⬚⬚⬚⬚⬚ POD

```
apiVersion: v1
kind: Pod
metadata:
  name: storage-pod
  namespace: storage-namespace
spec:
  containers:
  - name: app
    image: docker.io/library/nginx:alpine
```

⬚ Pod ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ `eth1` ⬚⬚⬚⬚⬚⬚

⬚⬚⬚⬚

1. ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚
2. ⬚⬚⬚⬚⬚⬚⬚⬚ IP ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ IP ⬚⬚⬚
3. ⬚⬚⬚⬚⬚⬚⬚ Overlay ⬚⬚⬚⬚⬚Underlay ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ Underlay ⬚⬚⬚⬚⬚⬚ Underlay ⬚⬚⬚⬚⬚
4. ⬚⬚⬚⬚⬚⬚⬚ `nodeNetwork` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

7.9 BGP ▯▯

Kube-OVN ▯▯▯ Pods▯Subnets▯Services ▯ EIPs ▯ IP ▯▯▯▯ BGP ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ IP ▯▯▯ ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `kube-ovn-speaker` ▯▯▯▯▯▯▯▯▯ Pod ▯ Subnet ▯▯▯▯▯ annotation▯

▯▯▯▯ EIP ▯▯▯ BGP▯▯▯▯▯▯▯▯▯▯▯▯ VPC NAT Gateway▯▯▯▯▯▯▯▯▯▯▯▯▯▯ EIPs▯

7.9.1 ▯▯ kube-ovn-speaker

`kube-ovn-speaker` ▯▯▯ GoBGP ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

▯▯▯▯ `kube-ovn-speaker` ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

```
kubectl label nodes speaker-node-1 ovn.kubernetes.io/bgp=true
kubectl label nodes speaker-node-2 ovn.kubernetes.io/bgp=true
```

> ▯▯▯▯▯ kube-ovn-speaker ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ ECMP▯

▯▯▯▯ yaml:

```
wget https://raw.githubusercontent.com/kubeovn/kube-ovn/release-1.16/yamls/speaker.yaml
```

▯▯ yaml ▯▯▯▯▯▯

▯▯▯▯▯▯▯▯▯▯▯▯

```
- --neighbor-address=10.32.32.254
- --neighbor-ipv6-address=2409:AB00:AB00:2000::AFB:8AFE
- --neighbor-as=65030
- --cluster-as=65000
#       IP
# - --allowed-source-addresses=10.32.32.2,10.32.32.3,10.32.32.4,10.32.32.5
```

▯▯▯▯▯▯▯▯▯▯▯

```
- --neighbor-address=10.32.32.252,10.32.32.253
- --neighbor-ipv6-address=2409:AB00:AB00:2000::AFB:8AFC,2409:AB00:AB00:2000::AFB:8AFD
- --neighbor-as=65030
- --cluster-as=65000
#       IP
# - --allowed-source-addresses=10.32.32.2,10.32.32.3,10.32.32.4,10.32.32.5
```

- `neighbor-address` : BGP Peer ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯
- `neighbor-as` : BGP Peer ▯ AS ▯▯
- `cluster-as` : ▯▯▯▯▯ AS ▯▯
- `allowed-source-addresses` : Speaker ▯▯▯▯▯▯▯▯ IP ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯Speaker ▯▯▯ `ip route get` ▯▯▯▯ BGP Peer ▯▯▯▯▯▯▯▯▯▯▯▯▯▯ IP ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Speaker ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ ECMP ▯▯▯▯▯▯▯▯▯▯ IP ▯▯▯▯▯▯▯▯▯▯ IP ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

▯▯ yaml:

```
kubectl apply -f speaker.yaml
```

▯▯▯▯▯ YAML ▯▯

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `kube-ovn-speaker` ▯▯▯▯ YAML ▯▯▯▯▯▯▯▯▯▯ `--config=/etc/kube-ovn/$(NODE_NAME).yaml` ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `KUBE_OVN_BGP_SPEAKER_CONFIG_FILE` ▯▯▯▯▯▯▯▯▯▯▯▯ `--config` ▯▯▯▯▯▯

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ ConfigMap ▯▯▯ key ▯▯▯key ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `<spec.nodeName>.yaml` ▯▯▯ `.yaml` ▯▯▯▯▯▯▯▯ Pod ▯ `spec.nodeName` ▯▯▯▯▯▯▯ `speaker-node-1` ▯ `speaker-node-2` ▯▯▯▯▯▯▯▯

```
apiVersion: v1
kind: ConfigMap
metadata:
  name: kube-ovn-bgp-speaker-config
```


2025 Kube-OVN Team

```
  namespace: kube-system
data:
  speaker-node-1.yaml: |
    cluster-as: 65000
    neighbor-address:
      - 10.32.32.254
    neighbor-as: 65030
    router-id: 10.32.32.2
  speaker-node-2.yaml: |
    cluster-as: 65001
    neighbor-address:
      - 10.32.32.254
    neighbor-as: 65030
    router-id: 10.32.32.3
```

□□ v2 Helm Chart □□□□ `bgpSpeaker.configMap` □□ ConfigMap□□□□ `bgpSpeaker.extraEnv` □□□ Pod □□ Downward API □ `NODE_NAME` □□□□□□□

```
bgpSpeaker:
  enabled: true
  configMap: kube-ovn-bgp-speaker-config
  configMapMountPath: /etc/kube-ovn/
  extraEnv:
    - name: KUBE_OVN_BGP_SPEAKER_CONFIG_FILE
      value: /etc/kube-ovn/$(NODE_NAME).yaml
```

□□□□□□□□□□□□□□□□□□□□ ConfigMap □□□ speaker □□□□□□□□□□ `NODE_NAME` □□□□□□□□□□□

```
env:
  - name: NODE_NAME
    valueFrom:
      fieldRef:
        fieldPath: spec.nodeName
  - name: KUBE_OVN_BGP_SPEAKER_CONFIG_FILE
    value: /etc/kube-ovn/$(NODE_NAME).yaml
```

□□□□ `--config` □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□ YAML □□□□□□□□□□□ speaker □□□□□

□□□□□□□□□□□□□□□□□□□□ kebab-case □□□□□□□□□□□□□□□

- `neighbor-address` □ `neighbor-ipv6-address` □IPv4 □ IPv6 □□□□□
- `allowed-source-addresses` □ `allowed-source-ipv6-addresses` □□□□□□□□□□□
- `cluster-as` □ `neighbor-as` □AS □□□□□□□□
- `grpc-host` □IPv4 □ IPv6 □□□□□□□
- `router-id` □IPv4 □□□□□□□BGP router ID □□□ IPv6□
- `node-ips` □□□□□□□□□ `IPv4` □ `IPv6` □□□□□□□□□□□□□□□
- `holdtime` □ `graceful-restart-time` □ `graceful-restart-deferral-time` □□□□□□□□□□□ `90s` □ `5m` □ `1h` □□□□□□□□□□□□□
- `announce-cluster-ip` □ `graceful-restart` □ `passivemode` □ `extended-nexthop` □ `nat-gw-mode` □ `enable-metrics` □ `enable-bfd` □□□□□
- `bfd-min-tx` □ `bfd-min-rx` □ `bfd-detection-multiplier` □□□□

□□□□□□□□□□□□□□□□□□□□ CLI □□□□□□□□□□□□□□□□□□□□ CLI □□□□□□□□□□□□□ CLI □□□□□□□□□□□□□□□□□□□□

7.9.2 □□ Pod/Subnet □□

□□□□ BGP □□□□□□□□□□□□□□□□ Subnet □ `natOutgoing` □□□ `false` □□□ Pod IP □□□□□□□□□□□□□

□□ annotation □□□□□□

```
kubectl annotate pod sample ovn.kubernetes.io/bgp=true
kubectl annotate subnet ovn-default ovn.kubernetes.io/bgp=true
```

□□ annotation □□□□□□

```
kubectl annotate pod sample ovn.kubernetes.io/bgp-
kubectl annotate subnet ovn-default ovn.kubernetes.io/bgp-
```

□□□□□□□□□□□□□□□□□□□

7.9.3 ClusterIP Service

Service ClusterIP kube-ovn-speaker --announce-cluster-ip true BGP

annotation

```
kubectl annotate service sample ovn.kubernetes.io/bgp=true
```

annotation

```
kubectl annotate service sample ovn.kubernetes.io/bgp-
```

7.9.4 EIPs

EIPs VPC NAT Gateway VpcNatGateway BGP BGP Sidecar

VPC NAT Gateway BGP BGP Speaker Sidecar NetworkAttachmentDefinition NAD VPC Subnet Sidecar Kubernetes API EIPs VPC CoreDNS NAD

NetworkAttachmentDefinition Subnet provider {nadName}.{nadNamespace}.ovn

```
apiVersion: "k8s.cni.cncf.io/v1"
kind: NetworkAttachmentDefinition
metadata:
  name: api-ovn-nad
  namespace: default
spec:
  config: '{
      "cniVersion": "0.3.0",
      "type": "kube-ovn",
      "server_socket": "/run/openvswitch/kube-ovn-daemon.sock",
      "provider": "api-ovn-nad.default.ovn"
    }'
---
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: vpc-apiserver-subnet
spec:
  protocol: IPv4
  cidrBlock: 100.100.100.0/24
  provider: api-ovn-nad.default.ovn
```

ovn-vpc-nat-config ConfigMap apiNadProvider BGP Speaker:

```
apiVersion: v1
kind: ConfigMap
metadata:
  name: ovn-vpc-nat-config
  namespace: kube-system
data:
  apiNadProvider: api-ovn-nad.default.ovn              # What NetworkAttachmentDefinition provider to use so that the sidecar
                                                       # can access the K8S API, as it can't by default due to VPC segmentation
  bgpSpeakerImage: docker.io/kubeovn/kube-ovn:v1.13.0  # Sets the BGP speaker image used
  image: docker.io/kubeovn/vpc-nat-gateway:v1.13.0
```

ovn-default provider

```
provider: api-ovn-nad.default.ovn
```

VPC NAT Gateway BGP

```
kind: VpcNatGateway
apiVersion: kubeovn.io/v1
metadata:
  name: vpc-natgw
spec:
  vpc: vpc1
  subnet: net1
  lanIp: 10.0.1.10
  bgpSpeaker:
    enabled: true
    asn: 65500
    remoteAsn: 65000
    neighbors:
      - 100.127.4.161
      - fd:01::1
    enableGracefulRestart: true # Optional
```


2025 Kube-OVN Team

```
    routerId: 1.1.1.1           # Optional
    holdTime: 1m                # Optional
    password: "password123"     # Optional
    extraArgs:                  # Optional, passed directly to the BGP speaker
      - -v5                     # Enables verbose debugging of the BGP speaker sidecar
  selector:
    - "kubernetes.io/os: linux"
  externalSubnets:
  - ovn-vpc-external-network # Network on which we'll speak BGP and receive/send traffic to the outside world
                             # BGP neighbors need to be on that network
```

████████████████ BGP ████ EIP▯

```
kubectl annotate eip sample ovn.kubernetes.io/bgp=true
```

7.9.5 ████

`kube-ovn-speaker` ████████████:

- **Cluster**: ████████████ speaker ███████ Pod IPs/Subnet CIDRs████████████████ IP ████████████ CIDR ▯ Pod████████████████ speaker ████████████████████ Pod▯▯ ████████████████████ Pod ▯ Subnet ██████████
- **Local**: ████████Pod IPs ███████ Pod ████████████████ Cluster ████████████ Pod ████████████

> ▯▯: ████ `Local` ████████████████ `kube-ovn-speaker` ███ Pod ████████ speaker ████████████████

████████ `Cluster` ██████ Pod/Subnet ▯ annotation `ovn.kubernetes.io/bgp` ███████

- `ovn.kubernetes.io/bgp=cluster` ▯ `ovn.kubernetes.io/bgp=true` ████ `Cluster` ███
- `ovn.kubernetes.io/bgp=local` ████ `Local` ███

> ██████ Service ████████ `kube-proxy` ██████ `ClusterIP` ▯▯ Service ██████████ `Cluster` ███

7.9.6 BGP ████

`kube-ovn-speaker` ████ BGP ████████████████████████████

- `announce-cluster-ip`: ███████ Service ███████ `false` ▯
- `auth-password`: BGP peer ███████
- `holdtime`: BGP ████████████████████████████████████ 90 ▯▯
- `graceful-restart`: ████ BGP Graceful Restart▯
- `graceful-restart-time`: BGP Graceful restart time ███ RFC4724 3▯
- `graceful-restart-deferral-time`: BGP Graceful restart deferral time ███ RFC4724 4.1▯
- `passivemode`: Speaker ███ passive ████████ peer▯
- `ebgp-multihop`: ebgp ttl ████ 1▯
- `allowed-source-addresses`: ▯ IP ████████████████Speaker ██████ `ip route get` ████ BGP Peer ████████████ IP ████████████████████ ECMP ▯▯▯▯▯▯▯▯▯▯ ▯ IP ██████
- `enable-bfd`: ▯▯ `kube-ovn-speaker` ▯▯ BFD████████████████████ `false` ██████“████ `kube-ovn-speaker` ▯▯ BFD”▯
- `bfd-min-tx`: `kube-ovn-speaker` ▯▯ BFD ████████████████ `1000` ▯1 ███
- `bfd-min-rx`: `kube-ovn-speaker` ▯▯ BFD ████████████████ `1000` ▯1 ███
- `bfd-detection-multiplier`: `kube-ovn-speaker` ▯▯ BFD ████████ `3` ███████ = `bfd-min-rx * bfd-detection-multiplier` ▯

7.9.7 BFD ███████

▯ BGP ████████████████ BFD▯Bidirectional Forwarding Detection▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ BGP ECMP ▯▯▯▯▯▯▯▯▯

▯ Kube-OVN ████BFD ▯▯▯▯▯▯▯▯▯▯▯▯▯▯

- ███████ **host network** ███████ Kubernetes Node ▯ host network ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ BFD ▯▯▯▯▯▯ BGP ECMP ▯▯▯▯▯▯▯▯▯▯▯▯

2025 Kube-OVN Team

- ■■■■**VPC** ■■■■■ `OVN logical router BFD` ■■ `VPC` CRD ■■■■■■■■■■ VPC ■■■■■■■■■■ kube-ovn controller ■■■■■■■■ VPC ■■■■■■■■ BFD■

■■■■■

```
flowchart TD
    A[BFD     ] --> B[   :     host network]
    A --> C[   : VPC   ]
    B --> D[   : kube-ovn-speaker    BFD]
    B --> E[   : openbfdd     ]
    C --> F[OVN logical router BFD]
```

■■■■■■■■■■■■ host network ■■■■■■■■■■■■■■■■■■■■■■■■■■

- ■■■■ **`kube-ovn-speaker`** ■■ **BFD**■■■■■ `kube-ovn-speaker` ■■■■■■■■■ GoBGP ■■ BFD ■■■■■■■■■ node host network ■■■■■■■■■■■■■■ BFD■
- ■■■■■■■■■ **`openbfdd`** ■■■■■■■■■■ BFD DaemonSet■■■■■■■■■■ node host network ■■■■■■■■■■■■■■ BFD■

> ■■■■■■■■■■■■■■■ BFD ■■■■■■■■■■■■■■■■■■■

```
    }
  }
}
```

 `session_state` `1` = UP `2` = DOWN `3` = ADMIN_DOWN `4` = INIT

 BFD GoBGP BGP hard reset `BFD is down` BGP

openbfdd

 BFD `kube-ovn-speaker` openbfdd BFD DaemonSet node host network BGP BFD `BFD_MULTI * max(BFD_MIN_TX, BFD_MIN_RX) = 3 * 1000ms = 3`

DaemonSet `hostNetwork: true` Pod

- **init-peer**: `ip route get` IP Volume
- **bfdd**: openbfdd init IP BFD `start-bfdd.sh` `bfdd-prestart.sh` startupProbe
- **reconcile**: 5 BFD peer

 yaml

```
wget https://raw.githubusercontent.com/kubeovn/kube-ovn/release-1.16/yamls/bfdd-daemonset.yaml
```

 `GATEWAY_ADDRESS` `ALLOWED_SOURCE_ADDRESSES` Speaker `--allowed-source-addresses`

```
env:
  - name: GATEWAY_ADDRESS
    value: "10.32.32.1"                          #
  - name: ALLOWED_SOURCE_ADDRESSES
    value: "10.32.32.2,10.32.32.3,10.32.32.4,10.32.32.5"  #   IP
  - name: BFD_MIN_TX
    value: "1000"                                #
  - name: BFD_MIN_RX
    value: "1000"                                #
  - name: BFD_MULTI
    value: "3"                                   #
```

 DaemonSet

```
kubectl apply -f bfdd-daemonset.yaml
```

BFD

```
#    BFD daemon
bfdd-control status

#      BFD    remote=  , local=    IP
bfdd-control status remote <gateway-ip> local <local-ip>

#    BFD
bfdd-control allow <gateway-ip>

#
bfdd-control session new set mintx <ms> ms   #
bfdd-control session new set minrx <ms> ms   #
bfdd-control session new set multi <n>       #

#
bfdd-control log type command no

#    init        IP
cat /bfdd-peer/local-ip

#    reconcile sidecar
kubectl logs -n kube-system ds/openbfdd -c reconcile

#    init
kubectl logs -n kube-system ds/openbfdd -c init-peer
```

OVN BFD

OVN BFD kube-ovn controller

2025 Kube-OVN Team

```
#    OVN BFD
kubectl ko nbctl list bfd

#           BFD
kubectl ko nbctl find bfd logical_port=<lrp-name>

#    OVN BFD
kubectl ko nbctl destroy bfd <uuid>
```

7.9.8 BGP routes debug

```
# show peer neighbor
gobgp neighbor

# show announced routes to one peer
gobgp neighbor 10.32.32.254 adj-out
```

PDF Slack Support

2026-10-28

2022-6-14

GitHub 

7.9.9

7.10 □□ MetalLB □ Kube-OVN Underlay □□

MetalLB □□□□ Kubernetes □□□□□□□□□□□□□□□□□□□□□□ Kubernetes □□□□ Service □□□□□□□□□□□□□□□


□□□□□□□□ MetalLB □ Kube-OVN □ Underlay □□□□□□□□

7.10.1 □□□□

Kube-OVN □□□ 1.14.0 □□□□ MetalLB □ Underlay □□□□□□□□□□□□□□□□□□

- □□□□□□□□□□□ MetalLB □□□ IP □□□□□□□□□□□□
- □□□□□ Pod □ MetalLB VIP □□□□ Underlay □□□
- □□□□□□ IP □□□□□□□□□□ SNAT

7.10.2 □□□□



2025 Kube-OVN Team

□ *1□MetalLB VIP □ Kube-OVN Underlay □□□□□□□□□*

MetalLB □ Kube-OVN Underlay □□□□□□□□□□

1. □□□□□□□□□□□□ VIP□□□ 10.180.204.252□□□ IP □ MetalLB □□ L2 □□□□□□□□□□□□ Node1 □□ metallb □ VIP
2. □□□□□□□□□□□□ VIP □□□□□□□□□□ `underlay0.341` □□□□
3. □□□□□□□□ `br-provider` □□□□□ Underlay □□□□□□
4. `br-provider` □□ OpenFlow □□□□□□□□□□ OVN □□□□□
5. □□□□ `underlay subnet` □□□□□□□ OVN □□□□□□ `ovn lb dnat` □□□
6. OVN □□□□□□□□□□□□□□□□ Pod□

□□□□□□□ 10.180.204.0/24□□□ VIP □□□ Pod □ IP □□□□□□□□□□

7.10.3 □□□□

- Kube-OVN □□□□□ `--enable-ovn-lb-prefer-local=true` □□
- Underlay □□□□ `enableExternalLBAddress=true`
- □ Underlay □□□ `excludeIps` □□□ MetalLB □□□□□□ IP □□

7.10.4 □□□□

1. □□ Kube-OVN

□□□□□□□□ Kube-OVN□□□ Kube-OVN □□□□□ `--enable-ovn-lb-prefer-local=true` □ `--ls-ct-skip-dst-lport-ips=false` □□□

```
#   kube-ovn-controller   Deployment
kubectl edit deployment -n kube-system kube-ovn-controller
```

□□□□□□□□□□□

```
--enable-ovn-lb-prefer-local=true
--ls-ct-skip-dst-lport-ips=false
```

2. □□ Underlay □□

□□□□□ Underlay □□□□□□□ LoadBalancer □□□□□□□ excludeIps □□□ MetalLB □□□□ IP □□□

```
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: underlay-subnet
spec:
  protocol: IPv4
  provider: ovn
  cidrBlock: 10.180.204.0/24  #
  gateway: 10.180.204.1
  excludeIps:
  - 10.180.204.250
  - 10.180.204.251
  - 10.180.204.252  # MetalLB            VIP 10.180.204.252
  natOutgoing: false
  enableExternalLBAddress: true   #     subnet   cidr    ip      metallb vip
```

3. □□ MetalLB

□□ MetalLB □□□□ □□ MetalLB□

```
kubectl apply -f https://raw.githubusercontent.com/metallb/metallb/v0.13.7/config/manifests/metallb-native.yaml
```

□□ MetalLB □□□□□ L2 □□□□□

```
apiVersion: metallb.io/v1beta1
kind: IPAddressPool
metadata:
```


2025 Kube-OVN Team

```
  name: underlay-pool
  namespace: metallb-system
spec:
  addresses:
  - 10.180.204.250-10.180.204.254  #       VIP 10.180.204.252
---
apiVersion: metallb.io/v1beta1
kind: L2Advertisement
metadata:
  name: l2-advert
  namespace: metallb-system
spec:
  ipAddressPools:
  - underlay-pool
```

4. □□ LoadBalancer □□□ Service

□□□□ LoadBalancer □□□ Service□□□□□□ Underlay □□□□ Pod□

```
apiVersion: apps/v1
kind: Deployment
metadata:
  labels:
    app: nginx
  name: deploy-169402624
spec:
  replicas: 3
  selector:
    matchLabels:
      app: nginx
  template:
    metadata:
      annotations:
        ovn.kubernetes.io/logical_switch: underlay-subnet
      labels:
        app: nginx
    spec:
      containers:
      - args:
        - netexec
        - --http-port
        - "80"
        image: kubeovn/agnhost:2.47
        imagePullPolicy: IfNotPresent
        name: nginx
---
apiVersion: v1
kind: Service
metadata:
  name: nginx-lb
spec:
  externalTrafficPolicy: Local
  ipFamilies:
  - IPv4
  ipFamilyPolicy: PreferDualStack
  ports:
  - port: 80
    protocol: TCP
    targetPort: 80
  selector:
    app: nginx
  type: LoadBalancer
```

7.10.5 □□□□□

1. □□ Service □□□□ MetalLB □□□ IP □□□

```
kubectl get svc nginx-lb
```

□□□□ EXTERNAL-IP □□□□□□ IP □□□□ 10.180.204.252□□

1. □□□□□ Service □ IP □□□

```
curl http://10.180.204.252
```

1. □□□□□□□□□□□□□□□ Pod□

□□□□□□ Service □ endpoints □ Pod □□□□□□□□□□□□□□□□□□□□

```
#    Service   endpoints
kubectl get endpoints nginx-lb
```


2025 Kube-OVN Team

```
#    Pod
kubectl get pods -l app=nginx -o wide
```

1. ■■■■■ IP ■■■■■

■ nginx Pod ■■■■■■■■■■■■■■■■■■■■ IP ■■■■■■■■■■ IP■■■■■■■ SNAT ■■ IP■

```
kubectl exec -it $(kubectl get pods -l app=nginx -o name | head -n1) -- cat /var/log/nginx/access.log
```

7.10.6 ■■■■

IP ■■■■■

MetalLB ■■■■■■■■■■ Underlay ■■ CIDR ■■■■■■■■■■ Underlay ■■ `excludeIps` ■■■■■■■■■■■■ IP ■■■■■

■■■■■■■

MetalLB ■■■■■ Kube-OVN Underlay ■■■■■■■■■■■■■■■■ `underlay0.341` ■■■■■■■■■■ VLAN ■■■■■■■■■■■■■■■■■■ VLAN ■■■ ARP ■■■■■■■■■■ MetalLB VIP■

■■■■■■■

■■■■■■■■■■■■■■■■■■■■■■ - Kube-OVN ■■■■ `--enable-ovn-lb-prefer-local=true` ■■ - Service ■■■■■ `externalTrafficPolicy: Local`

PDF Slack Support

2025■9■10■

2025■4■2■

GitHub


7.10.7 ■■

7.11 Cilium ⬚⬚

Cilium ⬚⬚⬚⬚ eBPF ⬚⬚⬚⬚⬚⬚⬚⬚Kube-OVN ⬚⬚⬚⬚ CNI Chaining ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ ⬚⬚⬚⬚⬚⬚⬚ Kube-OVN ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ eBPF ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

⬚⬚⬚⬚ Cilium⬚Kube-OVN ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

- ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚
- ⬚⬚ Hubble ⬚⬚⬚⬚⬚⬚



7.11.1 ⬚⬚⬚⬚

1. Linux ⬚⬚⬚⬚⬚⬚ 4.19 ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ eBPF ⬚⬚⬚⬚⬚
2. ⬚⬚⬚⬚ Helm ⬚⬚⬚ Cilium ⬚⬚⬚⬚⬚⬚ Helm ⬚⬚⬚ Installing Helm⬚

7.11.2 ⬚⬚ Kube-OVN

⬚⬚⬚⬚⬚⬚ Cilium ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ Kube-OVN ⬚⬚ `networkpolicy` ⬚⬚⬚⬚⬚⬚ CNI ⬚⬚⬚⬚⬚⬚

⬚ `install.sh` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

```
ENABLE_NP=false
CNI_CONFIG_PRIORITY=10
```

⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ `kube-ovn-controller` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ `networkpolicy` ⬚

```
args:
- --enable-np=false
```

⬚⬚ `kube-ovn-cni` ⬚⬚⬚⬚⬚⬚ CNI ⬚⬚⬚⬚⬚⬚

```
args:
- --cni-conf-name=10-kube-ovn.conflist
```


2025 Kube-OVN Team

⬚⬚⬚⬚⬚⬚⬚ Kube-OVN ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ Cilium ⬚⬚⬚⬚⬚

```
mv /etc/cni/net.d/01-kube-ovn.conflist /etc/cni/net.d/10-kube-ovn.conflist
```

7.11.3 ⬚⬚ Cilium

⬚⬚ `chaining.yaml` ⬚⬚⬚⬚⬚⬚⬚ Cilium ⬚ generic-veth ⬚⬚⬚

```
apiVersion: v1
kind: ConfigMap
metadata:
  name: cni-configuration
  namespace: kube-system
data:
  cni-config: |-
    {
      "name": "generic-veth",
      "cniVersion": "0.3.1",
      "plugins": [
        {
          "type": "kube-ovn",
          "server_socket": "/run/openvswitch/kube-ovn-daemon.sock",
          "ipam": {
              "type": "kube-ovn",
              "server_socket": "/run/openvswitch/kube-ovn-daemon.sock"
          }
        },
        {
          "type": "portmap",
          "snat": true,
          "capabilities": {"portMappings": true}
        },
        {
          "type": "cilium-cni"
        }
      ]
    }
```

⬚⬚⬚⬚⬚⬚⬚

```
kubectl apply -f chaining.yaml
```

⬚⬚ Helm ⬚⬚ Cilium⬚

```
helm repo add cilium https://helm.cilium.io/
helm install cilium cilium/cilium --version 1.11.6 \
    --namespace kube-system \
    --set cni.chainingMode=generic-veth \
    --set cni.customConf=true \
    --set cni.configMap=cni-configuration \
    --set tunnel=disabled \
    --set enableIPv4Masquerade=false \
    --set devices="eth+ ovn0 genev_sys_6081 vxlan_sys_4789" \
    --set enableIdentityMark=false
```

⬚⬚ Cilium ⬚⬚⬚⬚⬚

```
# cilium  status
    /¯¯\
 /¯¯\__/¯¯\    Cilium:         OK
 \__/¯¯\__/    Operator:       OK
 /¯¯\__/¯¯\    Hubble:         disabled
 \__/¯¯\__/    ClusterMesh:    disabled
    \__/

DaemonSet         cilium             Desired: 2, Ready: 2/2, Available: 2/2
Deployment        cilium-operator    Desired: 2, Ready: 2/2, Available: 2/2
Containers:       cilium             Running: 2
                  cilium-operator    Running: 2
Cluster Pods:     8/11 managed by Cilium
Image versions    cilium             quay.io/cilium/cilium:v1.11.6: 2
                  cilium-operator    quay.io/cilium/operator-generic:v1.11.6: 2
```

7.11.4 ⬚ Cilium ⬚⬚⬚⬚ Kube-OVN NAT ⬚⬚

Cilium ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ NAT ⬚⬚ Pod ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ ⬚⬚ NAT ⬚⬚⬚⬚⬚ VPC ⬚ Pod ⬚⬚⬚⬚⬚ SNAT/DNAT ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ IP ⬚⬚ Pod ⬚⬚⬚ IP⬚

Cilium ⬚⬚ **SIP**⬚Source IP⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚——⬚⬚⬚⬚⬚⬚ Pod IP ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ Hubble ⬚⬚⬚ **DROPPED**⬚⬚

2025 Kube-OVN Team

▯▯▯▯▯▯▯▯▯▯▯▯ IP ▯▯▯▯▯▯▯▯ NAT ▯▯▯▯▯▯▯▯

▯▯▯▯▯▯/Pod ▯▯▯▯▯▯▯▯▯**Cilium ≥ 1.20**▯

Cilium 1.20 ▯▯cilium/cilium#43505▯▯ ▯▯▯▯▯▯▯ **annotation** ▯ Pod ▯▯▯▯ SIP ▯▯▯▯

1. ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ annotation▯

```
kubectl annotate namespace <nat-gateway-namespace> \
  config.cilium.io/delegate-source-ip-verification=true
```

2. NAT ▯▯ Pod ▯▯▯▯ SIP ▯▯▯ annotation▯

```
apiVersion: v1
kind: Pod
metadata:
  annotations:
    config.cilium.io/disable-source-ip-verification: "true"
```

▯▯▯▯▯▯▯▯▯ NAT ▯▯ Pod ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

▯▯▯▯▯▯**Cilium < 1.20**▯

▯▯▯▯▯▯ Cilium▯▯▯ Helm Chart ▯▯▯▯▯▯ `enableSourceIPVerification` ▯ `false` ▯▯▯▯▯ SIP ▯▯▯▯

```
enableSourceIPVerification: false
```

PDF Slack Support

2026▯4▯28▯

2022▯5▯24▯



GitHub 



7.11.5 ▯▯

7.12 Cilium NetworkPolicy ⬚⬚

Kube-OVN ⬚⬚⬚⬚⬚⬚ Cilium ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ Cilium ⬚⬚⬚

⬚⬚⬚ Cilium ⬚⬚⬚⬚⬚⬚⬚ Cilium ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ Cilium L3 ⬚ L4 ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

7.12.1 ⬚⬚⬚⬚

⬚⬚⬚⬚ **Pod**

⬚⬚ namespace `test` ⬚⬚⬚⬚⬚ yaml⬚⬚ test namespace ⬚⬚⬚⬚⬚ label `app=test` ⬚ Pod⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ Pod⬚

```yaml
apiVersion: apps/v1
kind: Deployment
metadata:
  labels:
    app: test
  name: test
  namespace: test
spec:
  replicas: 1
  selector:
    matchLabels:
      app: test
  strategy:
    rollingUpdate:
      maxSurge: 25%
      maxUnavailable: 25%
    type: RollingUpdate
  template:
    metadata:
      labels:
        app: test
    spec:
      containers:
      - image: docker.io/library/nginx:alpine
        imagePullPolicy: IfNotPresent
        name: nginx
```

⬚⬚⬚⬚⬚⬚ yaml⬚⬚ default namespace ⬚⬚⬚⬚⬚ label `app=dynamic` ⬚ Pod ⬚⬚⬚⬚⬚⬚⬚⬚ Pod⬚

```yaml
apiVersion: apps/v1
kind: Deployment
metadata:
  labels:
    app: dynamic
  name: dynamic
  namespace: default
spec:
  replicas: 2
  selector:
    matchLabels:
      app: dynamic
  strategy:
    rollingUpdate:
      maxSurge: 25%
      maxUnavailable: 25%
    type: RollingUpdate
  template:
    metadata:
      creationTimestamp: null
      labels:
        app: dynamic
    spec:
      containers:
      - image: docker.io/library/nginx:alpine
        imagePullPolicy: IfNotPresent
        name: nginx
```

⬚⬚⬚⬚ Pod ⬚⬚ Label ⬚⬚:

```
# kubectl get pod -o wide --show-labels
NAME                       READY   STATUS    RESTARTS   AGE   IP           NODE                   NOMINATED NODE   READINESS GATES   LABELS
dynamic-7d8d7874f5-9v5c4   1/1     Running   0          28h   10.16.0.35   kube-ovn-worker        <none>           <none>            app=dynamic,pod-
template-hash=7d8d7874f5
dynamic-7d8d7874f5-s8z2n   1/1     Running   0          28h   10.16.0.36   kube-ovn-control-plane   <none>           <none>            app=dynamic,pod-
template-hash=7d8d7874f5
# kubectl get pod -o wide -n test --show-labels
NAME                       READY   STATUS    RESTARTS   AGE     IP           NODE                   NOMINATED NODE   READINESS GATES   LABELS
dynamic-7d8d7874f5-6dsg6   1/1     Running   0          7h20m   10.16.0.2    kube-ovn-control-plane   <none>           <none>            app=dynamic,pod-
template-hash=7d8d7874f5
```


2025 Kube-OVN Team

```
dynamic-7d8d7874f5-tjgtp       1/1     Running   0          7h46m   10.16.0.42   kube-ovn-worker          <none>           <none>           app=dynamic,pod-
template-hash=7d8d7874f5
label-test1-77b6764857-swq4k   1/1     Running   0          3h43m   10.16.0.12   kube-ovn-worker          <none>           <none>           app=test1,pod-
template-hash=77b6764857

#          Pod
test-54c98bc466-mft5s          1/1     Running   0          8h      10.16.0.41   kube-ovn-worker          <none>           <none>           app=test,pod-
template-hash=54c98bc466
```

L3 ...

... yaml... `CiliumNetworkPolicy` ...:

```yaml
apiVersion: "cilium.io/v2"
kind: CiliumNetworkPolicy
metadata:
  name: "l3-rule"
  namespace: test
spec:
  endpointSelector:
    matchLabels:
      app: test
  ingress:
  - fromEndpoints:
    - matchLabels:
        app: dynamic
```

... default namespace ... Pod ... Pod ... test namespace ... Pod ...

default namespace ...:

```
# kubectl exec -it dynamic-7d8d7874f5-9v5c4 -- bash
bash-5.0# ping -c 3 10.16.0.41
PING 10.16.0.41 (10.16.0.41): 56 data bytes

--- 10.16.0.41 ping statistics ---
3 packets transmitted, 0 packets received, 100% packet loss
```

test namespace ... Pod ...:

```
# kubectl exec -it -n test dynamic-7d8d7874f5-6dsg6 -- bash
bash-5.0# ping -c 3 10.16.0.41
PING 10.16.0.41 (10.16.0.41): 56 data bytes
64 bytes from 10.16.0.41: seq=0 ttl=64 time=2.558 ms
64 bytes from 10.16.0.41: seq=1 ttl=64 time=0.223 ms
64 bytes from 10.16.0.41: seq=2 ttl=64 time=0.304 ms

--- 10.16.0.41 ping statistics ---
3 packets transmitted, 3 packets received, 0% packet loss
round-trip min/avg/max = 0.223/1.028/2.558 ms
```

... Cilium ... `CiliumNetworkPolicy` ... `Namespace` ... Cilium ...

... **Namespace** ... Pod ... **Namespace** ... Pod ...

... Namespace ... Namespace ...

... `CiliumNetworkPolicy` ... namespace ...:

```yaml
  ingress:
  - fromEndpoints:
    - matchLabels:
        app: dynamic
        k8s:io.kubernetes.pod.namespace: default    #      Namespace    Pod
```

... `CiliumNetworkPolicy` ...:

```
# kubectl get cnp -n test  -o yaml l3-rule
apiVersion: cilium.io/v2
kind: CiliumNetworkPolicy
metadata:
  name: l3-rule
  namespace: test
spec:
  endpointSelector:
    matchLabels:
      app: test
  ingress:
  - fromEndpoints:
    - matchLabels:
```

```
        app: dynamic
    - matchLabels:
        app: dynamic
        k8s:io.kubernetes.pod.namespace: default
```

... default namespace ... Pod ... Pod ...:

```
# kubectl exec -it dynamic-7d8d7874f5-9v5c4 -n test -- bash
bash-5.0# ping -c 3 10.16.0.41
PING 10.16.0.41 (10.16.0.41): 56 data bytes
64 bytes from 10.16.0.41: seq=0 ttl=64 time=2.383 ms
64 bytes from 10.16.0.41: seq=1 ttl=64 time=0.115 ms
64 bytes from 10.16.0.41: seq=2 ttl=64 time=0.142 ms

--- 10.16.0.41 ping statistics ---
3 packets transmitted, 3 packets received, 0% packet loss
round-trip min/avg/max = 0.115/0.880/2.383 ms
```

... Kubernetes ... networkpolicy... Cilium ... Namespace ... Namespace ...

... Kube-OVN ...Kube-OVN ... k8s ... Namespace ... **Pod**... Pod... Namespace ... Namespace ... Pod... Pod ...

L4 ...

... yaml... L4 ...:

```
apiVersion: "cilium.io/v2"
kind: CiliumNetworkPolicy
metadata:
  name: "l4-rule"
  namespace: test
spec:
  endpointSelector:
    matchLabels:
      app: test
  ingress:
  - fromEndpoints:
    - matchLabels:
        app: dynamic
    toPorts:
    - ports:
      - port: "80"
        protocol: TCP
```

... Namespace ... Pod ...

```
# kubectl exec -it -n test dynamic-7d8d7874f5-6dsg6 -- bash
bash-5.0# ping -c 3 10.16.0.41
PING 10.16.0.41 (10.16.0.41): 56 data bytes

--- 10.16.0.41 ping statistics ---
3 packets transmitted, 0 packets received, 100% packet loss
bash-5.0#
bash-5.0# curl 10.16.0.41:80
<html>
<head>
        <title>Hello World!</title>
        <link href='//fonts.googleapis.com/css?family=Open+Sans:400,700' rel='stylesheet' type='text/css'>
        <style>
        body {
                background-color: white;
                text-align: center;
                padding: 50px;
                font-family: "Open Sans","Helvetica Neue",Helvetica,Arial,sans-serif;
        }
        #logo {
                margin-bottom: 40px;
        }
        </style>
</head>
<body>
                <h1>Hello World!</h1>
                                <h3>Links found</h3>
        <h3>I am on  test-54c98bc466-mft5s</h3>
        <h3>Cookie                  =</h3>
                                    <b>KUBERNETES</b> listening in 443 available at tcp://10.96.0.1:443<br />
                                            <h3>my name is hanhouchao!</h3>
                        <h3> RequestURI='/'</h3>
</body>
</html>
```

▯▯ Namespace ▯▯▯▯▯▯▯▯▯▯▯▯ Pod ▯▯▯▯

```
# kubectl exec -it -n test label-test1-77b6764857-swq4k -- bash
bash-5.0# ping -c 3 10.16.0.41
PING 10.16.0.41 (10.16.0.41): 56 data bytes

--- 10.16.0.41 ping statistics ---
3 packets transmitted, 0 packets received, 100% packet loss
bash-5.0#
bash-5.0# curl -v 10.16.0.41:80 --connect-timeout 10
*   Trying 10.16.0.41:80...
* After 10000ms connect time, move on!
* connect to 10.16.0.41 port 80 failed: Operation timed out
* Connection timeout after 10001 ms
* Closing connection 0
curl: (28) Connection timeout after 10001 ms
```

▯▯▯▯▯▯▯▯▯ Namespace ▯▯▯▯▯▯▯▯▯▯▯▯▯ L3 ▯▯▯▯▯▯▯▯▯▯▯▯

▯ L4 ▯▯▯▯▯▯▯▯▯ping ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ TCP ▯▯▯▯▯▯▯▯▯▯▯▯▯

▯▯ ICMP ▯▯▯▯▯▯▯▯▯▯▯▯▯ L4 ▯▯▯▯▯

L7 ▯▯▯▯▯▯▯

chaining ▯▯▯▯L7 ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Cilium ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Generic Veth Chaining▯

▯▯▯▯▯▯ issue 12454 ▯▯▯▯▯▯▯▯▯▯▯▯

PDF Slack Support

2026▯7▯4▯

2022▯8▯2▯

GitHub



7.13 Cilium ■■■■■■

Kube-OVN ■■■■■■■ Cilium ■■■■■■■■■■■■ Cilium ■■■

Cilium ■■■■■■■■■■■■■■■■■■■■■■■■■■■■ Hubble ■■■■Hubble ■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■

7.13.1 ■■ Hubble

■■■ Cilium ■■■■■■■■■■■■ Hubble ■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■ Hubble■

■■■■■■■■■■ helm ■■ Hubble■

```
helm upgrade cilium cilium/cilium --version 1.11.6 \
   --namespace kube-system \
   --reuse-values \
   --set hubble.relay.enabled=true \
   --set hubble.ui.enabled=true
```

■■■■ Hubble ■■■■■■ `cilium status` ■■■■■■■■■■ Hubble ■■■■■■

```
# cilium status
    /¯¯\
 /¯¯\__/¯¯\    Cilium:         OK
 \__/¯¯\__/    Operator:       OK
 /¯¯\__/¯¯\    Hubble:         OK
 \__/¯¯\__/    ClusterMesh:    disabled
    \__/

Deployment        hubble-relay       Desired: 1, Ready: 1/1, Available: 1/1
Deployment        cilium-operator    Desired: 2, Ready: 2/2, Available: 2/2
DaemonSet         cilium             Desired: 2, Ready: 2/2, Available: 2/2
Deployment        hubble-ui          Desired: 1, Ready: 1/1, Available: 1/1
Containers:       cilium             Running: 2
                  hubble-ui          Running: 1
                  hubble-relay       Running: 1
                  cilium-operator    Running: 2
Cluster Pods:     16/17 managed by Cilium
Image versions    hubble-relay       quay.io/cilium/hubble-relay:v1.11.6@sha256:fd9034a2d04d5b973f1e8ed44f230ea195b89c37955ff32e34e5aa68f3ed675a: 1
                  cilium-operator    quay.io/cilium/operator-generic:v1.11.6@sha256:9f6063c7bcaede801a39315ec7c166309f6a6783e98665f6693939cf1701bc17: 2
                  cilium             quay.io/cilium/cilium:v1.11.6@sha256:f7f93c26739b6641a3fa3d76b1e1605b15989f25d06625260099e01c8243f54c: 2
                  hubble-ui          quay.io/cilium/hubble-ui:v0.9.0@sha256:0ef04e9a29212925da6bdfd0ba5b581765e41a01f1cc30563cef9b30b457fea0: 1
                  hubble-ui          quay.io/cilium/hubble-ui-backend:v0.9.0@sha256:000df6b76719f607a9edefb9af94dfd1811a6f1b6a8a9c537cba90bf12df474b: 1
apple@bogon cilium %
```

■■ Hubble ■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■ ■■■■■■■■■■ Hubble CLI :

```
curl -L --fail --remote-name-all https://github.com/cilium/hubble/releases/download/v0.10.0/hubble-linux-amd64.tar.gz
sudo tar xzvfC hubble-linux-amd64.tar.gz /usr/local/bin
```

7.13.2 ■■■■■■■

Cilium ■■■■■■■■■■■■■■■■■■■

```
replicaset.apps/client-7df6cfbf7b           1         1         1       21s
replicaset.apps/client2-547996d7d8          1         1         1       21s
replicaset.apps/echo-other-node-d79544ccf   1         1         1       21s
replicaset.apps/echo-same-node-5d466d5444   1         1         1       21s
```

7.13.3 □□□□□□□□□□□□

□□□□□□□□□□□□□□□□□□□□□□ Cilium □□□□□□□□□□ □□□ `kube-system namespace` □□ Cilium □□ pod □□□ `hubble observe` □□□□□□□□□□□□□□□□□

```
# kubectl get pod -n kube-system -o wide
NAME                                      READY   STATUS    RESTARTS   AGE     IP           NODE                   NOMINATED NODE   READINESS GATES
cilium-d6h56                              1/1     Running   0          2d20h   172.18.0.2   kube-ovn-worker        <none>           <none>
cilium-operator-5887f78bbb-c7sb2          1/1     Running   0          2d20h   172.18.0.2   kube-ovn-worker        <none>           <none>
cilium-operator-5887f78bbb-wj8gt          1/1     Running   0          2d20h   172.18.0.3   kube-ovn-control-plane <none>           <none>
cilium-tq5xb                              1/1     Running   0          2d20h   172.18.0.3   kube-ovn-control-plane <none>           <none>
kube-ovn-pinger-7lgk8                     1/1     Running   0          21h     10.16.0.19   kube-ovn-control-plane <none>           <none>
kube-ovn-pinger-msvcn                     1/1     Running   0          21h     10.16.0.18   kube-ovn-worker        <none>           <none>

# kubectl exec -it -n kube-system cilium-d6h56 -- bash
root@kube-ovn-worker:/home/cilium# hubble observe --from-namespace kube-system
Jul 29 03:24:25.551: kube-system/kube-ovn-pinger-msvcn:35576 -> 172.18.0.3:6642 to-stack FORWARDED (TCP Flags: ACK, PSH)
Jul 29 03:24:25.561: kube-system/kube-ovn-pinger-msvcn:35576 -> 172.18.0.3:6642 to-stack FORWARDED (TCP Flags: RST)
Jul 29 03:24:25.561: kube-system/kube-ovn-pinger-msvcn:35576 -> 172.18.0.3:6642 to-stack FORWARDED (TCP Flags: ACK, RST)
Jul 29 03:24:25.572: kube-system/kube-ovn-pinger-msvcn:35578 -> 172.18.0.3:6642 to-stack FORWARDED (TCP Flags: SYN)
Jul 29 03:24:25.572: kube-system/kube-ovn-pinger-msvcn:35578 -> 172.18.0.3:6642 to-stack FORWARDED (TCP Flags: ACK)
Jul 29 03:24:25.651: kube-system/kube-ovn-pinger-msvcn:35578 -> 172.18.0.3:6642 to-stack FORWARDED (TCP Flags: ACK, PSH)
Jul 29 03:24:25.661: kube-system/kube-ovn-pinger-msvcn:35578 -> 172.18.0.3:6642 to-stack FORWARDED (TCP Flags: RST)
Jul 29 03:24:25.661: kube-system/kube-ovn-pinger-msvcn:35578 -> 172.18.0.3:6642 to-stack FORWARDED (TCP Flags: ACK, RST)
Jul 29 03:24:25.761: kube-system/kube-ovn-pinger-msvcn:52004 -> 172.18.0.3:6443 to-stack FORWARDED (TCP Flags: ACK, PSH)
Jul 29 03:24:25.779: kube-system/kube-ovn-pinger-msvcn -> kube-system/kube-ovn-pinger-7lgk8 to-stack FORWARDED (ICMPv4 EchoRequest)
Jul 29 03:24:25.779: kube-system/kube-ovn-pinger-msvcn <- kube-system/kube-ovn-pinger-7lgk8 to-endpoint FORWARDED (ICMPv4 EchoReply)
Jul 29 03:24:25.866: kube-system/hubble-ui-7596f7ff6f-7j6f2:55836 <- kube-system/hubble-relay-959988db5-zc5vv:4245 to-stack FORWARDED (TCP Flags: ACK)
Jul 29 03:24:25.866: kube-system/hubble-ui-7596f7ff6f-7j6f2:55836 <- kube-system/hubble-relay-959988db5-zc5vv:80 to-endpoint FORWARDED (TCP Flags: ACK)
Jul 29 03:24:25.866: kube-system/hubble-ui-7596f7ff6f-7j6f2:55836 -> kube-system/hubble-relay-959988db5-zc5vv:4245 to-stack FORWARDED (TCP Flags: ACK)
Jul 29 03:24:25.866: kube-system/hubble-ui-7596f7ff6f-7j6f2:55836 -> kube-system/hubble-relay-959988db5-zc5vv:4245 to-endpoint FORWARDED (TCP Flags: ACK)
Jul 29 03:24:25.975: kube-system/kube-ovn-pinger-7lgk8 -> kube-system/kube-ovn-pinger-msvcn to-endpoint FORWARDED (ICMPv4 EchoRequest)
Jul 29 03:24:25.975: kube-system/kube-ovn-pinger-7lgk8 <- kube-system/kube-ovn-pinger-msvcn to-stack FORWARDED (ICMPv4 EchoReply)
Jul 29 03:24:25.979: kube-system/kube-ovn-pinger-msvcn -> 172.18.0.3 to-stack FORWARDED (ICMPv4 EchoRequest)
Jul 29 03:24:26.037: kube-system/coredns-6d4b75cb6d-lbgjg:36430 -> 172.18.0.3:6443 to-stack FORWARDED (TCP Flags: ACK)
Jul 29 03:24:26.282: kube-system/kube-ovn-pinger-msvcn -> 172.18.0.2 to-stack FORWARDED (ICMPv4 EchoRequest)
```

□□ Hubble Relay □□Hubble □□□□□□□□□□□□□□□□□□□□□□

□□□□□□

□□□□□□□ Hubble API□□□□□□□□□□□□□□□□□□□□ Hubble Service□□□□□ `kubectl port-forward deployment/hubble-relay -n kube-system 4245:4245` □□□□□□□□ □□□□□□□□

□□□□□□□□□□ □□□□□

`kubectl port-forward` □□□□□□□□□□□□□□□□□□□□□□□□□□

□□□□□□□□□□□□□□□□ `hubble status` □□

```
# hubble status
Healthcheck (via localhost:4245): Ok
Current/Max Flows: 8,190/8,190 (100.00%)
Flows/s: 22.86
Connected Nodes: 2/2
```


■■■■■■

■■■■■■■ `hubble observe` ■■■■■■■■■■■■■■■ ■■■■■ cilium-test ■■■■■■■■■■■■■■■

```
apple@bogon ovn-test % hubble observe
Jul 28 08:00:07.033: cilium-test/client-7df6cfbf7b-qn7q6:56906 (ID:15432) -> kube-system/coredns-6d4b75cb6d-b444j:53 (ID:11307) to-endpoint FORWARDED (UDP)
Jul 28 08:00:07.033: cilium-test/client-7df6cfbf7b-qn7q6:56906 (ID:15432) <- kube-system/coredns-6d4b75cb6d-b444j:53 (ID:11307) to-stack FORWARDED (UDP)
Jul 28 08:00:07.095: 100.64.0.3:43037 (world) -> cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-endpoint FORWARDED (TCP Flags: SYN)
Jul 28 08:00:07.095: 100.64.0.3:43037 (world) <- cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-stack FORWARDED (TCP Flags: SYN, ACK)
Jul 28 08:00:07.096: 100.64.0.3:43037 (world) -> cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-endpoint FORWARDED (TCP Flags: ACK)
Jul 28 08:00:07.096: 100.64.0.3:43037 (world) -> cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-endpoint FORWARDED (TCP Flags: ACK, FIN)
Jul 28 08:00:07.096: 100.64.0.3:43037 (world) <- cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-stack FORWARDED (TCP Flags: ACK, FIN)
Jul 28 08:00:07.097: 100.64.0.3:43037 (world) -> cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-endpoint FORWARDED (TCP Flags: ACK)
Jul 28 08:00:07.249: 100.64.0.2:33419 (host) -> cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-endpoint FORWARDED (TCP Flags: SYN)
Jul 28 08:00:07.249: 100.64.0.2:33419 (host) <- cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-stack FORWARDED (TCP Flags: SYN, ACK)
Jul 28 08:00:07.250: 100.64.0.2:33419 (host) -> cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-endpoint FORWARDED (TCP Flags: ACK)
Jul 28 08:00:07.251: 100.64.0.2:33419 (host) -> cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-endpoint FORWARDED (TCP Flags: ACK, FIN)
Jul 28 08:00:07.251: 100.64.0.2:33419 (host) <- cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-stack FORWARDED (TCP Flags: ACK, FIN)
Jul 28 08:00:07.251: 100.64.0.2:33419 (host) -> cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-endpoint FORWARDED (TCP Flags: ACK)
Jul 28 08:00:07.323: cilium-test/client2-547996d7d8-jgblc:34927 (ID:14804) <- 172.18.0.3:31514 (kube-apiserver) to-endpoint FORWARDED (TCP Flags: SYN, ACK)
Jul 28 08:00:07.323: cilium-test/client2-547996d7d8-jgblc:34927 (ID:14804) -> 172.18.0.3:31514 (kube-apiserver) to-stack FORWARDED (TCP Flags: ACK)
Jul 28 08:00:07.324: 100.64.0.2:34927 (world) -> cilium-test/echo-same-node-5d466d5444-4vllm:8080 (ID:15976) to-endpoint FORWARDED (TCP Flags: ACK)
Jul 28 08:00:07.324: cilium-test/client2-547996d7d8-jgblc:34927 (ID:14804) -> 172.18.0.3:31514 (kube-apiserver) to-stack FORWARDED (TCP Flags: ACK, FIN)
Jul 28 08:00:07.324: 100.64.0.2:34927 (world) -> cilium-test/echo-same-node-5d466d5444-4vllm:8080 (ID:15976) to-endpoint FORWARDED (TCP Flags: ACK, FIN)
Jul 28 08:00:07.324: 100.64.0.2:34927 (world) <- cilium-test/echo-same-node-5d466d5444-4vllm:8080 (ID:15976) to-stack FORWARDED (TCP Flags: ACK, FIN)
Jul 28 08:00:07.324: cilium-test/client2-547996d7d8-jgblc:34927 (ID:14804) <- 172.18.0.3:31514 (kube-apiserver) to-endpoint FORWARDED (TCP Flags: ACK, FIN)
Jul 28 08:00:07.324: cilium-test/client2-547996d7d8-jgblc:34927 (ID:14804) -> 172.18.0.3:31514 (kube-apiserver) to-stack FORWARDED (TCP Flags: ACK)
Jul 28 08:00:07.324: 100.64.0.2:34927 (world) -> cilium-test/echo-same-node-5d466d5444-4vllm:8080 (ID:15976) to-endpoint FORWARDED (TCP Flags: ACK)
Jul 28 08:00:07.340: kube-system/hubble-relay-959988db5-zc5vv:46938 (ID:53347) -> 172.18.0.2:4244 (host) to-stack FORWARDED (TCP Flags: ACK, PSH)
Jul 28 08:00:07.340: kube-system/hubble-relay-959988db5-zc5vv:44656 (ID:53347) -> 172.18.0.3:4244 (kube-apiserver) to-stack FORWARDED (TCP Flags: ACK, PSH)
Jul 28 08:00:07.340: kube-system/hubble-relay-959988db5-zc5vv:46938 (ID:53347) <- 172.18.0.2:4244 (host) to-endpoint FORWARDED (TCP Flags: ACK, PSH)
Jul 28 08:00:07.341: kube-system/hubble-relay-959988db5-zc5vv:44656 (ID:53347) <- 172.18.0.3:4244 (kube-apiserver) to-endpoint FORWARDED (TCP Flags: ACK, PSH)
Jul 28 08:00:07.409: cilium-test/client-7df6cfbf7b-qn7q6:57326 (ID:15432) -> cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-stack FORWARDED (TCP Flags: SYN)
Jul 28 08:00:07.409: cilium-test/client-7df6cfbf7b-qn7q6:57326 (ID:15432) -> cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-endpoint FORWARDED (TCP Flags: SYN)
Jul 28 08:00:07.409: cilium-test/client-7df6cfbf7b-qn7q6:57326 (ID:15432) <- cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-stack FORWARDED (TCP Flags: SYN, ACK)
Jul 28 08:00:07.410: cilium-test/client-7df6cfbf7b-qn7q6:57326 (ID:15432) <- cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-endpoint FORWARDED (TCP Flags: SYN, ACK)
Jul 28 08:00:07.410: cilium-test/client-7df6cfbf7b-qn7q6:57326 (ID:15432) -> cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-stack FORWARDED (TCP Flags: ACK, PSH)
Jul 28 08:00:07.410: cilium-test/client-7df6cfbf7b-qn7q6:57326 (ID:15432) -> cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-stack FORWARDED (TCP Flags: ACK)
Jul 28 08:00:07.410: cilium-test/client-7df6cfbf7b-qn7q6:57326 (ID:15432) -> cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-endpoint FORWARDED (TCP Flags: ACK, PSH)
Jul 28 08:00:07.411: cilium-test/client-7df6cfbf7b-qn7q6:57326 (ID:15432) <- cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-stack FORWARDED (TCP Flags: ACK, PSH)
Jul 28 08:00:07.411: cilium-test/client-7df6cfbf7b-qn7q6:57326 (ID:15432) <- cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-endpoint FORWARDED (TCP Flags: ACK, PSH)
Jul 28 08:00:07.412: cilium-test/client-7df6cfbf7b-qn7q6:57326 (ID:15432) -> cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-stack FORWARDED (TCP Flags: ACK, FIN)
Jul 28 08:00:07.412: cilium-test/client-7df6cfbf7b-qn7q6:57326 (ID:15432) -> cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-endpoint FORWARDED (TCP Flags: ACK, FIN)
Jul 28 08:00:07.412: cilium-test/client-7df6cfbf7b-qn7q6:57326 (ID:15432) <- cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-stack FORWARDED (TCP Flags: ACK, FIN)
Jul 28 08:00:07.412: cilium-test/client-7df6cfbf7b-qn7q6:57326 (ID:15432) <- cilium-test/echo-other-node-d79544ccf-r688b:8080 (ID:50956) to-endpoint FORWARDED (TCP Flags: ACK, FIN)
apple@bogon ovn-test %
```

■■■■■■■■ `hubble observe` ■■■■■■■■■■■■■■■

... `cilium-test` namespace... Cilium ...



7.13.5 Hubble ...

Hubble ... Pod ... Hubble ...

... `hubble.metrics.enabled` ...:

```
helm upgrade cilium cilium/cilium --version 1.11.6 \
   --namespace kube-system \
   --reuse-values \
   --set hubble.relay.enabled=true \
   --set hubble.ui.enabled=true \
   --set hubble.metrics.enabled="{dns,drop,tcp,flow,icmp,http}"
```

... kube-system namespace ... `hubble-metrics` ... Endpoints ... Hubble ...:

```
# curl 172.18.0.2:9091/metrics
# HELP hubble_drop_total Number of drops
# TYPE hubble_drop_total counter
hubble_drop_total{protocol="ICMPv6",reason="Unsupported L3 protocol"} 2
# HELP hubble_flows_processed_total Total number of flows processed
# TYPE hubble_flows_processed_total counter
hubble_flows_processed_total{protocol="ICMPv4",subtype="to-endpoint",type="Trace",verdict="FORWARDED"} 335
hubble_flows_processed_total{protocol="ICMPv4",subtype="to-stack",type="Trace",verdict="FORWARDED"} 335
hubble_flows_processed_total{protocol="ICMPv6",subtype="",type="Drop",verdict="DROPPED"} 2
hubble_flows_processed_total{protocol="TCP",subtype="to-endpoint",type="Trace",verdict="FORWARDED"} 8282
hubble_flows_processed_total{protocol="TCP",subtype="to-stack",type="Trace",verdict="FORWARDED"} 6767
hubble_flows_processed_total{protocol="UDP",subtype="to-endpoint",type="Trace",verdict="FORWARDED"} 1642
hubble_flows_processed_total{protocol="UDP",subtype="to-stack",type="Trace",verdict="FORWARDED"} 1642
# HELP hubble_icmp_total Number of ICMP messages
# TYPE hubble_icmp_total counter
hubble_icmp_total{family="IPv4",type="EchoReply"} 335
hubble_icmp_total{family="IPv4",type="EchoRequest"} 335
hubble_icmp_total{family="IPv4",type="RouterSolicitation"} 2
# HELP hubble_tcp_flags_total TCP flag occurrences
# TYPE hubble_tcp_flags_total counter
hubble_tcp_flags_total{family="IPv4",flag="FIN"} 2043
hubble_tcp_flags_total{family="IPv4",flag="RST"} 301
hubble_tcp_flags_total{family="IPv4",flag="SYN"} 1169
hubble_tcp_flags_total{family="IPv4",flag="SYN-ACK"} 1169
```

PDF Slack Support

2023⬚3⬚26⬚

2022⬚8⬚2⬚

GitHub 

7.13.6 ⬚⬚

2025 Kube-OVN Team

7.14 ■■■■■■■

■■■■■■■

7.15 VIP ⬚⬚ IP

VIP ⬚⬚⬚ IP⬚⬚⬚⬚⬚ IP ⬚⬚⬚VIP ⬚⬚⬚⬚⬚⬚⬚ OpenStack Neutron Allowed-Address-Pairs⬚AAP⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ OVN Switch LB Rule ⬚⬚⬚⬚ VIP⬚ Pod ⬚⬚⬚⬚⬚ `IP` ⬚⬚⬚ IPAM ⬚⬚⬚VIP ⬚⬚⬚⬚⬚ Pod ⬚⬚⬚⬚⬚ ⬚⬚ VIP ⬚⬚⬚⬚⬚⬚⬚⬚⬚

- Allowed-Address-Pairs VIP
- Switch LB rule VIP

7.15.1 1. Allowed-Address-Pairs VIP

⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ IP ⬚⬚⬚⬚⬚⬚⬚ Pod ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

- Kubernetes ⬚⬚ Kubernetes ⬚⬚⬚⬚⬚⬚ Kubernetes ⬚⬚ Underlay ⬚⬚⬚⬚⬚⬚⬚ Subnet ⬚⬚⬚⬚⬚⬚
- LB ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ Subnet ⬚⬚ IP⬚⬚⬚⬚⬚⬚⬚⬚ Pod⬚

⬚⬚⬚VIP ⬚⬚⬚⬚ Allowed-Address-Pairs ⬚⬚ IP ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ IP ⬚⬚⬚⬚⬚⬚⬚⬚

- Keepalived ⬚⬚⬚⬚⬚⬚⬚⬚ IP ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

1.3 Pod 绑定 VIP 作为 AAP

Pod 通过在 annotation 中指定 VIP 作为 AAP 来将Pod 的 labels 匹配到 VIP 的 `selector` 来进行关联

Pod annotation 中指定要将 VIP绑定到该Pod，ovn.kubernetes.io/aaps: vip-aap,vip-aap2,vip-aap3

AAP 可以绑定多个 Pod 来实现多个Pod 共用一个 VIP 作为 subnet 中的 Port 来使用

1.3.1 创建 VIP 作为 AAP

```
apiVersion: kubeovn.io/v1
kind: Vip
metadata:
  name: vip-aap
spec:
  subnet: ovn-default
  namespace: default
  selector:
    - "app: aap1"
```

VIP 中可以指定以下两个参数来进行匹配

- `namespace` : AAP 会在该VIP 所在的命名空间下匹配VIP 所在命名空间下的 AAP 资源
- `selector` : AAP 会匹配指定 VIP 所在 Pod 所在命名空间下的 `namespace` 中 Pod所具有的 `key: value` 标签，多个标签之间为 AND 关系

创建完成后 VIP 会在 Port中

```
# kubectl ko nbctl show ovn-default
switch e32e1d3b-c539-45f4-ab19-be4e33a061f6 (ovn-default)
    port aap-vip
        type: virtual
```

```
apiVersion: v1
kind: Pod
metadata:
  name: busybox
  annotations:
    ovn.kubernetes.io/aaps: vip-aap
  labels:
    app: aap1
spec:
  containers:
    - name: busybox
      image: busybox
      command: ["sleep", "3600"]
      securityContext:
        capabilities:
          add:
            - NET_ADMIN
```

创建完成后 AAP 会绑定到

```
# kubectl ko nbctl list logical_switch_port aap-vip
_uuid               : cd930750-0533-4f06-a6c0-217ddac73272
addresses           : []
dhcpv4_options      : []
dhcpv6_options      : []
dynamic_addresses   : []
enabled             : []
external_ids        : {ls=ovn-default, vendor=kube-ovn}
ha_chassis_group    : []
mirror_rules        : []
name                : aap-vip
options             : {virtual-ip="10.16.0.100", virtual-parents="busybox.default"}
parent_name         : []
port_security       : []
tag                 : []
tag_request         : []
type                : virtual
up                  : false
```

virtual-ip 中会将 VIP 的 IP，virtual-parents 中会将 AAP 绑定 Pod 的 Port。

创建完成后 Pod 会绑定到

```
# kubectl exec -it busybox -- ip addr add 10.16.0.100/16 dev eth0
# kubectl exec -it busybox01 -- ip addr show eth0
35: eth0@if36: <BROADCAST,MULTICAST,UP,LOWER_UP,M-DOWN> mtu 1400 qdisc noqueue
    link/ether 00:00:00:e2:ab:0c brd ff:ff:ff:ff:ff:ff
    inet 10.16.0.7/16 brd 10.16.255.255 scope global eth0
       valid_lft forever preferred_lft forever
```

```
    inet 10.16.0.100/16 scope global secondary eth0
       valid_lft forever preferred_lft forever
    inet6 fe80::200:ff:fee2:ab0c/64 scope link
       valid_lft forever preferred_lft forever
```

□ Pod □□□□□□□□ IP□VIP □ IP □□□□□□□□□□□ subnet □□□□ Pod □□□□□ IP □□□□□

7.15.2 2. Switch LB rule vip

```yaml
apiVersion: kubeovn.io/v1
kind: Vip
metadata:
  name: slr-01
spec:
  subnet: ovn-default
  type: switch_lb_vip
```

- `subnet` : □□□ Subnet □□□ IP□
- `type` : □□□□□□□□□□□□□□□□□□ ipam ip □□□ `switch_lb_vip` □□□ vip □□□ switch lb □□ vip □□□ ip □□□□□□□□


7.15.3 3. □ v1.17 □□□□□□□□

v1.17 □□□□□ `ovn.kubernetes.io/vip` □ Pod □□ IP □□□□□□ `kube_host_vm_vip` □□□□□□□□□□□□ annotation □ Pod □□□□ VIP□□□□□ VIP □□□ Pod □□□□□ IP □□□□□

- □□□□□□ `ovn.kubernetes.io/vip` □ Pod □□□□□ IPAM □□□□ annotation □□□□□□□□□□
- □□□□□□□ Pod □□□□ IPAM □□□□□□□□ VIP□□□□□□□□□□ VIP□□□ Pod □□□□□□□□□□□□ controller □□□□□□□□□□VIP □□□□□□□□□□□□
- `kube_host_vm_vip` □□□□□□□□□□□□□□□□□□

7.16 Mellanox □□ Offload □□

Kube-OVN □□□□□□□□□□ OVS □□□□□□□□□□□□□□□□□□□□□□□□□□□□ CPU □□□□□□□□□□□□□□□□ CPU □□□□□□ □□□□□□□□□□□□Mellanox □ Accelerated Switching And Packet Processing (ASAP²) □□□□□□ OVS □□□□□□□□□□□□□□□□ eSwitch □□□□□□□□□□□□□□□□ OVS □□□□□□□□□□□□□□□□□□□□□□□□□□□□ CPU □□□□□□□□□□□□□□□□□□□□□□□□□□



Note

□□□□□□□□ 2022 □□□□□□□□□□□□□□□□□□□□

▯▯▯▯ ID ▯▯▯▯▯▯▯

```
# ls -l /sys/class/net/ | grep 84:00.0
lrwxrwxrwx 1 root root 0 Feb 4 16:16 enp132s0f0np0 -> ../../devices/pci0000:80/0000:80:08.0/0000:84:00.0/net/enp132s0f0np0
# ls -l /sys/class/net/ | grep 84:00.1
lrwxrwxrwx 1 root root 0 Feb 4 16:16 enp132s0f1np1 -> ../../devices/pci0000:80/0000:80:08.0/0000:84:00.1/net/enp132s0f1np1
```

▯▯▯▯▯▯▯▯ bond▯

> ▯▯▯▯▯▯ enp132s0f0np0 ▯ enp132s0f1np1 ▯▯ bond1

```
# ip link show enp132s0f0np0 | grep bond
160: enp132s0f0np0: <BROADCAST,MULTICAST,SLAVE,UP,LOWER_UP> mtu 1500 qdisc mq master bond1 state UP mode DEFAULT group default qlen 1000
# ip link show enp132s0f1np1 | grep bond
169: enp132s0f1np1: <BROADCAST,MULTICAST,SLAVE,UP,LOWER_UP> mtu 1500 qdisc mq master bond1 state UP mode DEFAULT group default qlen 1000
```

▯▯ bond ▯▯▯▯ VF▯

```
ifenslave -d bond1 enp132s0f0np0
ifenslave -d bond1 enp132s0f1np1
echo 0 > /sys/class/net/enp132s0f0np0/device/sriov_numvfs
echo 0 > /sys/class/net/enp132s0f1np1/device/sriov_numvfs
ip link set enp132s0f0np0 down
ip link set enp132s0f1np1 down
```

▯▯▯▯▯▯▯▯▯▯

> OVS ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯SMFS ▯ DMFS

- SMFS (software-managed flow steering)▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

```
84:00.5 Ethernet controller [0200]: Mellanox Technologies MT27800 Family [ConnectX-5 Virtual Function] [15b3:1018]
84:00.6 Ethernet controller [0200]: Mellanox Technologies MT27800 Family [ConnectX-5 Virtual Function] [15b3:1018]
84:00.7 Ethernet controller [0200]: Mellanox Technologies MT27800 Family [ConnectX-5 Virtual Function] [15b3:1018]
84:01.0 Ethernet controller [0200]: Mellanox Technologies MT27800 Family [ConnectX-5 Virtual Function] [15b3:1018]
84:01.1 Ethernet controller [0200]: Mellanox Technologies MT27800 Family [ConnectX-5 Virtual Function] [15b3:1018]
```

▯ VF ▯▯▯▯▯▯▯

```
echo 0000:84:00.2 > /sys/bus/pci/drivers/mlx5_core/unbind
echo 0000:84:00.3 > /sys/bus/pci/drivers/mlx5_core/unbind
echo 0000:84:00.4 > /sys/bus/pci/drivers/mlx5_core/unbind
echo 0000:84:00.5 > /sys/bus/pci/drivers/mlx5_core/unbind
echo 0000:84:00.6 > /sys/bus/pci/drivers/mlx5_core/unbind
echo 0000:84:00.7 > /sys/bus/pci/drivers/mlx5_core/unbind
echo 0000:84:01.0 > /sys/bus/pci/drivers/mlx5_core/unbind
echo 0000:84:01.1 > /sys/bus/pci/drivers/mlx5_core/unbind
```

▯▯ eSwitch ▯▯▯▯▯▯▯▯▯▯▯▯

```
devlink dev eswitch set pci/0000:84:00.0 mode switchdev
devlink dev eswitch set pci/0000:84:00.1 mode switchdev
ethtool -K enp132s0f0np0 hw-tc-offload on
ethtool -K enp132s0f1np1 hw-tc-offload on
```

SR-IOV VF ▯▯▯▯▯▯▯

SR-IOV VF LAG ▯▯▯▯▯ PF ▯▯ OVS ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ e-switch ▯▯▯▯▯ bond ▯▯▯▯▯

- Active-backup
- XOR
- LACP

> SR-IOV VF LAG ▯▯ LAG ▯▯▯▯▯▯▯▯▯▯bond ▯▯▯▯▯▯▯▯ bond PF ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ VF▯▯▯ VF ▯▯▯▯▯▯ bond ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ PF ▯▯▯▯▯ ▯▯▯▯▯▯ VF ▯▯▯▯▯▯▯▯ PF▯▯ XOR ▯ LACP ▯▯▯▯▯▯▯▯ PF ▯▯▯▯▯▯▯▯▯▯▯▯ VF ▯▯▯▯▯▯▯▯▯▯ PF ▯▯▯▯▯

▯▯▯▯▯▯▯ LACP ▯▯▯▯▯▯▯▯▯▯▯▯

```
modprobe bonding mode=802.3ad
ip link set enp132s0f0np0 master bond1
ip link set enp132s0f1np1 master bond1
ip link set enp132s0f0np0 up
ip link set enp132s0f1np1 up
ip link set bond1 up
```

> ▯▯▯▯▯▯▯▯▯▯ bond▯▯▯▯▯▯▯▯▯▯

▯▯▯▯▯▯▯▯▯▯ VF ▯▯▯

```
echo 0000:84:00.2 > /sys/bus/pci/drivers/mlx5_core/bind
echo 0000:84:00.3 > /sys/bus/pci/drivers/mlx5_core/bind
echo 0000:84:00.4 > /sys/bus/pci/drivers/mlx5_core/bind
echo 0000:84:00.5 > /sys/bus/pci/drivers/mlx5_core/bind
echo 0000:84:00.6 > /sys/bus/pci/drivers/mlx5_core/bind
echo 0000:84:00.7 > /sys/bus/pci/drivers/mlx5_core/bind
echo 0000:84:01.0 > /sys/bus/pci/drivers/mlx5_core/bind
echo 0000:84:01.1 > /sys/bus/pci/drivers/mlx5_core/bind
```

`NetworkManager` ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `NetworkManager` ▯▯▯▯▯▯▯

```
systemctl stop NetworkManager
systemctl disable NetworkManager
```

▯▯ DEVICE PLUGIN

▯▯▯▯▯▯▯ VF ▯▯▯▯▯▯▯▯▯▯▯▯▯ Pod ▯▯▯ VF ▯▯▯▯▯▯▯▯▯▯ SR-IOV Device Plugin ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ ▯▯▯▯▯▯▯▯

▯▯ SR-IOV ▯▯ Configmap▯

```
apiVersion: v1
kind: ConfigMap
metadata:
  name: sriovdp-config
  namespace: kube-system
data:
  config.json: |
```

```
    {
      "resourceList": [{
          "resourcePrefix": "mellanox.com",
          "resourceName": "cx5_sriov_switchdev",
          "selectors": {
                  "vendors": ["15b3"],
                  "devices": ["1018"],
                  "drivers": ["mlx5_core"]
              }
      }
      ]
    }
```

SR-IOV Device Plugin ▯▯▯▯▯▯ ConfigMap ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ConfigMap ▯ name ▯ sriovdp-config▯

- `selectors` : VF ▯▯▯
- `vendors` : ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯
- `devices` : ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯
- `drivers` : ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

`selectors` ▯▯▯▯▯ `pciAddresses` ▯ `acpiIndexes` ▯▯▯▯▯ VF ▯▯▯▯▯▯▯▯▯▯▯▯▯▯SR-IOV ConfigMap ▯▯

▯▯ SR-IOV ▯▯▯▯▯▯

```
kubectl apply -f https://raw.githubusercontent.com/k8snetworkplumbingwg/sriov-network-device-plugin/v3.6.2/deployments/sriovdp-daemonset.yaml
```

▯▯ SR-IOV ▯▯▯▯▯▯▯▯▯ Kubernetes Node ▯▯

```
kubectl describe node kube-ovn-01  | grep mellanox

mellanox.com/cx5_sriov_switchdev:  8
mellanox.com/cx5_sriov_switchdev:  8
mellanox.com/cx5_sriov_switchdev  0           0
```

▯▯ sriov-network-operator ▯▯ SR-IOV ▯ Device Plugin

▯▯ node-feature-discovery▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

```
kubectl apply -k https://github.com/kubernetes-sigs/node-feature-discovery/deployment/overlays/default?ref=v0.11.3
```

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ offload ▯▯▯▯▯▯▯▯ annotation:

```
kubectl label nodes [offloadNicNode] feature.node.kubernetes.io/network-sriov.capable=true
```

▯▯▯▯▯▯▯▯▯▯ Operator▯

```
git clone --depth=1 https://github.com/kubeovn/sriov-network-operator.git
kubectl apply -k sriov-network-operator/deploy
```

▯▯ Operator ▯▯▯▯▯▯▯▯▯▯

```
# kubectl get -n kube-system all | grep sriov
NAME                                            READY   STATUS    RESTARTS   AGE
pod/sriov-network-config-daemon-bf9nt           1/1     Running   0          8s
pod/sriov-network-operator-54d7545f65-296gb     1/1     Running   0          10s

NAME                                          DESIRED   CURRENT   READY   UP-TO-DATE   AVAILABLE   NODE
SELECTOR                                                  AGE
daemonset.apps/sriov-network-config-daemon    1         1         1       1            1           beta.kubernetes.io/os=linux,feature.node.kubernetes.io/
network-sriov.capable=true   8s

NAME                                       READY   UP-TO-DATE   AVAILABLE   AGE
deployment.apps/sriov-network-operator     1/1     1            1           10s

NAME                                                  DESIRED   CURRENT   READY   AGE
replicaset.apps/sriov-network-operator-54d7545f65     1         1         1       10s
```

▯▯ `SriovNetworkNodeState` ▯▯▯▯ `node1` ▯▯▯▯▯▯▯▯▯▯▯▯ Mellanox ▯▯▯

```
# kubectl get sriovnetworknodestates.sriovnetwork.openshift.io -n kube-system node1 -o yaml
apiVersion: sriovnetwork.openshift.io/v1
kind: SriovNetworkNodeState
spec: ...
```

```
status:
  interfaces:
  - deviceID: "1017"
    driver: mlx5_core
    mtu: 1500
    pciAddress: "0000:5f:00.0"
    totalvfs: 8
    vendor: "15b3"
    linkSeed: 25000Mb/s
    linkType: ETH
    mac: 08:c0:eb:f4:85:bb
    name: ens41f0np0
  - deviceID: "1017"
    driver: mlx5_core
    mtu: 1500
    pciAddress: "0000:5f:00.1"
    totalvfs: 8
    vendor: "15b3"
    linkSeed: 25000Mb/s
    linkType: ETH
    mac: 08:c0:eb:f4:85:bb
    name: ens41f1np1
```

SriovNetworkNodePolicy nicSelector

```
apiVersion: sriovnetwork.openshift.io/v1
kind: SriovNetworkNodePolicy
metadata:
  name: policy
  namespace: kube-system
spec:
  nodeSelector:
    feature.node.kubernetes.io/network-sriov.capable: "true"
  eSwitchMode: switchdev
  numVfs: 3
  nicSelector:
    pfNames:
    - ens41f0np0
    - ens41f1np1
  resourceName: cx_sriov_switchdev
```

SriovNetworkNodeState status

```
# kubectl get sriovnetworknodestates.sriovnetwork.openshift.io -n kube-system node1 -o yaml

...
spec:
  interfaces:
  - eSwitchMode: switchdev
    name: ens41f0np0
    numVfs: 3
    pciAddress: 0000:5f:00.0
    vfGroups:
    - policyName: policy
      vfRange: 0-2
      resourceName: cx_sriov_switchdev
  - eSwitchMode: switchdev
    name: ens41f1np1
    numVfs: 3
    pciAddress: 0000:5f:00.1
    vfGroups:
    - policyName: policy
      vfRange: 0-2
      resourceName: cx_sriov_switchdev
status:
  interfaces
  - Vfs:
    - deviceID: 1018
      driver: mlx5_core
      pciAddress: 0000:5f:00.2
      vendor: "15b3"
    - deviceID: 1018
      driver: mlx5_core
      pciAddress: 0000:5f:00.3
      vendor: "15b3"
    - deviceID: 1018
      driver: mlx5_core
      pciAddress: 0000:5f:00.4
      vendor: "15b3"
    deviceID: "1017"
    driver: mlx5_core
    linkSeed: 25000Mb/s
    linkType: ETH
    mac: 08:c0:eb:f4:85:ab
    mtu: 1500
    name: ens41f0np0
    numVfs: 3
    pciAddress: 0000:5f:00.0
    totalvfs: 3
    vendor: "15b3"
  - Vfs:
```

```
    - deviceID: 1018
      driver: mlx5_core
      pciAddress: 0000:5f:00.5
      vendor: "15b3"
    - deviceID: 1018
      driver: mlx5_core
      pciAddress: 0000:5f:00.6
      vendor: "15b3"
    - deviceID: 1018
      driver: mlx5_core
      pciAddress: 0000:5f:00.7
      vendor: "15b3"
    deviceID: "1017"
    driver: mlx5_core
    linkSeed: 25000Mb/s
    linkType: ETH
    mac: 08:c0:eb:f4:85:bb
    mtu: 1500
    name: ens41f1np1
    numVfs: 3
    pciAddress: 0000:5f:00.1
    totalvfs: 3
    vendor: "15b3"
```

▯▯ VF ▯▯▯▯

```
# lspci -nn | grep ConnectX
5f:00.0 Ethernet controller [0200]: Mellanox Technologies MT27800 Family [ConnectX-5] [15b3:1017]
5f:00.1 Ethernet controller [0200]: Mellanox Technologies MT27800 Family [ConnectX-5] [15b3:1017]
5f:00.2 Ethernet controller [0200]: Mellanox Technologies MT27800 Family [ConnectX-5 Virtual Function] [15b3:1018]
5f:00.3 Ethernet controller [0200]: Mellanox Technologies MT27800 Family [ConnectX-5 Virtual Function] [15b3:1018]
5f:00.4 Ethernet controller [0200]: Mellanox Technologies MT27800 Family [ConnectX-5 Virtual Function] [15b3:1018]
5f:00.5 Ethernet controller [0200]: Mellanox Technologies MT27800 Family [ConnectX-5 Virtual Function] [15b3:1018]
5f:00.6 Ethernet controller [0200]: Mellanox Technologies MT27800 Family [ConnectX-5 Virtual Function] [15b3:1018]
5f:00.7 Ethernet controller [0200]: Mellanox Technologies MT27800 Family [ConnectX-5 Virtual Function] [15b3:1018]
```

▯▯ PF ▯▯▯▯▯

```
# cat /sys/class/net/ens41f0np0/compat/devlink/mode
switchdev
```

7.16.3 ▯▯ Multus-CNI

SR-IOV Device Plugin ▯▯▯▯▯▯▯▯ ID ▯▯▯▯ Multus-CNI ▯▯▯ Kube-OVN▯▯▯▯▯▯▯ Multus-CNI ▯▯▯▯▯▯▯▯▯

▯▯ Multus-CNI ▯▯▯▯▯▯▯

```
kubectl apply -f https://raw.githubusercontent.com/k8snetworkplumbingwg/multus-cni/v4.0.2/deployments/multus-daemonset-thick.yml
```

> ▯▯▯multus ▯▯▯ Thin ▯ Thick ▯▯▯▯▯▯▯▯▯▯ SR-IOV ▯▯▯▯▯ Thick ▯▯▯

▯▯ `NetworkAttachmentDefinition` ▯

```
apiVersion: "k8s.cni.cncf.io/v1"
kind: NetworkAttachmentDefinition
metadata:
  name: sriov
  namespace: default
  annotations:
    k8s.v1.cni.cncf.io/resourceName: mellanox.com/cx5_sriov_switchdev
spec:
  config: '{
    "cniVersion": "0.3.1",
    "name": "kube-ovn",
    "plugins":[
        {
            "type":"kube-ovn",
            "server_socket":"/run/openvswitch/kube-ovn-daemon.sock",
            "provider": "sriov.default.ovn"
        },
        {
            "type":"portmap",
            "capabilities":{
                "portMappings":true
            }
        }
    ]
}'
```

- `provider`：▯▯▯▯▯ `NetworkAttachmentDefinition` ▯ {name}.{namespace}.ovn▯

7.16.4 Overlay ⬚⬚

Kube-OVN ⬚⬚⬚⬚⬚⬚⬚

⬚⬚⬚⬚⬚⬚⬚

```
wget https://raw.githubusercontent.com/kubeovn/kube-ovn/release-1.16/dist/images/install.sh
```

⬚⬚⬚⬚⬚⬚⬚ `IFACE` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ IP⬚

```
ENABLE_MIRROR=${ENABLE_MIRROR:-false}
HW_OFFLOAD=${HW_OFFLOAD:-true}
ENABLE_LB=${ENABLE_LB:-false}
IFACE="bond1"
#       SR-IOV   Device Plugin           bond    IFACE     bond1      bond     IFACE     enp132s0f0np0   enp132s0f1np1
```

⬚⬚ Kube-OVN⬚

```
bash install.sh
```

⬚⬚⬚⬚ **VF ⬚⬚⬚ Pod**

⬚⬚⬚⬚⬚⬚ yaml ⬚⬚⬚⬚⬚⬚ VF ⬚⬚⬚⬚⬚⬚⬚⬚⬚ Pod:

```yaml
apiVersion: v1
kind: Pod
metadata:
  name: nginx-overlay
  annotations:
    v1.multus-cni.io/default-network: default/sriov
    sriov.default.ovn.kubernetes.io/logical_switch: ovn-default
spec:
  containers:
  - name: nginx-overlay
    image: docker.io/library/nginx:alpine
    resources:
      requests:
        mellanox.com/cx5_sriov_switchdev: '1'
      limits:
        mellanox.com/cx5_sriov_switchdev: '1'
```

- `v1.multus-cni.io/default-network`：⬚⬚⬚⬚⬚⬚ `NetworkAttachmentDefinition` ⬚ {namespace}/{name}⬚
- `sriov.default.ovn.kubernetes.io/logical_switch`：⬚⬚ Pod ⬚⬚⬚⬚⬚⬚⬚⬚ Pod ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

7.16.5 Underlay ⬚⬚

Kube-OVN ⬚⬚⬚⬚⬚⬚⬚

⬚⬚⬚⬚⬚⬚⬚

```
wget https://raw.githubusercontent.com/kubeovn/kube-ovn/release-1.16/dist/images/install.sh
```

⬚⬚⬚⬚⬚⬚⬚ `IFACE` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ IP⬚

```
ENABLE_MIRROR=${ENABLE_MIRROR:-false}
HW_OFFLOAD=${HW_OFFLOAD:-true}
ENABLE_LB=${ENABLE_LB:-false}
IFACE=""
#     Underlay    IFACE         PF      IFACE         K8s                 PF
```

⬚⬚ Kube-OVN⬚

```
bash install.sh
```

⬚⬚⬚⬚ **VF ⬚⬚⬚ Pod**

⬚⬚⬚⬚⬚⬚ yaml ⬚⬚⬚⬚⬚⬚ VF ⬚⬚⬚⬚⬚⬚⬚⬚⬚ Pod:

2025 Kube-OVN Team

```
apiVersion: kubeovn.io/v1
kind: ProviderNetwork
metadata:
  name: underlay-offload
spec:
  defaultInterface: bond1

---
apiVersion: kubeovn.io/v1
kind: Vlan
metadata:
  name: vlan0
spec:
  id: 0
  provider: underlay-offload

---
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: vlan0
spec:
  protocol: IPv4
  provider: ovn
  cidrBlock: 10.10.204.0/24
  gateway: 10.10.204.254
  vlan: vlan0
  excludeIps:
  - 10.10.204.1..10.10.10.204.100

---
apiVersion: v1
kind: Pod
metadata:
  name: nginx-underlay
  annotations:
    k8s.v1.cni.cncf.io/networks: '[{
      "name": "sriov",
      "namespace": "default",
      "default-route": ["10.10.204.254"]
    }]'
    sriov.default.ovn.kubernetes.io/logical_switch: vlan0
spec:
  containers:
  - name: nginx-underlay
    image: docker.io/library/nginx:alpine
    resources:
      requests:
        mellanox.com/cx5_sriov_switchdev: '1'
      limits:
        mellanox.com/cx5_sriov_switchdev: '1'
```

- `v1.multus-cni.io/default-network` : ... `NetworkAttachmentDefinition` ... {namespace}/{name}...

> ... multus ... VF ... Pod... VF ... Pod ... VF ... Pod ... multus ...

... yaml ... VF ... Pod:

```
apiVersion: v1
kind: Pod
metadata:
  name: nginx-underlay-noVF
  annotations:
    ovn.kubernetes.io/logical_switch: vlan0
spec:
  containers:
  - name: nginx-underlay-noVF
    image: docker.io/library/nginx:alpine
```

... VF ... Pod... ovs-kernel ... e-switch ...

7.16.6 ...

... Pod ... `ovs-ovn` ...

```
# ovs-appctl dpctl/dump-flows -m type=offloaded
ufid:91cc45de-e7e9-4935-8f82-1890430b0f66, skb_priority(0/0),skb_mark(0/0),ct_state(0/0x23),ct_zone(0/0),ct_mark(0/0),ct_label(0/0x1),recirc_id(0),dp_hash(0/
0),in_port(5b45c61b307e_h),packet_type(ns=0/0,id=0/
0),eth(src=00:00:00:c5:6d:4e,dst=00:00:00:e7:16:ce),eth_type(0x0800),ipv4(src=0.0.0.0/0.0.0.0,dst=0.0.0.0/0.0.0.0,proto=0/0,tos=0/0,ttl=0/0,frag=no),
packets:941539, bytes:62142230, used:0.260s, offloaded:yes, dp:tc, actions:54235e5753b8_h
ufid:e00768d7-e652-4d79-8182-3291d852b791, skb_priority(0/0),skb_mark(0/0),ct_state(0/0x23),ct_zone(0/0),ct_mark(0/0),ct_label(0/0x1),recirc_id(0),dp_hash(0/
0),in_port(54235e5753b8_h),packet_type(ns=0/0,id=0/
0),eth(src=00:00:00:e7:16:ce,dst=00:00:00:c5:6d:4e),eth_type(0x0800),ipv4(src=0.0.0.0/0.0.0.0,dst=0.0.0.0/0.0.0.0,proto=0/0,tos=0/0,ttl=0/0,frag=no),
packets:82386659, bytes:115944854173, used:0.260s, offloaded:yes, dp:tc, actions:5b45c61b307e_h
```

▯▯▯ `offloaded:yes, dp:tc` ▯▯▯▯▯▯▯▯▯▯

PDF Slack Support

2025▯9▯10▯


2022▯5▯24▯

GitHub 

7.16.7 ▯▯

7.17 □□□□□ Offload □□

Kube-OVN □□□□□□□□□□ OVS □□□□□□□□□□□□□□□□□□□□□□□□□□□□ CPU □□□□□□□□□□□□□□□□ CPU □□□□□□ □□□□□□□□□□□□□□□□□ Agilio CX □□□□□□□□□□ OVS □□□□□□□□□□□□□□□□□□□ □□□□□□□ □□□□ OVS □□□□□□□□□□□□□□□□□□□□□□□□□□□□ CPU □□□□□□□□□□□□□□□□□□□□□□□□□□□



Note

□□□□□□□□ 2022 □□□□□□□□□□□□□□□□□□□□

```
    echo ASSY: defaults to ${DEFAULT_ASSY}
    echo APP: defaults to flower. flower-next is supported if updated
    echo      firmware has been installed.
    exit 1
fi

# It is recommended that the assembly be determined by inspection
# The following code determines the value via the debug interface
if [ "${ASSY}x" = "scanx" ]; then
    ethtool -W ${DEVICE} 0
    DEBUG=$(ethtool -w ${DEVICE} data /dev/stdout | strings)
    SERIAL=$(echo "${DEBUG}" | grep "^SN:")
    ASSY=$(echo ${SERIAL} | grep -oE AMDA[0-9]{4})
fi

PCIADDR=$(basename $(readlink -e /sys/class/net/${DEVICE}/device))
FWDIR="/lib/firmware/netronome"

# AMDA0081 and AMDA0097 uses the same firmware
if [ "${ASSY}" = "AMDA0081" ]; then
    if [ ! -e ${FWDIR}/${APP}/nic_AMDA0081.nffw ]; then
       ln -sf nic_AMDA0097.nffw ${FWDIR}/${APP}/nic_AMDA0081.nffw
   fi
fi

FW="${FWDIR}/pci-${PCIADDR}.nffw"
ln -sf "${APP}/nic_${ASSY}.nffw" "${FW}"

# insert distro-specific initramfs section here...
```

[redacted]

```
./agilio-tc-fw-select.sh ens47np0 scan
rmmod nfp
modprobe nfp
```

[redacted] VF [redacted] VF[redacted]

```
# cat /sys/class/net/ens3/device/sriov_totalvfs
65

# echo 4 > /sys/class/net/ens47/device/sriov_numvfs
```

7.17.3 [redacted] SR-IOV Device Plugin

[redacted] VF [redacted] Pod [redacted] VF [redacted] SR-IOV Device Plugin [redacted] [redacted]

[redacted] SR-IOV [redacted] Configmap[redacted]

```
apiVersion: v1
kind: ConfigMap
metadata:
  name: sriovdp-config
  namespace: kube-system
data:
  config.json: |
    {
      "resourceList": [{
          "resourcePrefix": "corigine.com",
          "resourceName": "agilio_sriov",
          "selectors": {
                  "vendors": ["19ee"],
                  "devices": ["6003"],
                  "drivers": ["nfp_netvf"]
              }
      }
      ]
    }
```

[redacted] SR-IOV Network Device Plugin [redacted] intel/sriov-network-device-plugin [redacted] k8snetworkplumbingwg[redacted]

```
kubectl apply -f https://raw.githubusercontent.com/k8snetworkplumbingwg/sriov-network-device-plugin/master/deployments/sriovdp-daemonset.yaml
```

[redacted] SR-IOV [redacted] Kubernetes Node [redacted]

```
kubectl describe no containerserver  | grep corigine

corigine.com/agilio_sriov:  4
corigine.com/agilio_sriov:  4
corigine.com/agilio_sriov  0           0
```

7.17.4 □□ Multus-CNI

SR-IOV Device Plugin □□□□□□□□ ID □□□□ Multus-CNI □□□ Kube-OVN□□□□□□□ Multus-CNI □□□□□□□□□

□□ Multus-CNI □□□□□□□

```
kubectl apply -f https://raw.githubusercontent.com/k8snetworkplumbingwg/multus-cni/master/deployments/multus-daemonset.yml
```

□□ `NetworkAttachmentDefinition` □

```
apiVersion: "k8s.cni.cncf.io/v1"
kind: NetworkAttachmentDefinition
metadata:
  name: default
  namespace: default
  annotations:
    k8s.v1.cni.cncf.io/resourceName: corigine.com/agilio_sriov
spec:
  config: '{
    "cniVersion": "0.3.1",
    "name": "kube-ovn",
    "plugins":[
        {
            "type":"kube-ovn",
            "server_socket":"/run/openvswitch/kube-ovn-daemon.sock",
            "provider": "default.default.ovn"
        },
        {
            "type":"portmap",
            "capabilities":{
                "portMappings":true
            }
        }
    ]
}'
```

- `provider` : □□□□□ `NetworkAttachmentDefinition` □ {name}.{namespace}.ovn□

7.17.5 Kube-OVN □□□□□□□

□□□□□□□

```
wget https://raw.githubusercontent.com/kubeovn/kube-ovn/release-1.16/dist/images/install.sh
```

□□□□□□□ `IFACE` □□□□□□□□□□□□□□□□□□□ IP□

```
ENABLE_MIRROR=${ENABLE_MIRROR:-false}
HW_OFFLOAD=${HW_OFFLOAD:-true}
ENABLE_LB=${ENABLE_LB:-false}
IFACE="ensp01"
```

□□ Kube-OVN□

```
bash install.sh
```

7.17.6 □□□□ VF □□□ Pod

□□□□□□ yaml □□□□□□ VF □□□□□□□□□ Pod:

```
apiVersion: v1
kind: Pod
metadata:
  name: nginx
  namespace: default
  annotations:
    v1.multus-cni.io/default-network: default/default
spec:
  containers:
    - name: nginx
      image: docker.io/library/nginx:alpine
      resources:
        requests:
          corigine.com/agilio_sriov: '1'
```


2025 Kube-OVN Team

```
        limits:
          corigine.com/agilio_sriov: '1'
```

- `v1.multus-cni.io/default-network`：⬚⬚⬚⬚⬚⬚ `NetworkAttachmentDefinition` ⬚ {namespace}/{name}⬚

⬚⬚⬚⬚ Pod ⬚⬚⬚⬚⬚ `ovs-ovn` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

```
# ovs-appctl dpctl/dump-flows -m type=offloaded
ufid:91cc45de-e7e9-4935-8f82-1890430b0f66, skb_priority(0/0),skb_mark(0/0),ct_state(0/0x23),ct_zone(0/0),ct_mark(0/0),ct_label(0/0x1),recirc_id(0),dp_hash(0/
0),in_port(5b45c61b307e_h),packet_type(ns=0/0,id=0/
0),eth(src=00:00:00:c5:6d:4e,dst=00:00:00:e7:16:ce),eth_type(0x0800),ipv4(src=0.0.0.0/0.0.0.0,dst=0.0.0.0/0.0.0.0,proto=0/0,tos=0/0,ttl=0/0,frag=no),
packets:941539, bytes:62142230, used:0.260s, offloaded:yes, dp:tc, actions:54235e5753b8_h
ufid:e00768d7-e652-4d79-8182-3291d852b791, skb_priority(0/0),skb_mark(0/0),ct_state(0/0x23),ct_zone(0/0),ct_mark(0/0),ct_label(0/0x1),recirc_id(0),dp_hash(0/
0),in_port(54235e5753b8_h),packet_type(ns=0/0,id=0/
0),eth(src=00:00:00:e7:16:ce,dst=00:00:00:c5:6d:4e),eth_type(0x0800),ipv4(src=0.0.0.0/0.0.0.0,dst=0.0.0.0/0.0.0.0,proto=0/0,tos=0/0,ttl=0/0,frag=no),
packets:82386659, bytes:115944854173, used:0.260s, offloaded:yes, dp:tc, actions:5b45c61b307e_h
```

⬚⬚⬚ `offloaded:yes, dp:tc` ⬚⬚⬚⬚⬚⬚⬚⬚⬚

PDF Slack Support

2026⬚4⬚28⬚

2022⬚5⬚24⬚

GitHub



7.17.7 ⬚⬚

7.18 ▯▯▯▯▯▯ Offload ▯▯

Kube-OVN ▯▯▯▯▯▯▯▯▯▯ OVS ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ CPU ▯▯▯▯▯▯▯▯▯▯▯▯▯▯ CPU ▯▯▯▯▯ ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ metaScale ▯▯▯▯▯▯▯▯▯ OVS ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ ▯▯▯▯ OVS ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ CPU ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

> **Note**
>
> 1. ▯▯▯▯▯▯▯▯ 2024 ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

```
ls -l /sys/class/net/ | grep b3:00.0
lrwxrwxrwx 1 root root 0 May  7 16:30 p3p1 -> ../../devices/pci0000:b2/0000:b2:00.0/0000:b3:00.0/net/p3p1
```

1. ...... VF ...

```
cat /sys/class/net/p3p1/device/sriov_totalvfs
512
```

1. .. VF.

```
echo '10' > /sys/class/net/p3p1/device/sriov_numvfs
```

1. .. VF ......

```
lspci -d 1f67:
b3:00.0 Ethernet controller: Device 1f67:1111 (rev 02)
b3:00.1 Ethernet controller: Device 1f67:1111 (rev 02)
b3:00.2 Ethernet controller: Device 1f67:1112
b3:00.3 Ethernet controller: Device 1f67:1112
b3:00.4 Ethernet controller: Device 1f67:1112
b3:00.5 Ethernet controller: Device 1f67:1112
b3:00.6 Ethernet controller: Device 1f67:1112
b3:00.7 Ethernet controller: Device 1f67:1112
b3:01.0 Ethernet controller: Device 1f67:1112
b3:01.1 Ethernet controller: Device 1f67:1112
b3:01.2 Ethernet controller: Device 1f67:1112
b3:01.3 Ethernet controller: Device 1f67:1112
```

1. .. switchdev ...

```
devlink dev eswitch set pci/0000:b3:00.0 mode switchdev
```

.. SR-IOV Device Plugin

1. .. SR-IOV .. ConfigMap.

```
apiVersion: v1
kind: ConfigMap
metadata:
  name: sriovdp-config
  namespace: kube-system
data:
  config.json: |
    {
        "resourceList": [{
                "resourceName": "xsc_sriov",
                "resourcePrefix": "yunsilicon.com",
                "selectors": {
                    "vendors": ["1f67"],
                    "devices": ["1012", "1112"]
                }}
        ]
    }
```

1. .. SR-IOV Device Plugin .. DevicePlugin.

2. .... SR-IOV ...

```
# kubectl describe node <node name> | grep yunsilicon.com/xsc_sriov
  yunsilicon.com/xsc_sriov:  10
  yunsilicon.com/xsc_sriov:  10
  yunsilicon.com/xsc_sriov  0            0
```

.. Multus-CNI

1. .. Multus-CNI ... Multus-CNI

```
kubectl apply -f https://raw.githubusercontent.com/k8snetworkplumbingwg/multus-cni/master/deployments/multus-daemonset.yml
```

1. .. NetworkAttachmentDefinition

```
apiVersion: "k8s.cni.cncf.io/v1"
kind: NetworkAttachmentDefinition
```

```
metadata:
  name: sriov-net1
  namespace: default
  annotations:
    k8s.v1.cni.cncf.io/resourceName: yunsilicon.com/xsc_sriov
spec:
  config: '{
    "cniVersion": "0.3.1",
    "name": "kube-ovn",
    "plugins":[
        {
            "type":"kube-ovn",
            "server_socket":"/run/openvswitch/kube-ovn-daemon.sock",
            "provider": "sriov-net1.default.ovn"
        },
        {
            "type":"portmap",
            "capabilities":{
                "portMappings":true
            }
        }
    ]
}'
```

... **SR-IOV ... Pod**

```
apiVersion: v1
kind: Pod
metadata:
  name: nginx
  annotations:
    v1.multus-cni.io/default-network: default/sriov-net1
spec:
  containers:
    - name: nginx
      image: docker.io/library/nginx:alpine
      resources:
        requests:
          yunsilicon.com/xsc_sriov: '1'
        limits:
          yunsilicon.com/xsc_sriov: '1'
```

Offload ...

... Pod ... `ovs-ovn` ...

```
ovs-appctl dpctl/dump-flows type=offloaded
flow-dump from pmd on cpu core: 9
ct_state(-new+est-rel+rpl+trk),ct_mark(0/
0x3),recirc_id(0x2d277),in_port(15),packet_type(ns=0,id=0),eth(src=00:00:00:9d:fb:1a,dst=00:00:00:ce:cf:b9),eth_type(0x0800),ipv4(dst=10.16.0.14,frag=no),
packets:6, bytes:588, used:7.276s, actions:ct(zone=4,nat),recirc(0x2d278)
ct_state(-new+est-rel-rpl+trk),ct_mark(0/
0x3),recirc_id(0x2d275),in_port(8),packet_type(ns=0,id=0),eth(src=00:00:00:ce:cf:b9,dst=00:00:00:9d:fb:1a),eth_type(0x0800),ipv4(dst=10.16.0.18,frag=no),
packets:5, bytes:490, used:7.434s, actions:ct(zone=6,nat),recirc(0x2d276)
ct_state(-new+est-rel-rpl+trk),ct_mark(0/0x1),recirc_id(0x2d276),in_port(8),packet_type(ns=0,id=0),eth(src=00:00:00:ce:cf:b9,dst=00:00:00:9d:fb:1a/
01:00:00:00:00:00),eth_type(0x0800),ipv4(frag=no), packets:5, bytes:490, used:7.434s, actions:15
recirc_id(0),in_port(15),packet_type(ns=0,id=0),eth(src=00:00:00:9d:fb:1a/
01:00:00:00:00:00,dst=00:00:00:ce:cf:b9),eth_type(0x0800),ipv4(dst=10.16.0.14/255.192.0.0,frag=no), packets:6, bytes:588, used:7.277s,
actions:ct(zone=6,nat),recirc(0x2d277)
recirc_id(0),in_port(8),packet_type(ns=0,id=0),eth(src=00:00:00:ce:cf:b9/01:00:00:00:00:00,dst=00:00:00:9d:fb:1a),eth_type(0x0800),ipv4(dst=10.16.0.18/255.192.0
packets:6, bytes:588, used:7.434s, actions:ct(zone=4,nat),recirc(0x2d275)
ct_state(-new+est-rel+rpl+trk),ct_mark(0/
0x1),recirc_id(0x2d278),in_port(15),packet_type(ns=0,id=0),eth(dst=00:00:00:ce:cf:b9/01:00:00:00:00:00),eth_type(0x0800),ipv4(frag=no), packets:6, bytes:588,
used:7.277s, actions:8
```

...

PDF Slack Support

2026...4...28...

2024...5...29...

GitHub 

2025 Kube-OVN Team

7.18.3 ▯▯

2025 Kube-OVN Team

7.19 □□□□□□ Offload □□

> **Note**
>
> □□□□□□□ 2024 □□□□□□□

```
        ]
    }
```

1. ▯▯▯▯▯ SR-IOV Device Plugin

```
kubectl apply -f https://raw.githubusercontent.com/k8snetworkplumbingwg/sriov-network-device-plugin/v3.6.2/deployments/sriovdp-daemonset.yaml
```

1. ▯▯ SR-IOV ▯▯▯▯▯▯▯▯▯▯ kubernetes Node ▯▯▯▯▯▯

```
kubectl describe node node1 | grep yusur
  yusur.tech/sriov_dpu:  7
  yusur.tech/sriov_dpu:  7
  yusur.tech/sriov_dpu  0           0
```

7.19.3 ▯▯ Multus-CNI

▯▯ Multus-CNI▯▯▯▯ Kube-OVN ▯▯▯▯ SRIOV ▯▯▯ Device ID▯

```
kubectl apply -f https://raw.githubusercontent.com/k8snetworkplumbingwg/multus-cni/v4.0.2/deployments/multus-daemonset-thick.yml
```

▯▯ `NetworkAttachmentDefinition` ▯

```
apiVersion:
  "k8s.cni.cncf.io/v1"
kind:
  NetworkAttachmentDefinition
metadata:
  name: test
  namespace: kube-system
  annotations:
    k8s.v1.cni.cncf.io/resourceName: yusur.tech/sriov_dpu
spec:
  config: '{
    "cniVersion": "0.3.1",
    "name": "kube-ovn",
    "plugins":[
        {
            "type":"kube-ovn",
            "server_socket":"/run/openvswitch/kube-ovn-daemon.sock",
            "provider": "test.kube-system.ovn"
        },
        {
            "type":"portmap",
            "capabilities":{
                "portMappings":true
            }
        }
    ]
}'
```

- `provider` : ▯▯▯▯▯ NetworkAttachmentDefinition ▯ `{name}.{namespace}.ovn` ▯

7.19.4 Kube-OVN ▯▯▯▯▯▯▯

1. ▯▯ ▯▯▯▯

```
wget https://raw.githubusercontent.com/kubeovn/kube-ovn/release-1.12/dist/images/install.sh
```

1. ▯▯▯▯▯▯▯IFACE ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ IP▯

```
ENABLE_MIRROR=${ENABLE_MIRROR:-false}
HW_OFFLOAD=${HW_OFFLOAD:-true}
ENABLE_LB=${ENABLE_LB:-false}
IFACE="p0"
```

1. ▯▯ kube-ovn

```
bash install.sh
```

▯▯▯▯ **VF ▯▯▯ pod**

▯▯▯▯▯ yaml ▯▯▯▯▯ VF ▯▯▯▯▯▯▯▯ Pod▯

2025 Kube-OVN Team

```
apiVersion: v1
kind: Pod
metadata:
  name: nginx
  namespace: default
  annotations:
    v1.multus-cni.io/default-network: kube-system/test
spec:
  containers:
    - name: nginx
      image: docker.io/library/nginx:alpine
      resources:
        requests:
          yusur.tech/sriov_dpu: '1'
        limits:
          yusur.tech/sriov_dpu: '1'
```

- `v1.multus-cni.io/default-network`：⬚⬚⬚⬚⬚⬚ `NetworkAttachmentDefinition` ⬚ `{namespace}/{name}` ⬚

Offload ⬚⬚

⬚⬚⬚⬚ Pod ⬚⬚⬚⬚⬚ `ovs-ovn` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

```
# ovs-appctl dpctl/dump-flows -m type=offloaded
ufid:67c2e10f-92d4-4574-be70-d072815ff166, skb_priority(0/0),skb_mark(0/0),ct_state(0/0x23),ct_zone(0/0),ct_mark(0/0),ct_label(0/0),recirc_id(0),dp_hash(0/
0),in_port(d85b161b6840_h),packet_type(ns=0/0,id=0/
0),eth(src=0a:c9:1c:70:01:09,dst=8a:18:a4:22:b7:7d),eth_type(0x0800),ipv4(src=10.0.1.10,dst=10.0.1.6,proto=6,tos=0/0x3,ttl=0/
0,frag=no),tcp(src=60774,dst=9001), packets:75021, bytes:109521630, offload_packets:75019, offload_bytes:109521498, used:3.990s,offloaded:yes,dp:tc,
actions:set(tunnel(tun_id=0x5,dst=192.168.201.12,ttl=64,tp_dst=6081,geneve({class=0x102,type=0x80,len=4,0xa0006}),flags(csum|key))),genev_sys_6081
ufid:7940666e-a0bd-42a5-8116-1e84e81bb338, skb_priority(0/0),tunnel(tun_id=0x5,src=192.168.201.12,dst=192.168.201.11,ttl=0/
0,tp_dst=6081,geneve({class=0x102,type=0x80,len=4,0x6000a}),flags(+key)),skb_mark(0/0),ct_state(0/0),ct_zone(0/0),ct_mark(0/0),ct_label(0/
0),recirc_id(0),dp_hash(0/0),in_port(genev_sys_6081),packet_type(ns=0/0,id=0/
0),eth(src=8a:18:a4:22:b7:7d,dst=0a:c9:1c:70:01:09),eth_type(0x0800),ipv4(src=10.0.1.6,dst=10.0.1.10,proto=6,tos=0/0,ttl=0/
0,frag=no),tcp(src=9001,dst=60774), packets:6946, bytes:459664, offload_packets:6944, offload_bytes:459532, used:4.170s,
dp:tc,offloaded:yes,actions:d85b161b6840_h
```

PDF Slack Support

2026⬚4⬚28⬚

2024⬚8⬚13⬚

GitHub



7.19.5 ⬚⬚

7.20 DPDK ⬚⬚

⬚⬚⬚⬚ Kube-OVN ⬚⬚⬚ OVS-DPDK ⬚⬚⬚⬚ KubeVirt ⬚⬚⬚⬚⬚ DPDK ⬚⬚⬚⬚⬚⬚⬚⬚

> ⬚⬚⬚ KubeVirt ⬚⬚⬚⬚⬚⬚ OVS-DPDK⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ patch Vhostuser implementation ⬚⬚ KubeVirt ⬚ KVM Device Plugin ⬚⬚⬚ OVS-DPDK⬚

7.20.1 ⬚⬚⬚⬚

- ⬚⬚⬚⬚⬚⬚⬚⬚ DPDK ⬚⬚⬚⬚⬚⬚⬚⬚
- ⬚⬚⬚⬚⬚ Hugepages⬚

7.20.2 ⬚⬚⬚⬚ DPDK ⬚⬚

⬚⬚⬚⬚⬚⬚ `driverctl` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ DPDK ⬚⬚⬚⬚⬚⬚

```
driverctl set-override 0000:00:0b.0 uio_pci_generic
```

7.20.3 ⬚⬚⬚⬚

⬚⬚⬚ OVS-DPDK ⬚⬚⬚⬚⬚⬚⬚⬚⬚ Kube-OVN ⬚⬚⬚⬚⬚⬚⬚⬚

```
kubectl label nodes <node> ovn.kubernetes.io/ovs_dp_type="userspace"
```

⬚⬚⬚ OVS-DPDK ⬚⬚⬚ `/opt/ovs-config` ⬚⬚⬚⬚⬚⬚⬚⬚⬚ `ovs-dpdk-config` ⬚

```
ENCAP_IP=192.168.122.193/24
DPDK_DEV=0000:00:0b.0
```

- `ENCAP_IP` : ⬚⬚⬚⬚⬚⬚⬚⬚
- `DPDK_DEV` : ⬚⬚⬚ PCI ID⬚

7.20.4 ⬚⬚ Kube-OVN

⬚⬚⬚⬚⬚⬚⬚⬚

```
wget https://raw.githubusercontent.com/kubeovn/kube-ovn/release-1.16/dist/images/install.sh
```

⬚⬚ DPDK ⬚⬚⬚⬚⬚⬚⬚⬚⬚

```
bash install.sh --with-hybrid-dpdk
```

7.20.5 ⬚⬚⬚⬚

⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ vhostuser ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ OVS-DPDK ⬚⬚⬚

⬚⬚ KVM Device Plugin ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ KVM Device Plugin⬚

```
kubectl apply -f https://raw.githubusercontent.com/kubevirt/kubernetes-device-plugins/master/manifests/kvm-ds.yml
```

⬚⬚ NetworkAttachmentDefinition⬚

```yaml
apiVersion: k8s.cni.cncf.io/v1
kind: NetworkAttachmentDefinition
metadata:
  name: ovn-dpdk
  namespace: default
spec:
  config: >-
    {
        "cniVersion": "0.3.0",
        "type": "kube-ovn",
```

```
        "server_socket": "/run/openvswitch/kube-ovn-daemon.sock",
        "provider": "ovn-dpdk.default.ovn",
        "vhost_user_socket_volume_name": "vhostuser-sockets",
        "vhost_user_socket_name": "sock"
    }
```

... Dockerfile ... VM ...

```
FROM quay.io/kubevirt/virt-launcher:v0.46.1

# wget http://cloud.centos.org/centos/7/images/CentOS-7-x86_64-GenericCloud.qcow2
COPY CentOS-7-x86_64-GenericCloud.qcow2 /var/lib/libvirt/images/CentOS-7-x86_64-GenericCloud.qcow2
```

...

```
apiVersion: v1
kind: ConfigMap
metadata:
  name: vm-config
data:
  start.sh: |
    chmod u+w /etc/libvirt/qemu.conf
    echo "hugetlbfs_mount = \"/dev/hugepages\"" >> /etc/libvirt/qemu.conf
    virtlogd &
    libvirtd &

    mkdir /var/lock

    sleep 5

    virsh define /root/vm/vm.xml
    virsh start vm

    tail -f /dev/null
  vm.xml: |
    <domain type='kvm'>
      <name>vm</name>
      <uuid>4a9b3f53-fa2a-47f3-a757-dd87720d9d1d</uuid>
      <memory unit='KiB'>2097152</memory>
      <currentMemory unit='KiB'>2097152</currentMemory>
      <memoryBacking>
        <hugepages>
          <page size='2' unit='M' nodeset='0'/>
        </hugepages>
      </memoryBacking>
      <vcpu placement='static'>2</vcpu>
      <cputune>
        <shares>4096</shares>
        <vcpupin vcpu='0' cpuset='4'/>
        <vcpupin vcpu='1' cpuset='5'/>
        <emulatorpin cpuset='1,3'/>
      </cputune>
      <os>
        <type arch='x86_64' machine='pc'>hvm</type>
        <boot dev='hd'/>
      </os>
      <features>
        <acpi/>
        <apic/>
      </features>
      <cpu mode='host-model'>
        <model fallback='allow'/>
        <topology sockets='1' cores='2' threads='1'/>
        <numa>
          <cell id='0' cpus='0-1' memory='2097152' unit='KiB' memAccess='shared'/>
        </numa>
      </cpu>
      <on_reboot>restart</on_reboot>
      <devices>
        <emulator>/usr/libexec/qemu-kvm</emulator>
        <disk type='file' device='disk'>
          <driver name='qemu' type='qcow2' cache='none'/>
          <source file='/var/lib/libvirt/images/CentOS-7-x86_64-GenericCloud.qcow2'/>
          <target dev='vda' bus='virtio'/>
        </disk>

        <interface type='vhostuser'>
          <mac address='00:00:00:0A:30:89'/>
          <source type='unix' path='/var/run/vm/sock' mode='server'/>
           <model type='virtio'/>
          <driver queues='2'>
            <host mrg_rxbuf='off'/>
          </driver>
        </interface>
        <serial type='pty'>
          <target type='isa-serial' port='0'>
            <model name='isa-serial'/>
          </target>
        </serial>
        <console type='pty'>
          <target type='serial' port='0'/>
```

```
        </console>
        <channel type='unix'>
          <source mode='bind' path='/var/lib/libvirt/qemu/channel/target/domain-1-vm/org.qemu.guest_agent.0'/>
          <target type='virtio' name='org.qemu.guest_agent.0' state='connected'/>
          <alias name='channel0'/>
          <address type='virtio-serial' controller='0' bus='0' port='1'/>
        </channel>

      </devices>
    </domain>
---
apiVersion: apps/v1
kind: Deployment
metadata:
  name: vm-deployment
  labels:
    app: vm
spec:
  replicas: 1
  selector:
    matchLabels:
      app: vm
  template:
    metadata:
      labels:
        app: vm
      annotations:
        k8s.v1.cni.cncf.io/networks: default/ovn-dpdk
        ovn-dpdk.default.ovn.kubernetes.io/ip_address: 10.16.0.96
        ovn-dpdk.default.ovn.kubernetes.io/mac_address: 00:00:00:0A:30:89
    spec:
      nodeSelector:
        ovn.kubernetes.io/ovs_dp_type: userspace
      securityContext:
        runAsUser: 0
      volumes:
        - name: vhostuser-sockets
          emptyDir: {}
        - name: xml
          configMap:
            name: vm-config
        - name: hugepage
          emptyDir:
            medium: HugePages-2Mi
        - name: libvirt-runtime
          emptyDir: {}
      containers:
        - name: vm
          image: vm-vhostuser:latest
          command: ["bash", "/root/vm/start.sh"]
          securityContext:
            capabilities:
              add:
                - NET_BIND_SERVICE
                - SYS_NICE
                - NET_RAW
                - NET_ADMIN
            privileged: false
            runAsUser: 0
          resources:
            limits:
              cpu: '2'
              devices.kubevirt.io/kvm: '1'
              memory: '8784969729'
              hugepages-2Mi: 2Gi
            requests:
              cpu: 666m
              devices.kubevirt.io/kvm: '1'
              ephemeral-storage: 50M
              memory: '4490002433'
          volumeMounts:
            - name: vhostuser-sockets
              mountPath: /var/run/vm
            - name: xml
              mountPath: /root/vm/
            - mountPath: /dev/hugepages
              name: hugepage
            - name: libvirt-runtime
              mountPath: /var/run/libvirt
```

▒▒▒▒▒▒▒▒▒▒▒▒▒ Pod ▒▒▒▒▒▒▒▒

```
# virsh set-user-password vm root 12345
Password set successfully for root in vm

# virsh console vm
Connected to domain 'vm'
Escape character is ^] (Ctrl + ])

CentOS Linux 7 (Core)
Kernel 3.10.0-1127.el7.x86_64 on an x86_64
```

```
localhost login: root
Password:
Last login: Fri Feb 25 09:52:54 on ttyS0
```

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

```
ip link set eth0 mtu 1400
ip addr add 10.16.0.96/16 dev eth0
ip ro add default via 10.16.0.1
ping 114.114.114.114
```

PDF Slack Support

2022▯7▯16▯

2022▯5▯24▯

GitHub 

7.20.6 ▯▯

2025 Kube-OVN Team

7.21 OpenStack ▯▯

▯▯▯▯▯▯▯▯▯▯▯▯▯ OpenStack ▯▯▯▯▯▯▯▯ Kubernetes ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ OpenStack Neutron ▯▯▯▯▯▯ OVN ▯▯▯▯▯▯▯▯▯▯▯▯▯ Kube-OVN ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ OVN ▯▯▯▯▯▯▯ OpenStack ▯ Kubernetes ▯▯▯▯▯

7.21.1 ▯▯▯▯▯

▯▯▯▯▯▯ OVN-IC ▯▯▯▯▯▯▯▯▯▯▯▯▯ Kubernetes ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

▒ OpenStack ▒▒ OVN ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

```
ovn-nbctl set NB_Global . name=op-az
```

▒▒▒▒ `OVN-IC` ▒▒▒▒▒▒▒▒▒ `OVN-IC` ▒▒▒▒

```
/usr/share/ovn/scripts/ovn-ctl --ovn-ic-nb-db=tcp:192.168.65.3:6645 \
  --ovn-ic-sb-db=tcp:192.168.65.3:6646 \
  --ovn-northd-nb-db=unix:/run/ovn/ovnnb_db.sock \
  --ovn-northd-sb-db=unix:/run/ovn/ovnsb_db.sock \
  start_ic
```

- `ovn-ic-nb-db` ▒ `ovn-ic-sb-db` : OVN-IC ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒
- `ovn-northd-nb-db` ▒ `ovn-northd-sb-db` : ▒▒▒▒ OVN ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

▒▒▒▒▒▒▒▒▒▒

```
ovs-vsctl set open_vswitch . external_ids:ovn-is-interconn=true
```

▒▒▒▒▒▒ OpenStack ▒ OVN ▒▒▒▒▒▒▒▒▒▒▒▒▒

▒▒ `ts` ▒▒▒▒▒▒▒ `router0` ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

```
ovn-nbctl lrp-add router0 lrp-router0-ts 00:02:ef:11:39:4f 169.254.100.73/24
ovn-nbctl lsp-add ts lsp-ts-router0 -- lsp-set-addresses lsp-ts-router0 router \
  -- lsp-set-type lsp-ts-router0 router \
  -- lsp-set-options lsp-ts-router0  router-port=lrp-router0-ts
ovn-nbctl lrp-set-gateway-chassis lrp-router0-ts {gateway chassis} 1000
ovn-nbctl set NB_Global . options:ic-route-adv=true options:ic-route-learn=true
```

▒▒▒▒▒▒ Kubernetes ▒▒▒▒▒▒

```
# ovn-nbctl lr-route-list router0
IPv4 Routes
               10.0.0.22            169.254.100.34 dst-ip (learned)
            10.16.0.0/16            169.254.100.34 dst-ip (learned)
```

▒▒▒▒▒▒ `router0` ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒ Kubernetes ▒ Pod ▒▒▒

7.21.2 ▒▒▒▒ OVN

▒▒▒▒▒▒OpenStack ▒ Kubernetes ▒▒▒▒▒▒▒▒ OVN▒▒▒▒▒▒▒▒▒▒ VPC ▒ Subnet ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

▒▒▒▒▒▒▒▒▒▒▒▒ Kube-OVN ▒▒ OVN▒OpenStack ▒▒ Neutron ▒▒▒▒▒▒▒▒▒▒ OVN ▒▒▒▒OpenStack ▒▒▒ networking-ovn ▒▒ Neutron ▒▒▒▒▒▒

Neutron ▒▒▒▒

▒▒ Neutron ▒▒▒▒ `/etc/neutron/plugins/ml2/ml2_conf.ini` ▒

```
[ovn]
...
ovn_nb_connection = tcp:[192.168.137.176]:6641,tcp:[192.168.137.177]:6641,tcp:[192.168.137.178]:6641
ovn_sb_connection = tcp:[192.168.137.176]:6642,tcp:[192.168.137.177]:6642,tcp:[192.168.137.178]:6642
ovn_l3_scheduler = OVN_L3_SCHEDULER
```

- `ovn_nb_connection` ▒ `ovn_sb_connection` : ▒▒▒▒▒▒▒ Kube-OVN ▒▒ `ovn-central` ▒▒▒▒▒▒▒

▒▒▒▒▒▒▒▒ OVS ▒▒▒

```
ovs-vsctl set open . external-ids:ovn-remote=tcp:[192.168.137.176]:6642,tcp:[192.168.137.177]:6642,tcp:[192.168.137.178]:6642
ovs-vsctl set open . external-ids:ovn-encap-type=geneve
ovs-vsctl set open . external-ids:ovn-encap-ip=192.168.137.200
```

- `external-ids:ovn-remote` : ▒▒▒▒▒▒▒ Kube-OVN ▒▒ `ovn-central` ▒▒▒▒▒▒▒
- `ovn-encap-ip` : ▒▒▒▒▒▒▒▒▒ IP ▒▒▒

2025 Kube-OVN Team

▒ **Kubernetes ▒▒▒ OpenStack ▒▒▒**

▒▒▒▒▒▒▒▒ Kubernetes ▒▒▒ OpenStack ▒▒▒▒▒▒▒ OpenStack ▒▒▒▒▒▒ Pod▒

> **Note**
>
> ▒▒▒▒▒▒▒▒ `kube-ovn-controller` ▒ args ▒▒▒▒▒▒▒ `--enable-external-vpc=true` ▒

▒▒ OpenStack ▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒▒

```
# openstack router list
+--------------------------------------+---------+--------+-------+----------------------------------+
| ID                                   | Name    | Status | State | Project                          |
+--------------------------------------+---------+--------+-------+----------------------------------+
| 22040ed5-0598-4f77-bffd-e7fd4db47e93 | router0 | ACTIVE | UP    | 62381a21d569404aa236a5dd8712449c |
+--------------------------------------+---------+--------+-------+----------------------------------+
# openstack network list
+--------------------------------------+----------+--------------------------------------+
| ID                                   | Name     | Subnets                              |
+--------------------------------------+----------+--------------------------------------+
| cd59e36a-37db-4c27-b709-d35379a7920f | provider | 01d73d9f-fdaa-426c-9b60-aa34abbfacae |
+--------------------------------------+----------+--------------------------------------+
# openstack subnet list
+--------------------------------------+-------------+--------------------------------------+----------------+
| ID                                   | Name        | Network                              | Subnet         |
+--------------------------------------+-------------+--------------------------------------+----------------+
| 01d73d9f-fdaa-426c-9b60-aa34abbfacae | provider-v4 | cd59e36a-37db-4c27-b709-d35379a7920f | 192.168.1.0/24 |
+--------------------------------------+-------------+--------------------------------------+----------------+
# openstack server list
+--------------------------------------+-------------------+--------+-----------------------+--------+--------+
| ID                                   | Name              | Status | Networks              | Image  | Flavor |
+--------------------------------------+-------------------+--------+-----------------------+--------+--------+
| 8433d622-a8d6-41a7-8b31-49abfd64f639 | provider-instance | ACTIVE | provider=192.168.1.61 | ubuntu | m1     |
+--------------------------------------+-------------------+--------+-----------------------+--------+--------+
```

▒ Kubernetes ▒▒▒▒ VPC ▒▒▒

```
# kubectl get vpc
NAME                                    STANDBY   SUBNETS
neutron-22040ed5-0598-4f77-bffd-e7fd4db47e93   true      ["neutron-cd59e36a-37db-4c27-b709-d35379a7920f"]
ovn-cluster                             true      ["join","ovn-default"]
```

`neutron-22040ed5-0598-4f77-bffd-e7fd4db47e93` ▒▒ OpenStack ▒▒▒▒▒ VPC ▒▒▒

▒▒▒▒▒▒▒ Kube-OVN ▒▒▒ VPC ▒ Subnet ▒▒▒▒ Pod ▒▒▒▒

VPC, Subnet ▒▒ Namespace `net2` ▒▒▒▒ Pod:

```yaml
apiVersion: v1
kind: Namespace
metadata:
  name: net2
---
apiVersion: kubeovn.io/v1
kind: Vpc
metadata:
  creationTimestamp: "2021-06-20T13:34:11Z"
  generation: 2
  labels:
    ovn.kubernetes.io/vpc_external: "true"
  name: neutron-22040ed5-0598-4f77-bffd-e7fd4db47e93
  resourceVersion: "583728"
  uid: 18d4c654-f511-4def-a3a0-a6434d237c1e
spec:
  namespaces:
  - net2
---
kind: Subnet
apiVersion: kubeovn.io/v1
metadata:
  name: net2
spec:
  vpc: neutron-22040ed5-0598-4f77-bffd-e7fd4db47e93
  namespaces:
    - net2
  cidrBlock: 12.0.1.0/24
  natOutgoing: false
---
apiVersion: v1
kind: Pod
metadata:
  name: ubuntu
```


2025 Kube-OVN Team

```
  namespace: net2
spec:
  containers:
    - image: docker.io/kubeovn/kube-ovn:v1.8.0
      command:
        - "sleep"
        - "604800"
      imagePullPolicy: IfNotPresent
      name: ubuntu
  restartPolicy: Always
```

PDF Slack Support

2025▯8▯4▯

2022▯5▯24▯

GitHub 

7.21.3 ▯▯

7.22 □□ IPsec □□□□□□□

Kube-OVN □□□□ OVN/OVS □□□ IPsec □□□□□□□□ Geneve□VXLAN □ STT □□□□□ IPsec □□□□ `kube-ovn-cni` Pod □□□□ `ipsec` □□ □□□CNI □□□□□□□□□□□ IKE/strongSwan□□□ CA Secret □□□□□ XFRM □□□

7.22.1 □□□□

- □□□□□□ UDP 500□IKE□□ UDP 4500□NAT-T□□
- □□□□□□ `xfrm` □ `af_key` □□□□□□□ OVN/OVS IPsec □□□ strongSwan □ libreswan □□□□
- Kube-OVN □□□□□□□□□□□ OVN/OVS □ IPsec agent□agent □□□□□ □□□□□□□□□□□□□□□□□□□ OVS monitor □□□□□□□□□□□□

7.22.2 □□□□□□□□□□

□□□□□□□□□ IPsec □□□□□□□ Pod □□□□□□□□□□□□□□□□

1. □□ `ENABLE_OVN_IPSEC=false` □□□□ Helm □□□□□□□ Kube-OVN□
2. □□ cert-manager □□ CA injector□□□□□□□□□□□□□□□□□□□ ClusterIssuer□□□□ cert-manager □□□ ClusterIssuer □ `Ready` □
3. □□ controller □ CNI DaemonSet □□□□□□□ Pod □□□□□□□ Kubernetes API□□□□ cert-manager □□ `hostNetwork` □
4. □□ controller □ CNI □ IPsec □□□□ `true` □□□□ rollout □□□

Kube-OVN □□ signer □□□□ cert-manager□□□□□□□□□□□□□□□□□ □ controller □□□□□□□□□□ Kubernetes CSR □□□□□controller □ □□□□ Pod□Node UID□chassis □□□□ CN/SAN □□□□□□□ cert-manager□ CNI ServiceAccount □□□□ CertificateRequest □□□□□□ controller □□ □□□□□ CSR □□□□□□ ClusterIssuer□

7.22.3 □□ IPsec

□□□□□□□□□

```
ENABLE_OVN_IPSEC=true
```

□□ Helm □□v1 chart □□ `func.ENABLE_OVN_IPSEC` □v2 chart □□ `features.enableOvnIpsec` □□□□□ cert-manager □□□□□□□ `--cert-manager-ipsec-cert=true` □v1□□ chart □□ `ipsec.certManager.enabled` □□□□□ issuer □□□□□□□□□□□□□□□□□□□□□□□□□ chart □ `ipsec` □□□□

□□□□CNI Pod □□□□□□□□□□ `ipsec` □□□□□ `/kube-ovn/kube-ovn-ipsec` □□□□□□ IPsec □□□□□□□□□□ IPsec □□ □ `NET_ADMIN` □ `NET_BIND_SERVICE` □ `SYS_NICE` □CNI □□□□□□ `SYS_NICE` □□□□□ IPsec □□□□□□□□□□□□□□Pod □ host network□ host PID □ ServiceAccount □□□□□□□ `ipsec` □□□□□□□ Kubernetes □□□

□□□□□ controller □□□□□□ DaemonSet UID□Pod □□□□□ bundle □ □□ Node UID□□□□□□□□□□□□□□□□□□□□ agent □□□□□□□□ □□□□□□□□□□□□□□ OVN □□□ IPsec □□□□□□□□□ Pod Ready □ □□□□ Node annotation □□□□□□□□CNI DaemonSet □□ `maxSurge: 0` □ `maxUnavailable: 1` □□□□□□□□□□□□□□□□□□□□□□□

7.22.4 □□□□□□□

IPsec agent □□□□□□□□□□CSR □□□□□□□□ generation□□□□□□□□□□ □□□ generation □□□□□ OVSDB □□□□□□□□□ `other_config` □□□□□□□□ □□□□□□□□□□□□□□□□□□ 40% □ 60% □□□□□□ □□□□□□□□□□□□□ □□□□□□□□□□□□□□□□□□□□□□□□agent □□ IKE □ monitor □□□□□□ □□□□□□□□ 1 □ 30 □□□□□

□□□□□□□□□□□ phase□reason□configurationApplied□runtimeHealthy□ protectionArmed□expires□□□ Node UID□chassis□generation □□□/□□□□□□□□□ PEM□□□□□ SA key□ `readyz` □□□□□□□□□□□□□□□□□□□□□□□□□□□ □□□□□□□□□□□□□□□ monitor □□□□□□□□□□□□□□□□□□□□□□□ SA □□□□□□□□IPsec □□□□□□□ Pod □□ NotReady□□□□□□□ CNI □□□

□□□□□□□□

```
kubectl get pods -n kube-system -l app.kubernetes.io/name=kube-ovn-cni
kubectl get csr
kubectl get clusterissuer
kubectl exec -n kube-system <kube-ovn-cni-pod> -c ipsec -- \
  ovs-appctl ipsec/show
```


2025 Kube-OVN Team

7.22.5 ████████

████████ Pod ██ `ipsec` ███████ controller ▯ CNI ▯ IPsec ████ `false` ▯controller ████ `Disabling` challenge██████ NB/SB ██████████████████ chart ██████ `ipsec` ████████ `ipsec-cleanup` init container▯

- ████ IPsec ████████████████ IKE/monitor███ CA█████ ███████
- ████████ root ████ `NET_ADMIN` ▯ `NET_BIND_SERVICE` ████ `SYS_NICE` ███ `restartPolicy` ▯probe ████████
- ███████ tunnel▯██████ SA ███ drain▯██████ Node UID▯ Pod UID▯CSR▯███ controller challenge▯██████████ owner ████ drain ██████████████████
- ███████████lease ████████ live ████████████████ output lease ███ guard▯██████ released receipt ██████████ owner ▯ SA▯policy ████

controller ████████████ receipt ████ `Disabled` ███ `maxUnavailable: 1` ███ rollout▯███████ init ████████ Pod▯ ███ Release epoch ████████████ init ████ Release barrier▯ controller ████ DaemonSet▯███████ Kubernetes ████████ ████████████████████████

7.22.6 ██████████

- `kubectl get csr` ▯▯ IPsec CSR ████ `kube-ovn-cni` Pod ▯ Node UID▯ ████████████████
- ▯▯ cert-manager ▯▯ClusterIssuer ████ Kube-OVN IPsec▯controller ▯ ▯▯ issuer▯namespace▯▯▯ ServiceAccount▯▯▯▯▯▯▯▯▯▯▯▯▯▯ ▯▯▯ cert-manager ▯▯ approver ████████
- controller ▯ Secret ▯ CertificateRequest ████████ namespace▯CSR ▯▯▯▯▯▯▯▯▯▯ signer ████████CNI ██████ CertificateRequest ▯▯▯▯
- ▯▯ `ovs-appctl ipsec/show` ▯ agent ▯ `readyz` ▯▯▯▯▯▯▯▯▯▯▯ monitor readback▯▯▯ guard ▯▯ UDP 500/4500 ███████ OVN/OVS ▯▯▯
- ██████ XFRM SA▯IPsec ████ `ovn-ipsec-coordination` ConfigMap▯ ████ controller ▯ agent ▯▯▯▯▯▯▯▯▯▯▯

PDF Slack Support

2026▯10▯29▯

2023▯4▯18▯

GitHub 

7.22.7 ▯▯

2025 Kube-OVN Team

7.23 OVN □□□□

□□□□□□□□ Pod□□□□□□□□□□□□ GRE/ERSPAN □□□□□□□□□□□□

> □□□□□ Kube-OVN □□□□□ v1.12□

7.23.1 □□ Multus-CNI

□□ Multus-CNI □□ □□ Multus□

7.23.2 □□□□□□□

□□□□□□□□□□□□□□□

```
apiVersion: "k8s.cni.cncf.io/v1"
kind: NetworkAttachmentDefinition
metadata:
  name: attachnet
  namespace: default
spec:
  config: |
    {
      "cniVersion": "0.3.1",
      "type": "kube-ovn",
      "server_socket": "/run/openvswitch/kube-ovn-daemon.sock",
      "provider": "attachnet.default.ovn"
    }
```

□□ `provider` □□□□□ `<NAME>.<NAMESPACE>.ovn` □

7.23.3 □□ Underlay □□

□□□□□□□□□□□□□□□□□□□□□□□□□□□MTU □□□□□□□□ LSP/Pod□□□□□□□ Underlay □□□□□□□

□□□□□□□□ Underlay □□□

```
apiVersion: kubeovn.io/v1
kind: ProviderNetwork
metadata:
  name: net1
spec:
  defaultInterface: eth1
---
apiVersion: kubeovn.io/v1
kind: Vlan
metadata:
  name: vlan1
spec:
  id: 0
  provider: net1
---
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
  name: subnet1
spec:
  protocol: IPv4
  cidrBlock: 172.19.0.0/16
  excludeIps:
  - 172.19.0.2..172.19.0.20
  gateway: 172.19.0.1
  vlan: vlan1
  provider: attachnet.default.ovn
```

□□□□□□ `provider` □□□□□□□□ `provider` □□□

7.23.4 □□□□□□ Pod

□□□□□□□□□□□□□□□□□□ Pod□

```
apiVersion: v1
kind: Pod
```

```
metadata:
  name: pod1
  annotations:
    k8s.v1.cni.cncf.io/networks: default/attachnet
spec:
  containers:
  - name: bash
    image: docker.io/kubeovn/kube-ovn:v1.17.0
    args:
    - bash
    - -c
    - sleep infinity
    securityContext:
      privileged: true
```

⬚⬚⬚⬚⬚⬚⬚⬚ Pod ⬚ IP ⬚⬚⬚

```
$ kubectl get ips | grep pod1
pod1.default                        10.16.0.12   00:00:00:FF:34:24  kube-ovn-worker  ovn-default
pod1.default.attachnet.default.ovn  172.19.0.21  00:00:00:A0:30:68  kube-ovn-worker  subnet1
```

⬚⬚⬚⬚⬚⬚⬚ IP ⬚⬚ `172.19.0.21` ⬚

7.23.5 ⬚⬚ OVN ⬚⬚⬚⬚

⬚⬚⬚⬚⬚⬚⬚⬚ OVN ⬚⬚⬚⬚⬚

```
kubectl ko nbctl mirror-add mirror1 gre 99 from-lport 172.19.0.21
kubectl ko nbctl lsp-attach-mirror coredns-787d4945fb-gpnkb.kube-system mirror1
```

⬚⬚ `coredns-787d4945fb-gpnkb.kube-system` ⬚ OVN LSP ⬚⬚⬚⬚⬚⬚⬚⬚ `<POD_NAME>.<POD_NAMESPACE>` ⬚

⬚⬚⬚ OVN ⬚⬚⬚⬚⬚⬚⬚⬚

```
ovn-nbctl mirror-add <NAME> <TYPE> <INDEX> <FILTER> <IP>

NAME   - add a mirror with given name
TYPE   - specify TYPE 'gre' or 'erspan'
INDEX  - specify the tunnel INDEX value
         (indicates key if GRE, erpsan_idx if ERSPAN)
FILTER - specify FILTER for mirroring selection
         ('to-lport' / 'from-lport')
IP     - specify Sink / Destination i.e. Remote IP

ovn-nbctl mirror-del [NAME]         remove mirrors
ovn-nbctl mirror-list               print mirrors

ovn-nbctl lsp-attach-mirror PORT MIRROR   attach source PORT to MIRROR
ovn-nbctl lsp-detach-mirror PORT MIRROR   detach source PORT from MIRROR
```

7.23.6 ⬚⬚⬚⬚⬚⬚ Pod

⬚⬚⬚⬚⬚⬚ Pod ⬚⬚⬚⬚⬚⬚⬚⬚

```
root@pod1:/kube-ovn# ip link add mirror1 type gretap local 172.19.0.21 key 99 dev net1
root@pod1:/kube-ovn# ip link set mirror1 up
```

⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ Pod ⬚⬚⬚⬚⬚⬚⬚⬚

```
root@pod1:/kube-ovn# tcpdump -i mirror1 -nnve
tcpdump: listening on mirror1, link-type EN10MB (Ethernet), snapshot length 262144 bytes
05:13:30.328808 00:00:00:a3:f5:e2 > 00:00:00:97:0f:6e, ethertype ARP (0x0806), length 42: Ethernet (len 6), IPv4 (len 4), Request who-has 10.16.0.7 tell
10.16.0.4, length 28
05:13:30.559167 00:00:00:a3:f5:e2 > 00:00:00:89:d5:cc, ethertype IPv4 (0x0800), length 212: (tos 0x0, ttl 64, id 57364, offset 0, flags [DF], proto UDP (17),
length 198)
    10.16.0.4.53 > 10.16.0.6.50472: 34511 NXDomain*- 0/1/1 (170)
05:13:30.559343 00:00:00:a3:f5:e2 > 00:00:00:89:d5:cc, ethertype IPv4 (0x0800), length 212: (tos 0x0, ttl 64, id 57365, offset 0, flags [DF], proto UDP (17),
length 198)
    10.16.0.4.53 > 10.16.0.6.45177: 1659 NXDomain*- 0/1/1 (170)
05:13:30.560625 00:00:00:a3:f5:e2 > 00:00:00:89:d5:cc, ethertype IPv4 (0x0800), length 200: (tos 0x0, ttl 64, id 57367, offset 0, flags [DF], proto UDP (17),
length 186)
    10.16.0.4.53 > 10.16.0.6.43848: 2636*- 0/1/1 (158)
05:13:30.562774 00:00:00:a3:f5:e2 > 00:00:00:89:d5:cc, ethertype IPv4 (0x0800), length 191: (tos 0x0, ttl 64, id 57368, offset 0, flags [DF], proto UDP (17),
length 177)
    10.16.0.4.53 > 10.16.0.6.37755: 48737 NXDomain*- 0/1/1 (149)
05:13:30.563523 00:00:00:a3:f5:e2 > 00:00:00:89:d5:cc, ethertype IPv4 (0x0800), length 187: (tos 0x0, ttl 64, id 57369, offset 0, flags [DF], proto UDP (17),
length 173)
    10.16.0.4.53 > 10.16.0.6.53887: 45519 NXDomain*- 0/1/1 (145)
05:13:30.564940 00:00:00:a3:f5:e2 > 00:00:00:89:d5:cc, ethertype IPv4 (0x0800), length 201: (tos 0x0, ttl 64, id 57370, offset 0, flags [DF], proto UDP (17),
```

```
length 187)
    10.16.0.4.53 > 10.16.0.6.40846: 25745 NXDomain*- 0/1/1 (159)
05:13:30.565140 00:00:00:a3:f5:e2 > 00:00:00:89:d5:cc, ethertype IPv4 (0x0800), length 201: (tos 0x0, ttl 64, id 57371, offset 0, flags [DF], proto UDP (17),
length 187)
    10.16.0.4.53 > 10.16.0.6.45214: 61875 NXDomain*- 0/1/1 (159)
05:13:30.566023 00:00:00:a3:f5:e2 > 00:00:00:55:e4:4e, ethertype IPv4 (0x0800), length 80: (tos 0x0, ttl 64, id 45937, offset 0, flags [DF], proto UDP (17),
length 66)
    10.16.0.4.44116 > 172.18.0.1.53: 16025+ [1au] AAAA? kube-ovn.io. (38)
```

7.23.7 ▯▯▯▯

1. ▯▯▯▯ ERSPAN ▯▯▯▯▯▯▯OVN ▯▯▯▯▯▯▯▯ Linux ▯▯▯▯▯▯▯▯ 4.14▯▯▯▯ ERSPAN ▯▯▯▯▯▯▯▯▯ IPv6 ▯▯▯▯▯▯▯Linux ▯▯▯▯▯▯▯▯ 4.16▯
2. ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ OVN ▯▯▯▯▯▯▯▯▯▯▯▯▯▯

PDF Slack Support

2025▯7▯2▯

2023▯4▯20▯

GitHub



7.23.8 ▯▯

2025 Kube-OVN Team

7.24 □□□□ DNS □□□ Kube-OVN □□

NodeLocal DNSCache □□□□□□□□□□ DaemonSet □□ DNS □□□□□□□□ DNS □□□□□□□□□□□ Kube-OVN □□□

7.24.1 □□□□ DNS □□□□

□□ Kubernetes □□□□□ DNS □□

□□□□□ Kubernetes □□□□ Nodelocaldnscache□

□□□□□□□□□□

```
#!bin/bash

localdns=169.254.20.10
domain=cluster.local
kubedns=10.96.0.10

wget https://raw.githubusercontent.com/kubernetes/kubernetes/master/cluster/addons/dns/nodelocaldns/nodelocaldns.yaml
sed -i "s/__PILLAR__LOCAL__DNS__/$localdns/g; s/__PILLAR__DNS__DOMAIN__/$domain/g; s/,__PILLAR__DNS__SERVER__//g; s/__PILLAR__CLUSTER__DNS__/$kubedns/g"
nodelocaldns.yaml

kubectl apply -f nodelocaldns.yaml
```

□□□□□□□□ kubelet □□□□□□□ `/var/lib/kubelet/config.yaml` □□ clusterDNS □□□□□□□□ DNS IP 169.254.20.10□□□□□ kubelet □□□

Kube-OVN □□ DNS □□

□□□ Kubernetes □ Nodelocal DNScache □□□□Kube-OVN □□□□□□□□□

UNDERLAY SUBNET □□ U2O □□

□□□ Underlay Subnet □□□□□□□ DNS □□□□□□□□ U2O □□□□□ `kubectl edit subnet {your subnet}` □□□□ `spec.u2oInterconnection = true` , □□□ Overlay Subnet □□□□□□□□□□

□ KUBE-OVN-CONTROLLER □□□□□□□□ DNS IP

```
kubectl edit deployment kube-ovn-controller -n kube-system
```

□ `spec.template.spec.containers.args` □□□□□ `--node-local-dns-ip=169.254.20.10`

□□□□□□□□ POD

□□□□□□ Pod □□□□ `/etc/resolv.conf` □ nameserver □□□□ DNS IP□□□□□□□□ Pod □ nameserver □□□□□□□□□ DNS ClusterIP□□□ u2o □□□□□□□□□□□□ Pod □□□□□ Pod □ □□

7.24.2 □□□□□□□ DNS □□□□

□□□□□□□□□□□□ Pod □□□□□□□□□□ Pod □ DNS □□□□□□□□□ 169.254.20.10□□□□□□□□□□

```
# kubectl exec -it pod1 -- nslookup github.com
Server:         169.254.20.10
Address:        169.254.20.10:53


Name:   github.com
Address: 20.205.243.166
```

□□□□□□□□□□□□□□□□□□□ DNS □□□□□□□ ovn0 □□□□□□□□ DNS □□□DNS □□□□□□□□□□

```
# tcpdump -i any port 53

06:20:00.441889 659246098c56_h P   ifindex 17 00:00:00:73:f1:06 ethertype IPv4 (0x0800), length 75: 10.16.0.2.40230 > 169.254.20.10.53: 1291+ A? baidu.com.
(27)
06:20:00.441889 ovn0  In  ifindex 7 00:00:00:50:32:cd ethertype IPv4 (0x0800), length 75: 10.16.0.2.40230 > 169.254.20.10.53: 1291+ A? baidu.com. (27)
06:20:00.441950 659246098c56_h P   ifindex 17 00:00:00:73:f1:06 ethertype IPv4 (0x0800), length 75: 10.16.0.2.40230 > 169.254.20.10.53: 1611+ AAAA?
baidu.com. (27)
06:20:00.441950 ovn0  In  ifindex 7 00:00:00:50:32:cd ethertype IPv4 (0x0800), length 75: 10.16.0.2.40230 > 169.254.20.10.53: 1611+ AAAA? baidu.com. (27)
06:20:00.442203 ovn0  Out ifindex 7 00:00:00:52:99:d8 ethertype IPv4 (0x0800), length 145: 169.254.20.10.53 > 10.16.0.2.40230: 1611* 0/1/0 (97)
```

```
06:20:00.442219 659246098c56_h Out ifindex 17 00:00:00:ea:b3:5e ethertype IPv4 (0x0800), length 145: 169.254.20.10.53 > 10.16.0.2.40230: 1611* 0/1/0 (97)
06:20:00.442273 ovn0  Out ifindex 7 00:00:00:52:99:d8 ethertype IPv4 (0x0800), length 125: 169.254.20.10.53 > 10.16.0.2.40230: 1291* 2/0/0 A 39.156.66.10, A
110.242.68.66 (77)
06:20:00.442278 659246098c56_h Out ifindex 17 00:00:00:ea:b3:5e ethertype IPv4 (0x0800), length 125: 169.254.20.10.53 > 10.16.0.2.40230: 1291* 2/0/0 A
39.156.66.10, A 110.242.68.66 (77)
```

7.24.3 ████

⚠️ ███

████████ NetworkPolicy██████ NetworkPolicy ███████ DNS IP██ 169.254.20.10████ CIDR████ NetworkPolicy ██ DNS ██████████ Pod ██████████

NetworkPolicy ████

███████ Pod ████ DNS ████████ NetworkPolicy ████

```yaml
apiVersion: networking.k8s.io/v1
kind: NetworkPolicy
metadata:
  name: allow-local-dns-and-node-cidr
  namespace: default  #
spec:
  podSelector: {}  #       Pod
  policyTypes:
  - Ingress
  - Egress
  egress:
  #       DNS
  - to:
    - ipBlock:
        cidr: 169.254.20.10/32
  #       CIDR          CIDR
  - to:
    - ipBlock:
        cidr: 10.0.0.0/8  #      CIDR
  ingress:
  #       DNS
  - from:
    - ipBlock:
        cidr: 169.254.20.10/32
  #       CIDR              CIDR
  - from:
    - ipBlock:
        cidr: 10.0.0.0/8  #      CIDR
```

████

- `169.254.20.10/32` ███ DNS ███ IP ██
- `10.0.0.0/8` ████ CIDR████████████████████

PDF Slack Support

2025年7月3日

2023年5月5日



GitHub 



7.24.4 ██

2025 Kube-OVN Team

7.25 □□ VPC NAT □□□□

7.25.1 □□

□□ VPC □□ Overlay □□□□□ `natOutgoing` □□□□Subnet □□□□ Pod □□□□□□□□ SNAT □□□□ IP□□□□□□□□□□□□□□□□□□□□ Pod □□□□□□ SNAT□

□□ NAT □□□□□□□□□□□□□□□□□□□□□□□□□□□□ CIDR □□ IP □□□□□ SNAT□

7.25.2 □□□□

□ `subnet.Spec` □□□ `natOutgoing` □□□ □□□□□□ `natOutgoingPolicyRules` □□□

```
spec:
  natOutgoing: true
  natOutgoingPolicyRules:
    - action: forward
      match:
        srcIPs: 10.0.11.0/30,10.0.11.254
    - action: nat
      match:
        srcIPs: 10.0.11.128/26
        dstIPs: 114.114.114.114,8.8.8.8
```

□□□□□□□□□ NAT □□□□□

1. □ IP □ 10.0.11.0/30 □□ 10.0.11.254 □□□□□□□□□□□ SNAT□
2. □ IP □ 10.0.11.128/26 □□□□ IP □ 114.114.114.114 □□ 8.8.8.8 □□□□□□□□□□ SNAT□

□□□□□

`action` □□□ `match` □□□□□□□□□□□□□ action, action □□□□ `forward` □ `nat` □ `forward` □□□□□□□□□□ SNAT, `nat` □□□□□□□□ SNAT□ □□□□ natOutgoingPolicyRules □□□ □□□□□□□□□□ SNAT□

`match` □□□□□□□□□□□□□□□□ `srcIPs` □ `dstIPs` □ □□□□□□□□□□□□□□□□□□□□□□ IP □ □□ IP□ `match.srcIPs` □ `match.dstIPs` □□□□ CIDR □ IP□□□□□□□□□□

□□□□□□ match □□□□□□□□□ `natOutgoingPolicyRules` □□□□□□□□□□□□□□□□ action □□□□□

PDF Slack Support

2023□10□25□

2023□6□5□

GitHub 

7.25.3 □□

2025 Kube-OVN Team

8. □□□□

8.1 □□□□

□□□□□□ Kube-OVN □□□□□□□□□□□□□□□□□□□□□□□□□□□□


□□□□□Kube-OVN □□ Kubernetes □ OVN □□□□□□□□□□□□□ SDN □□□□□□□□□ □□□□□ Kube-OVN □□□□□ OVN □□□□ Kubernetes □□□□□□□□□□ CNI□Service □ Networkpolicy□□□□□ □□ SDN □□□□□□□□□□□□□□□□□□□□□□□□□□□□□VPC□□□□QoS□ACL □□□□□□□

□□ Kube-OVN □□□□□□□□□□□□□□□□□□□□□□□□□□□□ Cilium□Submariner□Prometheus□KubeVirt □□□

8.1.1 □□□□

Kube-OVN □□□□□□□□□□□□□□

- □□ OVN/OVS □□□
- □□□□□□□ Agent□
- □□□□□□□□□□□□□□□



□□ **OVN/OVS** □□

□□□□□□□ OVN/OVS □□□□□□ Kube-OVN □□□□□□□□□□□□□□OVN/OVS □□□□□□□□□□□□□□□□□□ SDN □□□□□□□□□□ □ Kube-OVN □□□□□□□□□□□□□□□ ovn-architecture(7) □□□□□□□ OVN □□ □□□□□□□□□□Kube-OVN □□ OVN □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□ Kubernetes □□□

□□ OVN/OVS □□□□□□□□□□□□□□□□□□□ Kubernetes □□□□□

OVN-CENTRAL

`ovn-central` Deployment □□ OVN □□□□□□□□□□□ `ovn-nb`, `ovn-sb`, □ `ovn-northd` □

- `ovn-nb` □□□□□□□□□□□□□□□ API □□□□□□□□□□ `kube-ovn-controller` □□□□□□ `ovn-nb` □□□□□□□□□□

2025 Kube-OVN Team

- `ovn-sb` ████ `ovn-nb` ████████████████████████████████
- `ovn-northd` ██ `ovn-nb` ████████ `ovn-sb` ███████

██ `ovn-central` ████ Raft ████████████

OVS-OVN

`ovs-ovn` ▯ DaemonSet ██████████ Pod ████ `openvswitch`, `ovsdb`, ▯ `ovn-controller` ███████ `ovn-central` ▯ Agent ██████████████

██████ Agent

████ Kube-OVN ████████ OVN ▯ Kubernetes ████████████████████████████ ████████████████

KUBE-OVN-CONTROLLER

██████ Deployment ████ Kubernetes ████ OVN ██████████████ Kube-OVN ████████ `kube-ovn-controller` ████████████████████████████ OVN ████ ████████████ Pod▯Service▯Endpoint▯Node▯NetworkPolicy▯VPC▯Subnet▯Vlan▯ProviderNetwork▯

▯ Pod ████ `kube-ovn-controller` ███ Pod ████████████ IPAM ██████████ `ovn-central` ██ ████████████ ACL ██████ `kube-ovn-controller` ██████ ████████ CIDR████████████ Pod ▯ annotation ███ annotation ████ `kube-ovn-cni` ████████████

KUBE-OVN-CNI

██████ DaemonSet ████████████ CNI ██████████ OVS ███████

▯ DaemonSet ███ `kube-ovn` ████████████ `kubelet` ▯ `kube-ovn-cni` ████████████ CNI ██ ███ `kube-ovn-cni` ████████████████ `/opt/cni/bin` ████

`kube-ovn-cni` ████████████████████████████

1. ██ `ovn-controller` ▯ `vswitchd` ▯
2. ██ CNI add/del ███
   a. ████ veth ██ OVS ████
   b. ██ OVS ████
   c. ██████ iptables/ipset/route ████
3. ██████ QoS.
4. ████ `ovn0` ████████████████
5. ██████████ Vlan/Underlay/EIP ████
6. ████████████

██████████████

████████████████████████████ Kube-OVN ████████████████████████

KUBE-OVN-SPEAKER

██████ DaemonSet ██ Pod IP ████

████████████ BGP ███

KUBE-OVN-PINGER

██████ DaemonSet ██████████ OVS ████████████████████████████████ Kube-OVN ████▯

KUBE-OVN-MONITOR

██████ Deployment ██ OVN ██████████████████ Kube-OVN ████▯

KUBECTL-KO

████ kubectl ████████████████████████ kubectl ████▯

2025 Kube-OVN Team

PDF Slack Support

2025⬚9⬚10⬚

2022⬚5⬚24⬚

GitHub







8.1.2 ⬚⬚

8.2 What's Next

This document lists the features merged into the master branch for the next minor release.

8.2.1 Post-v1.16.0

- Add routed subnet mode with `/32` IPv4 or `/128` IPv6 Pod addresses and gateway hairpinning through the OVN logical router. #7294
- Add experimental NetworkPolicy ACL sampling with node-local decoding and `kubectl ko acl` troubleshooting commands. #7172
- QoS: support configurable ingress/egress burst limits via per-NIC annotations (`ovn.kubernetes.io/ingress_burst` and `ovn.kubernetes.io/egress_burst`). #6628
- VPC Egress Gateway: accept integer Mbps values and `M`, `Mi`, `G`, or `Gi` bit-rate quantities for per-replica bandwidth limits. #7115
- VPC NAT Gateway: allow placing the NAT gateway StatefulSet and its iptables-EIP custom resources in a user-specified namespace. #6595
- iptables-EIP: surface the bound external subnet in the `kubectl get iptables-eip` printer. #6672
- Helm Chart (kube-ovn-v2): ship PrometheusRule and Grafana dashboards out of the box. #6630

8.2.2 Post-v1.15.0

- NetworkPolicy now supports provider-scoped policies for multi-network pods using the `ovn.kubernetes.io/policy-for` annotation. #6223
- Support static IP/MAC for multiple interfaces on the same logical switch. #6060
- MetalLB underlay integration now supports IPv6 and dual-stack. #6159
- KubeVirt live-migration multi-chassis options now apply to all VM NICs, not just the primary one. #6241
- Add human-readable descriptions to all Kube-OVN CRD fields for better `kubectl explain` output. #6133 #6147
- Support BGP and EVPN (L3VPN) for VPC Egress Gateway, running FRR in the egress gateway Pod. #6224
- Support per-pod NIC granular DHCP control via annotations, overriding subnet-level DHCP settings. #6475
- Extend SecurityGroup API with tiers, larger priority range (1-16384), localAddress and port matches. #6330
- Use BigInt for SubnetStatus IP count fields to support large address ranges. #6403
- Improve hairpin logic to support FIP, SNAT from any CIDR within the VPC and LoadBalancers. #6445
- VPC NAT Gateway
- Support user-defined annotations on NAT gateway Pod template. #6256
- Allow SNAT EIP to FIP EIP traffic. #6329
- Allow any EIP to share external subnet gateway in one native VLAN. #6426
- VPC Egress Gateway
- Support custom resources and bandwidth limits. #6407
- Interconnection
- Add vendor ID to transit switches to avoid conflicts with other OVN controllers. #6186
- Reliability
- OpenFlow synchronization: detect and recover from stale or missing OVS flows automatically. #6117
- OVN DB: back up Raft header before rejoining cluster to improve recovery. #6106
- Performance
- Strip `managedFields` from informer cache to reduce memory usage. #6119
- Add field selectors to informer factory to reduce API server load. #6091
- Security
- Replace wildcard RBAC verbs with explicit verb lists. #6233
- Specify ephemeral storage limits for containers. #6259

2025 Kube-OVN Team

- Helm Chart
- Make DaemonSet update strategy configurable via `values.yaml`. #6136
- Introduce `extraEnv` variable for all components. #6142
- Add `affinity` and `nodeSelector` support for ovs-ovn and ovs-ovn-dpdk DaemonSets. #6308
- Add `external-gateway-config-ns` option for controller. #6211
- Introduce ServiceMonitor and labels to services. #6340

8.2.3 Post-v1.14.0

- ACL log supports ratelimiting. #5938
- Subnet with centralized gateway now supports nodeSelectors. #5956
- Overlay encapsulation NIC selection. #5946
- Performace: skip conntrack for specific dst CIDRs. #5821
- NetworkPolicy supports `lax` mode which only deny traffic type of TCP, UDP and SCTP. That means ARP, ICMP and DHCP traffic are alaways allowed. #5745
- Remove internal-port type interface code. #5794
- IPPool
- Multiple IPPools now can bind to the same Namespace. #5731
- Pods in a bound namespace will only get IPs from the bound pool(s), not other ranges in the subnet. #5731
- IPPool will create an AddressSet that can be work with VPC Policy Route and ACL. #5920
- `AdminNetworkPolicy` now supports specify egress peers using FQDNs. #5703
- Using ARP for IPv4 network ready check: now you don't need ACL allow rules for gateway to make Pod running. #5716
- Non-primary CNI mode: you can run Kube-OVN as the secondary only network, without annoying unused annotations and logical switch port allocations. #5618
- VPC NAT Gateway:
- No default EIP mode: the secondary interface can initialize without a default EIP to avoid the waste. #5605
- Custom routes: you can control the route rules within the vpc-nat-gateway Pods to control traffic paths. #5608
- Gratuitous ARP: VPC NAT Gateway automatically sends gratuitous ARP packets during initialization to accelerate network convergence. #5607
- Healthchecks for static endpoints in `SwitchLBRules`: SLR with both selector or endpoints key can support healthchecks. #5435
- Underlay
- Node Selectors for `ProviderNetwork`: instead of adding/removing nodes to the `ProviderNetwork` one by one, you can use node selectors to simplify the workflow. #5518
- Different `NetworkProvider`s can now share the same VLAN. #5471
- Auto create VLAN sub-interfaces. #5966
- Auto move VLAN sub-interfaces to OVS bridges. #5949
- Adding `pod_name` and `pod_namespace` labels to interface metrics. #5463
- IPSec
- Support `cert-manager` to issue certificates. #5365
- Request new certificate if current certificate is not trusted. #5710
- kubectl-ko
- Collect IPSec and xFRM information. #5472
- Replace `Endpoint` with `EndpointSlice`. #5425
- NetworkAttachment caching: reduce APIServer load in large-scale deployments with Multus. #5386
- Upgrade `OVS` to 3.5 and `OVN` to 25.03. #5537

2025 Kube-OVN Team

PDF Slack Support

2026⬚10⬚29⬚

2025⬚9⬚15⬚



GitHub 



8.2.4 ⬚⬚

8.3 ████████

██████████████████Kube-OVN ██████ ██ ████████████████

8.3.1 ███████

Kube-OVN ██████████████████

1. `default` ██████ Pod ██ IP ████████████ CIDR ▯ `10.16.0.0/16` ████ `10.16.0.1` ▯
2. `join` ██████ Node ▯ Pod ████████████████, ██ CIDR ▯ `100.64.0.0/16` ████ `100.64.0.1` ▯

████████████████████████

```
POD_CIDR="10.16.0.0/16"
POD_GATEWAY="10.16.0.1"
JOIN_CIDR="100.64.0.0/16"
EXCLUDE_IPS=""
```

`EXCLUDE_IP` ███ `POD_CIDR` ██████████████████ 192.168.10.20..192.168.10.30 ▯

████ Overlay ████████████████████ Service CIDR ███

████████████████████████████████████ Join ███

8.3.2 Service ████

████ `kube-proxy` ███ iptables ███████ Kube-OVN ████████████ Kube-OVN ████ Service ▯ CIDR ████████████

████████████████

```
SVC_CIDR="10.96.0.0/12"
```

███████

████████████ `kube-ovn-controller` Deployment ████

```
args:
- --service-cluster-ip-range=10.96.0.0/12
```

███████

8.3.3 Overlay ████

██████████████████Kube-OVN ██████ Kubernetes Node IP ████████████████████████████████

████████████████████████████████████

```
IFACE=eth1
```

████████████████████ `ens[a-z0-9]*,eth[a-z0-9]*` ▯

██████████ `kube-ovn-cni` DaemonSet ██████████

```
args:
- --iface=eth1
```

████████████████████████████████ annotation `ovn.kubernetes.io/tunnel_interface` ██████████████████ annotation ██████ `iface` ████████ annotation▯

```
kubectl annotate node no1 ovn.kubernetes.io/tunnel_interface=ethx
```

████████████████████ Overlay ██████████▯

2025 Kube-OVN Team

⬚⬚ `/32` ⬚⬚⬚⬚⬚⬚

⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ `/32` ⬚ `/128` ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

8.3.7 NetworkPolicy ⬚⬚⬚⬚

Kube-OVN ⬚⬚ OVN ⬚⬚ ACL ⬚⬚⬚ NetworkPolicy⬚⬚⬚⬚⬚⬚⬚⬚ NetworkPolicy ⬚⬚ ⬚⬚⬚⬚ Cilium Chain ⬚⬚⬚⬚⬚ eBPF ⬚⬚ NetworkPolicy⬚ ⬚⬚⬚⬚⬚⬚⬚⬚⬚ Kube-OVN ⬚ NetworkPolicy ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

```
ENABLE_NP=false
```

⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ `kube-ovn-controller` Deployment ⬚⬚⬚⬚⬚⬚⬚⬚

```
args:
- --enable-np=false
```

NetworkPolicy ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

8.3.8 EIP ⬚ SNAT ⬚⬚⬚⬚

⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ EIP ⬚ SNAT ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ `kube-ovn-controller` ⬚⬚⬚⬚⬚⬚ ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

```
args:
- --keep-vm-ip=false
```

8.3.12 CNI ⬚⬚⬚⬚⬚⬚

Kube-OVN ⬚⬚⬚⬚ `/opt/cni/bin` ⬚⬚⬚⬚⬚ CNI ⬚⬚⬚⬚⬚⬚ `/etc/cni/net.d` ⬚⬚⬚⬚⬚ CNI ⬚⬚⬚⬚ `01-kube-ovn.conflist` ⬚ ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ CNI ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

8.3.15 SSL ⬚⬚

OVN NB/SB ⬚⬚⬚ API ⬚ Kube-OVN secure-serving ⬚⬚⬚⬚⬚ TLS⬚TLS ⬚⬚⬚⬚⬚ ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ OVN central/DB ⬚ TLS⬚⬚⬚⬚ secure-serving ⬚⬚⬚⬚ TLS ⬚⬚⬚ cipher suites⬚

```
ENABLE_SSL=true
TLS_MIN_VERSION="TLS12"
TLS_MAX_VERSION="TLS13"
TLS_CIPHER_SUITES="TLS_ECDHE_RSA_WITH_AES_128_GCM_SHA256,TLS_AES_128_GCM_SHA256"
```

`TLS_MIN_VERSION` ⬚ `TLS_MAX_VERSION` ⬚⬚ `TLS10` ⬚ `TLS11` ⬚ `TLS12` ⬚ `TLS13` ⬚ ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

```
networking:
  ENABLE_SSL: true
  KUBE_OVN_TLS_ROTATION_INTERVAL: 8760h
```

classic Chart □□ `installMode: dataPlaneOnly` □□□□□□□□□□ `0` □□□ `kube-ovn-tls` □□□□□□□□□□□□□□

v2 Chart□ `charts/kube-ovn-v2` □□□ camel case □□

```
networking:
  enableSsl: true
  kubeOvnTlsRotationInterval: 8760h
```

Secret □□□□ `ovn-central` □ `ovs-ovn` □□ OVN □□□□ Kube-OVN □ Go client □□□□□□□□□□□□□□□□□□ TLS □□□□□□□□□□□□□□□□□□ Kube-OVN Pod□□□□□ `kube-ovn-tls` □ `kube-ovn.io/kube-ovn-tls-cert-hash` annotation□□□□□□ Pod □□□□□□□□□□ adoption □□□□□□□□

8.3.16 □□ conntrack □□□ CIDR □□

□□□□□□□□ conntrack □□□□□□□□□□□□□□□□□□□□ NAT/□□□□□□□□□□□□□□□□□□□□ `kube-ovn-controller` □□□□□□□□□□□□□□□ CIDR □□□□□□□

```
SKIP_CONNTRACK_DST_CIDRS="10.10.0.0/16,fd00:10::/64"
```

```
args:
- --skip-conntrack-dst-cidrs=10.10.0.0/16,fd00:10::/64
```

□□□□□□

8.3.17 □□ OVN IPSec

□□□ Kube-OVN □□□ OVN □□□ IPSec □□□□□□□□ Geneve/Vxlan/STT □□□□□□□□□□□□□□□□□□

```
ENABLE_OVN_IPSEC=true
```

□□□□ daemon □□□□□□□□□□

```
args:
- --enable-ovn-ipsec=true
```

□□□□□□ OVN IPSec□

8.3.18 AdminNetworkPolicy / DNS □□□□□□□

□□ AdminNetworkPolicy□ANP/CNP□□□□□ DNS □□□□□□□□□□□ `DNSNameResolver` CRD□□

```
ENABLE_ANP=true
ENABLE_DNS_NAME_RESOLVER=true
```

```
args:
- --enable-anp=true
- --enable-dns-name-resolver=true
```

□□□□□□□□□□□□□□□

8.3.19 VPC NAT Gateway □□□

□□□□□□ VPC NAT Gateway □□ controller□□□□□□

```
ENABLE_NAT_GW=true
```

□□ `ovn-vpc-nat-gw-config` ConfigMap □□□ `enable-vpc-nat-gw` □□□□□□□□□□□

8.3.20 ovn-northd □□□

□□□□□□□□□□□□ `ovn-northd` □□□□□□□□□□□□□□□

2025 Kube-OVN Team

```
OVN_NORTHD_N_THREADS=4
```

⬚⬚ 1⬚⬚⬚⬚⬚⬚ CPU ⬚⬚⬚⬚⬚

8.3.21 NetworkPolicy ⬚⬚⬚⬚

Kube-OVN ⬚⬚ `standard` / `lax` ⬚⬚ NetworkPolicy ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

```
NP_ENFORCEMENT=standard
```

```
args:
- --np-enforcement=standard
```

⬚⬚⬚⬚⬚ NetworkPolicy ⬚⬚⬚ `ovn.kubernetes.io/network_policy_enforcement` annotation ⬚⬚⬚⬚⬚ NetworkPolicy ⬚⬚⬚

8.3.22 VXLAN ⬚⬚ TX checksum offload

⬚⬚⬚⬚ VXLAN ⬚⬚⬚⬚⬚⬚ checksum offload ⬚⬚⬚⬚⬚⬚⬚⬚⬚

```
SET_VXLAN_TX_OFF=true
```

```
args:
- --set-vxlan-tx-off=true
```

8.3.23 KubeVirt ⬚⬚⬚⬚⬚⬚

⬚⬚⬚⬚⬚⬚⬚⬚⬚ KubeVirt ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

```
- --leader-elect-renew-deadline=20s
- --leader-elect-retry-period=6s
```

... `30s` ... `20s` ... `6s` ... duration...controller ... Kubernetes client ...

- `lease-duration` ... `renew-deadline` ...
- `renew-deadline` ... `retry-period` ... Kubernetes client-go leader election ... jitter factor... `1.2` ...

...

```
export LEADER_ELECT_LEASE_DURATION=1m
export LEADER_ELECT_RENEW_DEADLINE=40s
export LEADER_ELECT_RETRY_PERIOD=10s
bash install.sh
```

Helm ... chart ...classic chart ... `kube-ovn-controller.leaderElection` ...

```
kube-ovn-controller:
  leaderElection:
    leaseDuration: "30s"
    renewDeadline: "20s"
    retryPeriod: "6s"
```

v2 chart ... `controller.leaderElection` ...

```
controller:
  leaderElection:
    leaseDuration: "30s"
    renewDeadline: "20s"
    retryPeriod: "6s"
```

8.3.28 kube-ovn-monitor ...

`kube-ovn-monitor` ... Helm ... Deployment ...

```
# classic chart
kube-ovn-monitor:
  replicas: 1

# v2 chart
monitor:
  replicas: 1
```

classic chart ... `kube-ovn-monitor.replicas` ...v2 chart ... `monitor.replicas` ... `1` ... OVN central ... central ... OVN Raft ... `kube-ovn-monitor` ...

... Deployment ... master ... Pod ... master ... central ... Pod ... `Pending` ...

... Helm ... Deployment... chart ... `1` ... Helm values ... `kubectl scale` ... Deployment...

8.3.29 ... ip

kube-ovn-controller/kube-ovn-cni/kube-ovn-monitor ... ip... 0.0.0.0 ... ip ...

```
ENABLE_BIND_LOCAL_IP=true
```

... kube-ovn-monitor ... pod ip ...

```
# netstat -tunlp |grep kube-ovn
tcp        0      0 172.18.0.5:10661        0.0.0.0:*               LISTEN      2612/./kube-ovn-mon
```

... deployment ... daemonSet ...

```
env:
- name: ENABLE_BIND_LOCAL_IP
  value: "false"
```


2025 Kube-OVN Team

PDF Slack Support

2026⬚10⬚28⬚

2022⬚5⬚24⬚

GitHub



8.3.30 ⬚⬚

8.4 □□□□

Kube-OVN □□□□□□ Minor □□□ Patch □□□Minor □□□□□□□□□□□□OVN/OVS □□□□□□□□□□□□□API □□□Patch □□□□□□ Bug □□□□□□□□□□□□□□□□□□□□□□□□□ API□

8.4.1 □□□□

Kube-OVN □□□□□□□□□□□□□□□□□□□□□□□□□□ `master`, `release-1.12` □ `release-1.11` □□□□□□□□□□□□□ `release-1.12` □□□□□□□□□□□□□□□□□□ Bug □□□□□□□□□□□□□□□□□□□ backport □□□□□□□□□

□□□□□□□□□□□ `release-1.11` □□ backport □□□□□ Bug □□□□□□□□□□□□□□□□□□□

8.4.2 □□□□

Minor □□Patch □□□□□□ Bug □□□□□□□□□□□□ Bug □□□□□□□□□□□□

8.4.3 Patch □□□□□□

□□ Patch □□□□□□□□□□□□□ hack/release.sh □□□□□□□□□□□□□□□□□□□□□□□□□□□□

1. □□□□□□ Build □□□□□□□□
2. □□□ tag □□□ Docker Hub□□□□□
3. □□□ tag □□□ Github□□□□□
4. □□□□□□□□□□□□□□□□□
5. □□□□□□□□□□□□□□□□□
6. □□ Release Note PR□□□□□
7. □□ Release Note (□□)
8. □□ Merge github action □□□ Release Note PR
9. □□ Github Release □□□□□□
10. □ Github Release □□□□□□□□ Release□□□□□□□□□□□□□□□□ `v1.12.12` □□□□□□□□□□□□ Release Note □ Release □□

8.4.4 Minor □□□□□□

□□ Minor □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□

1. □ Github □□□□□□□□□□□□□□□□ `release-1.13` (□□)
2. □□□□□□ `VERSION`, `dist/images/install.sh`, `charts/kube-ovn/values.yaml` □ `charts/kube-ovn/Chart.yaml` □□□□□□□□□□□□ Minor □□□□□ `v1.14.0` (□□)
3. □□□ tag □□□ Docker Hub (□□)
4. □□□□□□□□□ tag □□□ Github (□□)
5. □□□□□□□□□□□□□□□□ `v1.13` □□□ `mkdocs.yml` □□□□ `version` □ `branch` □□ (□□)
6. □□ Release Note PR□□□□□
7. □□ Release Note (□□)
8. □□ Merge github action □□□ Release Note PR
9. □□ Github Release □□□□□□
10. □ Github Release □□□□□□□□ Release□□□□□□□□□□□□□□□□ `v1.13.0` □□□□□□□□□□□□ Release Note □ Release □□
11. □□□□□□□□ `VERSION` □□□□□□□□□□□ Patch □□□□□ `v1.13.1`

PDF Slack Support

2025 Kube-OVN Team

2024⬚5⬚16⬚

2024⬚5⬚8⬚



GitHub 




8.4.5 ⬚⬚

8.5 Underlay ▯▯▯▯

▯▯▯▯ Underlay ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯


8.5.1 ▯▯▯▯▯▯▯

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯




8.5.2 ▯▯▯▯▯▯▯

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯



8.5.3 ████████


██



> ██ br-provider-1 ▯ br-provider-2 ██████ OVS ████████████████████ Provider Network▯

8.5.4 □□□□□□□□


□□□



8.5.5 □□□□


□□□

2025 Kube-OVN Team




□□□ Pod □□□□□□□□□□□□□□□□

8.5.6 □ Vlan Tag □□□




8.5.7 □ VLAN □□




8.5.8 Pod □□ Service IP

Kube-OVN □□□ Kubernetes Service □□□□□□□□□□□□□□□□□□□□□□□ □ Pod □□□□ Service IP □□□□ Pod □□□□□□□□□□□□□ Service IP□□□ MAC □□□□□ MAC □□□□□□□ □□□□□□□□□□□ □□□□□□□□□□□□□□□□□ DNAT □□□□□□ IP □□□□□□ Service □□□□□ Endpoint □ IP □□□□ □□□□□□□□□□□□□□□□□□□ MAC □□□□□□□□□□□□□□□□□□□□

Service ▯▯▯▯▯▯▯▯▯▯ Pod



Service ▯▯▯▯▯▯▯▯▯▯ Pod



PDF Slack Support

2025 Kube-OVN Team

2022▯9▯23▯

2022▯5▯20▯

GitHub 

8.5.9 ▯▯

2025 Kube-OVN Team

8.6 □□ Netfilter □□

Kube-OVN □□□□ Netfilter □□□□□□ VPC □□□□□□Overlay□□□□ NAT □□□ □□□□□□□ `iptables` □ `nftables` □□□□□□□ iptables □□□□□□□□

8.6.1 □□□□□□□

`kube-ovn-cni` daemon □□□□□□ Netfilter □□□

□□	□□
`auto`	□□□□□□ kube-proxy □□□ `iptables` □ `ipvs` □□ iptables □□□ `nftables` □□ nftables □□□
`iptables`	□□□□ Kube-OVN □ iptables □ ipset □□□
`nftables`	□□□□ Kube-OVN □ nftables □□□□□

□□□□□ `auto` □□□□□□□□ kube-proxy □ `proxyMode` □□□□□□□□□□□□□□□□□□□□□ `kube-system` □□ `kube-proxy` ConfigMap□□□□□□ `http://localhost:10249/proxyMode` □□□□□□ 30 □□□□□□□□□□□□□□□□□□□□

□□□ ipset □□□□□□

□□□**IPv4/IPv6**□	□□	□□□□
ovn40services/ovn60services	hash:net	Service □□
ovn40subnets/ovn60subnets	hash:net	Overlay □□□□□□ NodeLocal DNS IP □□
ovn40subnets-nat/ovn60subnets-nat	hash:net	□□ NatOutgoing □ Overlay □□□□
ovn40subnets-distributed-gw/ovn60subnets-distributed-gw	hash:net	□□□□□□□□ Overlay □□□□
ovn40other-node/ovn60other-node	hash:net	□□□□□□□ IP □□
ovn40local-pod-ip-nat/ovn60local-pod-ip-nat	hash:ip	□□□
ovn40subnets-nat-policy	hash:net	□□□ natOutgoingPolicyRules □□□□□□□
ovn40natpr-418e79269dc5-dst	hash:net	natOutgoingPolicyRules □ rule □□□ dstIPs
ovn40natpr-418e79269dc5-src	hash:net	natOutgoingPolicyRules □ rule □□□ srcIPs

□□□ iptables □□□IPv4□□□□□□□

表	链	规则	作用	备注
filter	INPUT	-m set --match-set ovn40services src -j ACCEPT	允许 k8s Service 到 Pod 流量通过	--
filter	INPUT	-m set --match-set ovn40services dst -j ACCEPT	允许	--
filter	INPUT	-m set --match-set ovn40subnets src -j ACCEPT	允许	--
filter	INPUT	-m set --match-set ovn40subnets dst -j ACCEPT	允许	--
filter	FORWARD	-m set --match-set ovn40services src -j ACCEPT	允许	--
filter	FORWARD	-m set --match-set ovn40services dst -j ACCEPT	允许	--
filter	FORWARD	-m set --match-set ovn40subnets src -j ACCEPT	允许	--
filter	FORWARD	-m set --match-set ovn40subnets dst -j ACCEPT	允许	--
filter	FORWARD	-s 10.16.0.0/16 -m comment --comment "ovn-subnet-gateway,ovn-default"	允许从 subnet 发出的流量	10.16.0.0/16 为 subnet 的 cidr 由comment 标记为 ovn-subnet-gateway 用于区分 iptables 规则来自 subnet 的流量，便于区分 ovn-default 和 subnet 的流量
filter	FORWARD	-d 10.16.0.0/16 -m comment --comment "ovn-subnet-gateway,ovn-default"	允许发往 subnet 的流量	同上
filter	OUTPUT	-p udp -m udp --dport 6081 -j MARK --set-xmark 0x0	避免 SNAT	UDP: bad checksum on VXLAN interface
nat	PREROUTING	-m comment --comment "kube-ovn prerouting rules" -j OVN-PREROUTING	跳转 OVN-PREROUTING 规则	--
nat	POSTROUTING	-m comment --comment "kube-ovn postrouting rules" -j OVN-POSTROUTING	跳转 OVN-POSTROUTING 规则	--
nat	OVN-PREROUTING	-i ovn0 -m set --match-set ovn40subnets src -m set --match-set ovn40services dst -j MARK --set-xmark 0x4000/0x4000	为 Pod 访问 Service 流量打 masquerade 标记	用于后续 LB 规则
nat	OVN-PREROUTING	-p tcp -m addrtype --dst-type LOCAL -m set --match-	为 kube-proxy 的 ipvs 模式	

□	□	□□	□□	□□
		set KUBE-NODE-PORT-LOCAL-TCP dst -j MARK --set-xmark 0x80000/0x80000	□ ExternalTrafficPolicy □ Local □ Service □□□TCP□□□□□	
nat	OVN-PREROUTING	-p udp -m addrtype --dst-type LOCAL -m set --match-set KUBE-NODE-PORT-LOCAL-UDP dst -j MARK --set-xmark 0x80000/0x80000	□ ExternalTrafficPolicy □ Local □ Service □□□UDP□□□□□	□□
nat	OVN-POSTROUTING	-m set --match-set ovn40services src -m set --match-set ovn40subnets dst -m mark --mark 0x4000/0x4000 -j SNAT --to-source	□□□□ Service IP □□ Overlay Pod □□□□ IP □□□ IP□	□ kube-proxy □□ ipvs □□□□
nat	OVN-POSTROUTING	-m mark --mark 0x4000/0x4000 -j MASQUERADE	□□□□□□□□□□ SNAT	--
nat	OVN-POSTROUTING	-m set --match-set ovn40subnets src -m set --match-set ovn40subnets dst -j MASQUERADE	□□□□□□ Pod □□□ Service □□ □□ SNAT	--
nat	OVN-POSTROUTING	-m mark --mark 0x80000/0x80000 -m set --match-set ovn40subnets-distributed-gw dst -j RETURN	□□ ExternalTrafficPolicy □ Local □ Service □□□□ Endpoint □□□□□□□□□□□□ SNAT	--
nat	OVN-POSTROUTING	-m mark --mark 0x80000/0x80000 -j MASQUERADE	□□ ExternalTrafficPolicy □ Local □ Service □□□□ Endpoint □□□□□□□□□□ SNAT	--
nat	OVN-POSTROUTING	-p tcp -m tcp --tcp-flags SYN NONE -m conntrack --ctstate NEW -j RETURN	Pod IP □□□□□□□□□ SNAT	--
nat	OVN-POSTROUTING	-s 10.16.0.0/16 -m set ! --match-set ovn40subnets dst -j SNAT --to-source 192.168.0.101	Pod □□□□□□□□□□□□□□□ NatOutgoing □□□□□ IP □□□ □□□□□□ SNAT	10.16.0.0/16 □□□□□□192.168.0.101 □□□□□□□ IP
nat	OVN-POSTROUTING	-m set --match-set ovn40subnets-nat src -m set ! --match-set ovn40subnets dst -j MASQUERADE	Pod □□□□□□□□□□□□□□□ NatOutgoing□□□ SNAT	--
nat	OVN-POSTROUTING	-m set --match-set ovn40subnets-nat-policy src -m set ! --match-set ovn40subnets dst -j OVN-NAT-POLICY	Pod □□□□□□□□□□□□□□□ natOutgoingPolicyRules□ □□□□□□□□□□ SNAT	□□□ natOutgoingPolicyRules □□□□□□□□□□ OV NAT-POLICY □
nat			□□	

2025 Kube-OVN Team

⬚	⬚	⬚⬚	⬚⬚	⬚⬚
	OVN-POSTROUTING	-m mark --mark 0x90001/0x90001 -j MASQUERADE --random-fully		⬚ OVN-NAT-POLICY ⬚⬚⬚⬚⬚⬚⬚⬚ tag 0x90001/0x90001 ⬚⬚⬚ SNAT
nat	OVN-POSTROUTING	-m mark --mark 0x90002/0x90002 -j RETURN	⬚⬚	⬚ OVN-NAT-POLICY ⬚⬚⬚, ⬚⬚⬚⬚⬚ tag 0x90002/0x90002 ⬚⬚⬚ SNAT
nat	OVN-NAT-POLICY	-s 10.0.11.0/24 -m comment --comment natPolicySubnet-net1 -j OVN-NAT-PSUBNET-aa98851157c5	⬚⬚	10.0.11.0/24 ⬚⬚⬚⬚ net1 ⬚ CIDR⬚ OVN-NAT-PSUBNET-aa98851157c5 ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ natOutgoingPolicyRules ⬚⬚
nat	OVN-NAT-PSUBNET-xxxxxxxxxxxx	-m set --match-set ovn40natpr-418e79269dc5-src src -m set --match-set ovn40natpr-418e79269dc5-dst dst -j MARK --set-xmark 0x90002/0x90002	⬚⬚	418e79269dc5 ⬚⬚ natOutgoingPolicyRules ⬚⬚⬚⬚⬚⬚ ID⬚⬚⬚⬚⬚ status.natOutgoingPolicyRules[index].Rule ⬚⬚⬚⬚ ⬚⬚ srcIPs ⬚⬚ ovn40natpr-418e79269dc src⬚ dstIPS ⬚⬚ ovn40natpr-418e79269dc5-dst ⬚⬚⬚ tag 0x90002
mangle	OVN-OUTPUT	-d 10.241.39.2/32 -p tcp -m tcp --dport 80 -j MARK --set-xmark 0x90003/0x90003	⬚ kubelet ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ ⬚ tproxy	
mangle	OVN-PREROUTING	-d 10.241.39.2/32 -p tcp -m tcp --dport 80 -j TPROXY --on-port 8102 --on-ip 172.18.0.3 --tproxy-mark 0x90004/0x90004	⬚ kubelet ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ ⬚ tproxy	

PDF Slack Support

2026⬚10⬚29⬚

2022⬚9⬚6⬚

GitHub



8.6.3 ⬚⬚

2025 Kube-OVN Team

8.7 ▯▯▯▯▯▯▯▯

8.7.1 ▯▯▯▯

Kube-OVN ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Github ▯▯▯▯▯▯▯▯▯▯▯▯▯▯/▯▯▯▯▯▯▯▯▯▯▯▯ Github ▯▯▯ Issue ▯ PR▯▯▯ Maintainer ▯ Review ▯▯▯ Github Action ▯▯▯▯▯▯▯▯▯▯▯▯▯▯

8.7.2 ▯▯▯▯

Kube-OVN ▯▯ Go ▯▯▯▯▯ Go Modules ▯▯▯▯▯ ▯▯▯▯▯▯▯▯ `GO111MODULE="on"` ▯

golangci-lint ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

```
make kind-init
make kind-install-underlay
make e2e-underlay-single-nic
```

▯▯▯▯ ovn vpc nat gw eip, fip, snat, dnat ▯▯▯▯▯▯▯▯▯▯

```
make kind-init
make kind-install
make ovn-vpc-nat-gw-conformance-e2e
```

▯▯▯▯ iptables vpc nat gw eip, fip, snat, dnat ▯▯▯▯▯▯▯▯▯▯

```
make kind-init
make kind-install-vpc-nat-gw
make iptables-vpc-nat-gw-conformance-e2e
```

▯▯▯▯ loadbalancer service ▯▯▯▯▯▯▯▯▯▯

```
make kind-init
make kind-install-lb-svc
make kube-ovn-lb-svc-conformance-e2e
```

▯▯▯▯▯▯▯▯▯▯▯▯

```
make kind-clean
```

PDF Slack Support

2025▯6▯29▯

2022▯5▯20▯

GitHub

+1

8.7.6 ▯▯

8.8 □□□ OVS/OVN □□

□□ OVN/OVS □□□□□□□□□ SDN □□□□□□□□□□□ Kubernetes □□□□□□□□□□□□□ □□ Kube-OVN □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□Kube-OVN □□□ OVN/OVS □□□□□□□□□□□□□ □□□□ OVN/OVS □□ Kube-OVN □□□□□□□□□□□□□□□ □□□□□□□□□□□□□□□

□□□□□□□□□

- 4228eab1d7 □□ vswitchd ofport_usage □□□□□□□□□□□□□
- 54056ea65d □□□□ timer□□□□□□□□□□□□□□□
- 6b4dcb311f □□ fdb □□□□□□
- f627b7721e □□ hairpin □□□ fdb □□□□□□□□□
- 3f3e3a436f □ ovsdb-tool □ join-cluster □□□□□ Server ID □□□
- a6cb8215a8 □□ QoS □□□□□□□□
- d4d76ddb2e ovsdb-tool□□□ fix-cluster □□□
- ffd2328d4a netdev□□□□□□□□□□□ CPU □□□□
- d088c5d8c2 ovs-router□□□□□ kube-ipvs0 □□□□□
- 1b31f07dc6 □□□□□□□□□□□□□□□□□
- 54b7678229 □□ ovs-sandbox □□□ docker run□
- 9ee66bd91b □□□□□□□□□□
- e889d46924 □□ Underlay □□□□□ resubmit □□□□□□□
- f9e97031b5 ovn-controller□□□ Kube-OVN □□□ localnet □□□ GARP□
- 78cade0187 □□□□□□□□ conntrack □□□□
- 85aa6263ad northd□□□□□□□□ DNS IP □□□ conntrack□
- 34dc3e3fcf lflow□□□ lport □□□□□□□□□□□ conntrack□
- a297b840c2 □□□□□□□□□□□□□□ DNAT □□□□□□□□□ lsp□
- 03e35ed9c5 ovn-controller□□□□□□□□□□□□□□□□□□□
- e7d3ba53cd □□ ACL □□□□□□□□ DNS IP □ conntrack□
- 9286e1fd57 □□□□□□□□□□
- e5916eb53a □□□□□□□□□□□□□□□□ lr-lb DNAT □□□
- e4e6ea9c5f □□□□□□ BFD LRP□
- e76880e792 northd□□□ nb □□ version_compatibility□
- 477695a010 northd□□□□ localnet □□□ lrp □□□ arp/nd □□□
- 2209d9a335 □□ ovn-controller □□□□ LSP □□□□□□□□
- 52b727b331 □□□□□□□□□□□□ ovn-northd □□□□□□□□
- 53b9837f7f □□ LB □ ACL □□□□□□□□□□□□□
- 737d9f932e □□□ GW □□□□□□□□□□□□□
- sbrec-delete-null-check □□ ovn-controller □ sbrec □□□□□□□□□□□□□

□□□□□□□□□

- 20626ea909 □□□□□□□ LB □ ACL □□□□□□□□□□□□□□□□□□□□
- a2d9ff3ccd Deb □□□□□□□□□□□□□

PDF Slack Support

2025 Kube-OVN Team

2026⬚4⬚28⬚

2022⬚5⬚24⬚

GitHub 

8.8.1 ⬚⬚

8.9 ▯▯▯▯▯▯

Kube-OVN ▯▯ OVN/OVS ▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `Geneve` ▯ `Vxlan` ▯ `STT` ▯▯▯▯▯▯▯▯▯ ▯▯▯▯▯▯▯▯▯▯▯▯▯▯

8.9.5 ▯▯

8.10 Kube-OVN □□□□

□□□□□ Kube-OVN □□□□□□□□□□

8.10.1 ovn-monitor

OVN □□□□□□□□□□

□□	□□□	□□
Gauge	kube_ovn_ovn_status	OVN □□□□□ (2) □ follower□ (1) □ leader, (0) □□□□□□
Gauge	kube_ovn_failed_req_count	OVN □□□□□□□
Gauge	kube_ovn_log_file_size_bytes	OVN □□□□□□□□□
Gauge	kube_ovn_db_file_size_bytes	OVN □□□□□□□□□□
Gauge	kube_ovn_chassis_info	OVN chassis □□ (1) □□□□(0) □□□
Gauge	kube_ovn_db_status	OVN □□□□□, (1) □□□□ (0) □□□□
Gauge	kube_ovn_logical_switch_info	OVN logical switch □□□□□ (1)□□□□□□ logical switch □□□
Gauge	kube_ovn_logical_switch_external_id	OVN logical switch external_id □□□□□ (1)□□□□□□ external-id □□□
Gauge	kube_ovn_logical_switch_port_binding	OVN logical switch □ logical switch port □□□□□□□ (1)□□□□□□□□□□
Gauge	kube_ovn_logical_switch_tunnel_key	□ OVN logical switch □□□ tunnel key □□□
Gauge	kube_ovn_logical_switch_ports_num	OVN logical switch □ logical port □□□□
Gauge	kube_ovn_logical_switch_port_info	OVN logical switch port □□□□□ (1)□□□□□□□□□□□
Gauge	kube_ovn_logical_switch_port_tunnel_key	□ OVN logical switch port □□□ tunnel key □□□
Gauge	kube_ovn_cluster_enabled	(1) OVN □□□□□□□□□ (0) OVN □□□□□□□□□□
Gauge	kube_ovn_cluster_role	□□□□□□□□□□□□□ (1)□□□□□□□□□□□□□□□
Gauge	kube_ovn_cluster_status	□□□□□□□□□□□□□ (1)□□□□□□□□□□□□□□□
Gauge	kube_ovn_cluster_term	RAFT term □□□
Gauge	kube_ovn_cluster_leader_self	□□□□□□□□□□ leader (1) □□ (0) □□□
Gauge	kube_ovn_cluster_vote_self	□□□□□□□□□□□□□□□ leader (1) □□ (0) □□□
Gauge	kube_ovn_cluster_election_timer	□□ election timer □□
Gauge	kube_ovn_cluster_log_not_committed	□ commit □ RAFT □□□□□
Gauge	kube_ovn_cluster_log_not_applied	□ apply □ RAFT □□□□□
Gauge	kube_ovn_cluster_log_index_start	□□ RAFT □□□□□□□□□
Gauge	kube_ovn_cluster_log_index_next	RAFT □□□□□□□□□□
Gauge	kube_ovn_cluster_inbound_connections_total	□□□□□□□□□□□□
Gauge	kube_ovn_cluster_outbound_connections_total	□□□□□□□□□□□□
Gauge	kube_ovn_cluster_inbound_connections_error_total	□□□□□□□□□□□□□□□
Gauge	kube_ovn_cluster_outbound_connections_error_total	□□□□□□□□□□□□□□□

2025 Kube-OVN Team

8.10.2 ovs-monitor

`ovsdb  vswitchd `

□□	□□□	□□
Gauge	ovs_status	OVS □□□□□ (1) □□□□(0) □□□□
Gauge	ovs_info	OVS □□□□□□□ (1)□□□□□□□□□□□□
Gauge	failed_req_count	OVS □□□□□□□
Gauge	log_file_size_bytes	OVS □□□□□□□□□□□□□□
Gauge	db_file_size_bytes	OVS □□□□□□□□□□□□□□□
Gauge	datapath	Datapath □□□□□□□ (1)□□□□□□□□□□□□
Gauge	dp_total	□□ OVS □ datapath □□□
Gauge	dp_if	Datapath □□□□□□□□□ (1)□□□□□□□□□□□□
Gauge	dp_if_total	□□ datapath □ port □□□
Gauge	dp_flows_total	Datapath □ flow □□□
Gauge	dp_flows_lookup_hit	Datapath □□□□□ flow □□□□□□
Gauge	dp_flows_lookup_missed	Datapath □□□□□□ flow □□□□□□
Gauge	dp_flows_lookup_lost	Datapath □□□□□□ userspace □□□□□□□□□
Gauge	dp_masks_hit	Datapath □□□□□ mask □□□□□□
Gauge	dp_masks_total	Datapath □ mask □□□□
Gauge	dp_masks_hit_ratio	Datapath □ □□□□□ mask □□□□
Gauge	interface	OVS □□□□□□□□□ (1)□□□□□□□□□□□□
Gauge	interface_admin_state	□□□□□□□□ (0) □ down, (1) □ up, (2) □□□□□□
Gauge	interface_link_state	□□□□□□□□ (0) □ down, (1) □ up, (2) □□□□□□
Gauge	interface_mac_in_use	OVS Interface □□□ MAC □□
Gauge	interface_mtu	OVS Interface □□□ MTU□
Gauge	interface_of_port	OVS Interface □□□ OpenFlow Port ID□
Gauge	interface_if_index	OVS Interface □□□ Index□
Gauge	interface_tx_packets	OVS Interface □□□□□□
Gauge	interface_tx_bytes	OVS Interface □□□□□□
Gauge	interface_rx_packets	OVS Interface □□□□□□
Gauge	interface_rx_bytes	OVS Interface □□□□□□
Gauge	interface_rx_crc_err	OVS Interface □□□□□□□□□□□
Gauge	interface_rx_dropped	OVS Interface □□□□□□□□
Gauge	interface_rx_errors	OVS Interface □□□□□□□□
Gauge	interface_rx_frame_err	OVS Interface □□□□□□□□
Gauge	interface_rx_missed_err	OVS Interface □□□ miss □□□
Gauge	interface_rx_over_err	OVS Interface □□□ overrun □□□
Gauge	interface_tx_dropped	OVS Interface □□□□□□□□

□□	□□□	□□
Gauge	interface_tx_errors	OVS Interface □□□□□□□□
Gauge	interface_collisions	OVS interface □□□□□

8.10.3 kube-ovn-pinger

□□□□□□□□□□□□

□□	□□□	□□
Gauge	pinger_ovs_up	□□ OVS □□□
Gauge	pinger_ovs_down	□□ OVS □□□
Gauge	pinger_ovn_controller_up	□□ ovn-controller □□□
Gauge	pinger_ovn_controller_down	□□ ovn-controller □□□
Gauge	pinger_inconsistent_port_binding	OVN-SB □ portbinding □□□□□ OVS interface □□□□□□□
Gauge	pinger_apiserver_healthy	kube-ovn-pinger □□□□ apiserver□
Gauge	pinger_apiserver_unhealthy	kube-ovn-pinger □□□□ apiserver□
Histogram	pinger_apiserver_latency_ms	kube-ovn-pinger □□ apiserver □□□
Gauge	pinger_internal_dns_healthy	kube-ovn-pinger □□□□□□□□□
Gauge	pinger_internal_dns_unhealthy	kube-ovn-pinger □□□□□□□□□
Histogram	pinger_internal_dns_latency_ms	kube-ovn-pinger □□□□□□□□□
Gauge	pinger_external_dns_healthy	kube-ovn-pinger □□□□□□□□□
Gauge	pinger_external_dns_unhealthy	kube-ovn-pinger □□□□□□□□□
Histogram	pinger_external_dns_latency_ms	kube-ovn-pinger □□□□□□□□□
Histogram	pinger_pod_ping_latency_ms	kube-ovn-pinger ping Pod □□□
Gauge	pinger_pod_ping_lost_total	kube-ovn-pinger ping Pod □□□□□
Gauge	pinger_pod_ping_count_total	kube-ovn-pinger ping Pod □□□
Histogram	pinger_node_ping_latency_ms	kube-ovn-pinger ping Node □□□
Gauge	pinger_node_ping_lost_total	kube-ovn-pinger ping Node □□□
Gauge	pinger_node_ping_count_total	kube-ovn-pinger ping Node □□□
Histogram	pinger_external_ping_latency_ms	kube-ovn-pinger ping □□□□ □□□
Gauge	pinger_external_ping_lost_total	kube-ovn-pinger ping □□□□□□□

2025 Kube-OVN Team

8.10.4 kube-ovn-controller

`kube-ovn-controller` [illegible]

[illegible]	[illegible]	[illegible]
Histogram	rest_client_request_latency_seconds	[illegible] apiserver [illegible]
Counter	rest_client_requests_total	[illegible] apiserver [illegible]
Counter	lists_total	API list [illegible]
Summary	list_duration_seconds	API list [illegible]
Summary	items_per_list	API list [illegible]
Counter	watches_total	API watch [illegible]
Counter	short_watches_total	[illegible] API watch [illegible]
Summary	watch_duration_seconds	API watch [illegible]
Summary	items_per_watch	API watch [illegible]
Gauge	last_resource_version	[illegible] resource version[illegible]
Histogram	ovs_client_request_latency_milliseconds	[illegible] OVN [illegible]
Gauge	subnet_available_ip_count	[illegible] IP [illegible]
Gauge	subnet_used_ip_count	[illegible] IP [illegible]

8.10.5 kube-ovn-cni

`kube-ovn-cni` [illegible]

[illegible]	[illegible]	[illegible]
Histogram	cni_op_latency_seconds	CNI [illegible]
Counter	cni_wait_address_seconds_total	CNI [illegible]
Counter	cni_wait_connectivity_seconds_total	CNI [illegible]
Counter	cni_wait_route_seconds_total	CNI [illegible]
Histogram	rest_client_request_latency_seconds	[illegible] apiserver [illegible]
Counter	rest_client_requests_total	[illegible] apiserver [illegible]
Counter	lists_total	API list [illegible]
Summary	list_duration_seconds	API list [illegible]
Summary	items_per_list	API list [illegible]
Counter	watches_total	API watch [illegible]
Counter	short_watches_total	[illegible] API watch [illegible]
Summary	watch_duration_seconds	API watch [illegible]
Summary	items_per_watch	API watch [illegible]
Gauge	last_resource_version	[illegible] resource version[illegible]
Histogram	ovs_client_request_latency_milliseconds	[illegible] OVN [illegible]

2025 Kube-OVN Team

PDF Slack Support

2026▯4▯28▯

2022▯6▯21▯

GitHub 

8.10.6 ▯▯

2025 Kube-OVN Team

8.11 Kube-OVN ⬚⬚⬚⬚

⬚⬚ Kube-OVN ⬚⬚⬚⬚⬚⬚⬚ Kube-OVN ⬚⬚⬚ CRD ⬚⬚⬚⬚⬚⬚ CRD ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

8.11.1 ⬚⬚⬚ Condition ⬚⬚

⬚⬚⬚⬚	⬚⬚	⬚⬚
type	String	⬚⬚⬚⬚
status	String	⬚⬚⬚⬚⬚⬚⬚ `True` ⬚ `False` ⬚ `Unknown`
reason	String	⬚⬚⬚⬚⬚⬚⬚
message	String	⬚⬚⬚⬚⬚⬚⬚⬚⬚
observedGeneration	Int64	⬚⬚⬚⬚⬚⬚⬚⬚
lastUpdateTime	Time	⬚⬚⬚⬚⬚⬚⬚⬚
lastTransitionTime	Time	⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

⬚⬚ CRD ⬚⬚⬚⬚⬚Status ⬚⬚ Condition ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚

8.11.2 ⬚⬚⬚⬚⬚⬚

Subnet ⬚⬚

SUBNET

⬚⬚⬚⬚	⬚⬚	⬚⬚
apiVersion	String	⬚⬚ Kubernetes ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ kubeovn.io/v1
kind	String	⬚⬚ Kubernetes ⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚⬚ `Subnet`
metadata	ObjectMeta	⬚⬚ Kubernetes ⬚⬚⬚⬚⬚⬚⬚
spec	SubnetSpec	Subnet ⬚⬚⬚⬚⬚⬚⬚⬚
status	SubnetStatus	Subnet ⬚⬚⬚⬚⬚⬚

2025 Kube-OVN Team

SubnetSpec

□□□□	□□	□□
default	Bool	□□□□□□□□□□
vpc	String	□□□□ VPC□□□□ ovn-cluster
protocol	String	IP □□□□□□□□ `IPv4` □ `IPv6` □ `Dual` □□□□ MAC □ Underlay □□□□□ `Mac`
namespaces	[]String	□□□□□□□ namespace □□
cidrBlock	String	□□□□□□□□□ 10.16.0.0/16
gateway	String	□□□□□□□□□□□□□ CIDRBlock □□□□□□□□□
excludeIps	[]String	□□□□□□□□□□□□□□□□□□
provider	String	□□□ OVN□□□□□□□□□□□□□□□ NetworkAttachmentDefinition □□Kube-OVN □□□□□□□□□□□□□□□ Subnet □□
gatewayType	String	Overlay □□□□□□□□□□□□□□□ `distributed` □ `centralized`
gatewayNode	String	□□□□□□ centralized □□□□□□□□□□□□□□□□□□□□□□
gatewayNodeSelectors	[]LabelSelector	□□□□□□□□
natOutgoing	Bool	□□□□□□□□ NAT□□□□□ `externalEgressGateway` □□□□□□□□□□
externalEgressGateway	String	□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□ `natOutgoing` □□□□□□□□□
policyRoutingPriority	Uint32	□□
policyRoutingTableID	Uint32	□□□□□□□□□□□□ TableID□□□□□□□□□□□□□□□□
mtu	Uint32	□□□ MTU □□
private	Bool	□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□
routed	Bool	□□□□□□□□□□□□□□□□ Pod □□ `/32` □IPv4□□ `/128` □IPv6□□□□□□□□□□□□□□□□□□ OVN □□□□□□□□
allowSubnets	[]String	□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□
vlan	String	□□□□□□ Vlan □□
vips	[]String	□□□ virtual □□ lsp □ virtual-ip □□□□
logicalGateway	Bool	□□□□□□□□□
disableGatewayCheck	Bool	□□ Pod □□□□□□□□□□□□□□
disableInterConnection	Bool	□□□□□□□□□□□□□□□□
enableDHCP	Bool	□□□□□□□□□□ lsp □ dhcp □□□□
dhcpV4Options	String	□□□ lsp dhcpv4_options □□□ DHCP_Options □□
dhcpV6Options	String	□□□ lsp dhcpv6_options □□□ DHCP_Options □□
enableIPv6RA	Bool	□□□□□□□□□□□ lrp □□□□□□□□ ipv6_ra_configs □□
ipv6RAConfigs	String	□□□□□□□□□ lrp □□□ipv6_ra_configs □□□□□□□
acls	[]Acl	□□□□ logical-switch □□□ acls □□
allowEWTraffic	Bool	□□□□□□□□□□
natOutgoingPolicyRules	[]NatOutgoingPolicyRule	NAT □□□□□□□
u2oInterconnectionIP	String	Underlay/Overlay □□□□□ IP □□
u2oInterconnection	Bool	□□□□ Overlay/Underlay □□□□□

2025 Kube-OVN Team

[illegible]	[illegible]	[illegible]
u2oFeatures	U2OFeatures	Underlay/Overlay [illegible]
enableLb	*Bool	[illegible] logical-switch [illegible] load-balancer [illegible]
enableEcmp	Bool	[illegible] ECMP [illegible]
enableMulticastSnoop	Bool	[illegible]
enableExternalLBAddress	Bool	[illegible]
routeTable	String	[illegible]
namespaceSelectors	[]LabelSelector	[illegible]
nodeNetwork	String	Underlay [illegible]

U2OFeatures

[illegible]	[illegible]	[illegible]
overlayOnlyRouting	Bool	[illegible] Overlay CIDR [illegible] U2O [illegible]

Acl

[illegible]	[illegible]	[illegible]
direction	String	Acl [illegible] `from-lport` [illegible] `to-lport`
priority	Int	Acl [illegible] 0 [illegible] 32767
match	String	Acl [illegible]
action	String	Acl [illegible] `allow-related` [illegible] `allow-stateless` [illegible] `allow` [illegible] `drop` [illegible] `reject` [illegible]

NatOutgoingPolicyRule

[illegible]	[illegible]	[illegible]
match	NatOutGoingPolicyMatch	[illegible]
action	String	[illegible]

NatOutGoingPolicyMatch

[illegible]	[illegible]	[illegible]
srcIPs	String	[illegible] IP [illegible]
dstIPs	String	[illegible] IP [illegible]

2025 Kube-OVN Team

SubnetStatus

□□□□	□□	□□
conditions	[]SubnetCondition	□□□□□□□□□□□□□□□□□□□□□□ Condition □□
v4availableIPs	BigInt	□□□□□□□□ IPv4 IP □□□□□□□□□□□□ IPv6 □□□□□□□ float64 □□□□□□□
v4availableIPrange	String	□□□□□□□□ IPv4 □□□□□
v4usingIPs	BigInt	□□□□□□□□ IPv4 IP □□□□□
v4usingIPrange	String	□□□□□□□□ IPv4 □□□□□
v6availableIPs	BigInt	□□□□□□□□ IPv6 IP □□□□□
v6availableIPrange	String	□□□□□□□□ IPv6 □□□□□
v6usingIPs	BigInt	□□□□□□□□ IPv6 IP □□□□□
v6usingIPrange	String	□□□□□□□□ IPv6 □□□□□
activateGateway	String	□□□□□□□□□□□□□□□□□□□□□□□□□□□□
dhcpV4OptionsUUID	String	□□□ lsp dhcpv4_options □□□ DHCP_Options □□□□
dhcpV6OptionsUUID	String	□□□ lsp dhcpv6_options □□□ DHCP_Options □□□□
u2oInterconnectionIP	String	□□ Overlay/Underlay □□□□□□□□□□□□□□□□ IP □□
u2oInterconnectionMAC	String	□□ Overlay/Underlay □□□□□□□□□□□□□□□□ MAC □□
u2oInterconnectionVPC	String	□□ Overlay/Underlay □□□□□□□□□ VPC
natOutgoingPolicyRules	[]NatOutgoingPolicyRuleStatus	NAT □□□□□□□□□
gatewayMAC	String	□□□□□□□□□□ MAC □□
mcastQuerierIP	String	□□□□□□ IP □□
mcastQuerierMAC	String	□□□□□□ MAC □□

IP □□

IP

□□□□	□□	□□
apiVersion	String	□□ Kubernetes □□□□□□□□□□□□□□□□□□□ kubeovn.io/v1
kind	String	□□ Kubernetes □□□□□□□□□□□□□□□□□□□ `IP`
metadata	ObjectMeta	□□ Kubernetes □□□□□□□□
spec	IPSpec	IP □□□□□□□□□

2025 Kube-OVN Team

IPSpec

[illegible]	[illegible]	[illegible]
podName	String	[illegible] Pod [illegible]
namespace	String	[illegible] Pod [illegible] Namespace [illegible]
subnet	String	IP [illegible] Subnet
attachSubnets	[]String	[illegible] IP [illegible]
nodeName	String	[illegible] Pod [illegible]
ipAddress	String	IP [illegible] `v4IP` `v6IP` [illegible]
v4IpAddress	String	IPv4 IP [illegible]
v6IpAddress	String	IPv6 IP [illegible]
attachIps	[]String	[illegible] IP [illegible] IP [illegible]
macAddress	String	[illegible] Pod [illegible] MAC [illegible]
attachMacs	[]String	[illegible] IP [illegible] MAC [illegible]
containerID	String	[illegible] Pod [illegible] Container ID
podType	String	[illegible] Pod[illegible] `StatefulSet` [illegible] `VirtualMachine` [illegible]

Vpc [illegible]

VPC

[illegible]	[illegible]	[illegible]
apiVersion	String	[illegible] Kubernetes [illegible] kubeovn.io/v1
kind	String	[illegible] Kubernetes [illegible] `Vpc`
metadata	ObjectMeta	[illegible] Kubernetes [illegible]
spec	VpcSpec	Vpc [illegible]
status	VpcStatus	Vpc [illegible]

VpcSpec

[illegible]	[illegible]	[illegible]
defaultSubnet	String	[illegible]
namespaces	[]String	Vpc [illegible]
staticRoutes	[]StaticRoute	[illegible]
policyRoutes	[]PolicyRoute	[illegible]
vpcPeerings	[]VpcPeering	VPC [illegible]
enableExternal	Bool	[illegible]
extraExternalSubnets	[]String	[illegible]
enableBfd	Bool	[illegible] BFD ([illegible])
bfdPort	BFDPort	BFD [illegible]

2025 Kube-OVN Team

StaticRoute

[illegible]	[illegible]	[illegible]
policy	String	[illegible]
cidr	String	[illegible]
nextHopIP	String	[illegible] IP [illegible]
ecmpMode	String	ECMP [illegible]
bfdId	String	BFD ID
routeTable	String	[illegible]

PolicyRoute

[illegible]	[illegible]	[illegible]
priority	Int	[illegible]
match	String	[illegible]
action	String	[illegible] `allow` [illegible] `drop` [illegible] `reroute`
nextHopIP	String	[illegible] IP [illegible] action [illegible] reroute [illegible]

VpcPeering

[illegible]	[illegible]	[illegible]
remoteVpc	String	[illegible] VPC [illegible]
localConnectIP	String	[illegible] IP [illegible] CIDR[illegible] `169.254.0.1/30` [illegible] `169.254.0.1/30,fd00::1/64` [illegible] CIDR [illegible]

BFDPort

[illegible]	[illegible]	[illegible]
enabled	Bool	[illegible] BFD
ip	String	BFD [illegible] IP [illegible]
nodeSelector	LabelSelector	[illegible] BFD LRP [illegible]

BFDPortStatus

[illegible]	[illegible]	[illegible]
name	String	BFD [illegible]
ip	String	BFD [illegible] IP [illegible]
nodes	[]String	BFD [illegible]

2025 Kube-OVN Team

VpcStatus

▯▯▯▯	▯▯	▯▯
conditions	[]VpcCondition	Vpc ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Condition ▯▯
standby	Bool	▯▯▯▯▯ VPC
default	Bool	▯▯▯▯▯ VPC
defaultLogicalSwitch	String	▯▯▯▯▯▯▯▯▯▯
router	String	▯▯▯▯▯▯▯▯▯
tcpLoadBalancer	String	TCP ▯▯▯▯▯▯▯▯
udpLoadBalancer	String	UDP ▯▯▯▯▯▯▯▯
sctpLoadBalancer	String	SCTP ▯▯▯▯▯▯▯▯
tcpSessionLoadBalancer	String	TCP ▯▯▯▯▯▯▯▯▯▯
udpSessionLoadBalancer	String	UDP ▯▯▯▯▯▯▯▯▯▯
sctpSessionLoadBalancer	String	SCTP ▯▯▯▯▯▯▯▯▯▯
subnets	[]String	VPC ▯▯▯▯▯▯▯
vpcPeerings	[]String	VPC ▯▯▯▯▯▯▯
enableExternal	Bool	▯▯▯▯▯▯▯▯▯
extraExternalSubnets	[]String	▯▯▯▯▯▯▯▯
enableBfd	Bool	▯▯▯▯ BFD
bfdPort	BFDPortStatus	BFD ▯▯▯▯

8.11.3 Underlay ▯▯▯▯

Vlan

▯▯▯▯	▯▯	▯▯
apiVersion	String	▯▯ Kubernetes ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ kubeovn.io/v1
kind	String	▯▯ Kubernetes ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `Vlan`
metadata	ObjectMeta	▯▯ Kubernetes ▯▯▯▯▯▯▯▯
spec	VlanSpec	Vlan ▯▯▯▯▯▯▯▯▯
status	VlanStatus	Vlan ▯▯▯▯▯▯▯

VLANSPEC

▯▯▯▯	▯▯	▯▯
vlanId	Int	▯▯▯▯▯▯▯▯ id
providerInterfaceName	String	▯▯▯▯▯▯▯▯ provider
id	Int	Vlan tag ▯▯▯▯▯▯▯▯ 0~4095▯▯▯▯▯▯▯▯▯
provider	String	Vlan ▯▯▯ ProviderNetwork ▯▯▯▯▯▯▯▯▯▯▯▯

2025 Kube-OVN Team

VLANSTATUS

...	...	...
subnets	[]String	Vlan ...
conflict	Bool	...
conditions	[]VlanCondition	Vlan ... Condition ...

ProviderNetwork

...	...	...
apiVersion	String	... Kubernetes ... kubeovn.io/v1
kind	String	... Kubernetes ... `ProviderNetwork`
metadata	ObjectMeta	... Kubernetes ...
spec	ProviderNetworkSpec	ProviderNetwork ...
status	ProviderNetworkStatus	ProviderNetwork ...

PROVIDERNETWORKSPEC

...	...	...
defaultInterface	String	...
customInterfaces	[]CustomInterface	...
nodeSelector	LabelSelector	... OVS ... matchLabels ... matchExpressions... nodeSelector... excludeNodes ...
excludeNodes	[]String	...
exchangeLinkName	Bool	... OVS ...
autoCreateVlanSubinterfaces	Bool	... VLAN ...
preserveVlanInterfaces	Bool	... VLAN ...
vlanInterfaces	[]String	... VLAN ... eth0.10, bond0.20...

CustomInterface

...	...	...
interface	String	Underlay ...
nodes	[]String	...

PROVIDERNETWORKSTATUS

...	...	...
ready	Bool	...
readyNodes	[]String	...
notReadyNodes	[]String	...
vlans	[]String	... Vlan ...
conditions	[]ProviderNetworkCondition	ProviderNetwork ... Condition ...

2025 Kube-OVN Team

8.11.4 □□□□

SecurityGroup

□□□□	□□	□□
apiVersion	String	□□ Kubernetes □□□□□□□□□□□□□□□□□□□□ kubeovn.io/v1
kind	String	□□ Kubernetes □□□□□□□□□□□□□□□□□□□□ `SecurityGroup`
metadata	ObjectMeta	□□ Kubernetes □□□□□□□□
spec	SecurityGroupSpec	SecurityGroup □□□□□□□□□
status	SecurityGroupStatus	SecurityGroup □□□□□□□

SECURITYGROUPSPEC

□□□□	□□	□□
ingressRules	[]SecurityGroupRule	□□□□□□□□
egressRules	[]SecurityGroupRule	□□□□□□□□
allowSameGroupTraffic	Bool	□□□□□□□□□□□□□□
tier	Int	ACL □□□□

SecurityGroupRule

□□□□	□□	□□
ipVersion	String	IP □□□□□□□ `ipv4` □ `ipv6`
protocol	SgProtocol	□□□□□□□□□ `all` □ `icmp` □ `tcp` □ `udp`
priority	Int	□□□□□□□□□□□□ 1-16384□□□□□□□□□□□□□
remoteType	SgRemoteType	□□□□□□□□□ `address` □ `securityGroup`
remoteAddress	String	□□□□
remoteSecurityGroup	String	□□□□□□□□
portRangeMin	Int	□□□□□□□□□□□□□□□ 1
portRangeMax	Int	□□□□□□□□□□□□□□□ 65535
localAddress	String	□□□□□□ CIDR
sourcePortRangeMin	Int	□□□□□□□□□□□□□□□□ 1
sourcePortRangeMax	Int	□□□□□□□□□□□□□□□□ 65535
policy	SgPolicy	□□□□□□□□□ `allow` □ `pass` □ `drop`

2025 Kube-OVN Team

SECURITYGROUPSTATUS

[illegible]	[illegible]	[illegible]
portGroup	String	[illegible]
allowSameGroupTraffic	Bool	[illegible]
ingressMd5	String	[illegible] MD5 [illegible]
egressMd5	String	[illegible] MD5 [illegible]
ingressLastSyncSuccess	Bool	[illegible]
egressLastSyncSuccess	Bool	[illegible]

8.11.5 [illegible] IP

Vip

[illegible]	[illegible]	[illegible]
apiVersion	String	[illegible] Kubernetes [illegible] kubeovn.io/v1
kind	String	[illegible] Kubernetes [illegible] `Vip`
metadata	ObjectMeta	[illegible] Kubernetes [illegible]
spec	VipSpec	Vip [illegible]
status	VipStatus	Vip [illegible]

VIPSPEC

[illegible]	[illegible]	[illegible]
namespace	String	VIP [illegible]
subnet	String	VIP [illegible]
type	String	VIP [illegible]
v4ip	String	IPv4 [illegible]
v6ip	String	IPv6 [illegible]
macAddress	String	MAC [illegible]
selector	[]String	[illegible]
attachSubnets	[]String	[illegible]

VIPSTATUS

[illegible]	[illegible]	[illegible]
conditions	[]VipCondition	VIP [illegible] Condition [illegible]
type	String	VIP [illegible]
v4ip	String	IPv4 [illegible]
v6ip	String	IPv6 [illegible]
mac	String	MAC [illegible]
selector	[]String	[illegible] Pod [illegible]

2025 Kube-OVN Team

SwitchLBRule

▯▯▯▯	▯▯	▯▯
apiVersion	String	▯▯ Kubernetes ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ kubeovn.io/v1
kind	String	▯▯ Kubernetes ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `SwitchLBRule`
metadata	ObjectMeta	▯▯ Kubernetes ▯▯▯▯▯▯▯▯
spec	SwitchLBRuleSpec	SwitchLBRule ▯▯▯▯▯▯▯▯▯
status	SwitchLBRuleStatus	SwitchLBRule ▯▯▯▯▯▯▯

SWITCHLBRULESPEC

▯▯▯▯	▯▯	▯▯
vip	String	▯▯ IP ▯▯
namespace	String	▯▯▯▯▯▯▯
selector	[]String	▯▯▯▯▯▯
endpoints	[]String	▯▯▯▯▯▯▯
sessionAffinity	String	▯▯▯▯▯▯
ports	[]SwitchLBRulePort	▯▯▯▯▯

SwitchLBRulePort

▯▯▯▯	▯▯	▯▯
name	String	▯▯▯▯▯
port	Int32	▯▯▯▯
targetPort	Int32	▯▯▯▯▯▯
protocol	String	▯▯▯▯▯

SWITCHLBRULESTATUS

▯▯▯▯	▯▯	▯▯
conditions	[]SwitchLBRuleCondition	SwitchLBRule ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ Condition ▯▯
ports	String	SwitchLBRule ▯▯▯▯▯
service	String	SwitchLBRule ▯▯▯▯▯ service ▯▯

RouterLBRule

▯▯▯▯	▯▯	▯▯
apiVersion	String	▯▯ Kubernetes ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ kubeovn.io/v1
kind	String	▯▯ Kubernetes ▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `RouterLBRule`
metadata	ObjectMeta	▯▯ Kubernetes ▯▯▯▯▯▯▯▯
spec	RouterLBRuleSpec	RouterLBRule ▯▯▯▯▯▯▯▯▯
status	RouterLBRuleStatus	RouterLBRule ▯▯▯▯▯▯▯

2025 Kube-OVN Team

ROUTERLBRULESPEC

字段名	类型	说明
ovnEip	String	关联 OVN EIP 名称
vpc	String	所属 VPC
namespace	String	命名空间
selector	[]String	选择器
endpoints	[]String	端点列表
sessionAffinity	String	会话亲和
ports	[]RouterLBRulePort	端口列表

RouterLBRulePort

字段名	类型	说明
name	String	端口名
port	Int32	端口号
targetPort	Int32	目标端口
protocol	String	协议类型

ROUTERLBRULESTATUS

字段名	类型	说明
conditions	[]RouterLBRuleCondition	RouterLBRule 当前状态的 Condition 列表
ports	String	RouterLBRule 端口信息
service	String	RouterLBRule 关联的 service 名称

8.11.6 QoS 和 IP 管理

QoSPolicy

字段名	类型	说明
apiVersion	String	遵循 Kubernetes 的 API 版本规范 kubeovn.io/v1
kind	String	遵循 Kubernetes 的资源类型规范，`QoSPolicy`
metadata	ObjectMeta	遵循 Kubernetes 的元数据规范
spec	QoSPolicySpec	QoSPolicy 的详细规格

QOSPOLICYSPEC

字段名	类型	说明
bandwidthLimitRules	QoSPolicyBandwidthLimitRules	带宽限速规则列表
shared	Bool	是否共享策略
bindingType	QoSPolicyBindingType	绑定类型，`EIP` 或 `NATGW`

2025 Kube-OVN Team

QoSPolicyBandwidthLimitRule

字段名	类型	说明
name	String	规则名称
interface	String	网卡名称
rateMax	String	最大带宽Mbps，支持 `100` 或 `0.5` 这500Kbps这
burstMax	String	最大突发MB，支持 `10` 或 `0.5` 这500KB这
priority	Int	规则优先级
direction	QoSPolicyRuleDirection	规则方向，支持 `ingress` 和 `egress`
matchType	QoSPolicyRuleMatchType	匹配类型，支持 `ip`
matchValue	String	匹配内容

QOSPOLICYSTATUS

字段名	类型	说明
bandwidthLimitRules	QoSPolicyBandwidthLimitRules	绑定的带宽限速规则
shared	Bool	是否共享策略
bindingType	QoSPolicyBindingType	绑定类型
conditions	[]Condition	QoSPolicy 状态条件

IPPool

字段名	类型	说明
apiVersion	String	遵循 Kubernetes 规范的接口版本 kubeovn.io/v1
kind	String	遵循 Kubernetes 规范的接口类型，`IPPool`
metadata	ObjectMeta	遵循 Kubernetes 规范的对象元数据
spec	IPPoolSpec	IPPool 的规格说明
status	IPPoolStatus	IPPool 的状态信息

IPPOOLSPEC

字段名	类型	说明
subnet	String	子网名称
namespaces	[]String	这 IPPool 可以被哪些命名空间使用 IPPool 这 Pod
ips	[]String	IP 或者 CIDR 地址范围 ipCount 互斥
ipCount	Int32	需要从子网中自动分配多少个 IPv4 这 IPv6 地址，范围 1-32，与 ips 互斥
enableAddressSet	Bool	是否为 AddressSet 创建对应 ACL

2025 Kube-OVN Team

IPPOOLSTATUS

□□□□	□□	□□
v4AvailableIPs	BigInt	IPv4 □□ IP □□□□
v4AvailableIPRange	String	IPv4 □□ IP □□□□
v4UsingIPs	BigInt	IPv4 □□□ IP □□□□
v4UsingIPRange	String	IPv4 □□□ IP □□□□
v6AvailableIPs	BigInt	IPv6 □□ IP □□□□
v6AvailableIPRange	String	IPv6 □□ IP □□□□
v6UsingIPs	BigInt	IPv6 □□□ IP □□□□
v6UsingIPRange	String	IPv6 □□□ IP □□□□
ips	[]String	□□□□□□□ IP □□□□□□□□□□□□□□□□□□□
conditions	[]IPPoolCondition	IP □□□□□□□□□□□□□□□□□□ Condition □□

8.11.7 NAT □□□ IP □□

IptablesEIP

□□□□	□□	□□
apiVersion	String	□□ Kubernetes □□□□□□□□□□□□□□□□□□□ kubeovn.io/v1
kind	String	□□ Kubernetes □□□□□□□□□□□□□□□□□□□ `IptablesEIP`
metadata	ObjectMeta	□□ Kubernetes □□□□□□□□
spec	IptablesEIPSpec	IptablesEIP □□□□□□□□
status	IptablesEIPStatus	IptablesEIP □□□□□□□

IPTABLESEIPSPEC

□□□□	□□	□□
v4ip	String	IPv4 □□
v6ip	String	IPv6 □□
macAddress	String	MAC □□
natGwDp	String	NAT □□□□□□□
qosPolicy	String	QoS □□
externalSubnet	String	□□□□
namespace	String	NAT □□□□□□□□Deployment □ StatefulSet□□ Pod □□□ Namespace□□□□□□□□ VpcNatGateway □ controller □□□ Namespace □□□□□□□□□□□□□□□□□□ Namespace □□

2025 Kube-OVN Team

IPTABLESEIPSTATUS

...	...	...
ready	Bool	IptablesEIP ...
ip	String	IptablesEIP ... IP ... IPv4 ...
redo	String	IptablesEIP CRD ...
nat	String	IptablesEIP ... `fip` ... `snat` ... `dnat`
qosPolicy	String	QoS ...
conditions	[]IptablesEIPCondition	IptablesEIP ... Condition ...

OvnEip

...	...	...
apiVersion	String	... Kubernetes ... kubeovn.io/v1
kind	String	... Kubernetes ... `OvnEip`
metadata	ObjectMeta	... Kubernetes ...
spec	OvnEipSpec	OvnEip ...
status	OvnEipStatus	OvnEip ...

OVNEIPSPEC

...	...	...
externalSubnet	String	...
v4Ip	String	IPv4 ...
v6Ip	String	IPv6 ...
macAddress	String	MAC ...
type	String	... lrp、lsp ... nat

OVNEIPSTATUS

...	...	...
conditions	[]OvnEipCondition	OvnEip ...
type	String	OVN EIP ...
nat	String	NAT ...
ready	Bool	EIP ...
v4Ip	String	IPv4 ...
v6Ip	String	IPv6 ...
macAddress	String	MAC ...

2025 Kube-OVN Team

IptablesFIPRule

□□□□	□□	□□
apiVersion	String	□□ Kubernetes □□□□□□□□□□□□□□□□□□□□ kubeovn.io/v1
kind	String	□□ Kubernetes □□□□□□□□□□□□□□□□□□□□ `IptablesFIPRule`
metadata	ObjectMeta	□□ Kubernetes □□□□□□□□
spec	IptablesFIPRuleSpec	IptablesFIPRule □□□□□□□□□

IPTABLESFIPRULESPEC

□□□□	□□	□□
eip	String	□□ IP □□
internalIP	String	□□ IP □□

IPTABLESFIPRULESTATUS

□□□□	□□	□□
conditions	[]IptablesFIPRuleCondition	IptablesFIPRule □□□□□□□
ready	Bool	FIP □□□□□□□□□
v4ip	String	IPv4 EIP □□
v6ip	String	IPv6 EIP □□
natGwDp	String	NAT □□□□□□□
redo	String	IptablesFIPRule CRD □□□□
internalIP	String	□□ IP □□

OvnFip

□□□□	□□	□□
apiVersion	String	□□ Kubernetes □□□□□□□□□□□□□□□□□□□□ kubeovn.io/v1
kind	String	□□ Kubernetes □□□□□□□□□□□□□□□□□□□□ `OvnFip`
metadata	ObjectMeta	□□ Kubernetes □□□□□□□□
spec	OvnFipSpec	OvnFip □□□□□□□□□
status	OvnFipStatus	OvnFip □□□□□□□

2025 Kube-OVN Team

OVNFIPSPEC

□□□□	□□	□□
ovnEip	String	□□□ OVN EIP
ipType	String	IP □□□□□□ vip □ ip
ipName	String	IP □□
vpc	String	□□ VPC
v4Ip	String	IPv4 □□
v6Ip	String	IPv6 □□
type	String	□□□□□□ distributed □ centralized

OVNFIPSTATUS

□□□□	□□	□□
conditions	[]OvnFipCondition	OvnFip □□□□□□
ready	Bool	FIP □□□□□□
vpc	String	□□ VPC
v4Eip	String	IPv4 EIP □□
v6Eip	String	IPv6 EIP □□
v4Ip	String	IPv4 □□
v6Ip	String	IPv6 □□
macAddress	String	MAC □□

IptablesDnatRule

□□□□	□□	□□
apiVersion	String	□□ Kubernetes □□□□□□□□□□□□□□□□□□□□ kubeovn.io/v1
kind	String	□□ Kubernetes □□□□□□□□□□□□□□□□□□ `IptablesDnatRule`
metadata	ObjectMeta	□□ Kubernetes □□□□□□□□
spec	IptablesDnatRuleSpec	IptablesDnatRule □□□□□□□□

2025 Kube-OVN Team

IPTABLESDNATRULESPEC

...	...	...
eip	String	... IP ... clusterIP ...
clusterIP	String	Kubernetes Service ClusterIP... VPC ...
externalPort	String	...
protocol	String	...
internalIP	String	... IP ...
internalPort	String	...
type	String	DNAT ... `exclusive` ... `share` ...
sessionAffinity	String	... share ... `""` ... `ClientIP`
sessionAffinityTimeoutSeconds	Int32	ClientIP ... 10800...3 ...

IPTABLESDNATRULESTATUS

...	...	...
conditions	[]IptablesDnatRuleCondition	IptablesDnatRule ...
ready	Bool	DNAT ...
v4ip	String	IPv4 EIP ...
v6ip	String	IPv6 EIP ...
natGwDp	String	NAT ...
redo	String	IptablesDnatRule CRD ...
protocol	String	...
internalIP	String	... IP ...
internalPort	String	...
externalPort	String	...

OvnDnatRule

...	...	...
apiVersion	String	... Kubernetes ... kubeovn.io/v1
kind	String	... Kubernetes ... `OvnDnatRule`
metadata	ObjectMeta	... Kubernetes ...
spec	OvnDnatRuleSpec	OvnDnatRule ...
status	OvnDnatRuleStatus	OvnDnatRule ...

2025 Kube-OVN Team

OVNDNATRULESPEC

□□□□	□□	□□
ovnEip	String	□□□ OVN EIP
ipType	String	IP □□□□□□ vip □ ip
ipName	String	IP □□
internalPort	String	□□□□
externalPort	String	□□□□
protocol	String	□□□□
vpc	String	□□ VPC
v4Ip	String	IPv4 □□
v6Ip	String	IPv6 □□

OVNDNATRULESTATUS

□□□□	□□	□□
vpc	String	□□ VPC
v4Eip	String	IPv4 EIP □□
v6Eip	String	IPv6 EIP □□
externalPort	String	□□□□
v4Ip	String	IPv4 □□
v6Ip	String	IPv6 □□
internalPort	String	□□□□
protocol	String	□□□□
ipName	String	IP □□
ready	Bool	DNAT □□□□□□□□
conditions	[]OvnDnatRuleCondition	OVN DNAT □□□□□□□□□□□□□□□□□□□□ Condition □□

IptablesSnatRule

□□□□	□□	□□
apiVersion	String	□□ Kubernetes □□□□□□□□□□□□□□□□□□□ kubeovn.io/v1
kind	String	□□ Kubernetes □□□□□□□□□□□□□□□□□□ `IptablesSnatRule`
metadata	ObjectMeta	□□ Kubernetes □□□□□□□□
spec	IptablesSnatRuleSpec	IptablesSnatRule □□□□□□□□

IPTABLESSNATRULESPEC

□□□□	□□	□□
eip	String	□□ IP □□
internalCIDR	String	□□ CIDR □□

2025 Kube-OVN Team

IPTABLESSNATRULESTATUS

...	...	...
conditions	[]IptablesSnatRuleCondition	IptablesSnatRule ...
ready	Bool	SNAT ...
v4ip	String	IPv4 EIP ...
v6ip	String	IPv6 EIP ...
natGwDp	String	NAT ...
redo	String	IptablesSnatRule CRD ...
internalCIDR	String	... CIDR ...

OvnSnatRule

...	...	...
apiVersion	String	... Kubernetes ... kubeovn.io/v1
kind	String	... Kubernetes ... `OvnSnatRule`
metadata	ObjectMeta	... Kubernetes ...
spec	OvnSnatRuleSpec	OvnSnatRule ...
status	OvnSnatRuleStatus	OvnSnatRule ...

OVNSNATRULESPEC

...	...	...
ovnEip	String	... OVN EIP
vpcSubnet	String	VPC ...
ipName	String	IP ...
vpc	String	... VPC
v4IpCidr	String	IPv4 CIDR ...
v6IpCidr	String	IPv6 CIDR ...

OVNSNATRULESTATUS

...	...	...
conditions	[]OvnSnatRuleCondition	OvnSnatRule ...
ready	Bool	SNAT ...
vpc	String	... VPC
v4Eip	String	IPv4 EIP ...
v6Eip	String	IPv6 EIP ...
v4IpCidr	String	IPv4 CIDR ...
v6IpCidr	String	IPv6 CIDR ...

2025 Kube-OVN Team

8.11.8 VPC □□□□

VpcNatGateway

□□□□	□□	□□
apiVersion	String	□□ Kubernetes □□□□□□□□□□□□□□□□□□□□ kubeovn.io/v1
kind	String	□□ Kubernetes □□□□□□□□□□□□□□□□□□□□ `VpcNatGateway`
metadata	ObjectMeta	□□ Kubernetes □□□□□□□□
spec	VpcNatGatewaySpec	VpcNatGateway □□□□□□□□□
status	VpcNatGatewayStatus	VpcNatGateway □□□□□□□

VPCNATGATEWAYSPEC

□□□□	□□	□□
vpc	String	VPC □□ Pod □□□ VPC □□
subnet	String	VPC □□ Pod □□□□□□□□
namespace	String	VPC □□□□□□□□Deployment □ StatefulSet□□ Pod □□□ Namespace□□□□□□□ controller □□□ Namespace□□□□□□□□□
externalSubnets	[]String	□□□□□□□
lanIp	String	□□□ LAN IP□□ HA □□□□□□□□□□□□□□□□□□□□□□□□□□□□□HA □□□□□□□□□□
replicas	Int32	□□□□□□□□□□□□□□□ 1 □□□□□□□ 1 □□□ Deployment □□□□□□□
selector	[]String	□□ Kubernetes Selector □□□□
tolerations	[]Toleration	□□ Kubernetes □□□□□
affinity	Affinity	□□ Kubernetes □□□□□□
qosPolicy	String	QoS □□□□
bgpSpeaker	VpcBgpSpeaker	BGP speaker □□
bfd	VpcNatGatewayBFDConfig	BFD □□□□□□□□HA □□□
internalSubnets	[]String	□□□□□□□□□□□□□□□□□□□ 0.0.0.0/0 □ ::/0 □□□□□□□□□ NAT □□□□
internalCIDRs	[]String	□ CIDR □□□□□□□□□□□□□□ 0.0.0.0/0 □ ::/0 □□□□□□□□□ NAT □□□□
routes	[]Route	□□□□□□□
noDefaultEIP	Bool	□□□□□□□ EIP □□
annotations	map[String]String	StatefulSet NAT □□ Pod □□□□□□□ annotations□□□□□□□□□

2025 Kube-OVN Team

VpcBgpSpeaker

■■■■	■■	■■
enabled	Bool	■■■■ BGP speaker
asn	Uint32	■■■■■■■■
remoteAsn	Uint32	■■■■■■■■
neighbors	[]String	BGP ■■■■
holdTime	Duration	BGP ■■■■
routerId	String	BGP ■■■ ID
password	String	BGP ■■■■
enableGracefulRestart	Bool	■■■■■■■■■
extraArgs	[]String	■■■■■■■

VpcNatGatewayBFDConfig

■■■■	■■	■■
enabled	Bool	■■■■ BFD ■■■■■■■■■ VPC ■ spec.bfd.enabled ■ true
minRX	Int32	BFD ■■■■■■■■ms■■■■ 1000
minTX	Int32	BFD ■■■■■■■■ms■■■■ 1000
multiplier	Int32	BFD ■■■■■■■■ 3

Route

■■■■	■■	■■
cidr	String	■■■■ CIDR
nextHopIP	String	■■■ IP ■■

VPCNATGATEWAYSTATUS

■■■■	■■	■■
qosPolicy	String	QoS ■■■■
externalSubnets	[]String	■■■■■■■
selector	[]String	■■ Kubernetes Selector ■■■■
tolerations	[]Toleration	■■ Kubernetes ■■■■
affinity	Affinity	■■ Kubernetes ■■■■■
lanIp	String	■■■■ LAN ■■■HA ■■■■■■■■■■■■■■■■■■■
replicas	Int32	■■■ `spec.replicas` ■■■■■ `spec.replicas` ■ workload ■■■■ 1 ■■■■■■■■■■■■■■■ 0■
ready	Bool	■■ workload ■■■■■
workload	VpcNatWorkload	■■■■■■■■■■
internalSubnets	[]String	■■■■■■■■■■
internalCIDRs	[]String	■■■■■ CIDR ■■

2025 Kube-OVN Team

VpcNatWorkload

...	...	...
apiVersion	String	... API ...
kind	String	... `Deployment` ... `StatefulSet`
name	String	...
nodes	[]String	...

`VpcNatGateway` ... `spec.lanIp` ... controller ... `spec.lanIp` ... `spec.replicas` ... 1 ... `spec.lanIp` ... ... `status.lanIp` ...HA ... `status.replicas` ... `spec.replicas` ... `status.ready` ... workload ... `spec.replicas` ... workload ... 1 ... `status.replicas` ... 0...

VpcEgressGateway

...	...	...
apiVersion	String	... Kubernetes ... kubeovn.io/v1
kind	String	... Kubernetes ... `VpcEgressGateway`
metadata	ObjectMeta	... Kubernetes ...
spec	VpcEgressGatewaySpec	VpcEgressGateway ...
status	VpcEgressGatewayStatus	VpcEgressGateway ...

2025 Kube-OVN Team

VPCEGRESSGATEWAYSPEC

...	...	...
vpc	String	... VPC... VPC
bgpConf	String	... `BgpConf` ...
evpnConf	String	... `EvpnConf` ... EVPN ...
replicas	Int32	... 1
prefix	String	...`<prefix><veg-name>`
image	String	... kube-ovn-controller ...
internalSubnet	String	... VPC ... CNI ... provider ... `<nad-name>.<nad-namespace>.ovn` ... NetworkAttachmentDefinition ...
externalSubnet	String	...
externalNetworkMode	String	...`Attachment` ... externalSubnet... `PrimaryCNI` ... Pod ...
internalIPs	[]String	... IP ... `v4,v6` ...
externalIPs	[]String	... IP ... `v4,v6` ...
internalIPPool	String	... `IPPool` ... `internalSubnet` ... `internalIPs` ...
externalIPPool	String	... `IPPool` ... `externalSubnet` ... `externalIPs` ...
selectors	[]VpcEgressGatewaySelector	.../Pod ... CNI ...`policies`
trafficPolicy	String	...`Cluster` ... `Local` ... VPC ...
podAntiAffinity	String	Pod ...`Required` ...`Preferred` ...
bfd	VpcEgressGatewayBFDConfig	BFD ...
policies	[]VpcEgressGatewayPolicy	...
nodeSelector	[]VpcEgressGatewayNodeSelector	...
tolerations	[]Toleration	... Kubernetes ...
priorityClassName	String	... Pod ... PriorityClass ...
resources	ResourceRequirements	...
bandwidth	BandwidthLimit	.../... Mbps ... bit-rate quantity
observability	VpcEgressGatewayObservability	...conntrack ...JSON ... ServiceMonitor ...

VpcEgressGatewaySelector

...	...	...
namespaceSelector	LabelSelector	...
podSelector	LabelSelector	Pod ...

2025 Kube-OVN Team

VpcEgressGatewayBFDConfig

■■■■	■■	■■
enabled	Boolean	■■■■ BFD■■■■■ VPC ■ `.spec.bfd.enabled=true` ■■■■ false
minRX	Int32	BFD ■■■■■■■ms■■■■ 1000
minTX	Int32	BFD ■■■■■■■ms■■■■ 1000
multiplier	Int32	BFD ■■■■■■■ 3

VpcEgressGatewayPolicy

■■■■	■■	■■
snat	Boolean	■■■■■■■■■■ SNAT/MASQUERADE■■■ false
ipBlocks	[]String	■■■ CIDR ■■
subnets	[]String	■■■■■■■■■■

VpcEgressGatewayNodeSelector

■■■■	■■	■■
matchLabels	map[String]String	■■■■■■■
matchExpressions	[]NodeSelectorRequirement	■■■■■■■■
matchFields	[]NodeSelectorRequirement	■■■■■■■■

BandwidthLimit

■■■■	■■	■■
ingress	Int64 ■ String	■■■■■■■■ VPC ■■■■■■■■■■■■■■■■■■■■■■ Mbps■quantity ■ `M` ■ `Mi` ■ `G` ■ `Gi` bit/s
egress	Int64 ■ String	■ VPC ■■■■■■■■■■■■■■■■■■■■■■■■■■■■■■ Mbps■quantity ■ `M` ■ `Mi` ■ `G` ■ `Gi` bit/s

VpcEgressGatewayObservability

■■ Kubernetes 1.29 ■■■■■■■■■■■■■■■■■■■■■■■■ schema ■■■■■■■■■■ VPC Egress Gateway ■■■■■■

■■■■	■■	■■
resources	ResourceRequirements	■■■observer sidecar ■■■■■■ request ■ `20m` CPU ■ `64Mi` ■■■limit ■ `200m` CPU ■ `256Mi` ■■
interfaceMetrics	VpcEgressGatewayObservabilityFeature	■■■■■■■■■■
conntrack	VpcEgressGatewayConntrackObservability	conntrack ■■■■■■■■■
serviceMonitor	VpcEgressGatewayServiceMonitor	■■■■■■■■ ServiceMonitor ■■■■■

VpcEgressGatewayObservabilityFeature

■■■■	■■	■■
enabled	Boolean	■■■■■■■■■■■ false

2025 Kube-OVN Team

VpcEgressGatewayConntrackObservability

■■■■	■■	■■
metrics	VpcEgressGatewayObservabilityFeature	■■■ NAT conntrack ■■■■
log	VpcEgressGatewayConntrackLog	JSON Lines NAT ■■■■■

VpcEgressGatewayConntrackLog

■■■■	■■	■■
enabled	Boolean	■■■ JSON ■■■■■ observer ■■■■■■■■■ false
events	[]String	■■■■■■■■■■■■■■ `start` ■/■ `end` ■■■■■■■■
rateLimit	VpcEgressGatewayConntrackLogRateLimit	■■ Pod ■■■■■■
filters	VpcEgressGatewayConntrackLogFilters	■■■include ■ exclude ■■

VpcEgressGatewayConntrackLogRateLimit

■■■■	■■	■■
recordsPerSecond	Int32	■■■■■■■■■■■■ 1 ■ 100000■■■ 100
burst	Int32	■■■■■■■■■■■■ 1 ■ 1000000■■■ 1000

VpcEgressGatewayConntrackLogFilters

■■■■	■■	■■
include	[]VpcEgressGatewayConntrackLogFilter	■■■■■ 64 ■ include ■■■■■■■■■■ NAT ■
exclude	[]VpcEgressGatewayConntrackLogFilter	■■■■■ 64 ■ exclude ■■■exclude ■■■■

VpcEgressGatewayConntrackLogFilter

■■■■■■■■■■■■■ AND ■■■■■■■■■■■■■■■■■■■■■■■■■■ OR ■■■

■■■■	■■	■■
addressFamilies	[]String	■■■ `ipv4` ■/■ `ipv6`
protocols	[]String	■■■ `tcp` ■ `udp` ■ `sctp` ■ `icmp` ■ `icmpv6` ■/■ `other`
natTypes	[]String	■■■ `snat` ■ `dnat` ■/■ `snat_dnat`
original	VpcEgressGatewayConntrackTupleFilter	■■ tuple ■■
translated	VpcEgressGatewayConntrackTupleFilter	■■■ tuple ■■

VpcEgressGatewayConntrackTupleFilter

■■■■	■■	■■
sourceCIDRs	[]String	■■■■ CIDR■■■ 64 ■
destinationCIDRs	[]String	■■■■■ CIDR■■■ 64 ■
sourcePorts	[]VpcEgressGatewayPortRange	■■■■■■■■■■■■■■■■■ 64 ■
destinationPorts	[]VpcEgressGatewayPortRange	■■■■■■■■■■■■■■■■■■■ 64 ■

2025 Kube-OVN Team

VpcEgressGatewayPortRange

...	...	...
start	Int32	... 0 ... 65535
end	Int32	... `start` ... 65535

VpcEgressGatewayServiceMonitor

...	...	...
labels	map[String]String	...ServiceMonitor ... selector ...
annotations	map[String]String	...ServiceMonitor annotations

VPCEGRESSGATEWAYSTATUS

...	...	...
replicas	Int32	... scale ...
labelSelector	String	... scale ...
ready	Boolean	...
phase	String	... `Pending` ... `Processing` ... `Completed`
internalIPs	[]String	... IP ...
externalIPs	[]String	... IP ...
conditions	[]Condition	...
workload	VpcEgressWorkload	...

VpcEgressWorkload

...	...	...
apiVersion	String	... API ...
kind	String	... `Deployment`
name	String	...
nodes	[]String	...

BgpConf

...cluster-scoped... `VpcEgressGateway.spec.bgpConf` ...

...	...	...
apiVersion	String	... Kubernetes ... kubeovn.io/v1
kind	String	... Kubernetes ... `BgpConf`
metadata	ObjectMeta	... Kubernetes ...
spec	BgpConfSpec	BgpConf ...

2025 Kube-OVN Team

BGPCONFSPEC

■■■■	■■	■■
localASN	UInt32	■■ BGP AS Number
peerASN	UInt32	■■ BGP AS Number
routerId	String	■■■BGP Router ID
neighbours	[]String	BGP ■■ IP ■■
password	String	■■■TCP MD5 ■■■■
holdTime	Duration	■■■BGP Hold time
keepaliveTime	Duration	■■■BGP Keepalive ■■
connectTime	Duration	■■■BGP Connect ■■
ebgpMultiHop	Boolean	■■■■■■■ eBGP MultiHop
gracefulRestart	Boolean	■■■■■■■ BGP Graceful Restart

EvpnConf

■■■■cluster-scoped■■■■■ `VpcEgressGateway.spec.evpnConf` ■■■■■■ EVPN ■■■■■ VNI ■ Route Target■

■■■■	■■	■■
apiVersion	String	■■ Kubernetes ■■■■■■■■■■■■■■■■■■■■ kubeovn.io/v1
kind	String	■■ Kubernetes ■■■■■■■■■■■■■■■■■■■■[`EvpnConf`
metadata	ObjectMeta	■■ Kubernetes ■■■■■■■■
spec	EvpnConfSpec	EvpnConf ■■■■■■■■■

EVPNCONFSPEC

■■■■	■■	■■
vni	UInt32	EVPN VNI
routeTargets	[]String	Route Target ■■

DNSNameResolver

■■■■cluster-scoped■■■■■ `enable-dns-name-resolver` ■■■ ANP/CNP ■■■■■■■■■■■■ DNS ■■■■■

■■■■	■■	■■
apiVersion	String	■■ Kubernetes ■■■■■■■■■■■■■■■■■■■■ kubeovn.io/v1
kind	String	■■ Kubernetes ■■■■■■■■■■■■■■■■■■■■[`DNSNameResolver`
metadata	ObjectMeta	■■ Kubernetes ■■■■■■■■
spec	DNSNameResolverSpec	DNSNameResolver ■■■■■■■■■
status	DNSNameResolverStatus	DNSNameResolver ■■■■■■■

2025 Kube-OVN Team

DNSNAMERESOLVERSPEC

...	...	...
name	String	... DNS ... `*.` ...

DNSNAMERESOLVERSTATUS

...	...	...
resolvedNames	[]DNSNameResolverResolvedName	... DNS ... IP ...

DNSNameResolverResolvedName

...	...	...
dnsName	String	... DNS ...
resolvedAddresses	[]DNSNameResolverResolvedAddress	... IP、TTL ...
conditions	[]Condition	... `Degraded` ...
resolutionFailures	Int32	... 5 ... TTL ...

DNSNameResolverResolvedAddress

...	...	...
ip	String	... IP ...
ttlSeconds	Int32	TTL ... `lastLookupTime + ttlSeconds` ...
lastLookupTime	Time	...

VpcDns

...	...	...
apiVersion	String	... Kubernetes ... kubeovn.io/v1
kind	String	... Kubernetes ... `VpcDns`
metadata	ObjectMeta	... Kubernetes ...
spec	VpcDNSSpec	VpcDns ...
status	VpcDNSStatus	VpcDns ...

VPCDNSSPEC


...	...	...
replicas	Int32	...
vpc	String	... VPC
subnet	String	...

PDF Slack Support

2025 Kube-OVN Team

2026▯11▯5▯

2023▯2▯16▯



GitHub



+3

8.11.9 ▯▯

8.12 Annotation □□□□

Kube-OVN □□□□□□ Pod □ Node Annotation □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□ Annotation □□□□□□□□□□□□□□□□□□

> □□□□□ Annotation □□□□□□□□□□□□□□□□

2025 Kube-OVN Team

8.12.1 Pod Annotation

Key	Value	Description
ovn.kubernetes.io/allocated	`true` or `false`	Pod
ovn.kubernetes.io/routed	`true` or `false`	Pod OVN
ovn.kubernetes.io/routes	String	Pod
ovn.kubernetes.io/mac_address	String	Pod Mac Pod Annotation Mac
ovn.kubernetes.io/ip_address	String	Pod IP Pod Annotation IP
ovn.kubernetes.io/ip_family	`ipv4` or `ipv6`	Pod IP
\<nadName>.\<nadNamespace>.kubernetes.io/ip_address.\<interfaceName>	String	IPinterfaceName Multus interface ovn.kubernetes.io/ip_address
\<nadName>.\<nadNamespace>.kubernetes.io/mac_address.\<interfaceName>	String	MACinterfaceName Multus interface
ovn.kubernetes.io/cidr	String	Pod CIDR
ovn.kubernetes.io/gateway	String	Pod Gateway
ovn.kubernetes.io/ip_pool	IP	Pod Workload IP
ovn.kubernetes.io/bgp	`true`, `cluster`, `local`	BGP Pod
ovn.kubernetes.io/snat	String	Pod SNAT
ovn.kubernetes.io/eip	String	Pod EIP
ovn.kubernetes.io/vip	String	v1.17 Annotation `ovn.kubernetes.io/ip_address` `ovn.kubernetes.io/ip_pool` IPPool Pod
ovn.kubernetes.io/aaps	String	Pod AAPs (Additional Allowed Addresses Pairs)
ovn.kubernetes.io/virtualmachine	String	Pod VirtualMachineInstance
ovn.kubernetes.io/activation_strategy	String	Pod
ovn.kubernetes.io/logical_router	String	Pod VPC
ovn.kubernetes.io/layer2_forward	`true` or `false`	Pod OVN LSP `unknown`
ovn.kubernetes.io/port_security	`true` or `false`	Pod Port Security
ovn.kubernetes.io/logical_switch	String	Pod
ovn.kubernetes.io/vlan_id	Int	Pod Vlan ID
ovn.kubernetes.io/ingress_rate	Int	Pod Mbits/s
ovn.kubernetes.io/egress_rate	Int	Pod Mbits/s
ovn.kubernetes.io/ingress_burst	Int	Pod burst Mbit 80% `0` burst
ovn.kubernetes.io/egress_burst	Int	Pod burst Mbit 80% `0` burst
ovn.kubernetes.io/security_groups	String	Pod Security Group
ovn.kubernetes.io/default_route	`true` or `false`	
ovn.kubernetes.io/provider_network	String	Pod ProviderNetwork
ovn.kubernetes.io/mirror	`true` or `false`	Pod

2025 Kube-OVN Team

Key	Value	Description
ovn.kubernetes.io/north_gateway	String	Pod
ovn.kubernetes.io/latency	Int	Pod ms
ovn.kubernetes.io/limit	Int	Pod qdisc
ovn.kubernetes.io/loss	Float	Pod
ovn.kubernetes.io/jitter	Int	Pod ms
ovn.kubernetes.io/generate-hash	`true` or `false`	Pod
ovn.kubernetes.io/attachmentprovider	String	Pod
ovn.kubernetes.io/vpc_nat_gw	String	VPC NAT Gateway Pod
ovn.kubernetes.io/vpc_nat_gw_init	`true` or `false`	VPC NAT Gateway Pod
ovn.kubernetes.io/vpc_nat_gw_container_restarted	`true` or `false`	VPC NAT Gateway
ovn.kubernetes.io/vpc_nat_gw_activated	`true` or `false`	VPC NAT Gateway
\<provider>.kubernetes.io/ip_pool	IP	provider IP
\<provider>.kubernetes.io/ip_family	`ipv4` or `ipv6`	provider IP
\<provider>.kubernetes.io/dhcp-v4-options	String	provider DHCPv4
\<provider>.kubernetes.io/port_security	`true` or `false`	provider
\<provider>.kubernetes.io/ingress_burst	Int	provider burst Mbit
\<provider>.kubernetes.io/egress_burst	Int	provider burst Mbit

8.12.2 Node Annotation

Key	Value	Description
ovn.kubernetes.io/allocated	`true` or `false`	`ovn0` `join`
ovn.kubernetes.io/mac_address	String	Node `ovn0` Mac
ovn.kubernetes.io/ip_address	String	Node `ovn0` IP
ovn.kubernetes.io/cidr	String	Node `ovn0` `join` CIDR
ovn.kubernetes.io/gateway	String	Node `ovn0` `join` Gateway
ovn.kubernetes.io/chassis	String	Node OVN-SouthBoundDB Chassis ID
ovn.kubernetes.io/port_name	String	Node `ovn0` OVN-NorthboundDB LSP
ovn.kubernetes.io/logical_switch	String	Node `ovn0`
ovn.kubernetes.io/tunnel_interface	String	
ovn.kubernetes.io/node_networks	String	Pod attachment networks NetworkAttachmentDefinition

8.12.3 Namespace Annotation

Key	Value	Description
ovn.kubernetes.io/cidr	CIDR	Namespace CIDR
ovn.kubernetes.io/exclude_ips	excludeIPs	Namespace excludeIPs

2025 Kube-OVN Team

8.12.4 Subnet Annotation

Key	Value	Description
ovn.kubernetes.io/bgp	`true`, `cluster`, `local`	□□□□□□ BGP □□□□□□
ovn.kubernetes.io/vpc	String	□□□□□ VPC□□□□□□□□□□ VPC □□□

8.12.5 Service Annotation

Key	Value	Description
ovn.kubernetes.io/bgp	`true`, `cluster`, `local`	□□□□□□ BGP □□ Service □□□□ ClusterIP Service □□□□□□ Pod/Subnet □□□
ovn.kubernetes.io/switch_lb_vip	String	Service □ Kube-OVN □□□□□□ VIP □□
ovn.kubernetes.io/vpc	String	Service □□□ VPC
ovn.kubernetes.io/service_external_ip_from_subnet	`true` or `false`	Service □□ IP □□□□□□□
ovn.kubernetes.io/service_health_check	`true` or `false`	Service □□□□□□□□
ovn.kubernetes.io/lb_svc_img	String	□□□□□□□□□□□

8.12.6 Networkpolicy Annotation


Key	Value	Description
ovn.kubernetes.io/enable_log	`true` or `false`	□□□□ NetworkPolicy □□
ovn.kubernetes.io/log_acl_actions	"allow,drop,pass" □□□□□□□□ □□	□□□□ Action ACL □□□
ovn.kubernetes.io/acl_log_meter_rate	Int	NetworkPolicy □□□□□□□□□□□□□□□/□
ovn.kubernetes.io/network_policy_enforcement	`standard` or `lax`	□□ NetworkPolicy □□□□□□□□□□□□□□
ovn.kubernetes.io/network_policy_for	String	□□□ NetworkPolicy □□□□□□□ provider□□□ `<nadName>.<nadNamespace>.ovn` □

PDF Slack Support

2026□10□29□

2024□6□12□

GitHub



+2

8.12.7 □□

2025 Kube-OVN Team

8.13 □□□□

□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□

8.13.1 □□

□□□

Bad	Good
□□	□□

□□□□□□□□□□□□□□□□□□□□□

Bad	Good
Kube-OVN □□□□□□□□□□□□□□ 1.10 □□ Kube-OVN□	Kube-OVN □□□□□□□□□□□□□□ 1.10 □□ Kube-OVN□

□□□□□□□□ □□ □□□□□□□□□□□□ □□ □□□

Bad	Good
□□□□□□□□□□□□□□ □□□□□□□□□□□□□□□□□	□□□□□□□□□□□□□□□□ □□□□□□□□□□□□□□□□□
`wget 127.0.0.1`	`wget 127.0.0.1`

8.13.2 □□□

yaml □□□□□□□□□ yaml□

Bad	Good

``
apiVersion: kubeovn.io/v1
kind: Subnet
metadata:
    name: attach-subnet
``
	``yaml
	apiVersion: kubeovn.io/v1
	kind: Subnet
	metadata:
	    name: attach-subnet
	``

□□□□□□□□□□□□□□□□□ bash□

Bad	Good

``
wget 127.0.0.1
``
	``bash
	wget 127.0.0.1
	``

2025 Kube-OVN Team

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `#` ▯▯▯▯▯▯▯▯▯▯▯▯▯

Bad	Good
oilbeater@macdeMac-3 ~ ping 114.114.114.114 -c 3 PING 114.114.114.114 (114.114.114.114): 56 data bytes 64 bytes from 114.114.114.114: icmp_seq=0 ttl=83 time=10.429 ms 64 bytes from 114.114.114.114: icmp_seq=1 ttl=79 time=11.360 ms 64 bytes from 114.114.114.114: icmp_seq=2 ttl=76 time=10.794 ms --- 114.114.114.114 ping statistics --- 3 packets transmitted, 3 packets received, 0.0% packet loss round-trip min/avg/max/stddev = 10.429/10.861/11.360/0.383 ms	# ping 114.114.114.114 -c 3 PING 114.114.114.114 (114.114.114.114): 56 data bytes 64 bytes from 114.114.114.114: icmp_seq=0 ttl=83 time=10.429 ms 64 bytes from 114.114.114.114: icmp_seq=1 ttl=79 time=11.360 ms 64 bytes from 114.114.114.114: icmp_seq=2 ttl=76 time=10.794 ms --- 114.114.114.114 ping statistics --- 3 packets transmitted, 3 packets received, 0.0% packet loss round-trip min/avg/max/stddev = 10.429/10.861/11.360/0.383 ms

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯ `#` ▯▯▯

Bad	Good
# mv /etc/origin/ovn/ovnnb_db.db /tmp # mv /etc/origin/ovn/ovnsb_db.db /tmp	mv /etc/origin/ovn/ovnnb_db.db /tmp mv /etc/origin/ovn/ovnsb_db.db /tmp

8.13.3 ▯▯

▯▯▯▯▯▯▯▯ `md` ▯▯▯▯▯

Bad	Good
[ ](http://kubeovn.github.io/prepare)	[ ](./prepare.md)

Bad	Good
[Kubernetes](http://kubernetes.io)	[Kubernetes](http://kubernetes.io){: target="_blank" }

8.13.4 ▯▯

▯▯

Bad	Good

``bash
wget 127.0.0.1
``
	``bash
	wget 127.0.0.1
	``

▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯▯

Bad	Good

``bash
wget 127.0.0.1
``
	``bash
	wget 127.0.0.1
	``

PDF Slack Support

2025 Kube-OVN Team

2025▯9▯10▯

2022▯7▯19▯



GitHub 



8.13.5 ▯▯

9. □□□□

Kube-OVN □□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□□

9.1 □□□□

- Slack□□ CNCF Slack □□□□□ #kube-ovn □□
- LinkedIn□Kube-OVN □□□□
- Issue / □□□□ GitHub Issues □□□□□GitHub Discussions □□□□□□

9.2 □□□□

- □□□□□□□□□□□□□□□□□□□□□□□□

9.3 □□

- □□ □□□□ □ □□□□ □□□□□□
- □□ USERS.md □□□□□□□□

PDF Slack Support

2026□4□28□

2022□6□20□

GitHub 

9.4 □□

2025 Kube-OVN Team