

DRAWING INDEX

Sheet	Title	Rev	Issued
E-000	Legend, Drawing Index, General Notes	0	2026-09-08
E-001	Single-Line Diagram	0	2026-09-08
E-002	Panel Schedule LP-1	0	2026-09-08
E-101	Lighting Plan, Main Floor	0	2026-09-08
E-102	Power Plan, Main Floor	0	2026-09-08

LEGEND

Symbol	Meaning
	Type M1: 2x4 LED troffer, recessed in T-bar ceiling
	Type M2: exit sign, LED, running man pictogram
	Type M3: emergency battery unit with two remote-capable heads
\$	Type M4: single-pole switch, 15A, 1200 mm above finished floor
	Type M5: duplex receptacle, 15A, 125V, CSA 5-15R, 400 mm above finished floor
LP-1-1	Circuit tag: panel LP-1, circuit 1
-----	Feeder route, see single-line diagram

ABBREVIATIONS

AFF: above finished floor. EMT: electrical metallic tubing. MDP: main distribution panel. THHN: thermoplastic high heat-resistant nylon-coated conductor. Cu: copper. 1P, 3P: one pole, three pole. VA: volt-amperes. kVA: kilovolt-amperes.

MATERIALS SCHEDULE

Descriptions are the Owner's standard material descriptions for this project. Use them as written.

Mark	Description	Unit	Section
M1	2x4 LED troffer	each	26 51 00
M2	Exit sign, LED	each	26 52 00
M3	Emergency battery unit with heads	each	26 52 00
M4	Single-pole switch	each	26 27 26
M5	Duplex receptacle, 15A, incl. box and device	each	26 27 26
M6	20A branch circuit breaker	each	26 24 16
M7	42-circuit panelboard, 225A, surface	each	26 24 16
M8	Dry-type transformer, 75 kVA	each	26 22 13
M9	Feeder, 3C plus ground, 100A in EMT	metre	26 05 00
M10	EMT 21 mm	metre	26 05 33
M11	Copper conductor #12 THHN	metre	26 05 19

GENERAL NOTES

- The work is the electrical fit-out of the main floor of an existing single-storey building. The base building shell is complete. There is no demolition.
- Supply and install materials as listed on the materials schedule and specified in Division 26. Conduit fittings, boxes, supports, and connectors are incidental to the listed materials and are not measured separately.
- Branch circuits: three #12 THHN copper conductors (line, neutral, bond) in 21 mm EMT per circuit. Circuit runs are not dimensioned. Allow an average run of 25 m per branch circuit shown in use on panel schedule LP-1. Spare breakers are not wired.
- Feeder F1 is dimensioned on the single-line diagram.
- Transformer T1 secondary conductors to panel LP-1, and the T1 bonding connection to the existing building ground bus, are part of the transformer installation.
- The work does not penetrate any fire-rated separation.
- Fire alarm, data, and security systems are by others and are not part of this contract.
- Coordinate a shutdown of the existing MDP with the Owner, outside library opening hours, to connect feeder F1 to the existing spare breaker.
- Test every circuit and provide a typed panel directory for LP-1.

Brightline Consulting Engineers Ltd.

Electrical engineering. Project BCE-26-114

PROJECT

Quillbrook Public Library, Main Floor
Electrical Fit-out

2150 Heron Crescent, Quillbrook, Alberta

OWNER

Quillbrook Public Library Board

REVISIONS

Rev	Description	Date
0	Issued for tender	2026-09-08

SCALE

Not to scale

SHEET TITLE

Legend, Drawing Index, General Notes

SHEET

E-000