

GET Api/CardRequests/{id}

[Help](#) [Page Home](#)

GET Api/CardRequests/{id}

Retrieve the current status of a particular Card Request

Required Permissions

None.

Request Information

Headers/Cookies

Name	Description
JWT	OAuth Token

URI Parameters

Name	Description	Type	Additional information
id	The ID of the Card Request you want the status of	string	Required

Body Parameters

None.

Response Information

A CardRequestStatusModel filled with the current status of the card request.

DCG.WebAPI.Models.CardRequestStatusModel

Name	Description	Type	Additional information
CardRequestID		string	None.

Name	Description	Type	Additional information
Status	GET Api/CardRequests/{id}	DCG.Card.CardRequestStatusEnum	None.
PINOffset		string	None.
PVV		string	None.
ErrorID		DCG.Card.CardRequestErrorEnum	None.
ErrorDescription		string	None.
DeviceErrorID		integer	None.
DeviceErrorDescription		string	None.
DeviceErrorCodes		Collection of string	None.
PrinterQueuePosition		integer	None.
CardMailerPrinted		boolean	None.
PINMailerPrinted		boolean	None.
Track1Data		string	None.
Track2Data		string	None.
Track3Data		string	None.
RequestedTrackItem		string	None.

Response body formats

application/json, text/json

Sample:

```
{
  "cardRequestID": "sample string 1",
  "status": 2,
  "pinOffset": "1234",
  "pvv": "5678",
  "errorID": 2,
  "errorDescription": "Error Description",
```

GET Api/CardRequests/{id}

```

    "deviceErrorID": 3,
    "deviceErrorDescription": "Device Error Description",
    "deviceErrorCodes": [
      "155",
      "175"
    ],
    "printerQueuePosition": 4,
    "cardMailerPrinted": true,
    "pinMailerPrinted": true,
    "track1Data": "Track 1 Data",
    "track2Data": "Track 2 Data",
    "track3Data": "Track 3 Data",
    "requestedTrackItem": "Requested Track Item"
  }

```

application/xml, text/xml

Sample:

```

<CardRequestStatusModel xmlns:xsd="http://www.w3.org/2001/XMLSchema"
xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance">
  <CardRequestID>sample string 1</CardRequestID>
  <Status>InPrinterQueue</Status>
  <PINOffset>1234</PINOffset>
  <PVV>5678</PVV>
  <ErrorID>CardMailerPrintFail</ErrorID>
  <ErrorDescription>Error Description</ErrorDescription>
  <DeviceErrorID>3</DeviceErrorID>
  <DeviceErrorDescription>Device Error
Description</DeviceErrorDescription>
  <DeviceErrorCodes>
    <string>155</string>
    <string>175</string>
  </DeviceErrorCodes>
  <PrinterQueuePosition>4</PrinterQueuePosition>
  <CardMailerPrinted>true</CardMailerPrinted>
  <PINMailerPrinted>true</PINMailerPrinted>
  <Track1Data>Track 1 Data</Track1Data>
  <Track2Data>Track 2 Data</Track2Data>
  <Track3Data>Track 3 Data</Track3Data>
  <RequestedTrackItem>Requested Track Item</RequestedTrackItem>
</CardRequestStatusModel>

```

© 2014-2018 Entrust Datacard Corporation. All rights reserved..

Datacard and CardWizard are registered trademarks and service marks of Entrust Datacard Corporation in the United States and other countries.