C1010 (BK)

13A006



12A581



F08243

(1) 57 (BK)
(2) 14 (BN)
(3) 12 (LG/BK)
(4) 13 (RD/BK)
(5) 2 (WH/LB)
(6) 3 (LG/WH)
(7) 13 (RD/BK)
(8) –

C1011

12A581

Blower motor relay



F05147

Pin	Circuit	Circuit function
30	37 (YE)	Voltage supplied at all times (overload protected)
85	753 (YE/RD)	Function selector switch assembly, front, output
86	57 (BK)	Ground
87	515 (OG/RD)	Blower motor relay, switch, output
87A	–	not used

C1016

12A581

PCM power relay



F05147

Pin	Circuit	Circuit function
30	37 (YE)	Voltage supplied at all times (overload protected)
85	570 (BK/WH)	Ground
86	16 (RD/LG)	Voltage supplied in Start and Run (overload protected)
87	361 (RD)	Voltage supplied in Start and Run (overload protected)
87A	–	not used

C1017a

10K304/14300/14439

Starter relay (11450)



F01085

Pin	Circuit	Circuit function
1	290 (GY) 2037 (RD) 303 (YE)	Battery cable +

C1017b

14300

Starter relay (11450)

F01025

Pin	Circuit	Circuit function
1	2037	Battery cable +