-21

C63

14401



F15010

Pin	Circuit	Circuit Function
1	10-GL37 (GY/OG)	Signal 2 (Y–direction, reverse, downward)
2	31S-BB6 (BK/YE)	Ground, switched
	31S-BB16 (BK/RD)	Ground, switched
3	31S-GL6 (BK/OG)	Ground, switched
	31S-GL6A (BK/OG) +	Ground (power return), switched
	31S-GL6 (BK/OG)	Ground (power return), switched
4	29-RE14 (OG/BK)	Voltage supplied at all times (overload protected)
5	31S-TA34 (BK/YE)	Ground, switched
6	5-EG7 (BU/RD) +	Data link, bus negative
	5-EG8 (BU/WH)	Data link, bus negative
	5-EG9 (BU/BK)	Data link, bus negative
7	8-GL37 (WH/GN)	Sensor signal
8	31S-BB16 (BK/RD)	Ground, switched
9	8-MD24 (WH/GN)	Sensor signal
	8-MD24 (WH/GN) +	Sensor signal
	8-PG18 (WH/BU)	Sensor signal
	8-GM11 (WH/BK) +	Sensor signal
	8-MD24 (WH/GN)	Sensor signal
	8-RE22 (WH/VT)	Sensor signal
	8-PG18 (WH/BU)	Sensor signal
10	9-GA7 (BN/RD)	Sensor signal return (reference/ground)
	9-GA7 (BN/RD) +	Sensor signal return (reference/ground)
	9-GA7A (BN/RD)	Sensor signal return (reference/ground)
11	8-GA7 (WH/RD)	Sensor signal
	8-GA7 (WH/RD) +	Sensor signal
	8-GA7A (WH/RD)	Sensor signal
12	8-GH9 (WH/BU)	Sensor signal
13	15S-FA17 (GN/OG)	Voltage, ignition switch in Start or Run (not overload protected), switched
14	31S-GC20 (BK/OG)	Ground, switched
	31S-GC20 (BK/OG) +	Ground, switched
	31S-GC20A (BK/OG)	Ground, switched
15	4-EG7 (GY/RD) +	Data link, bus positive
	4-EG8 (GY/VT)	Data link, bus positive
	4-EG9 (GY/OG)	Data link, bus positive