C1008

14290

K107
A/C clutch relay



F05064

Pin	Circuit	Circuit Function
1	361 (RD)	Voltage supplied in Start and Run (overload protected)
	361 (RD)	Voltage supplied in Start and Run (overload protected)
2	331 (PK/YE)	A/C clutch relay, control
3	883 (PK/LB)	Voltage supplied at all times (overload protected)
4	–	not used
5	347 (BK/YE)	A/C clutch relay, switched output
	347 (BK/YE)	A/C clutch relay, switched output

C1017

14290

K22
Starter relay



F05051

Pin	Circuit	Circuit Function
87	1050 (LG/VT)	Voltage supplied at all times (overload protected)
87A	–	not used
86	329 (PK)	Starter relay, control
85	1093 (TN/RD)	Power, Hot in Start with Park or Neutral
	1093 (TN/RD)	Power, Hot in Start with Park or Neutral
30	33 (WH/PK)	switched power, to starter solenoid

C1016

14290

K163
PCM power relay



F05064

Pin	Circuit	Circuit Function
1	20 (WH/LB)	Voltage supplied in Start and Run (overload protected)
2	57 (BK)	Ground
3	1075 (BN/LB)	Voltage supplied at all times (overload protected)
4	–	not used
5	361 (RD)	Voltage supplied in Start and Run (overload protected)

C1021

13N052

E1
Headlamp, left



F03169

Pin	Circuit	Circuit Function
1	12 (LG/BK)	Power, Hot with High Beams on
2	161 (DG/OG)	Headlamp, right, (Low beam lamp feed)
3	13 (RD/BK)	Power, Hot with Low Beams on