## C459

### 14K024

N282
Multifunction switch




F11003

| Pin | Circuit | Circuit Function |
|---|---|---|
| 1 | – | not used |
| 2 | 29S-LE12 (OG/YE) | Voltage supplied at all times (overload protected), switched |
| 3 | – | not used |
| 4 | 29-LE10 (OG/GN) | Voltage supplied at all times (overload protected) |
| 5 | 29S-LE10 (OG/GN) | Voltage supplied at all times (overload protected), switched |
| 6 | – | not used |
| 7 | 31-LG25 (BK) | Ground |
| 8 | 49S-LG1 (BU) | Pulsed power feed (overload protected), switched |
| 9 | 49S-LG2 (BU/RD) | Pulsed power feed (overload protected), switched |
| 10 | 29-LG27 (OG/BK) | Voltage supplied at all times (overload protected) |
| 11 | 15-LG25 (GN/BU) | Voltage, ignition switch in Start or Run (not overload protected) |

## C465

### 14K733

K32
A/C Wide Open
Throttle (WOT) relay




F04018

| Pin | Circuit | Circuit Function |
|---|---|---|
| 1 | 15-FA11 (GN/YE) | Voltage, ignition switch in Start or Run (not overload protected) |
| 2 | 91S-FA11 (BK/YE) | Ground, switched |
| 3 | 15S-FA5 (GN/BU) + 15S-FA7 (GN/BU) | Voltage, ignition switch in Start or Run (not overload protected), switched |
| 5 | 15S-FA12 (GN/BU) | Voltage, ignition switch in Start or Run (not overload protected), switched |