-108

C1009

K279
Low speed engine
cooling fan relay A

Pin	Circuit	Circuit Function
1	15S-PA21A (GN/WH)	Battery voltage, hot in Start and Run only (not overload protected), switched
2	31S-PA21A (BK/WH)	Ground (power return), switched
3	15S-PA22A (GN/YE)	Battery voltage, hot in Start and Run only (not overload protected), switched
4	31S-PA6 (GN/YE)	Ground (power return), switched
5	15S-PA22C (GN/YE)	Battery voltage, hot in Start and Run only (not overload protected), switched

C1010

K280
Low speed engine
cooling fan relay B

Pin	Circuit	Circuit Function
1	15S-PA21B (GN/WH)	Battery voltage, hot in Start and Run only (not overload protected), switched
2	31S-PA21A (BK/WH)	Ground (power return), switched
	31S-PA21 (BK/WH)	Ground (power return), switched
3	15S-PA16 (GN/OG)	Battery voltage, hot in Start and Run only (not overload protected), switched
4	31S-PA22B (BK/YE)	Ground (power return), switched
5	15S-PA22C (GN/YE)	Battery voltage, hot in Start and Run only (not overload protected), switched