C171

9D930/
12B637

B48
Heated Oxygen
Sensor (HO2S) #11
(9G444)



F04265

Pin	Circuit	Circuit function
1	391 (RD/YE)	Voltage supplied in Start and Run (overload protected)
2	387 (RD/WH)	Heated Oxygen Sensor (HO2S) #11 (9G444), heater
3	359 (GY/RD)	signal, return
4	74 (GY/LB)	Heated Oxygen Sensor (HO2S) #11 (9G444), input

C172

7C078/
15525

B47
Heated Oxygen
Sensor (HO2S) #21
(9G444)



F04265

Pin	Circuit	Circuit function
1	391 (RD/YE)	Voltage supplied in Start and Run (overload protected)
2	388 (YE/LB)	Heated Oxygen Sensor (HO2S) #21 (9G444), heater
3	359 (GY/RD)	signal, return
4	94 (RD/BK)	Heated Oxygen Sensor (HO2S) #21 (9G444), input

C174

12B637

U10
Ignition transformer
capacitor 1 (18801)

F01031

Pin	Circuit	Circuit function
1	1118 (RD)	PCM power relay, output