C228a

14401

A205
Electronic Automatic
Temperature Control
(EATC) module



F26015

Pin	Circuit	Circuit Function
1	8-FB5 (WH/BK)	Sensor signal
2	8–FB2 (WH/RD)	Sensor signal
3	8-FB7 (WH)	Sensor signal
4	–	not used
5	91S-FB3 (BK/OG)	Ground, Switched
6	91S-FB4 (BK/GN)	Ground, Switched
7	–	not used
8	10-FA45 (GY/VT)	Signal 2 (Y–direction, reverse, downward)
9	33-FB8 (YE/RD)	Switched between: Battery voltage, Ground or Open
10	32-FB8 (WH/RD)	Switched between: Battery voltage, Ground or Open
11	32-FB2 (WH/RD)	Switched between: Battery voltage, Ground or Open
12	33-FB2 (YE/RD)	Switched between: Battery voltage, Ground or Open
13	32-FB5 (WH/BK)	Switched between: Battery voltage, Ground or Open

Pin	Circuit	Circuit Function
14	9-FA48 (BN/GN)	Sensor signal return (reference/ground)
15	8-FB8 (WH/RD)	Sensor signal
16	8-FB6 (WH/VT)	Sensor signal
17	9-FA2 (BN/RD)	Sensor signal return (reference/ground)
18	91S-FA76 (BK/OG)	Ground, Switched
19	31S-FA23 (BK/BU)	Ground, Switched
20	91S-HB7 (BK/BU)	Ground, Switched
21	–	not used
22	32-FB6 (WH/VT)	Switched between: Battery voltage, Ground or Open
23	33-FB6 (YE/VT)	Switched between: Battery voltage, Ground or Open
24	32-FB7 (WH)	Switched between: Battery voltage, Ground or Open
25	33-FB7 (YE)	Switched between: Battery voltage, Ground or Open
26	33-FB5 (YE/BK)	Switched between: Battery voltage, Ground or Open