C270a (BK)

12A581

Central Junction
Box (CJB) (14A068)



F12137

Pin	Circuit	Circuit function
1	325 (DB/OG)	Starter relay (11450), control
2	1928 (RD/WH)	Voltage supplied in Start and Run (overload protected)
3	1093 (TN/RD)	Power, Hot in Start with Park or Neutral
4	35 (OG/LB)	Voltage supplied at all times (overload protected), generator sense circuit
5	–	not used
6	12 (LG/BK)	Power, Hot with High Beams on
7	6 (YE/LG)	Horn relay, switched power, output
8	1138 (VT/WH)	Voltage supplied in Start and Run (overload protected)
9	391 (RD/YE)	Voltage supplied in Start and Run (overload protected)
10	361 (RD)	Voltage supplied in Start and Run (overload protected)
11	–	not used
12	478 (TN/OG)	switched output to fog lamps

C270b (BK)

12A581

Central Junction
Box (CJB) (14A068)



F12056

* with High Intensity Discharge (HID) lamps
** Early production
*** Late production

Pin	Circuit	Circuit function
1	295 (LB/PK)	Voltage supplied in Start and Run (overload protected)
2	–	not used
3	533 (TN/RD)	Voltage supplied in Start and Run (overload protected)
4	729 (RD/WH)	Voltage supplied at all times (overload protected)
5	160 (DB/WH)	Headlamp, left (13008), (Low beam lamp feed)
	*1338 (WH)	Headlamp, left (13008), (Low beam lamp feed)
6	1002 (BK/PK)	Voltage in Run or Accessory (overload protected)
7	883 (PK/LB)	Voltage supplied at all times (overload protected)
8	**705 (LG/OG)	Battery saver relay, switched power
9	161 (DG/OG)	Headlamp, right (13008), (Low beam lamp feed)
	*1336 (LG/WH)	Headlamp, right (13008), (Low beam lamp feed)
10	***10 (LG/RD)	Hot at all times (overload protected)
11	238 (DG/YE)	Fuel pump relay, switched power, output
12	926 (LB/OG)	Fuel pump relay, control

C270c (BK)

12A581

Central Junction
Box (CJB) (14A068)



F02519

Pin	Circuit	Circuit function
1	1053 (LB/PK)	Voltage supplied at all times (overload protected)
2	532 (OG/YE)	Voltage supplied at all times (overload protected)