COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Turn Switch/ Cornering Switch Circuits	6, 10, 8, 1, and 7	Hazard Switch to Normal (OFF) and Turn Switch to Turn Left	Closed Circuit
	6 and 2, 5, 1, and 3	Hazard Switch to Normal (OFF) and Turn Switch to Turn Right	Closed Circuit
Hazard Switch Circuit	6 and 5, 8, 2, 10	Hazard Switch to Hazard (ON) (Button pushed-in and then released to fully extended position.)	Closed Circuit
Stoplamp Feed Through Circuit	9 and 10, 2	Hazard Switch to Normal (OFF) and Turn Switch to Neutral	Closed Circuit

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Without Auto Dim Headlamp			
Flash to Pass Circuit	7 and 5, 3 and 2	Pull and hold Lever Stalk toward Steering Wheel	Closed Circuit
Dimmer HIGH Beam Circuit	1 and 5	Lever Stalk in detent away from Steering Wheel	Closed Circuit
Dimmer LOW Beam Circuit	2 and 5	Lever Stalk in detent toward Steering Wheel	Closed Circuit