C1008

14290

K107
A/C clutch relay



F05064

Pin	Circuit	Circuit Function
1	331 (PK/YE)	A/C clutch relay, control
2	361 (RD)	Voltage supplied in Start and Run (overload protected)
3	883 (PK/LB)	Voltage supplied at all times (overload protected)
4	–	not used
5	321 (GY/WH)	A/C clutch relay, switched output

C1016

14290

K163
PCM power relay



F05051

Pin	Circuit	Circuit Function
87	361 (RD)	Voltage supplied in Start and Run (overload protected)
87A	–	not used
86	546 (DG/YE)	Voltage supplied in Start and Run (overload protected)
85	570 (BK/WH)	Ground
30	554 (YE/BK)	Voltage supplied at all times (overload protected)

C1011

14290

K73
Blower motor relay



F05051

Pin	Circuit	Circuit Function
87	181 (BN/OG)	Voltage supplied at all times (overload protected)
87A	–	not used
86	260 (RD/OG)	Blower motor relay, control
85	57 (BK)	Ground
30	371 (PK/WH)	Blower motor relay, switched output

C1017

14290

K22
Starter relay



F05051

Pin	Circuit	Circuit Function
87	113 (YE/LB)	Starter motor to Starter relay
87A	–	not used
86	325 (DB/OG)	Starter relay, control
	57 (BK)	Ground
85	1093 (TN/RD)	Power, Hot in Start with Park or Neutral
30	37 (YE)	Voltage supplied at all times (overload protected)