C270d (GY)

14401

Central Junction
Box (CJB) (14A068)



F10091

Pin	Circuit	Circuit function
1	1040 (RD/BK)	Voltage in Run (overload protected)
2	1001 (WH/YE)	Voltage supplied at all times (overload protected)
3	1112 (WH/LB)	Voltage supplied in Start and Run (overload protected)
4	640 (RD/YE)	Voltage supplied in Start and Run (overload protected)
5	797 (LG/VT)	Voltage supplied at all times (overload protected)
6	1049 (BN/PK)	Power point (19N236), Fused battery feed
7	37 (YE)	Battery voltage, hot in Run only
8	1044 (WH/YE)	Voltage, ignition switch in Start or Run (not overload protected)
9	297 (BK/LG)	Power, Hot in Run or Acc
10	40 (LB/WH)	Voltage supplied at all times (overload protected)

C270e (GY)

14A005

Central Junction
Box (CJB) (14A068)



F10091

Pin	Circuit	Circuit function
1	1371 (TN/OG)	Auxiliary blower motor relay, control
2	–	not used
3	59 (DG/VT)	Heated mirrors, feed
4	10 (LG/RD)	Voltage supplied at all times (overload protected)
5	1507 (WH/RD)	Voltage supplied at all times (overload protected)
6	1040 (RD/BK)	Voltage in Run (overload protected)
7	1322 (BN/WH)	Front blower motor relay, control
8	640 (RD/YE)	Voltage supplied in Start and Run (overload protected)
9	1231 (RD/WH)	Voltage supplied at all times (overload protected)
10	–	not used