## C2047

**14401**

K2
Indicator flasher
relay (13350)




F05016

| Pin | Circuit | Circuit function |
|---|---|---|
| 30 | 294 (WH/LB) | Voltage in Run (overload protected) |
| 85 | 383 (RD/WH) | Voltage supplied at all times (overload protected) |
| 86 | 57 (BK) | Ground |
| 87 | 44 (LB) | Indicator flasher relay (13350), to, Multifunction switch |
| 87a | 385 (WH/RD) | Indicator flasher relay (13350), to, Multifunction switch |

## C2051

K50
One–touch window
relay




F05051

| Pin | Circuit | Circuit function |
|---|---|---|
| 30 | 996 (OG/WH) | Switched power, output / Ground |
| 85 | 400 (LB/BK) | Accessory delay relay, output |
| 86 | – | Switched ground |
| 87 | – | Switched power |
| 87a | 57 (BK) | Ground |

## C2048

K115
Battery saver relay




F05110

## C2059

**14401**

K52
Park lamp relay




F05110

| Pin | Circuit | Circuit function |
|---|---|---|
| 1 | 195 (TN/WH) | Park lamp relay – fused feed |
| 2 | 7 (LG/YE) | Park lamp relay, to, Central security module |
| 3 | 195 (TN/WH) | Park lamp relay – fused feed |
| 4 | – | not used |
| 5 | 14 (BN) | Power, Exterior lamps |