COMPONENT TESTING: MULTIFUNCTION SWITCH 149-6

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Turn Switch/ Circuits	6 and 9, 3	Hazard Switch to Normal (OFF) and Turn Switch to Turn Left	Closed Circuit
	6 and 2, 2	Hazard Switch to Normal (OFF) and Turn Switch to Turn Right	Closed Circuit
Hazard Switch Circuit	6 and 2, 3, 2, 9	Hazard Switch to Hazard (ON) (Button pushed-in and then released to fully extended position.)	Closed Circuit
Stoplamp Feed Through Circuit	9 and 9, 2	Hazard Switch to Normal (OFF) and Turn Switch to Neutral	Closed Circuit
Cornering Switch Circuits	2 and 7	Hazard Switch to Normal (OFF) and Turn Switch to Turn Left	Closed Circuit
	2 and 3	Hazard Switch to Normal (OFF) and Turn Switch to Turn Left	Closed Circuit

COMPONENT TESTING PROCEDURE

TO TEST	Connect Self-Powered Test Light or Ohmmeter to Terminals	Move Switch to These Positions	A Good Switch Will Indicate
Flash-to-Pass Circuit	7 and 5	Pull and hold Lever Stalk toward Steering Wheel	Closed Circuit
Dimmer High Beam Circuit	2 and 5	Lever Stalk in detent away from Steering Wheel	Closed Circuit