C1160

12B637

M251
EGR stepper motor



F06245

Pin	Circuit	Circuit function
1	338 (TN/RD)	EGR stepper motor – B2
2	34 (LB/OG)	Voltage supplied in Start and Run (overload protected)
3	337 (GY/RD)	EGR stepper motor – B1
4	335 (VT/OG)	EGR stepper motor – A1
5	34 (LB/OG)	Voltage supplied in Start and Run (overload protected)
6	336 (DG)	EGR stepper motor – A2

C1161

12B637

A261
Swirl control monitor



F03201

Pin	Circuit	Circuit function
1	1107 (WH)	Swirl control monitor, to, Powertrain Control Module (PCM) (12A650)
2	359 (GY/RD)	signal, return
3	351 (BN/WH)	Reference, voltage

C1162

12B637

B248
Electronic thermo-stat



F02055

Pin	Circuit	Circuit function
1	653 (DB)	Electronic thermostat, to, Powertrain Control Module (PCM) (12A650)
2	34 (LB/OG)	Voltage supplied in Start and Run (overload protected)

C1163

12B637

Y57
Swirl control sole-noid valve



F02281

Pin	Circuit	Circuit function
1	34 (LB/OG)	Voltage supplied in Start and Run (overload protected)
2	1276 (WH/OG)	Swirl control solenoid valve, to, Powertrain Control Module (PCM) (12A650)

C1180

12B637

B41
Camshaft position sensor (6B288)

2.3L



F02101

3.0L

F02109

Pin	Circuit	Circuit function
1	359 (GY/RD)	signal, return
2	282 (DB/OG)	Camshaft position sensor (6B288), input