TeraMove-H: Crowd-Aware Association, Power Control and Reconfiguration of Movable THz Access Points in Hybrid THz/Wi-Fi Indoor Networks

Author 1, Author 2, Author 3
Department of Computer Science and Engineering, Indian Institute of Technology Bhilai, India

***Abstract*—Indoor terahertz (THz) access points (APs) need line of sight, so the people they serve are also what blocks them. Earlier work places APs with a mixed-integer program and moves them with a tiered swarm optimizer when crowds degrade coverage. We extend this line of work to a hybrid network in which fixed Wi-Fi APs coexist with movable THz APs, and we add two electronic control steps that run before any hardware moves. First, user association is posed as a maximum generalized assignment problem under per-AP airtime budgets and solved greedily. Second, a minimum-power control step, based on Yates' standard interference functions, switches idle THz APs off and lowers transmit power without losing any served user. Only when these steps fail does the network re-steer beams and, finally, move APs along per-room ceiling rails. We evaluate the scheme with an energy-conserving antenna model, discrete human blockers, 3GPP self-blocking and ITU-R absorption, over 30 crowd realizations on a 32 m×20 m academic floor. At a demand of 1 Gb/s per user, TeraMove-H satisfies 84.4% of users versus 44.8% without adaptation and 50.9% for the original TeraMove. It cuts THz transmit power by 62.1% and moves APs 18.8% less than a flat genetic algorithm with the same evaluation budget, which in turn satisfies 2.8 percentage points more users. We also map the demand and crowd-size regime in which no physical movement is needed at all.**

***Index Terms*—THz communications, user association, power control, hybrid networks, movable access points, human blockage.**

I. Introduction

The THz band offers tens of gigahertz of contiguous spectrum for indoor 6G links [1], [2]. Its propagation, however, is quasi-optical: free-space loss is high, molecular absorption adds frequency-selective loss, and a human body in the path attenuates the link by tens of decibels [3], [4]. In an indoor deployment, the people who need the capacity are also the main source of blockage.

Recent work addressed this in two steps. A mixed-integer linear program (MILP) chose three-dimensional AP positions, heights and orientations for an empty building [5]. TeraMove [6] then reacted to crowd-induced coverage loss with a tiered particle swarm optimizer (PSO) [7], [8] that first re-steers beams, then changes AP heights, and finally relocates APs. Two simplifications limit both works. They consider only THz APs, so a user whose THz links are blocked is simply lost. They also treat association as *strongest-signal* and power as fixed, so the cheapest control knobs of a real network are never used before hardware moves.

This paper adds a Wi-Fi layer and these two control knobs, and makes the following contributions:

- A hybrid THz/Wi-Fi model in which every person is both a potential user and a cylinder-shaped blocker. Service is measured as the fraction of users who receive a demanded rate $R_{\min}$ under per-AP airtime sharing (Sec. III).
- An airtime-aware association that serves users over THz and Wi-Fi APs. We pose it as a maximum generalized assignment problem (GAP), show that the feasibility version is NP-complete, and solve it with a greedy that we compare with an exact solver. We also give a minimum-power control step with a monotone convergence guarantee (Sec. IV).
- The TeraMove-H escalation: re-association, then sleep and power control, then beam re-steering, then mechanical reconfiguration confined to per-room rails.
- An evaluation with real baselines over 30 seeds. It includes a demand×crowd regime map, temporal handover analysis and sensing-error robustness, and it documents corrections to the earlier simulator (Sec. V).

II. Related Work

THz/mmWave blockage. Human blockage and its temporal statistics have been modeled analytically for mmWave and THz [3], [4]. Multi-connectivity mitigates blockage by keeping links to several APs [9], and vision can predict blockage in advance [10]. **AP placement and mobility.** Line-of-sight-aware placement has been studied for mmWave WLANs [11]. Mobility has been exploited through UAV base stations [12], movable indoor APs [13] and movable antennas [14], and [5], [6] combined it with THz placement. **Association and power.** Load-aware association in heterogeneous networks maximizes a utility over AP loads [15]. The closest hybrid analogue is access-point selection in hybrid Li-Fi/Wi-Fi networks, where an optical layer that needs line of sight is backed by Wi-Fi [16]. Power control under SINR targets builds on the Foschini–Miljanic iteration and Yates' framework [17], [18]. To our knowledge, no prior work combines airtime-aware hybrid asso-

ciation, minimum-power control and physical reconfiguration of THz APs under crowd blockage.

III. System Model

A. Building, access points and people

The building is the 32 m×20 m×3 m academic floor of [5], [6]. It has 12 rooms separated by full-height concrete, wooden and glass partitions, plus 1 m-high cubicles. The set $\mathcal{T}$ contains the $|\mathcal{T}| = 14$ THz APs of the MILP solution [5, Fig. 1]. THz AP a has state $\theta_a = (x_a, y_a, z_a, \phi_a, \alpha_a)$: position, height $z_a \in \{2.0, 2.2, \ldots, 3.0\}$ m, compass azimuth ϕ_a in 45° steps, and sector width $\alpha_a \in \{30, 45, 60, 75, 90, 120\}°$. Each AP rides a ceiling rail inside its own room. (x_a, y_a) therefore stays in that room, 0.25 m from its walls, on a 0.25 m grid. The set $\mathcal{W}$ holds four fixed Wi-Fi APs on the 3 m ceiling: one at the centre of each of the two large lower rooms and two in the upper hall (at $x = 10$ and 22 m, $y = 16$ m).

People are drawn from a clustered point process: 80% belong to six Gaussian clusters ($\sigma = 1$ m) with uniform centres [19], and 20% are uniform background. Bodies are vertical cylinders of radius 0.2 m and height 1.6 m [5]. Placement is hard-core: bodies do not overlap and keep 0.25 m from walls. Each person carries an active device at 1.0 m height with probability 0.5; these devices form the user set $\mathcal{U}$. Each user faces a uniformly random direction. Every user demands rate $R_{\min}$.

B. THz link

For AP a and user u at 3-D distance d, the path loss in dB is

$$L_{a,u} = 20\log_{10}\tfrac{4\pi f d}{c} + 4.343\,k(f)\,d + L^{\mathrm{st}}_{a,u} + \min(n_{a,u}L_h, L_h^{\max}) + L_{\mathrm{sb}}\mathbf{1}^{\mathrm{sb}}_{a,u}. \quad (1)$$

The terms are as follows:

- **Absorption.** $f = 300$ GHz, and $k(f) = 1.54 \times 10^{-3}\ \mathrm{m}^{-1}$ (6.68 dB/km). We computed this value with ITU-R P.676 [20], [21] for indoor air at 23 °C and 10 g/m^3 water vapour.
- **Static penetration.** L^{st} adds 30/20/15 dB for every concrete/wooden/glass partition that the ray crosses below the partition's height [5]. The ray from a ceiling AP to a 1 m device never dips below 1 m, so the 1 m cubicles never attenuate a THz or Wi-Fi link in this geometry.
- **Bodies.** $n_{a,u}$ counts the bodies whose disc the ray's ground projection crosses at a height of at most 1.6 m. The test is exact: the chord through the disc is computed analytically. The user's own body is excluded here. Each body costs $L_h = 20$ dB [5], saturating at $L_h^{\max} = 40$ dB.
- **Self-blocking.** $\mathbf{1}^{\mathrm{sb}}$ indicates that the AP lies in the user's self-blocking region. We use the 3GPP portrait-mode region (azimuth 260° ± 60° relative to the device, zenith 100° ± 40°), which costs $L_{\mathrm{sb}} = 30$ dB [22].

Antennas. An AP radiates a flat-top sector: gain $G_m(\alpha)$ over the lower half-space within $\pm\alpha/2$ of ϕ_a, and $g_s = -10$ dBi elsewhere. The main lobe subtends a solid angle of α steradians. Conservation of radiated power therefore gives

$$G_m(\alpha) = \frac{4\pi - g_s(4\pi - \alpha)}{\alpha}, \quad (2)$$

i.e., 13.4, 10.4 and 7.4 dBi for $\alpha = 30°$, 60° and 120°. The device steers a pencil beam of $G_r = 20$ dBi at its serving AP [2]. The same normalization gives a main-lobe half-angle of 10.9°, with −10 dBi outside it. Interference from AP b therefore enters through the device's main lobe only if b lies within 10.9° of the serving direction.

SINR and rate. All THz APs share a $B = 10$ GHz channel, and every AP that is switched on transmits. Let $h_{b,u} = G^t_{b,u}10^{-L_{b,u}/10}$, and let $G^r_{u,a,b}$ be the device gain towards b when its beam points at a. Then

$$\mathrm{SINR}_{u,a} = \frac{p_a h_{a,u} G_r}{N_0 + \sum_{b\neq a} p_b h_{b,u} G^r_{u,a,b}}, \quad (3)$$

with $N_0 = -174 + 10\log_{10} B + \mathrm{NF} = -64.0$ dBm (NF = 10 dB). A link is usable if $\mathrm{SINR} \geq \gamma_{\mathrm{th}} = 5$ dB [6]. Its capacity is $c_{u,a} = B\min(\log_2(1 + \mathrm{SINR}_{u,a}), 6)$ (64-QAM cap); unusable links have $c_{u,a} = 0$. The maximum THz power is $P_{\max} = 20$ dBm per AP.

C. Wi-Fi link

Each Wi-Fi AP transmits 20 dBm with a 3 dBi antenna in its own 160 MHz channel at 6 GHz (802.11ax), so Wi-Fi APs do not interfere with each other. The device antenna has 0 dBi gain. Path loss follows the 3GPP InH-Office model [22]. A link is in line of sight if it crosses no full-height partition and no body; otherwise $\mathrm{PL} = \max(\mathrm{PL}_{\mathrm{LOS}}, 17.3 + 38.3\log_{10} d + 24.9\log_{10} f_c)$. The rate is the 2-stream 160 MHz PHY rate of the highest MCS whose minimum input sensitivity [23] is met, times a MAC efficiency of 0.7. The best Wi-Fi rate is therefore 1.68 Gb/s.

D. Service model

Each AP time-shares its channel among its users. User u needs airtime $\tau_{u,a} = R_{\min}/c_{u,a}$ on AP a, and each AP grants at most a total airtime of 1. With $x_{u,a} \in \{0, 1\}$ the association, the *satisfaction* is $S = |\mathcal{U}|^{-1}\sum_{u,a} x_{u,a}$, the fraction of users who receive $R_{\min}$.

IV. Problem and Method

A. Problem

Given the current state θ^0 and a new crowd, the network solves

$$\max_{\theta,\mathbf{p},\mathbf{x}} S(\mathbf{x}) \quad (4)$$
$$\text{s.t. } \textstyle\sum_a x_{u,a} \leq 1\ \ \forall u, \quad \sum_u \tau_{u,a}(\theta,\mathbf{p})\,x_{u,a} \leq 1\ \ \forall a,$$
$$x_{u,a} = 0 \text{ if } c_{u,a} < R_{\min}, \quad 0 \leq p_a \leq P_{\max}, \quad \theta_a \in \Theta_a.$$

Among near-optimal solutions, the operator prefers the least physical displacement $\sum_a \|(x_a, y_a, z_a) - (x^0_a, y^0_a, z^0_a)\|$ and then the least transmit power.

Proposition 1. *Given the link capacities $c_{u,a}$ (i.e., fixed θ and* $\mathbf{p}$*), deciding whether all users can be served is NP-complete.*

Proof. The problem is in NP. Reduce from PARTITION with integers $s_1, \ldots, s_k$ that sum to $2T$. Use two APs and set $c_{u,1} = c_{u,2} = R_{\min}T/s_u$, so that $\tau_{u,a} = s_u/T$. Both airtime budgets hold with every user served if and only if the integers split into two halves of equal sum. □

B. Association: greedy GAP

For a fixed configuration, (4) is a maximum GAP with unit profits [24]. The greedy sorts all feasible user–AP pairs (THz and Wi-Fi) by airtime $\tau_{u,a}$ and assigns a pair if its user is still unassigned and the AP's budget allows it. It runs in $O(KM\log(KM))$ for K users and M APs. For a single AP, smallest-airtime-first maximizes the number served, but the greedy is not optimal in general. We therefore measure its gap against the exact integer program solved with HiGHS [25] (Sec. V-F). *Threshold offload*, the hybrid baseline, sends a user to its strongest THz AP if that AP's SINR is at least γ_{th}, and to its best Wi-Fi AP otherwise.

C. Sleep and minimum-power control

With the association fixed, every THz AP with no users is switched off ($p_a = 0$) and users are re-associated. This repeats for up to three rounds, stopping when nothing changes, and a round is kept only if S does not decrease. Then let $L_a = \sum_{u\in\mathcal{U}_a}\tau_{u,a} \le 1$ be AP a's airtime load. If each user's airtime is stretched by $1/L_a$, the user still receives $R_{\min}$ at capacity $c_u^\star = c_{u,a}L_a$. This gives the SINR target $\gamma_u = \max(\gamma_{\text{th}}, 2^{c_u^\star/B} - 1)$. Define

$$I_a(\mathbf{p}) = \max_{u\in\mathcal{U}_a} \frac{\gamma_u\left(N_0 + \sum_{b\neq a} p_b h_{b,u} G^r_{u,a,b}\right)}{G_r h_{a,u}}. \tag{5}$$

Proposition 2. *Start from the current powers $\mathbf{p}^0$ and iterate $\mathbf{p} \leftarrow \min(\mathbf{I}(\mathbf{p}), P_{\max})$. The iteration decreases monotonically and converges to the minimal power vector $\mathbf{p}^\star \le \mathbf{p}^0$ at which every THz-served user still receives $R_{\min}$ and no airtime budget is exceeded.*

Proof. $\mathbf{I}$ is a standard interference function [18]. It is positive because $N_0 > 0$, monotone because all coupling coefficients are non-negative, and scalable because $\mu\mathbf{I}(\mathbf{p}) > \mathbf{I}(\mu\mathbf{p})$ for $\mu > 1$. At $\mathbf{p}^0$ every served pair satisfies $\log_2(1+\text{SINR}) \ge c_{u,a}/B \ge c_u^\star/B$, so $\mathbf{I}(\mathbf{p}^0) \le \mathbf{p}^0$. From such a feasible point the iteration is non-increasing and converges to the unique fixed point, which is the minimal feasible vector [18]. Because the iterates never exceed $\mathbf{p}^0 \le P_{\max}$, the cap never binds. At $\mathbf{p}^\star$, $c_u \ge c_u^\star$, so user u needs airtime at most $\tau_{u,a}/L_a$, and the loads sum to at most 1. □

In the implementation, a 10^{-6} relative margin on γ_u absorbs floating-point error. Every run also re-checks that each served user still receives $R_{\min}$ and that every airtime budget holds.

Algorithm 1 TeraMove-H adaptation for one crowd snapshot

1: **T0:** greedy GAP over $\mathcal{T}\cup\mathcal{W}$ at $P_{\max}$; **if** $S \ge \eta$ **goto** 6
2: **T1:** sleep idle APs, re-associate, minimum power; **if** $S \ge \eta$ **goto** 6
3: **T2:** GA over (ϕ_a, α_a), budget U; **if** $S \ge \eta$ **goto** 6
4: **M:** GA over all of θ_a within rooms, budget $3U$
5: Hungarian matching of new to old AP states inside each room
6: Sleep + minimum-power control on the final configuration

D. The TeraMove-H escalation

Algorithm 1 stops at the first stage whose satisfaction reaches $\eta = 0.9$. The search stages maximize the fitness

$$F = 0.6S + 0.4Q + 0.5\,\mathbf{1}[S \ge \eta] - \beta M - \gamma C_p. \tag{6}$$

The terms are:

- $Q = |\mathcal{U}|^{-1}\sum_u \min(1, \max_a c_{u,a}/R_{\min})$, a smooth link-quality term that rewards progress before a user is fully served.
- M, the displacement normalized by $|\mathcal{T}|$ times the building diagonal.
- C_p, TeraMove's anti-clustering penalty (minimum AP spacing $d_{\min} = 3$ m).
- $\beta = 0.25$ and $\gamma = 0.3$, TeraMove's configuration D [6].

Inside the search, S and Q come from the greedy association at full power. Sleep and power control run on each stage's result.

Search. One budget unit is $U = 40\times40 = 1600$ fitness evaluations. Each search stage (T2 and M) runs a real-coded genetic algorithm (GA) whose population includes the current configuration, so a stage never returns a worse fitness. The GA uses population 40, binary tournaments, BLX-0.5 crossover [26] with probability 0.9, Gaussian mutation (σ = 10% of the range, rate $1/d$ over the d free dimensions) and elitism. In stage M, about one third of the population starts within ±2 m of the current positions, as in TeraMove. Within each room, the Hungarian algorithm [27] decides which physical AP takes which new state, minimizing total displacement. A stage's result is kept only if it does not lower S.

V. Evaluation

A. Setup

Unless stated otherwise: 120 people, $R_{\min}$ = 1 Gb/s, and 30 independent seeds. All methods see the same crowd in each seed and draw from the same random stream (common random numbers). We report the mean with a 95% Student-t confidence interval; paired differences are tested with the Wilcoxon signed-rank test.

Commissioning. Under the present model, the MILP layout [5] with TeraMove's 60° beams covers 66.2% of the empty floor (grid cells with SINR ≥ 5 dB). We therefore re-tune its azimuths, widths and heights once for the empty building: PSO tiers 2–3 followed by per-AP coordinate descent, with




Fig. 1. Commissioned deployment (14 THz AP sectors, 4 Wi-Fi APs) and one crowd realization (seed 0). The background is the THz SINR of a virtual device at each 1 m cell with this crowd present; 85.5% of cells reach 5 dB.

the MILP positions unchanged. This raises empty-floor coverage to 100.0%, and the result is the starting state of every experiment (Fig. 1).

Methods.

- *Static*: commissioned layout, THz only, strongest-SINR association.
- *TeraMove* [6]: its grid-coverage fitness, PSO tiers 2/3/4 of one unit each, THz only.
- *Wi-Fi only.*
- *THz-only cascade*: TeraMove-H without Wi-Fi.
- *Threshold offload*: TeraMove-H with the threshold-offload rule.
- *Flat PSO* and *flat GA*: the same T0 and T1 steps, then one search over all dimensions at once with the fitness (6) and TeraMove-H's worst-case budget of $4U = 6400$ evaluations (no beam-only stage).
- Ablations of TeraMove-H: without power control, without movement (T0–T2 only), and with TeraMove's PSO tiers 2/3/4 (budgets $U, U, 2U$) instead of the GA stages.

B. Differences from the earlier model

We re-implemented the model of [5], [6] from scratch, which revealed several defects in the original simulator; Table I lists them. The most consequential is the azimuth convention. The MILP reports azimuths as compass bearings, but the simulator read them as mathematical angles, so APs listed at 135° pointed out of the building. With the original simulator, the empty-floor coverage of the MILP layout is 43.9% under the mathematical reading and 60.8% under the correct compass reading. The results reported in [6] therefore start from a misoriented deployment.

C. Main comparison

Table II and Fig. 2 summarize the results. Here 59.3 users are active on average. Without adaptation, the static network satisfies 44.8% of users. TeraMove reaches only 50.9%. Its fitness rewards grid coverage rather than served users, and it cannot use Wi-Fi. TeraMove-H reaches 84.4±2.6%. Reassociation alone (T0) gives 51.6%, and the beam stage

TABLE I
EARLIER SIMULATOR VERSUS THIS WORK

Earlier simulator	This work
Azimuth read as math angle	Compass bearing, as in [5]
30 dBi at every beamwidth	Energy-conserving gain (2)
Absorption 0.05 m^{-1} (217 dB/km)	ITU-R P.676: 6.68 dB/km
Noise −94 dBm in text, −64 in code	N_0 = −64.0 dBm from B and NF
Users at grid corners (on walls)	Users are people; grid at cell centres
Fractional density×20 dB, unbounded	Discrete bodies, exact test, capped
APs may cross walls	Per-room rails, Hungarian per room

TABLE II
MAIN COMPARISON (R_{min} = 1 GB/S, 120 PEOPLE, 30 SEEDS; MEAN, 95% CI ON S; OFF = APS SWITCHED OFF)

Method	S (%)	Displ. (m)	$\sum p$ (W)	Off	Evals
Static	44.8±3.1	0.0	1.40	0.0	0
Wi-Fi only	6.8±0.2	0.0	0.00	14.0	0
TeraMove	50.9±2.5	11.8	1.40	0.0	4800
THz-only cascade	77.2±2.5	25.8	0.55	4.2	6400
Threshold offload	83.0±2.8	23.3	0.51	4.3	6400
Flat PSO	78.3±2.5	22.4	0.45	4.4	6400
Flat GA	87.2±2.6	30.3	0.61	4.0	6400
w/ HPSO tiers	75.0±2.5	13.5	0.43	4.5	6400
w/o power ctrl	84.4±2.6	24.6	1.40	0.0	6400
w/o movement	58.9±2.6	0.0	0.36	4.9	1600
TeraMove-H	84.4±2.6	24.6	0.53	4.1	6400

without movement gives 58.9%; the remaining gain requires moving APs.

The THz-only cascade reaches 77.2%, so the Wi-Fi layer adds 7.2 percentage points (pp). At 1 Gb/s, Wi-Fi serves about 4.0 users per snapshot, because one Wi-Fi AP sustains at most 1.68 Gb/s. Threshold offload reaches 83.0% ($p = 0.01$ versus TeraMove-H); the association rule matters most at lower demand (Sec. V-D).

Power control switches off 4.1 of the 14 APs on average and lowers total THz power from 1.40 W to 0.53 W (62.1% less). Because all methods share random numbers, the variant without power control follows the same search and ends with the same satisfaction and displacement (84.4%, 24.6 m). Power control changes only the transmit power, as Proposition 2 guarantees.

The flat GA satisfies 2.8 pp more users than TeraMove-H (87.2%, $p = 0.02$). It also moves APs 30.3 m in total against 24.6 m ($p = 0.007$), so TeraMove-H moves 18.8% less. Under the same worst-case budget, neither method dominates the other: they are two points on a Pareto front (Fig. 3). With PSO stages instead of GA stages, TeraMove-H reaches 75.0%, and flat PSO reaches 78.3%. The GA explores the discrete beam, height and rail space better. At equal budgets it reaches higher fitness than PSO throughout the search (Fig. 4), so the GA is the search engine of TeraMove-H.




Fig. 2. Satisfied users and total AP displacement per method (mean and 95% CI over 30 seeds).




Fig. 3. Satisfaction versus displacement (mean, 95% CI). The variant without power control coincides with TeraMove-H and is not shown.




Fig. 4. Best fitness (6) versus evaluations, averaged over seeds that reach the search stages.

D. When must APs move? Demand–crowd regime

Fig. 5 sweeps $R_{\min} \in \{0.1, 0.25, 0.5, 1, 2\}$ Gb/s and 60–240 people. At 0.1 Gb/s, Wi-Fi absorbs the users whose THz links are blocked: re-association alone serves 93.2% on average, and 78% of the snapshots reach η without moving any AP. At 2 Gb/s, re-association serves 41.7%, no snapshot is resolved electronically (0%), and APs must move. Table III compares the association rules. The satisfaction difference between the greedy GAP and threshold offload is 1.5, 1.9, 1.3, 0.8 and 0.0 pp at 0.1, 0.25, 0.5, 1 and 2 Gb/s. The airtime-aware association pays off when Wi-Fi capacity is a scarce resource worth allocating; at 2 Gb/s, Wi-Fi can hardly serve anyone. Without Wi-Fi, satisfaction does not change with demand up to 1 Gb/s, because a THz AP has far more capacity than its users need and only coverage limits service. Over the whole grid, TeraMove-H moves APs 24.2% less than the flat GA.

TABLE III
SATISFACTION AND DISPLACEMENT VERSUS DEMAND (MEAN OVER CROWD SIZES AND SEEDS)

$R_{\min}$ (Gb/s)	0.1	0.25	0.5	1	2
THz-only cascade S (%)	75.6	75.6	75.6	75.6	75.4
Threshold offload S (%)	96.5	90.5	84.6	79.5	75.2
TeraMove-H S (%)	98.0	92.4	85.9	80.3	75.2
Flat GA S (%)	98.7	94.0	88.3	83.3	78.1
TeraMove-H displ. (m)	4.5	16.1	18.7	22.4	26.1
Flat GA displ. (m)	6.3	20.9	25.7	30.0	33.0

E. Temporal operation

In each seed, the crowd evolves over 6 epochs: clusters drift 1.5 m per epoch and people keep their identity. Each method starts every epoch from its previous configuration (Fig. 6). Over all epochs, TeraMove-H satisfies 87.9% of users with 77.2 m of cumulative movement. The flat GA satisfies 90.3% with 98.0 m, TeraMove 53.9%, and the static network 43.0%. Among users served in consecutive epochs, 32.0% change their serving AP under TeraMove-H, and 10.4% switch between THz and Wi-Fi.

F. Association optimality and sensing error

Over 450 instances (all demands, three configurations per seed), the greedy matches the exact optimum in 90.9% of cases. Its largest shortfall is 5 users, and its worst ratio to the optimum is 92.4%. The greedy takes a median of 0.29 ms, and




Fig. 5. Regime map (mean over 30 seeds per cell): satisfaction of TeraMove-H, share of snapshots resolved without any movement, and TeraMove-H displacement.




Fig. 6. Satisfaction per epoch (top, mean and 95% CI) and mean cumulative displacement (bottom) under a drifting crowd.




Fig. 7. Sensitivity of TeraMove-H to position-sensing error (mean, 95% CI).

the exact solver 32.9 ms. TeraMove-H assumes that people's positions are sensed, for example by LiDAR [6]. We perturb the optimizer's view of every position by Gaussian noise of standard deviation σ and evaluate on the true crowd (Fig. 7). Satisfaction is 84.4, 68.0, 63.7 and 62.7% for $\sigma = 0$, 0.25, 0.5 and 1 m. Even with 1 m error, the search beats re-association alone (51.6%), but the sensitivity is high. A 0.4 m-wide body decides whether a THz link exists, so a configuration tuned to a slightly wrong crowd can place beams exactly behind people. TeraMove-H therefore needs decimetre-level context, or a search that is robust to position error (future work).

VI. Discussion and Limitations

Exposure. The largest THz EIRP is 33.4 dBm ($\alpha = 30°$), which gives 0.69 W/m^2 at 0.5 m. This is below the ICNIRP 2020 general-public whole-body reference level of 10 W/m^2 for 2–300 GHz [28], so exposure does not constrain power here. **Model scope.** Links are line-of-sight only; specular reflections would add paths and raise every method's satisfaction. Interference assumes that every AP that is switched on transmits continuously, which is pessimistic. The Wi-Fi model uses median path loss without shadow fading. The sensing study perturbs only positions; device orientation is assumed known. **Mechanics.** At an assumed rail speed of 0.2 m/s, the largest single-AP move of TeraMove-H takes 37.6 s on average, so the mechanical stage suits scheduled rather than per-second adaptation. **Search.** Under an equal budget, the flat GA attains higher satisfaction at the cost of more movement. An operator who values satisfaction over movement can lower β or skip stage T2.

VII. Conclusion

TeraMove-H extends movable THz AP reconfiguration to a hybrid THz/Wi-Fi network with airtime-aware association and minimum-power control. Relative to the static deployment,

it raises the share of satisfied users by 39.6 pp at 1 Gb/s, and it cuts THz transmit power by 62.1%. Wi-Fi offload makes physical movement unnecessary at low demand, while at multi-gigabit demand movement remains essential. The re-implementation also corrected several defects of the earlier simulator, and all results here come from runs of the corrected model.

References

[1] I. F. Akyildiz, J. M. Jornet, and C. Han, "Terahertz band: Next frontier for wireless communications," *Physical Communication*, vol. 12, pp. 16–32, 2014.

[2] T. S. Rappaport *et al.*, "Wireless communications and applications above 100 GHz: Opportunities and challenges for 6G and beyond," *IEEE Access*, vol. 7, pp. 78 729–78 757, 2019.

[3] V. Petrov, M. Komarov, D. Moltchanov, J. M. Jornet, and Y. Koucheryavy, "Interference and SINR in millimeter wave and terahertz communication systems with blocking and directional antennas," *IEEE Transactions on Wireless Communications*, vol. 16, no. 3, pp. 1791–1808, 2017.

[4] M. Gapeyenko *et al.*, "On the temporal effects of mobile blockers in urban millimeter-wave cellular scenarios," *IEEE Transactions on Vehicular Technology*, vol. 66, no. 11, pp. 10 124–10 138, 2017.

[5] Project team, "Cost-efficient 3D access point deployment in THz networks considering dynamic human blockage," B.Tech. project manuscript, Indian Institute of Technology Bhilai, 2026.

[6] ——, "TeraMove: Context-aware reconfiguration of THz access points for resilient pervasive connectivity," B.Tech. project manuscript, Indian Institute of Technology Bhilai, 2026.

[7] J. Kennedy and R. Eberhart, "Particle swarm optimization," in *Proc. IEEE International Conference on Neural Networks (ICNN)*, vol. 4, 1995, pp. 1942–1948.

[8] Y. Shi and R. Eberhart, "A modified particle swarm optimizer," in *Proc. IEEE International Conference on Evolutionary Computation (ICEC)*, 1998, pp. 69–73.

[9] V. Petrov *et al.*, "Dynamic multi-connectivity performance in ultra-dense urban mmWave deployments," *IEEE Journal on Selected Areas in Communications*, vol. 35, no. 9, pp. 2038–2055, 2017.

[10] G. Charan, M. Alrabeiah, and A. Alkhateeb, "Vision-aided 6G wireless communications: Blockage prediction and proactive handoff," *IEEE Transactions on Vehicular Technology*, vol. 70, no. 10, pp. 10 193–10 208, 2021.

[11] Y. Liu, Y. Jian, R. Sivakumar, and D. M. Blough, "Maximizing line-of-sight coverage for mmWave wireless LANs with multiple access points," *IEEE/ACM Transactions on Networking*, vol. 30, no. 2, pp. 698–716, 2022.

[12] M. Alzenad, A. El-Keyi, F. Lagum, and H. Yanikomeroglu, "3-D placement of an unmanned aerial vehicle base station (UAV-BS) for energy-efficient maximal coverage," *IEEE Wireless Communications Letters*, vol. 6, no. 4, pp. 434–437, 2017.

[13] T. Murakami, S. Oka, Y. Takatori, M. Mizoguchi, and F. Maehara, "On the feasibility of an adaptive movable access point system in a static indoor WLAN environment," *IEICE Transactions on Communications*, vol. E101-B, no. 7, pp. 1693–1700, 2018.

[14] L. Zhu, W. Ma, and R. Zhang, "Movable antennas for wireless communication: Opportunities and challenges," *IEEE Communications Magazine*, vol. 62, no. 6, pp. 114–120, 2024.

[15] Q. Ye, B. Rong, Y. Chen, M. Al-Shalash, C. Caramanis, and J. G. Andrews, "User association for load balancing in heterogeneous cellular networks," *IEEE Transactions on Wireless Communications*, vol. 12, no. 6, pp. 2706–2716, 2013.

[16] X. Wu, M. Safari, and H. Haas, "Access point selection for hybrid Li-Fi and Wi-Fi networks," *IEEE Transactions on Communications*, vol. 65, no. 12, pp. 5375–5385, 2017.

[17] G. J. Foschini and Z. Miljanic, "A simple distributed autonomous power control algorithm and its convergence," *IEEE Transactions on Vehicular Technology*, vol. 42, no. 4, pp. 641–646, 1993.

[18] R. D. Yates, "A framework for uplink power control in cellular radio systems," *IEEE Journal on Selected Areas in Communications*, vol. 13, no. 7, pp. 1341–1347, 1995.

[19] M. Haenggi, *Stochastic Geometry for Wireless Networks*. Cambridge University Press, 2012.

[20] ITU-R, "Attenuation by atmospheric gases and related effects," International Telecommunication Union, Recommendation P.676-13, 2022.

[21] I. del Portillo, "ITU-Rpy: A Python implementation of the ITU-R P. recommendations, version 0.4.0," Software, https://github.com/inigodelportillo/ITU-Rpy.

[22] 3GPP, "Study on channel model for frequencies from 0.5 to 100 GHz," 3rd Generation Partnership Project, Technical Report TR 38.901, V17.0.0, 2022.

[23] IEEE, "IEEE standard for information technology–part 11: Wireless LAN medium access control (MAC) and physical layer (PHY) specifications–amendment 1: Enhancements for high-efficiency WLAN," IEEE Std 802.11ax-2021, 2021.

[24] L. Fleischer, M. X. Goemans, V. S. Mirrokni, and M. Sviridenko, "Tight approximation algorithms for maximum general assignment problems," in *Proc. ACM-SIAM Symposium on Discrete Algorithms (SODA)*, 2006, pp. 611–620.

[25] Q. Huangfu and J. A. J. Hall, "Parallelizing the dual revised simplex method," *Mathematical Programming Computation*, vol. 10, no. 1, pp. 119–142, 2018.

[26] L. J. Eshelman and J. D. Schaffer, "Real-coded genetic algorithms and interval-schemata," in *Foundations of Genetic Algorithms 2*. Morgan Kaufmann, 1993, pp. 187–202.

[27] H. W. Kuhn, "The Hungarian method for the assignment problem," *Naval Research Logistics Quarterly*, vol. 2, no. 1–2, pp. 83–97, 1955.

[28] International Commission on Non-Ionizing Radiation Protection (ICNIRP), "Guidelines for limiting exposure to electromagnetic fields (100 kHz to 300 GHz)," *Health Physics*, vol. 118, no. 5, pp. 483–524, 2020.