

CSM V3 — HARDWARE ORDER SHEET

Wood Base V1.1 Electrical Mounting • Rev V1.0 • 2026-06-04

NAME: _____

ORDER DATE: _____

1. BOLTS (machine screws, partial thread OK, pan or socket head)

☐	QTY	SIZE	USE	NOTES
☐	4	M5 × 35 mm	NEMA 23 motor flange	Use w/ lock washer + threadlock
☐	4	M4 × 30 mm	PSU chassis	Pan-head; rubber washer optional
☐	4	M3 × 30 mm	Arduino Mega (with standoffs)	10 mm standoff under PCB
☐	2	M3 × 25 mm	TB6600 stepper driver flange	Through 4 mm flange tabs
☐	6	M3 × 22 mm	Bucks (×4) + Terminal (×2)	Or VHB pad on Bucks → skip 4 of these

Subtotal: 20 bolts (or 16 if using VHB on Bucks)

2. WASHERS

☐	8	M5 flat washer	Under motor bolt head AND nut	
☐	4	M5 lock washer	Under motor nut (anti-vibration)	MANDATORY — motor vibrates
☐	8	M4 flat washer	PSU top + bottom	
☐	24	M3 flat washer	All M3 bolts, both sides	Pack of 50 is fine

3. NUTS

☐	4	M5 hex nut	Motor underside	
☐	4	M4 hex nut	PSU underside	
☐	12	M3 hex nut	All M3 bolts	Nyloc nut OK — extra security

4. NYLON STANDOFFS (M3 female-female, threaded)

☐	4	M3 × 10 mm nylon standoff	Under Arduino Mega	PCB airflow
☐	4	M3 × 5 mm nylon standoff	Under each Buck	Optional if using VHB tape

5. CONSUMABLES

☐	1	Loctite 243 (blue)	Threadlock for M5 motor bolts	Small bottle is plenty
☐	1	3M VHB tape (optional)	Alt mounting for Bucks	20×20 mm pads, qty 8
☐	1	Pack ferrules 0.5-2.5 mm ²	Wire ends into screw terms	Crimper required
☐	1	Pack heat shrink 3-8 mm	Wire terminations	Black + red mixed

6. DRILL BITS (verify you have these before starting)

☐	1	Ø 2.0 mm HSS	Pilot drill for ALL positions	Prevents wandering
☐	1	Ø 3.2 mm HSS	M3 clearance (10 holes)	Mega, Bucks, Terminal
☐	1	Ø 3.5 mm HSS	M3 clearance for TB6600 (2 holes)	TB6600 flange
☐	1	Ø 4.5 mm HSS	M4 clearance for PSU (4 holes)	PSU chassis
☐	1	Ø 5.5 mm HSS	M5 clearance for motor (4 holes)	NEMA 23 flange
☐	1	Ø 100 mm hole saw OR jigsaw	Take-down (1 hole)	Center on datum
☐	1	Ø 8 mm HSS (optional)	Counterbore PSU + motor nuts	Recess nut into wood