GO Pro HD Hero 960 Cheat Sheet		
SHT - Shutter Button	PWR - Power/Mode button	
`SEt`	SHT enters settings menu. PWR cycles through options	
`onF/on0`	One Button Mode (automatically record when powered on) **On/Off**	
`F/P/3/PE5`	Default Power-up Mode	**Video/SinglePhoto/TriplePhoto/TimeLapsePhoto**
`r1/r2/r3`	Video Resolution	**16:9SD/16:9HD/4:3HD**
`Cnt/SPt`	Exposure Setting	**CenterAverage/SpotMeter**
`UP/UPd`	Image Rotation	**RightsideUp/UpsideDown**
`LFF/LF0`	Live Video Feed Enable	**VideoOff/VideoOn**
`oS0/oSF`	Onscreen Display for Live Feed	**On/Off**
`P2/P5/P10/P30/P60`	Time Lapse Photo every X seconds	**2/5/10/30/60 seconds**
`bL0/bLF`	LED Blink	**On/Off**
`bP0/bPF`	Beeping Sound	**On/Off**
`nSC/PAL`	Video format	**NTSC/PAL**
`LSt`	Press SHT to delete last. Once blinking press SHT again to delete, or do nothing to cancel.	
`ALL`	Press SHT to format card. Once blinking press SHT again to format or do nothing to cancel.	
`OFF/60/120/300`	Auto Power Off Time	**Disable/60/120/300 seconds**
`dAt`	Date/Time. SHT to enter submenu. PWR to change setting, SHT to move to next.	
`ESC`	SHT to exit settings menu	