



Technical reference manual
1.0.0

EtherBench

Assembling

As the device is composed of multiple boards, some tools will be required:

- A PH0 screwdriver
- A soldering setup

Soldering

While the soldering can be done by anyone, stay safe when doing it (airy place, free space and heat resistant tools).

Top board

The top board is the one which require soldering. Place the two side boards on the top level board notch, and solder them in place.

Assembly

Ensure the boards are soldered at right angle. Failing to do it will eventually end up in the inability to assemble the system.

Pinout

Most of the pins are ground. Therefore, it may not be surprising to get a single solder blob over all the pins. This is not an issue. Only a single connection, on side side has active signals on it.

Motherboard

Now, place the daughter board on it's dedicated slot on the motherboard, and screw it in place.

Finally, you can place the top board on the notch on the motherboard. The pogo pins on the motherboard shall make contact with the pads under the top board. Fix that in place using the four screw, on each corner. Tight them correctly, as they're going to be used for ground.

Replacing the daughter board

The two screws on the daughter board can be removed without removing the top board, as there's two 10mm hole on the right position. You can just unscrew and pull the daughter board off its slot directly.