Rockchip Linux Memory Allocator Developer Guide

ID: RK-KF-YF-469

Release Version: V1.0.0

Release Date: 2022-06-25

Security Level: □Top-Secret □Secret □Internal ■Public

DISCLAIMER

THIS DOCUMENT IS PROVIDED “AS IS”. ROCKCHIP ELECTRONICS CO., LTD.(“ROCKCHIP”)DOES NOT PROVIDE ANY WARRANTY OF ANY KIND, EXPRESSED, IMPLIED OR OTHERWISE, WITH RESPECT TO THE ACCURACY, RELIABILITY, COMPLETENESS,MERCHANTABILITY, FITNESS FOR ANY PARTICULAR PURPOSE OR NON-INFRINGEMENT OF ANY REPRESENTATION, INFORMATION AND CONTENT IN THIS DOCUMENT. THIS DOCUMENT IS FOR REFERENCE ONLY. THIS DOCUMENT MAY BE UPDATED OR CHANGED WITHOUT ANY NOTICE AT ANY TIME DUE TO THE UPGRADES OF THE PRODUCT OR ANY OTHER REASONS.

Trademark Statement

"Rockchip", "瑞芯微", "瑞芯" shall be Rockchip’s registered trademarks and owned by Rockchip. All the other trademarks or registered trademarks mentioned in this document shall be owned by their respective owners.

All rights reserved. ©2022. Rockchip Electronics Co., Ltd.

Beyond the scope of fair use, neither any entity nor individual shall extract, copy, or distribute this document in any form in whole or in part without the written approval of Rockchip.

Rockchip Electronics Co., Ltd.

No.18 Building, A District, No.89, software Boulevard Fuzhou, Fujian,PRC

Website: www.rock-chips.com

Customer service Tel: +86-4007-700-590

Customer service Fax: +86-591-83951833

Customer service e-Mail: fae@rock-chips.com

Preface

Overview

This document introduces technologies related to the memory allocator on the Rockchip Linux 5.10 platform.

Linux 5.10 introduces the DMA-HEAP memory allocator, with code located in the `drivers/dma-buf/heaps/` directory. It is dedicated to allocating DMABUF-type memory and returns the dmabuf file descriptor (fd) to user space via ioctl.

Product Version

Chip Models	Kernel Version
RK3588, RV1106	Linux-5.10

Intended Audience

This document (this guide) is primarily intended for the following engineers:

- Technical Support Engineers
- Software Development Engineers

Revision History

Version	Author	Date	Description
V1.0.0	Xu Jianqun	2022-06-25	Initial version

Table of Contents

Rockchip Linux Memory Allocator Developer Guide

1. Allocator 1: DMA-HEAP
    1.1 system-heap
    1.2 cma-heap
2. Allocator 2: DRM-GEM
3. Allocator 3: VB2-MEMOPS
4. RV1106-Specific Allocator: RK-DMA-HEAP
    4.1 rk-dma-heap-info

1. Allocator 1: DMA-HEAP

The allocator driver code is located in the `drivers/dma-buf/heaps/` directory.

```
drivers/dma-buf/heaps/
├── cma_heap.c  Contiguous Memory Allocator driver
├── deferred-free-helper.c  Driver for deferred memory release
├── deferred-free-helper.h
├── Kconfig
├── Makefile
├── page_pool.c  Memory page cache Driver
├── page_pool.h
└── system_heap.c  Driver for the non-contiguous physical address and contiguous
virtual address memory allocator
```

A heap driver represents an allocator for a specific memory type and supports modular compilation. Linux provides two typical memory allocator drivers: system-heap and cma-heap.

1.1 system-heap

The system-heap supports CPU cache by default. Memory allocated by this allocator is cached for CPU access, enabling fast access speeds; however, data consistency between the device and the CPU must be maintained via software operations. This driver extends to an allocator that does not support CPU cache, known as system-uncached-heap.

The system-heap supports defer-free by default, meaning memory release is delayed. When the memory page cache is non-empty, memory allocation is fast. The memory page cache relies on the mm shrinker for appropriate reclamation.

The system-heap adds an allocator to the dma-heap via add_dma_heap(), obtains a unique index, and creates the allocator device under `/dev/dma_heap/`, such as `/dev/dma_heap/system-heap` and `/dev/dma_heap/system-uncached-heap`.

1.2 cma-heap

The cma-heap supports CPU cache by default. Memory allocated by this allocator is cached for CPU access, enabling fast access speeds; however, data consistency between the device and the CPU must be maintained via software operations.

The cma-heap allocates memory pages from cma_alloc. The CMA memory region is determined by the CMA driver; for details, refer to the `Rockchip_Developer_Guide_Linux_CMA_CN` document. This allocator provides physically contiguous memory, suitable for direct access by peripherals without an IOMMU.

2. Allocator 2: DRM-GEM

The allocator Driver code is located in the `drivers/gpu/drm/rockchip/` directory.

3. Allocator 3: VB2-MEMOPS

The allocator Driver code is located in the `drivers/media/common/videobuf2/` directory.

4. RV1106-Specific Allocator: RK-DMA-HEAP

RK-DMA-HEAP is a DMABUF memory allocator specific to the RV1106, based on DMA-HEAP.

The main differences between RK-DMA-HEAP and DMA-HEAP are:

	Linux API	**RETURN**
Linux DMABUF Allocation	rk_dma_heap_buffer_alloc	struct dma_buf *
Linux PAGE Array Allocation	rk_dma_heap_alloc_contig_pages	struct page *
Debug List Support		

> DMA-HEAP is a DMABUF allocator; however, RK-DMA-HEAP supports both DMABUF allocation and regular page array allocation.

4.1 rk-dma-heap-info

The debug node for RK-DMA-HEAP is `/proc/rk_dma_heap/rk-dma-heap-info`. Reading this node outputs extensive information as follows:

```
# cat /proc/rk_dma_heap/rk-dma-heap-info
dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5656
    Alloc by (vmpi                ) [0x03e1b000-0x03e33fff] 0x00019000 (100 KiB)
        Attached Devices:
Total 0 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5655
    Alloc by (vmpi                ) [0x03e02000-0x03e1afff] 0x00019000 (100 KiB)
        Attached Devices:
        ffa50000.rkvenc
Total 1 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5654
    Alloc by (vmpi                ) [0x03d96000-0x03e01fff] 0x0006c000 (432 KiB)
        Attached Devices:
Total 0 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5653
    Alloc by (vmpi                ) [0x03d86000-0x03d95fff] 0x00010000 (64 KiB)
        Attached Devices:
```

```
Total 0 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5652
    Alloc by (vmpi                ) [0x03d76000-0x03d85fff] 0x00010000 (64 KiB)
        Attached Devices:
        ffa50000.rkvenc
        ffa50000.rkvenc
Total 2 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5637
    Alloc by (vmpi                ) [0x03c76000-0x03d75fff] 0x00100000 (1024
KiB)
        Attached Devices:
        ffa50000.rkvenc
        ffa50000.rkvenc
Total 2 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5636
    Alloc by (vmpi                ) [0x03c74000-0x03c75fff] 0x00002000 (8 KiB)
        Attached Devices:
        ffa50000.rkvenc
Total 1 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5635
    Alloc by (vmpi                ) [0x03c72000-0x03c73fff] 0x00002000 (8 KiB)
        Attached Devices:
        ffa50000.rkvenc
Total 1 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5626
    Alloc by (vmpi                ) [0x03c40000-0x03c71fff] 0x00032000 (200 KiB)
        Attached Devices:
        ffa50000.rkvenc
Total 1 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5625
    Alloc by (vmpi                ) [0x03c3f000-0x03c3ffff] 0x00001000 (4 KiB)
        Attached Devices:
        ffa50000.rkvenc
Total 1 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5624
    Alloc by (vmpi                ) [0x03c37000-0x03c3efff] 0x00008000 (32 KiB)
        Attached Devices:
        ffa50000.rkvenc
Total 1 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5623
    Alloc by (vmpi                ) [0x03c36000-0x03c36fff] 0x00001000 (4 KiB)
        Attached Devices:
        ffa50000.rkvenc
Total 1 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5622
    Alloc by (vmpi                ) [0x03c2e000-0x03c35fff] 0x00008000 (32 KiB)
        Attached Devices:
        ffa50000.rkvenc
Total 1 devices attached
```

```
dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5621
    Alloc by (vmpi                ) [0x03b64000-0x03c2dfff] 0x000ca000 (808 KiB)
        Attached Devices:
        ffa50000.rkvenc
Total 1 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5610
    Alloc by (vmpi                ) [0x03acf000-0x03b63fff] 0x00095000 (596 KiB)
        Attached Devices:
        ffa00000.rkisp
        ffa50000.rkvenc
        ffa00000.rkisp
        ffa00000.rkisp
        ffa00000.rkisp
Total 5 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5609
    Alloc by (vmpi                ) [0x03ac0000-0x03acefff] 0x0000f000 (60 KiB)
        Attached Devices:
        ffa50000.rkvenc
Total 1 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5608
    Alloc by (vmpi                ) [0x03ab1000-0x03abffff] 0x0000f000 (60 KiB)
        Attached Devices:
        ffa50000.rkvenc
Total 1 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5607
    Alloc by (vmpi                ) [0x038ef000-0x03ab0fff] 0x001c2000 (1800
KiB)
        Attached Devices:
        ffa50000.rkvenc
Total 1 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5606
    Alloc by (vmpi                ) [0x038ed000-0x038eefff] 0x00002000 (8 KiB)
        Attached Devices:
        ffa50000.rkvenc
Total 1 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5605
    Alloc by (vmpi                ) [0x038b3000-0x038ecfff] 0x0003a000 (232 KiB)
        Attached Devices:
        ffa50000.rkvenc
Total 1 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5604
    Alloc by (vmpi                ) [0x038b1000-0x038b2fff] 0x00002000 (8 KiB)
        Attached Devices:
        ffa50000.rkvenc
Total 1 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5603
    Alloc by (vmpi                ) [0x03877000-0x038b0fff] 0x0003a000 (232 KiB)
        Attached Devices:
        ffa50000.rkvenc
```

```
Total 1 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5602
    Alloc by (vmpi                ) [0x0324e000-0x03876fff] 0x00629000 (6308
KiB)
        Attached Devices:
        ffa50000.rkvenc
Total 1 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5586
    Alloc by (ff660000.npu        ) [0x0308c000-0x030f7fff] 0x0006c000 (432 KiB)
        Attached Devices:
Total 0 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5585
    Alloc by (ff660000.npu        ) [0x03087000-0x0308bfff] 0x00005000 (20 KiB)
        Attached Devices:
Total 0 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5584
    Alloc by (ff660000.npu        ) [0x03082000-0x03086fff] 0x00005000 (20 KiB)
        Attached Devices:
Total 0 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5583
    Alloc by (ff660000.npu        ) [0x0307d000-0x03081fff] 0x00005000 (20 KiB)
        Attached Devices:
Total 0 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5582
    Alloc by (ff660000.npu        ) [0x0306b000-0x0307cfff] 0x00012000 (72 KiB)
        Attached Devices:
Total 0 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5581
    Alloc by (ff660000.npu        ) [0x03059000-0x0306afff] 0x00012000 (72 KiB)
        Attached Devices:
Total 0 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5580
    Alloc by (ff660000.npu        ) [0x03047000-0x03058fff] 0x00012000 (72 KiB)
        Attached Devices:
Total 0 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5579
    Alloc by (ff660000.npu        ) [0x02e5f000-0x03046fff] 0x001e8000 (1952
KiB)
        Attached Devices:
Total 0 devices attached

dma-heap:<rk-dma-heap-cma> -dmabuf  i_ino = 5328
    Alloc by (vmpi                ) [0x02800000-0x02802fff] 0x00003000 (12 KiB)
        Attached Devices:
Total 0 devices attached

dma-heap:<rk-dma-heap-cma> -non dmabuf
    Alloc by (ffa00000.rkisp      ) [0x02803000-0x02813fff] 0x00011000 (68 KiB)
dma-heap:<rk-dma-heap-cma> -non dmabuf
```

```
    Alloc by (ffa00000.rkisp      ) [0x02814000-0x02824fff] 0x00011000 (68 KiB)
dma-heap:<rk-dma-heap-cma> -non dmabuf
    Alloc by (ffa00000.rkisp      ) [0x02825000-0x02825fff] 0x00001000 (4 KiB)
dma-heap:<rk-dma-heap-cma> -non dmabuf
    Alloc by (ffa00000.rkisp      ) [0x02826000-0x02826fff] 0x00001000 (4 KiB)
dma-heap:<rk-dma-heap-cma> -non dmabuf
    Alloc by (ffa00000.rkisp      ) [0x02827000-0x02dddfff] 0x005b7000 (5852
KiB)
dma-heap:<rk-dma-heap-cma> -non dmabuf
    Alloc by (ffa00000.rkisp      ) [0x02dde000-0x02e4efff] 0x00071000 (452 KiB)
dma-heap:<rk-dma-heap-cma> -non dmabuf
    Alloc by (rkisp-vir0          ) [0x02e4f000-0x02e52fff] 0x00004000 (16 KiB)
dma-heap:<rk-dma-heap-cma> -non dmabuf
    Alloc by (rkisp-vir0          ) [0x02e53000-0x02e56fff] 0x00004000 (16 KiB)
dma-heap:<rk-dma-heap-cma> -non dmabuf
    Alloc by (rkisp-vir0          ) [0x02e57000-0x02e5afff] 0x00004000 (16 KiB)
dma-heap:<rk-dma-heap-cma> -non dmabuf
    Alloc by (rkisp-vir0          ) [0x02e5b000-0x02e5efff] 0x00004000 (16 KiB)
dma-heap:<rk-dma-heap-cma> -non dmabuf
    Alloc by (ffa00000.rkisp      ) [0x030f8000-0x03249fff] 0x00152000 (1352
KiB)
dma-heap:<rk-dma-heap-cma> -non dmabuf
    Alloc by (ffa00000.rkisp      ) [0x0324a000-0x0324dfff] 0x00004000 (16 KiB)

Total : 0x1634000 (22736 KiB)
```

Generally, use 'Alloc' to filter allocation information.

```
# cat /proc/rk_dma_heap/rk-dma-heap-info |grep Alloc
        Alloc by (vmpi                ) [0x03e1b000-0x03e33fff] 0x00019000 (100
KiB)
        Alloc by (vmpi                ) [0x03e02000-0x03e1afff] 0x00019000 (100
KiB)
        Alloc by (vmpi                ) [0x03d96000-0x03e01fff] 0x0006c000 (432
KiB)
        Alloc by (vmpi                ) [0x03d86000-0x03d95fff] 0x00010000 (64
KiB)
        Alloc by (vmpi                ) [0x03d76000-0x03d85fff] 0x00010000 (64
KiB)
        Alloc by (vmpi                ) [0x03c76000-0x03d75fff] 0x00100000 (1024
KiB)
        Alloc by (vmpi                ) [0x03c74000-0x03c75fff] 0x00002000 (8
KiB)
        Alloc by (vmpi                ) [0x03c72000-0x03c73fff] 0x00002000 (8
KiB)
        Alloc by (vmpi                ) [0x03c40000-0x03c71fff] 0x00032000 (200
KiB)
        Alloc by (vmpi                ) [0x03c3f000-0x03c3ffff] 0x00001000 (4
KiB)
        Alloc by (vmpi                ) [0x03c37000-0x03c3efff] 0x00008000 (32
KiB)
        Alloc by (vmpi                ) [0x03c36000-0x03c36fff] 0x00001000 (4
KiB)
        Alloc by (vmpi                ) [0x03c2e000-0x03c35fff] 0x00008000 (32
KiB)
        Alloc by (vmpi                ) [0x03b64000-0x03c2dfff] 0x000ca000 (808
KiB)
```

```
        Alloc by (vmpi                ) [0x03acf000-0x03b63fff] 0x00095000 (596
KiB)
        Alloc by (vmpi                ) [0x03ac0000-0x03acefff] 0x0000f000 (60
KiB)
        Alloc by (vmpi                ) [0x03ab1000-0x03abffff] 0x0000f000 (60
KiB)
        Alloc by (vmpi                ) [0x038ef000-0x03ab0fff] 0x001c2000 (1800
KiB)
        Alloc by (vmpi                ) [0x038ed000-0x038eefff] 0x00002000 (8
KiB)
        Alloc by (vmpi                ) [0x038b3000-0x038ecfff] 0x0003a000 (232
KiB)
        Alloc by (vmpi                ) [0x038b1000-0x038b2fff] 0x00002000 (8
KiB)
        Alloc by (vmpi                ) [0x03877000-0x038b0fff] 0x0003a000 (232
KiB)
        Alloc by (vmpi                ) [0x0324e000-0x03876fff] 0x00629000 (6308
KiB)
        Alloc by (ff660000.npu        ) [0x0308c000-0x030f7fff] 0x0006c000 (432
KiB)
        Alloc by (ff660000.npu        ) [0x03087000-0x0308bfff] 0x00005000 (20
KiB)
        Alloc by (ff660000.npu        ) [0x03082000-0x03086fff] 0x00005000 (20
KiB)
        Alloc by (ff660000.npu        ) [0x0307d000-0x03081fff] 0x00005000 (20
KiB)
        Alloc by (ff660000.npu        ) [0x0306b000-0x0307cfff] 0x00012000 (72
KiB)
        Alloc by (ff660000.npu        ) [0x03059000-0x0306afff] 0x00012000 (72
KiB)
        Alloc by (ff660000.npu        ) [0x03047000-0x03058fff] 0x00012000 (72
KiB)
        Alloc by (ff660000.npu        ) [0x02e5f000-0x03046fff] 0x001e8000 (1952
KiB)
        Alloc by (vmpi                ) [0x02800000-0x02802fff] 0x00003000 (12
KiB)
        Alloc by (ffa00000.rkisp      ) [0x02803000-0x02813fff] 0x00011000 (68
KiB)
        Alloc by (ffa00000.rkisp      ) [0x02814000-0x02824fff] 0x00011000 (68
KiB)
        Alloc by (ffa00000.rkisp      ) [0x02825000-0x02825fff] 0x00001000 (4
KiB)
        Alloc by (ffa00000.rkisp      ) [0x02826000-0x02826fff] 0x00001000 (4
KiB)
        Alloc by (ffa00000.rkisp      ) [0x02827000-0x02dddfff] 0x005b7000 (5852
KiB)
        Alloc by (ffa00000.rkisp      ) [0x02dde000-0x02e4efff] 0x00071000 (452
KiB)
        Alloc by (rkisp-vir0          ) [0x02e4f000-0x02e52fff] 0x00004000 (16
KiB)
        Alloc by (rkisp-vir0          ) [0x02e53000-0x02e56fff] 0x00004000 (16
KiB)
        Alloc by (rkisp-vir0          ) [0x02e57000-0x02e5afff] 0x00004000 (16
KiB)
        Alloc by (rkisp-vir0          ) [0x02e5b000-0x02e5efff] 0x00004000 (16
KiB)
        Alloc by (ffa00000.rkisp      ) [0x030f8000-0x03249fff] 0x00152000 (1352
KiB)
```

```
        Alloc by (ffa00000.rkisp      ) [0x0324a000-0x0324dfff] 0x00004000 (16
KiB)
```

Format: Alloc by ([dmabuf name]) [0xaaaaaaaa-0xbbbbbbbb] 0xzzzzzzzz (dd KiB)

1. [dmabuf name]: The thread name that allocates memory in the Driver is set to the dmabuf name by default; this default value is overridden if a specific string is specified by each module. For example, vmpi is the thread name in rockit that calls rk-dma-heap.
2. [0xaaaaaaaa-0xbbbbbbbb]: 0xaaaaaaaa is the start address (physical address) of the memory region, and 0xbbbbbbbb is the end address (physical address).
3. 0xzzzzzzzz: The hexadecimal value of the memory region size.
4. dd KiB: The decimal value of the memory region size converted to KiB.