



4DS NEXUS · OWNER DESK

BOLOLO SECURITY

Business administration & command oversight

USER MANUAL — OWNER

Your login is the master key for Bololo Security on 4DS Nexus. This guide shows the control panel visually: who to create, what to watch each morning, and when to stay out of a live panic.

- OWNER
- CONTROL ROOM
- INSTALLATION
- CLIENT
- OFFICER

PREPARED FOR

Bololo Security

AUDIENCE

Owner / Managing Director

DEVICE

Desktop or laptop

PREPARED BY

4DS Solutions (Pty) Ltd

SIGN-IN

Control Panel · /login

ISSUED

5 September 2026 · v1.1

DOC 4DS-BOLOLO-UM-OWN-01 · CONTROLLED OPERATIONAL COPY · CONFIDENTIAL

Use the numbered sections in order the first time. After that, jump to the screen you need.

01	Who this login is for	03
02	Sign in & first-day timeline	04
03	Control panel map	05
04	Teams, roles & invitations	06
05	Customers, jobs & money	07
06	Daily owner loop	08
07	Faults & escalation	09

Issue the other four manuals to dispatchers, technicians, clients and officers. Do not give this Owner manual to field staff.

The Owner account sees the whole company. Use it to set people up and to audit the shift — not to sit on every radio call.

YOU USE OWNER FOR

- Creating dispatchers, officers, technicians and clients
- Company settings, branches and passwords
- Customers, plans, store and install jobs
- A morning read of the Ops Board

HAND THESE TO OTHERS

- Live panic dispatch → Control Room manual
- Driving to a job → Officer manual
- Fitting cameras → Installation manual
- Household panic button → Client manual

RULE 01

Least privilege

Give each person the smallest role that still lets them work.

RULE 02

One login each

Never share the Owner password.
Deactivate leavers the same day.

RULE 03

Doors

Control Panel /login · Officer
/officer/login · Technician /tech/login
· Client /portal/login · Supervisor
/supervisor/login.

01 Change password	02 Company details	03 Branches / teams	04 Invite staff	05 Add customers	06 Staff the board
--------------------------	--------------------------	---------------------------	--------------------	---------------------	-----------------------

1 Open the Bololo / 4DS address → choose **Control Panel** (not Client, Officer or Technician).

2 Enter organisation, Owner email and password. You land on the **Ops Board**.

3 Settings: confirm company name, phones and address.

4 Teams & Users: create at least one Dispatcher before any client goes live.

! **Do not go live empty-handed**

A client Panic with nobody on the Ops Board is a failed launch. Confirm a dispatcher is signed in first.

This is the desktop you work in. The red item is the home screen after login.

4DS Nexus — Bololo Security

Ops Board
Command Hub
Live Map
Dispatch
Incidents
CCTV
Customers
Teams
Settings

7
OPEN ALERTS

4
ON DUTY

2
INSTALL JOBS

OPS BOARD
Open panics sit at the top. Click the incident — do not manage it only on WhatsApp.

LIVE
Map · CCTV · Dispatch
Where the shift actually happens.
Supervisors live here.

BUSINESS
Customers · Store · Jobs
Who pays, what was sold, what must
be installed.

ADMIN
Teams · Settings · Analytics
Who can log in, rules, and the
month's picture.

Open **Teams & Users**. Each row is a real person and a portal.

OWNER This manual Full business + operations.	DISPATCHER Control Room Map, CCTV, incidents, chat.
OFFICER Officer App Jobs, GPS, evidence, SOS.	TECHNICIAN Install app Job board, cameras, stock.
CLIENT Client Portal Panic, alarm, family, vehicles.	SUPERVISOR Field oversight Roster, performance, map.

- 1 Add user → name, email, role, branch → temporary password or invite link.
- 2 Tell them which door to use: Control Panel, Officer, Technician or Client Portal.
- 3 When they leave: set Inactive the same day.

CUSTOMERS**Subscriber files**

Plan, property, vehicles, invite status. Check here before blaming the app.

INSTALL JOBS**Work for technicians**

Address, kit, date, assigned tech. Status should move every visit.

STORE**Gear catalogue**

Products and orders linked to installs.

ANALYTICS**The month in numbers**

Incidents, officers, response picture for the owner meeting.

%**Revenue share records**

Keep monthly client payments accurate. The signed 4DS agreement uses 10% of payments connected to the system — this screen is how you stay honest, not how you dispatch.

Watch the live board without taking over

If a panic is open and unassigned, phone the on-duty dispatcher. Do not resolve a live panic from Owner unless Control Room has confirmed false or complete.

AM Ops Board	AM Install diary	Day New customers	Day Leaver access	PM Open criticals	Month Revenue file
-----------------	---------------------	----------------------	----------------------	----------------------	-----------------------

MORNING

3-minute scan

Open panics, officers on duty, overnight leftovers.

ANYTIME

People hygiene

Deactivate anyone who left. No shared logins.

END OF DAY

No silent fires

Every high-priority ticket has an owner and a next step.

MONTH-END

Numbers

Active clients and payments before 4DS share calculation.

LOGIN**Cannot sign in**

Organisation + email + caps lock. Reset from Teams if you still have an admin. Else 4DS.

ACCESS**Wrong screens**

Wrong role on the user record — fix in Teams & Users.

CLIENT**Panic dead**

Confirm CLIENT login + active plan + a dispatcher on the board.

MAP**Grey tiles**

Map pictures need internet. Pins still work on a local network.

SOS Platform down

Fall back to radio / phone SOP. Tell 4DS. Do not invent a second unofficial client list in a notebook that nobody else can see.

APP SUPPORT**4DS Solutions**

www.4dsnexus.co.za · quote “Bololo Security
— Owner desk”

OPERATIONS**Bololo Security**

Radio and supervisor for SOP. 4DS Solutions
only for platform faults.

DOCUMENT**5 September 2026 · v1.1**

Controlled copy. Do not issue to another
company or role.