

Calculations for the wave packet through a potential barrier application

Loric Vandentempel

April 2020

Contents

1	Introduction	2
2	Time independent Schrödinger equation	2
3	Different cases	3
3.1	$x < x_{start}$	3
3.2	$x_{start} \leq x \leq x_{end}$	3
3.3	$x > x_{end}$	3
3.3.1	Summary of the cases	3
4	Finding the value of the constants	4
4.1	Case 1: $E - V_{barrier} \geq 0$ and $E - V_{after} \geq 0$	4
4.1.1	Continuity at x_{start}	4
4.1.2	Continuity at x_{end}	5
4.1.3	Solving x_{start} and x_{end} together	5
4.1.4	Summary of the values for R , T , A and B	6
4.2	Case 2: $E - V_{barrier} \geq 0$ and $E - V_{after} < 0$	6
4.2.1	Continuity at x_{start}	6
4.2.2	Continuity at x_{end}	6
4.2.3	Solving x_{start} and x_{end} together	6
4.2.4	Summary of the values for R , T , A and B	6
4.3	Case 3: $E - V_{barrier} < 0$ and $E - V_{after} \geq 0$	6
4.3.1	Continuity at x_{start}	6
4.3.2	Continuity at x_{end}	6
4.3.3	Solving x_{start} and x_{end} together	7
4.3.4	Summary of the values for R , T , A and B	7
4.4	Case 4: $E - V_{barrier} < 0$ and $E - V_{after} < 0$	7
4.4.1	Continuity at x_{start}	7
4.4.2	Continuity at x_{end}	7
4.4.3	Solving x_{start} and x_{end} together	7
4.4.4	Summary of the values for R , T , A and B	7

1 Introduction

The aim is to display a wave packet (of wave number k_0 and energy E) passing through a square potential barrier with variable parameters. These are x_{start} and x_{end} where the potential step starts and ends; V_{before} , $V_{barrier}$ and V_{after} , respectively the values of the potential before x_{start} , in between x_{start} and x_{end} , and after x_{end} .

2 Time independent Schrödinger equation

Let's start by calculating the value of the wave function only with the spacial variations (the temporal ones will be calculated later). The stationary Schrödinger equation can be written like this

$$-\frac{\hbar^2}{2m} \frac{d^2\psi(x)}{dx^2} + V(x)\psi(x) = E\psi(x) \quad (1)$$

To be able to use our parameters we can change the equation by using the wave number value for matter

$$k_0 = \frac{\sqrt{2mE}}{\hbar} \quad (2)$$

By rearranging we get

$$\frac{\hbar^2}{2m} = \frac{E}{k_0^2} \quad (3)$$

Replacing it in the Schrödinger equation gives

$$-\frac{E}{k_0^2} \frac{d^2\psi(x)}{dx^2} + V(x)\psi(x) = E\psi(x) \quad (4)$$

Rearranging and simplifying the writing gets us

$$\psi'' + (E - V(x)) \frac{k_0^2}{E} \psi = 0 \quad (5)$$

By solving this differential equation, you get 2 different equations for $\psi(x)$ depending on the sign of $E - V(x)$

$$\psi(x) = \alpha e^{ikx} + \beta e^{-ikx} \quad \text{if} \quad E - V(x) \geq 0 \quad (6)$$

$$\psi(x) = \gamma \sinh(Kx) + \lambda \cosh(Kx) \quad \text{if} \quad E - V(x) < 0 \quad (7)$$

with

$$k^2 = (E - V(x)) \frac{k_0^2}{E} \quad (8)$$

$$K^2 = (V(x) - E) \frac{k_0^2}{E} \quad (9)$$

3 Different cases

3.1 $x < x_{start}$

We assume a module of the original wave function of $\alpha = 1$ and we calculate the value of k_s with Equation 8.

$$\psi(x) = e^{ik_s x} + R e^{-ik_s x} \quad \text{if} \quad E - V_{before} \geq 0 \quad (10)$$

$$\psi(x) = 0 \quad \text{if} \quad E - V_{before} < 0 \quad (11)$$

Where R is the reflection coefficient.

For Equation 11, the energy is smaller than the potential so the packet cannot exist in its starting position.

3.2 $x_{start} \leq x \leq x_{end}$

$$\psi(x) = A e^{ik_b x} + B e^{-ik_b x} \quad \text{if} \quad E - V_{barrier} \geq 0 \quad (12)$$

$$\psi(x) = A \sinh(K_b x) + B \cosh(K_b x) \quad \text{if} \quad E - V_{barrier} < 0 \quad (13)$$

Where k_b and K_b are the values of k and K calculated from Equation 8 and Equation 9.

3.3 $x > x_{end}$

We assume that the potential stays the same from x_{end} to $+\infty$, so there is no backward component to the wave function ($\beta = \lambda = 0$).

$$\psi(x) = T e^{ik_e x} \quad \text{if} \quad E - V_{after} \geq 0 \quad (14)$$

$$\psi(x) = T \sinh(K_e x) \quad \text{if} \quad E - V_{after} < 0 \quad (15)$$

Where k_e and K_e are the values of k and K calculated from Equation 8 and Equation 9.

3.3.1 Summary of the cases

First let's look at Equation 11: from $-\infty$ to x_{start} the value of the wave function is 0. By continuity we can deduce that the wave function is null everywhere.

From there we can see that there are 4 more cases for $E - V_{before} \geq 0$ for which the equations to use are:

- (10), (12) and (14) for $E - V_{barrier} \geq 0$ and $E - V_{after} \geq 0$ (subsection 4.1);
- (10), (12) and (15) for $E - V_{barrier} \geq 0$ and $E - V_{after} < 0$ (subsection 4.2);
- (10), (13) and (14) for $E - V_{barrier} < 0$ and $E - V_{after} \geq 0$ (subsection 4.3);
- (10), (13) and (15) for $E - V_{barrier} < 0$ and $E - V_{after} < 0$ (subsection 4.4).

4 Finding the value of the constants

All constants are found using the continuity of the wave function and its derivative at the boundaries: $\psi_{left}(\chi) = \psi_{right}(\chi)$ and $\psi'_{left}(\chi) = \psi'_{right}(\chi)$. This makes for total of 4 equations with 4 unknowns (2 equations at x_{start} and 2 at x_{end}).

All these cases are calculated with $E - V_{before} \geq 0$ and Equation 10. For simplicity, all notations of x_{start} and x_{end} will be replaced by x_s and x_e .

4.1 Case 1: $E - V_{barrier} \geq 0$ and $E - V_{after} \geq 0$

4.1.1 Continuity at x_{start}

$$(10 = 12) \quad \psi(x_s) = e^{ik_s x_s} + R e^{-ik_s x_s} = A e^{ik_b x_s} + B e^{-ik_b x_s} \quad (16)$$

$$\Leftrightarrow \boxed{R = e^{ik_s x_s} (A e^{ik_b x_s} + B e^{-ik_b x_s} - e^{ik_s x_s})} \quad (17)$$

$$(10' = 12') \quad \psi'(x_s) = ik_s e^{ik_s x_s} - ik_s R e^{-ik_s x_s} = ik_b A e^{ik_b x_s} - ik_b B e^{-ik_b x_s} \quad (18)$$

$$\Leftrightarrow \frac{k_s}{k_b} (e^{ik_s x_s} - R e^{-ik_s x_s}) = A e^{ik_b x_s} - B e^{-ik_b x_s} \quad (19)$$

Let's set $\boxed{D = \frac{k_s}{k_b}}$ and $\boxed{E = e^{ix_s}}$. Equation 16 becomes

$$E^{k_s} + \frac{R}{E^{k_s}} = A E^{k_b} + \frac{B}{E^{k_b}} \quad (20)$$

And Equation 19 becomes

$$D(E^{k_s} - \frac{R}{E^{k_s}}) = A E^{k_b} - \frac{B}{E^{k_b}} \quad (21)$$

$$\Leftrightarrow E^{k_s} - \frac{R}{E^{k_s}} = \frac{A}{D} E^{k_b} - \frac{B}{D E^{k_b}} \quad (22)$$

From there, Equation 20 can be added to Equation 22

$$2E^{k_s} = (1 + \frac{1}{D}) A E^{k_b} + (1 - \frac{1}{D}) \frac{B}{E^{k_b}} \quad (23)$$

$$\Leftrightarrow \frac{B}{E^{k_b}} (1 - \frac{1}{D}) = 2E^{k_s} - (1 + \frac{1}{D}) A E^{k_b} \quad (24)$$

$$\Leftrightarrow B = \frac{E^{k_b}}{1 - 1/D} [2E^{k_s} - (1 + \frac{1}{D}) A E^{k_b}] \quad (25)$$

And replacing the values of D and E gets us

$$\boxed{B = \frac{e^{ik_b x_s}}{1 - k_b/k_s} [2e^{ik_s x_s} - (1 + \frac{k_b}{k_s}) A e^{ik_b x_s}]} \quad (26)$$

4.1.2 Continuity at x_{end}

$$(12 = 14) \quad \psi(x_e) = Ae^{ik_b x_e} + Be^{-ik_b x_e} = Te^{ik_e x_e} \quad (27)$$

$$\Leftrightarrow \boxed{T = e^{-ik_e x_e} (Ae^{ik_b x_e} + Be^{-ik_b x_e})} \quad (28)$$

$$(12' = 14') \quad \psi'(x_e) = ik_b Ae^{ik_b x_e} - ik_b Be^{-ik_b x_e} = ik_e Te^{ik_e x_e} \quad (29)$$

$$\frac{k_b}{k_e} (Ae^{ik_b x_e} - Be^{-ik_b x_e}) = Te^{ik_e x_e} \quad (30)$$

Let's set $\boxed{F = e^{ix_e}}$ and $\boxed{G = \frac{k_b}{k_e}}$. Equation 27 becomes

$$AF^{k_b} + \frac{B}{F^{k_b}} = TF^{k_e} \quad (31)$$

And Equation 30 becomes

$$G(AF^{k_b} - \frac{B}{F^{k_b}}) = TF^{k_e} \quad (32)$$

Subtracting Equation 31 from Equation 32 gives

$$(1 - G)(AF^{k_b} - \frac{B}{F^{k_b}}) = 0 \quad (33)$$

$$\Leftrightarrow B = AF^{2k_b} \quad (34)$$

Replacing with the value of F gets us

$$\boxed{B = Ae^{2ik_b x_e}} \quad (35)$$

4.1.3 Solving x_{start} and x_{end} together

Equating the values of B in Equation 25 and Equation 34 gives this equation

$$B = \frac{E^{k_b}}{1 - 1/D} [2E^{k_s} - (1 + \frac{1}{D})AE^{k_b}] = AF^{2k_b} \quad (36)$$

$$\Leftrightarrow \frac{2E^{k_s k_b}}{1 - 1/D} = AF^{2k_b} + \frac{1 + 1/D}{1 - 1/D} AE^{2k_b} \quad (37)$$

$$\Leftrightarrow A = \frac{1}{F^{2k_b} + \frac{1+1/D}{1-1/D} E^{2k_b}} \frac{2E^{k_s k_b}}{1 - 1/D} \quad (38)$$

Replacing the values for D , E and F gives the final result for A , from which the values for B , R and T can be deduced.

$$\boxed{A = \frac{1}{e^{2ik_b x_e} + \frac{1+k_b/k_s}{1-k_b/k_s} e^{2ik_b x_s}} \frac{2e^{ik_s k_b x_s}}{1 - k_b/k_s}} \quad (39)$$

4.1.4 Summary of the values for R , T , A and B

$$A = \frac{1}{e^{2ik_b x_e} + \frac{1+k_b/k_s}{1-k_b/k_s} e^{2ik_b x_s}} \frac{2e^{ik_s k_b x_s}}{1 - k_b/k_s} \quad (40)$$

$$B = Ae^{2ik_b x_e} \quad (41)$$

$$R = e^{ik_s x_s} (Ae^{ik_b x_s} + Be^{-ik_b x_s} - e^{ik_s x_s}) \quad (42)$$

$$T = e^{-ik_e x_e} (Ae^{ik_b x_e} + Be^{-ik_b x_e}) \quad (43)$$

4.2 Case 2: $E - V_{\text{barrier}} \geq 0$ and $E - V_{\text{after}} < 0$

4.2.1 Continuity at x_{start}

$$(10 = 12) \quad \psi(x_s) = e^{ik_s x_s} + Re^{-ik_s x_s} = Ae^{ik_b x_s} + Be^{-ik_b x_s} \quad (44)$$

$$(10' = 12') \quad \psi'(x_s) = ik_s e^{ik_s x_s} - ik_s Re^{-ik_s x_s} = ik_b Ae^{ik_b x_s} - ik_b Be^{-ik_b x_s} \quad (45)$$

4.2.2 Continuity at x_{end}

$$(12 = 15) \quad \psi(x_e) = Ae^{ik_b x_e} + Be^{-ik_b x_e} = T \sinh(K_e x_e) \quad (46)$$

$$(12' = 15') \quad \psi'(x_e) = ik_b Ae^{ik_b x_e} - ik_b Be^{-ik_b x_e} = TK_e \cosh(K_e x_e) \quad (47)$$

4.2.3 Solving x_{start} and x_{end} together

4.2.4 Summary of the values for R , T , A and B

4.3 Case 3: $E - V_{\text{barrier}} < 0$ and $E - V_{\text{after}} \geq 0$

4.3.1 Continuity at x_{start}

$$(10 = 13) \quad \psi(x_s) = e^{ik_s x_s} + Re^{-ik_s x_s} = A \sinh(K_b x_s) + B \cosh(K_b x_s) \quad (48)$$

$$(10' = 13') \quad \psi'(x_s) = ik_s e^{ik_s x_s} - Rik_s e^{-ik_s x_s} = AK_b \cosh(K_b x_s) + BK_b \sinh(K_b x_s) \quad (49)$$

4.3.2 Continuity at x_{end}

$$(13 = 14) \quad \psi(x_e) = A \sinh(K_b x_e) + B \cosh(K_b x_e) = Te^{ik_e x_e} \quad (50)$$

$$(13' = 14') \quad \psi'(x_e) = AK_b \cosh(K_b x_e) + BK_b \sinh(K_b x_e) = ik_e Te^{ik_e x_e} \quad (51)$$

4.3.3 Solving x_{start} and x_{end} together

4.3.4 Summary of the values for R , T , A and B

4.4 Case 4: $E - V_{barrier} < 0$ and $E - V_{after} < 0$

4.4.1 Continuity at x_{start}

$$(10 = 13) \quad \psi(x_s) = e^{ik_s x_s} + R e^{-ik_s x_s} = A \sinh(K_b x_s) + B \cosh(K_b x_s) \quad (52)$$

$$(10' = 13') \quad \psi'(x_s) = ik_s e^{ik_s x_s} - R i k_s e^{-ik_s x_s} = A K_b \cosh(K_b x_s) + B K_b \sinh(K_b x_s) \quad (53)$$

4.4.2 Continuity at x_{end}

$$(13 = 15) \quad \psi(x_e) = A \sinh(K_b x_e) + B \cosh(K_b x_e) = T \sinh(K_e x_e) \quad (54)$$

$$(13' = 15') \quad \psi'(x_e) = A K_b \cosh(K_b x_e) + B K_b \sinh(K_b x_e) = T K_e \cosh(K_e x_e) \quad (55)$$

4.4.3 Solving x_{start} and x_{end} together

4.4.4 Summary of the values for R , T , A and B