

Rack 1	In Row	Rack 3	Rack 5	In Row	Rack 7	Rack 9	In Row	Rack 11	Rack 13	In Row	Rack 15	Rack 17	In Row	SAI
Pasillo Caliente														
Rack 2	In Row	Rack 4	Rack 6	In Row	Rack 8	Rack 10	In Row	Rack 12	Rack 14	In Row	Rack 16	Rack 18	In Row	SAI

Equipamiento	Unidades	Rack Units	Rack Units Total	Consumo (W)	Consumo Total
Chasis HPE Synergy 12000 Frame	20	10	200	2650	53000
Switch Cisco MDS 9132T	2	1	2	650	1300
Switches Cisco Nexus 3048	N	1	N	120	120*N
Switch Cisco Nexus 9316D-GX	2	1	2	420	840
Sistema de almacenamiento HPE 3PAR StoreServ 9450	1	86	86	-	4900
Routers Cisco C8300-1N1S-6T	2	1	2	500	1000
Firewall Cisco ASA 5516-X	2	1	2	100	200
Servidores rack HPE Proliant DL380	270	1	270	460	124200
Total RU			644 + N	Total W	185,440 + 120*N

RACK 1 - 2		
Unidades	Elemento	RU
1	Switches Cisco Nexus 3048	1
1	Switch Cisco Nexus 9316D-GX	1
1	Routers Cisco C8300-1N1S-6T	1
1	Firewall Cisco ASA 5516-X	1
30	Servidores rack HPE Proliant DL380	30
Total / unidad		34 / 42 RU

RACK 3 - 12		
Unidades	Elemento	RU
1	Switches Cisco Nexus 3048	1
2	Chasis HPE Synergy 12000 Frame	2*10
15	Servidores rack HPE Proliant DL380	15
Total / unidad		36 / 42 RU

RACK 13 - 14		
Unidades	Elemento	RU
1	Switches Cisco Nexus 3048	1
30	Servidores rack HPE Proliant DL380	30
Total / unidad		31 / 42 RU

RACK 15 - 16		
Unidades	Elemento	RU
1	Switch Cisco MDS 9132T	1
1	Control.HPE 3PAR 9450 Storage Node	8
10	Bast. HPE 3PAR 9000 24-disk 2U SFF	10*2
Total / unidad		29 / 42 RU

RACK 17-18		
Unidades	Elemento	RU
1	Switches Cisco Nexus 3048	1
10	Bast. HPE 3PAR 9000 24-disk 2U SFF	10*2
Total / unidad		21 / 42 RU

	Racks	RU usada	RU usada (%)	RU libre	RU libre (%)
Total	18	590 / 756	78,05	166 / 756	21,95