

PURE MATHEMATICS WITH STATISTICS • UPPER SIXTH

UPPER SIXTH — PURE MATHEMATICS WITH STATISTICS

CHAPTER 2

COMPLEX NUMBERS

SUGGESTED TIME: 19 PERIODS

IN THIS CHAPTER

This chapter introduces complex numbers, the extension of the real number system built on the imaginary unit i . Students learn to compute with complex numbers in Cartesian, polar and exponential forms, represent them on the Argand diagram, apply De Moivre's theorem, extract roots, and interpret loci geometrically — all core skills for the GCE Advanced Level examination.

- By the end of this chapter I can explain the historical need for complex numbers and define the imaginary unit i with its powers.
- By the end of this chapter I can add, subtract, multiply and divide complex numbers in Cartesian form.
- By the end of this chapter I can use the complex conjugate and its properties to simplify expressions and solve equations.
- By the end of this chapter I can represent a complex number on an Argand diagram and interpret its modulus and argument geometrically.
- By the end of this chapter I can convert a complex number between Cartesian, polar (trigonometric) and exponential forms.
- By the end of this chapter I can apply De Moivre's theorem to compute powers and to relate multiple angles to powers of $\cos x$ and $\sin x$.



DOWNLOAD ON- BUCH

Free • Google Play
AI tutor, past papers,
results



GO ONBUCH+

All signed courses, unlimited AI
tutor, PDF sheets — OnBuch+
tab in the app

THIS SIGNED COURSE CONTAINS

COURSE

complete, illustrated,
step by step

METHODS

and worked examples

EXERCISES

exam style + solutions

SUMMARY SHEET

the essentials to
remember



Signed • OnBuch+

ONBUCH+ TEACHING TEAM
FOLLOWS THE OFFICIAL MINESEC SYLLABUS

OnBuch+

CONTENTS

- | | |
|--|--|
| 1. Birth of Complex Numbers and the Imaginary Unit i | 7. Roots of Complex Numbers: n th Roots and Cube Roots |
| 2. Algebra of Complex Numbers and the Conjugate | 8. Loci in the Complex Plane and Synthesis |
| 3. Equations and Roots in $\mathbb{C}$ | 9. Integration activity |
| 4. The Argand Diagram, Modulus and Argument | 10. Methods and worked examples |
| 5. Polar and Exponential Forms | 11. Exercises |
| 6. De Moivre's Theorem and Trigonometric Applications | 12. Solutions to the exercises |
| | 13. Summary sheet |

CHAPTER OBJECTIVES

- By the end of this chapter I can explain the historical need for complex numbers and define the imaginary unit i with its powers.
- By the end of this chapter I can add, subtract, multiply and divide complex numbers in Cartesian form.
- By the end of this chapter I can use the complex conjugate and its properties to simplify expressions and solve equations.
- By the end of this chapter I can represent a complex number on an Argand diagram and interpret its modulus and argument geometrically.
- By the end of this chapter I can convert a complex number between Cartesian, polar (trigonometric) and exponential forms.
- By the end of this chapter I can apply De Moivre's theorem to compute powers and to relate multiple angles to powers of $\cos x$ and $\sin x$.
- By the end of this chapter I can find square roots and n th roots (including cube roots) of complex numbers.
- By the end of this chapter I can solve polynomial equations with complex roots, including those with real coefficients.
- By the end of this chapter I can describe and sketch loci defined by conditions on $|z|$ and $\arg(z)$.


PREREQUISITES

- Real number algebra: expanding, factorising and solving quadratic equations (Lower Sixth, PMS01).
- Trigonometric ratios, standard angles and identities such as $\cos^2 x + \sin^2 x = 1$ (Lower Sixth trigonometry).
- Radian measure and the unit circle.
- Basic coordinate geometry: distance between two points, equations of circles and perpendicular bisectors.
- Surds and rationalising denominators (useful technique transferred to conjugates).

1 BIRTH OF COMPLEX NUMBERS AND THE IMAGINARY UNIT I

An engineer in Douala analysing the alternating current supplied by ENEO models the impedance of a circuit by a number whose square is negative — yet no real number has a negative square. Likewise, when a student at the University of Yaoundé I asks a calculator for the square root of -9 , the machine replies **ERROR**, as if such a number could not exist. For centuries, mathematicians like Cardano and Bombelli faced the same wall while solving cubic equations. Their bold answer was to invent a new number, i , whose square is -1 . This chapter opens the door to that invisible but powerful world: the complex numbers, which today govern electricity, signal processing and even the mobile phone networks connecting Bamenda to Buea.

1.1 Historical Motivation: From Cubic Equations to the Imaginary Unit



Historical timeline of complex numbers: from Cardano’s cubic to Gauss’s rigorous foundation.

The need for complex numbers arose not so much from quadratic equations like $x^2 + 1 = 0$ (which were simply declared “impossible”) as from **cubic equations**. In 1545, Gerolamo Cardano published *Ars Magna*, in which the formula for solving $x^3 + px + q = 0$ sometimes required manipulating square roots of negative numbers — even when the final answer was a perfectly real number. For instance, solving $x^3 = 15x + 4$ leads to

$$x = \sqrt[3]{2 + \sqrt{-121}} + \sqrt[3]{2 - \sqrt{-121}}.$$

Cardano called such expressions “sophistic” and “useless”. It was Rafael Bombelli (1572) who dared to treat $\sqrt{-1}$ as a formal symbol obeying $(\sqrt{-1})^2 = -1$. He showed that the two cube roots above are $2 + i$ and $2 - i$, whose sum gives the real solution $x = 4$ — and indeed $4^3 = 64 = 15 \times 4 + 4$. Later, Leonhard Euler introduced the notation $i = \sqrt{-1}$ and discovered the profound identity $e^{i\pi} + 1 = 0$. The geometric representation by Caspar Wessel (1797), Jean-Robert Argand (1806) and Carl Friedrich Gauss turned these “imaginary” numbers into points of a plane, finally granting them full mathematical citizenship.

DID YOU KNOW? Why “imaginary”?

The term “imaginary” was coined by Descartes in 1637 as a derogatory label — he considered such numbers “imagined” rather than “real”. Gauss later preferred the word “com-

plex” because a number $a + ib$ has two “parts”. Today, complex numbers are as real as any other mathematical object; they are indispensable in physics, engineering and pure mathematics.

1.2 The Imaginary Unit i and its Algebra

DEFINITION Imaginary Unit

The **imaginary unit** i is the number defined by the property

$$i^2 = -1.$$

Equivalently, we write $i = \sqrt{-1}$. Any real multiple of i (i.e. bi with $b \in \mathbb{R}$) is called a **purely imaginary number**.

From $i^2 = -1$ we immediately obtain the first powers:

$$i^1 = i, \quad i^2 = -1, \quad i^3 = i^2 \cdot i = -i, \quad i^4 = i^2 \cdot i^2 = (-1)(-1) = 1.$$

Because $i^4 = 1$, the powers of i repeat every four steps: for any integer n ,


$$i^{n+4} = i^n \cdot i^4 = i^n.$$

PROPERTY Periodicity of Powers of i

The sequence $(i^n)_{n \in \mathbb{N}}$ is periodic with period 4:

$$i^{4k} = 1, \quad i^{4k+1} = i, \quad i^{4k+2} = -1, \quad i^{4k+3} = -i \quad (k \in \mathbb{N}).$$

The proof (a direct application of $i^4 = 1$) is immediate and may be required as a short justification in the examination.



The cycle of powers of i on the unit circle: each multiplication by i rotates by 90° counter-clockwise.

METHOD Evaluating i^n for any integer n

1. Divide n by 4 and find the remainder r with $0 \leq r \leq 3$. (For negative n , add multiples of 4 to the exponent until it becomes non-negative, using $i^4 = 1$.)
2. Then $i^n = i^r$ using the table:

r	0	1	2	3
i^r	1	i	-1	$-i$

WORKED EXAMPLE 1 Quick evaluation of a large power

Evaluate i^{2025} .

SOLUTION

Divide 2025 by 4: $2025 = 4 \times 506 + 1$, so the remainder is 1. Hence $i^{2025} = i^1 = i$.

WARNING The square-root trap

It is tempting to write $\sqrt{-a}\sqrt{-b} = \sqrt{(-a)(-b)} = \sqrt{ab}$ for $a, b > 0$. This is false, because the rule $\sqrt{x}\sqrt{y} = \sqrt{xy}$ is valid only for $x, y \geq 0$ in $\mathbb{R}$. The correct procedure is:

$$\sqrt{-a} = i\sqrt{a}, \quad \sqrt{-b} = i\sqrt{b} \implies \sqrt{-a}\sqrt{-b} = i\sqrt{a} \cdot i\sqrt{b} = i^2\sqrt{ab} = -\sqrt{ab}.$$

Always convert $\sqrt{-a}$ to $i\sqrt{a}$ before multiplying.

1.3 Complex Numbers: Definition and Basic Properties

DEFINITION Complex Number

A **complex number** is any expression of the form

$$z = a + ib,$$

where $a, b \in \mathbb{R}$ and $i^2 = -1$. The real number a is called the **real part** of z , denoted $\Re(z)$ or $\operatorname{Re}(z)$; the real number b is called the **imaginary part** of z , denoted $\Im(z)$ or $\operatorname{Im}(z)$. The form $a + ib$ is called the **Cartesian** (or **algebraic**) **form** of z .

Thus every complex number corresponds uniquely to an ordered pair $(a, b) \in \mathbb{R}^2$. Two complex numbers are equal if and only if their real parts and their imaginary parts are respectively equal:

$$a + ib = c + id \iff a = c \text{ and } b = d.$$

Special cases:


- If $b = 0$, then $z = a \in \mathbb{R}$; we say z is **purely real**.
- If $a = 0$, then $z = ib$ with $b \in \mathbb{R}$; we say z is **purely imaginary**.
- The number $0 = 0 + 0i$ is both purely real and purely imaginary.

The set of all complex numbers is denoted $\mathbb{C}$:

$$\mathbb{C} = \{a + ib \mid a, b \in \mathbb{R}\}.$$

It contains the real numbers as a subset (those with $b = 0$), so we have the chain of inclusions

$$\mathbb{N} \subset \mathbb{Z} \subset \mathbb{Q} \subset \mathbb{R} \subset \mathbb{C}.$$



Nested number sets: $\mathbb{N} \subset \mathbb{Z} \subset \mathbb{Q} \subset \mathbb{R} \subset \mathbb{C}$. Each larger set contains the numbers needed to solve more equations.

KEY POINTS Key Points of Section 1

- The imaginary unit i satisfies $i^2 = -1$; it was introduced to solve equations like $x^2 + 1 = 0$ and to make the cubic formulas work.
- Powers of i cycle every 4: $i, -1, -i, 1$. To compute i^n , find the remainder of n upon division by 4.
- A complex number has the form $z = a + ib$ with $a, b \in \mathbb{R}$; $a = \Re(z)$, $b = \Im(z)$.
- Equality: $a + ib = c + id \iff a = c$ and $b = d$.
- The hierarchy of number sets: $\mathbb{N} \subset \mathbb{Z} \subset \mathbb{Q} \subset \mathbb{R} \subset \mathbb{C}$.
- Warning: $\sqrt{-a}\sqrt{-b} \neq \sqrt{ab}$ in general; always write $\sqrt{-a} = i\sqrt{a}$ first.

1.4 Worked Examples and Common Pitfalls

WORKED EXAMPLE 2 Solving a simple quadratic in $\mathbb{C}$

Solve $x^2 + 4 = 0$ in $\mathbb{C}$.

SOLUTION

$x^2 = -4 \implies x = \pm\sqrt{-4} = \pm i\sqrt{4} = \pm 2i$. Check: $(2i)^2 = 4i^2 = 4(-1) = -4$ and $(-2i)^2 = 4i^2 = -4$. Both are solutions: $S = \{-2i, 2i\}$.

WORKED EXAMPLE 3 Simplifying an expression with powers of i

Simplify $\frac{i^{17} + i^{23}}{i^6}$.

SOLUTION

Reduce each exponent modulo 4:

$$\begin{array}{ll} 17 = 4 \times 4 + 1 & \implies i^{17} = i, \\ 23 = 4 \times 5 + 3 & \implies i^{23} = -i, \\ 6 = 4 \times 1 + 2 & \implies i^6 = -1. \end{array}$$

Hence

$$\frac{i^{17} + i^{23}}{i^6} = \frac{i + (-i)}{-1} = \frac{0}{-1} = 0.$$

WORKED EXAMPLE 4 Using the equality of two complex numbers

Find the real numbers x and y such that $(x + 2y) + i(3x - y) = 5 + 5i$.

SOLUTION

By equality of the real and imaginary parts:

$$\begin{cases} x + 2y = 5 \\ 3x - y = 5 \end{cases}$$

From the second equation, $y = 3x - 5$. Substituting into the first: $x + 2(3x - 5) = 5$, so $7x = 15$, giving $x = \frac{15}{7}$ and $y = 3 \times \frac{15}{7} - 5 = \frac{45 - 35}{7} = \frac{10}{7}$. Check: $\frac{15}{7} + 2 \times \frac{10}{7} = \frac{35}{7} = 5$ and $3 \times \frac{15}{7} - \frac{10}{7} = \frac{35}{7} = 5$. ■

EXERCISE 1 Practice: Powers of i and Complex Forms

- Evaluate: (a) i^{2024} (b) i^{-13} (c) $i^{100} + i^{101} + i^{102} + i^{103}$.
- Write each number in the form $a + ib$ and identify $\Re(z)$ and $\Im(z)$:

(a) 5 (b) $-3i$ (c) $\sqrt{-18}$ (d) $(2+i)(1+i)$.

3. True or False? Justify.

(a) $\sqrt{-9} \cdot \sqrt{-4} = 6$.

(b) Every real number is a complex number.

(c) The imaginary part of $3 - 4i$ is $-4i$.

4. Find real numbers x and y such that $2x + iy = 4 - 3i$.

SOLUTION Exercise 1

- (a) $2024 = 4 \times 506 + 0$, remainder 0 $\Rightarrow i^{2024} = 1$. (b) $-13 = 4 \times (-4) + 3$, so $i^{-13} = i^3 = -i$. (Equivalently $i^{-13} = 1/i^{13} = 1/i = -i$, since $i \times (-i) = -i^2 = 1$.) (c) The four consecutive powers give $i^{100} = 1, i^{101} = i, i^{102} = -1, i^{103} = -i$; the sum is $1 + i - 1 - i = 0$.
- (a) $5 = 5 + 0i$: $\Re(z) = 5, \Im(z) = 0$. (b) $-3i = 0 - 3i$: $\Re(z) = 0, \Im(z) = -3$. (c) $\sqrt{-18} = i\sqrt{18} = 3\sqrt{2}i$: $\Re(z) = 0, \Im(z) = 3\sqrt{2}$. (d) $(2+i)(1+i) = 2 + 2i + i + i^2 = 1 + 3i$: $\Re(z) = 1, \Im(z) = 3$.
- (a) False: $\sqrt{-9}\sqrt{-4} = 3i \cdot 2i = 6i^2 = -6 \neq 6$. (b) True: any $a \in \mathbb{R}$ can be written $a + 0i \in \mathbb{C}$. (c) False: the imaginary part is the real number -4 , not $-4i$.
- Equating parts: $2x = 4$ and $y = -3$, so $x = 2, y = -3$.

WARNING GCE Multiple-Choice Trap

In a multiple-choice question you may be asked: “What is i^{2025} ?” with options $i, -1, -i, 1$. The quick method: $2025 = 4 \times 506 + 1$, so the answer is i . Never attempt to multiply i by itself 2025 times! Also remember: the imaginary part of $a + ib$ is the real number b , not ib .

DID YOU KNOW? Complex Numbers in Cameroon's Technology

The mobile phone networks that connect Yaoundé, Douala, Bamenda and Buea rely on complex numbers for signal modulation, error-correcting codes and antenna design. Alternating current, such as that distributed by ENEO, is analysed using phasors — complex numbers representing amplitude and phase. Medical imaging techniques such as MRI use complex Fourier transforms to reconstruct images. The “imaginary” unit i is therefore very real in everyday Cameroonian life!

2 ALGEBRA OF COMPLEX NUMBERS AND THE CONJUGATE

In the previous section, we discovered how the need to solve equations like $x^2 + 1 = 0$ led mathematicians to introduce the **imaginary unit** i , defined by $i^2 = -1$. We saw that every complex number can be written uniquely in the **standard (or Cartesian) form** $z = a + ib$, where $a, b \in \mathbb{R}$. Now we must learn how to calculate with these numbers: add, subtract, multiply, divide, and manipulate their conjugates. These algebraic skills are the bedrock of every later topic — polar form, De Moivre's theorem, loci, and the solution of polynomial equations in $\mathbb{C}$. Master them now, and the rest of the chapter will flow naturally.

2.1 Addition and Subtraction of Complex Numbers

Adding or subtracting complex numbers is completely analogous to adding vectors in the plane: we simply combine the real parts and the imaginary parts separately.

DEFINITION Addition and Subtraction in $\mathbb{C}$

Let $z_1 = a + ib$ and $z_2 = c + id$ with $a, b, c, d \in \mathbb{R}$. Then

$$z_1 \pm z_2 = (a \pm c) + i(b \pm d).$$

EXAMPLE Addition and Subtraction

Let $z_1 = 3 + 4i$ and $z_2 = -2 + 7i$. Compute $z_1 + z_2$ and $z_1 - z_2$.

$$z_1 + z_2 = (3 + (-2)) + i(4 + 7) = 1 + 11i,$$

$$z_1 - z_2 = (3 - (-2)) + i(4 - 7) = 5 - 3i.$$

KEY POINTS Key Point

The set $\mathbb{C}$ is closed under addition and subtraction: the sum or difference of two complex numbers is always a complex number. The operations are commutative and associative, just as in $\mathbb{R}$.

2.2 Multiplication of Complex Numbers

Multiplication uses the distributive law (FOIL) together with the defining rule $i^2 = -1$.

DEFINITION Multiplication in $\mathbb{C}$

For $z_1 = a + ib$ and $z_2 = c + id$,

$$z_1 z_2 = (a + ib)(c + id) = ac + iad + ibc + i^2 bd = (ac - bd) + i(ad + bc).$$

EXAMPLE Multiplication

Multiply $(2 + 3i)$ by $(4 - i)$.

$$\begin{aligned}(2 + 3i)(4 - i) &= 2 \cdot 4 + 2(-i) + 3i \cdot 4 + 3i(-i) \\ &= 8 - 2i + 12i - 3i^2 \\ &= 8 + 10i - 3(-1) \\ &= 11 + 10i.\end{aligned}$$

WARNING Classic Trap: Squaring a Complex Number


Many students write $(a + ib)^2 = a^2 + b^2$. This is false! The correct expansion is

$$(a + ib)^2 = a^2 + 2iab + i^2 b^2 = (a^2 - b^2) + 2iab.$$

For example, $(2 + 3i)^2 = 4 + 12i + 9i^2 = -5 + 12i$, not $4 + 9 = 13$.

2.3 The Complex Conjugate

The **complex conjugate** is a simple but extraordinarily powerful operation: it reflects a complex number across the real axis.



The conjugate $\bar{z}$ is the mirror image of z in the real axis.

DEFINITION Complex Conjugate

For $z = a + ib$ ($a, b \in \mathbb{R}$), the **complex conjugate** of z is

$$\bar{z} = a - ib.$$

On the Argand diagram, $\bar{z}$ is the reflection of z across the real axis.

PROPERTY Fundamental Identity: $z\bar{z}$ is Real and Non-Negative

$$z\bar{z} = (a + ib)(a - ib) = a^2 - i^2b^2 = a^2 + b^2 \in \mathbb{R}_{\geq 0}.$$

This product is exactly the square of the modulus of z (denoted $|z|^2$), which we will study in Section 4. Proof is examinable.

EXAMPLE Conjugates

Find $\bar{z}$ for each z :

1. $z = 5 - 2i \Rightarrow \bar{z} = 5 + 2i$
2. $z = -3 \Rightarrow \bar{z} = -3$ (real numbers are self-conjugate)

$$3. z = 4i \Rightarrow \bar{z} = -4i \text{ (purely imaginary numbers change sign)}$$

2.4 Division of Complex Numbers

Division is the only operation that does not immediately yield the standard form $a + ib$. The trick — standard in GCE examinations — is to multiply numerator and denominator by the conjugate of the denominator, turning the denominator into a real number.

METHOD Division Algorithm: $\frac{z_1}{z_2}$ in Standard Form

Let $z_1 = a + ib, z_2 = c + id$ ($z_2 \neq 0$).


1. Write the quotient as a fraction: $\frac{a + ib}{c + id}$.
2. Multiply numerator and denominator by $\bar{z}_2 = c - id$:

$$\frac{a + ib}{c + id} \cdot \frac{c - id}{c - id}$$

3. Expand the numerator using FOIL; the denominator becomes $c^2 + d^2$ (a real number) because $(c + id)(c - id) = c^2 + d^2$.

4. Separate the real and imaginary parts:

$$\frac{(ac + bd) + i(bc - ad)}{c^2 + d^2} = \frac{ac + bd}{c^2 + d^2} + i \frac{bc - ad}{c^2 + d^2}$$

**EXAMPLE** Division

Express $\frac{3+4i}{1-2i}$ in the form $a+ib$.

$$\begin{aligned}\frac{3+4i}{1-2i} &= \frac{3+4i}{1-2i} \cdot \frac{1+2i}{1+2i} \\ &= \frac{(3+4i)(1+2i)}{1^2+2^2} \\ &= \frac{3+6i+4i+8i^2}{5} \\ &= \frac{3+10i-8}{5} \\ &= \frac{-5+10i}{5} \\ &= -1+2i.\end{aligned}$$

WORKED EXAMPLE 5 GCE-Style Division

Simplify $\frac{(2-i)^2}{3+i}$ and express the result in the form $a+ib$.

SOLUTION

Solution. First compute the numerator:

$$(2-i)^2 = 4 - 4i + i^2 = 3 - 4i.$$

Now divide:

$$\frac{3-4i}{3+i} = \frac{3-4i}{3+i} \cdot \frac{3-i}{3-i} = \frac{(3-4i)(3-i)}{9+1} = \frac{9-3i-12i+4i^2}{10} = \frac{9-15i-4}{10} = \frac{5-15i}{10} = \frac{1}{2} - \frac{3}{2}i.$$

Answer: $\frac{1}{2} - \frac{3}{2}i$.

2.5 Properties of Complex Conjugates

The conjugate operation interacts beautifully with all algebraic operations. These properties are frequently tested in multiple-choice and short-answer GCE questions.

PROPERTY Algebraic Properties of the Conjugate

For all $z_1, z_2 \in \mathbb{C}$:

$$1. \overline{z_1 \pm z_2} = \bar{z}_1 \pm \bar{z}_2$$

$$2. \overline{z_1 z_2} = \bar{z}_1 \bar{z}_2$$

$$3. \overline{\left(\frac{z_1}{z_2}\right)} = \frac{\bar{z}_1}{\bar{z}_2} \quad (z_2 \neq 0)$$

$$4. \bar{\bar{z}} = z \text{ (involution)}$$

$$5. z + \bar{z} = 2\operatorname{Re}(z) \quad \text{and} \quad z - \bar{z} = 2i\operatorname{Im}(z)$$

$$6. z \in \mathbb{R} \iff z = \bar{z}$$

$$7. z \text{ is purely imaginary} \iff z = -\bar{z}$$

Proofs of (1)–(3) are straightforward using Cartesian forms and are examinable.

EXAMPLE Using Conjugate Properties

Let $z_1 = 2 + 3i$, $z_2 = 1 - i$. Verify $\overline{z_1 z_2} = \bar{z}_1 \bar{z}_2$.

$$z_1 z_2 = (2 + 3i)(1 - i) = 2 - 2i + 3i - 3i^2 = 5 + i$$

$$\overline{z_1 z_2} = 5 - i.$$

$$\bar{z}_1 \bar{z}_2 = (2 - 3i)(1 + i) = 2 + 2i - 3i - 3i^2 = 5 - i. \quad \checkmark$$

KEY POINTS Quick Extraction of Real and Imaginary Parts

From $z + \bar{z} = 2\operatorname{Re}(z)$ and $z - \bar{z} = 2i\operatorname{Im}(z)$, we obtain

$$\operatorname{Re}(z) = \frac{z + \bar{z}}{2}, \quad \operatorname{Im}(z) = \frac{z - \bar{z}}{2i}.$$

These formulas are extremely useful when z is given in polar or exponential form (Sections 5 and 6).

2.6 Simplification of Expressions (GCE-Style Drill)

GCE papers often ask you to simplify expressions that mix products, quotients, powers, and conjugates. The golden rule: **always convert everything to standard form $a + ib$ at the end.**

WORKED EXAMPLE 6 Mixed Expression

Simplify $\frac{(1 + 2i)(3 - i)}{(2 + i)^2}$ and write the result as $a + ib$.

SOLUTION

Step 1: Simplify the numerator using conjugate properties.

$$\overline{(1+2i)(3-i)} = \overline{1+2i} \overline{3-i} = (1-2i)(3+i).$$

Compute:

$$(1-2i)(3+i) = 3+i-6i-2i^2 = 3-5i+2 = 5-5i.$$

Step 2: Simplify the denominator.

$$(2+i)^2 = 4+4i+i^2 = 3+4i.$$

Step 3: Divide.

$$\frac{5-5i}{3+4i} = \frac{5-5i}{3+4i} \cdot \frac{3-4i}{3-4i} = \frac{15-20i-15i+20i^2}{9+16} = \frac{15-35i-20}{25} = \frac{-5-35i}{25} = -\frac{1}{5} - \frac{7}{5}i.$$

Answer: $-\frac{1}{5} - \frac{7}{5}i.$

WARNING Common Mistakes in Mixed Expressions

- Conjugating only part of a product: $\overline{z_1 z_2} \neq z_1 \bar{z}_2$. You must conjugate each factor: $\overline{z_1 z_2} = \bar{z}_1 \bar{z}_2$.
- Forgetting to rationalise the final denominator: Even if you used conjugate properties correctly, the final answer must be in the form $a + ib$ with $a, b \in \mathbb{R}$.
- Sign errors when expanding $(c+id)(c-id)$: Remember $(c+id)(c-id) = c^2 + d^2$, not $c^2 - d^2$.

2.7 Consolidation Exercises**EXERCISE 2** Exercise 2.1

Express each of the following in the form $a + ib$ ($a, b \in \mathbb{R}$):

1. $(3-2i) + (-1+5i)$

2. $(4+i)(2-3i)$

3. $\frac{2+3i}{1-i}$

4. $\frac{(1+i)^2}{2-i}$

5. $\overline{(2-i)(3+4i)}$

6. $\overline{\frac{3-4i}{1+2i}}$

7. $\frac{1}{2+3i} + \frac{1}{2-3i}$

8. $(1+i)^4$ (Hint: square twice)

SOLUTION Exercise 2.1

1. $2+3i$

2. $11-10i$

3. $-\frac{1}{2} + \frac{5}{2}i$

4. $-\frac{2}{5} + \frac{4}{5}i$

5. $10-5i$

6. $\frac{11}{5} - \frac{2}{5}i$

7. $\frac{4}{13}$ (real)

8. -4

EXERCISE 3 Exercise 2.2 — GCE Style

Given that $z = x + iy$ satisfies $\frac{z}{z^*} = 3 + 4i$, where z^* denotes the conjugate of z , find the ratio $x : y$.

SOLUTION Exercise 2.2

Let $z = x + iy$, then $z^* = x - iy$.

$$\frac{x+iy}{x-iy} = 3+4i \implies x+iy = (3+4i)(x-iy) = 3x-3iy+4ix-4i^2y = (3x+4y) + i(4x-3y).$$

Equate real and imaginary parts:

$$x = 3x + 4y \implies -2x = 4y \implies x = -2y,$$

$$y = 4x - 3y \implies 4y = 4x \implies x = y.$$

The only solution to both is $x = y = 0$, but $z \neq 0$ for the quotient to be defined. Re-check: The second equation gives $y = 4x - 3y \Rightarrow 4y = 4x \Rightarrow x = y$. Combined with $x = -2y$, we get $y = -2y \Rightarrow 3y = 0 \Rightarrow y = 0$, contradiction. Wait — there is no non-zero z satisfying this equation! Let's verify: $\left| \frac{z}{z^*} \right| = \frac{|z|}{|z^*|} = 1$, but $|3 + 4i| = 5 \neq 1$. Hence no such complex number exists. This is a classic GCE trap: always check the modulus first!

DID YOU KNOW? Historical Note

The symbol $\bar{z}$ for the conjugate was introduced by Cauchy in 1821. Earlier, Gauss used the notation z' and called it the norm of z (what we now call the modulus squared). The geometric interpretation as reflection in the real axis is due to Argand (1806) and Wessel (1799), whose work was largely ignored until the 1830s. In Cameroon's GCE examinations, both $\bar{z}$ and z^* are accepted notations for the conjugate — be comfortable with both.

KEY POINTS Summary of Section 2

- Addition/Subtraction: combine real and imaginary parts separately.
- Multiplication: use FOIL and $i^2 = -1$; $(a + ib)(c + id) = (ac - bd) + i(ad + bc)$.
- Conjugate: $\overline{a + ib} = a - ib$; geometric reflection in the real axis.
- Key identity: $z\bar{z} = a^2 + b^2 = |z|^2 \in \mathbb{R}_{\geq 0}$.
- Division: multiply numerator and denominator by the conjugate of the denominator.
- Conjugate properties: linear over $+$, $-$, $\times$, $\div$; $\bar{\bar{z}} = z$; $z + \bar{z} = 2\operatorname{Re}(z)$, $z - \bar{z} = 2i\operatorname{Im}(z)$.
- Always give final answers in standard form $a + ib$.

3 EQUATIONS AND ROOTS IN $\mathbb{C}$

In the previous section we learned to add, multiply and divide complex numbers, and we discovered the **complex conjugate** $\bar{z}$, which behaves beautifully under all four operations. We now put this algebra to work. The whole reason complex numbers were invented was to solve equations: the equation $x^2 + 1 = 0$ has no solution in $\mathbb{R}$, but it has two solutions in $\mathbb{C}$. In this section we learn to solve linear and quadratic equations in $\mathbb{C}$, and we prove one of the most elegant theorems of the GCE syllabus: for polynomials with real coefficients, complex roots always come in **conjugate pairs**.

3.1 The Idea of a Root of a Complex Number (Lesson 29)

DEFINITION Root of a complex number

Let w be a complex number and n a positive integer. An **n th root** of w is any complex number z such that

$$z^n = w.$$

In particular, a square root of w is a solution of $z^2 = w$.

In $\mathbb{R}$, a negative number has no square root. In $\mathbb{C}$ the situation is transformed: **every** non-zero complex number has exactly two square roots, three cube roots, and in general n distinct n th roots. For example, the equation $z^2 = -9$ has the two solutions $z = 3i$ and $z = -3i$, since $(\pm 3i)^2 = 9i^2 = -9$.

EXAMPLE First encounter with square roots in $\mathbb{C}$

Solve $z^2 = -16$. We seek z with $z^2 = -16 = 16i^2$, so $z^2 - (4i)^2 = 0$, i.e. $(z - 4i)(z + 4i) = 0$. Hence $z = 4i$ or $z = -4i$. Notice the two roots are opposites of each other.

Finding the square roots of a general complex number such as $3 + 4i$ requires a method (solving for the real and imaginary parts, or using the polar form); we develop it fully in the lessons on the square root of a complex number and on n th roots. For now, keep the concept in mind: solving $z^2 = w$ is always possible in $\mathbb{C}$.

3.2 Linear Equations with Complex Coefficients (Lesson 30)

A linear equation $az + b = 0$ with $a, b \in \mathbb{C}$, $a \neq 0$, is solved exactly as in $\mathbb{R}$: isolate z and divide, using the conjugate technique of Lesson 27.

WORKED EXAMPLE 7 A linear equation in $\mathbb{C}$

Solve $(2 + i)z + 3 - i = 0$, giving the answer in the form $x + iy$.

SOLUTION

Solution. $z = \frac{-(3 - i)}{2 + i} = \frac{-3 + i}{2 + i}$. Multiply numerator and denominator by the conjugate of the denominator:

$$z = \frac{(-3 + i)(2 - i)}{(2 + i)(2 - i)} = \frac{-6 + 3i + 2i - i^2}{4 + 1} = \frac{-5 + 5i}{5} = -1 + i.$$

Check: $(2 + i)(-1 + i) + 3 - i = (-2 + 2i - i + i^2) + 3 - i = (-3 + i) + 3 - i = 0$. ✓

The key point: in $\mathbb{C}$ a linear equation $az + b = 0$ ($a \neq 0$) always has exactly one solution, $z = -b/a$,

because division by any non-zero complex number is always possible.

3.3 Quadratic Equations with Real Coefficients

Consider $az^2 + bz + c = 0$ with $a, b, c \in \mathbb{R}$, $a \neq 0$, and discriminant $\Delta = b^2 - 4ac$. Completing the square (valid in $\mathbb{C}$, since only the four operations are used) gives

$$a\left(z + \frac{b}{2a}\right)^2 = \frac{b^2 - 4ac}{4a} = \frac{\Delta}{4a} \quad \Longleftrightarrow \quad \left(z + \frac{b}{2a}\right)^2 = \frac{\Delta}{4a^2}.$$

Everything now depends on the sign of Δ .

METHOD Solving $az^2 + bz + c = 0$ with real coefficients

1. Compute $\Delta = b^2 - 4ac$.
2. If $\Delta > 0$: two distinct real roots $z = \frac{-b \pm \sqrt{\Delta}}{2a}$.
3. If $\Delta = 0$: one (double) real root $z = -\frac{b}{2a}$.
4. If $\Delta < 0$: write $\sqrt{\Delta} = i\sqrt{|\Delta|}$ and apply the usual formula:

$$z = \frac{-b \pm i\sqrt{|\Delta|}}{2a},$$

giving two conjugate complex roots.

WARNING A negative discriminant is not the end of the story

In Lower Sixth you learned that $\Delta < 0$ means “no real solution”. In $\mathbb{C}$ this becomes: two conjugate complex solutions. Never write “no solution” at Advanced Level — write “no real solution; the complex solutions are ...”.

WORKED EXAMPLE 8 Solving $z^2 - 2z + 5 = 0$


Solve $z^2 - 2z + 5 = 0$ in $\mathbb{C}$.

SOLUTION

Solution. $\Delta = (-2)^2 - 4(1)(5) = 4 - 20 = -16 < 0$. Hence $\sqrt{\Delta} = i\sqrt{16} = 4i$ and

$$z = \frac{2 \pm 4i}{2} = 1 \pm 2i.$$

The roots are $z_1 = 1 + 2i$ and $z_2 = 1 - 2i = \overline{z_1}$: a conjugate pair, as promised. Check: $(1 + 2i)^2 - 2(1 + 2i) + 5 = (1 + 4i - 4) - 2 - 4i + 5 = 0$. ✓



The roots of $z^2 - 2z + 5 = 0$ plotted on an Argand diagram: they are reflections of each other in the real axis — the geometric meaning of conjugation.

3.4 The Conjugate Root Theorem

Why did the roots above come out as conjugates? It is not a coincidence.

PROPERTY Conjugate Root Theorem — proof examinable

Let $P(z) = a_n z^n + a_{n-1} z^{n-1} + \dots + a_1 z + a_0$ be a polynomial with real coefficients. If $\alpha \in \mathbb{C}$ satisfies $P(\alpha) = 0$, then $P(\bar{\alpha}) = 0$. In words: complex roots of a real polynomial occur in conjugate pairs.

Proof. Suppose $P(\alpha) = 0$, i.e. $a_n \alpha^n + \dots + a_1 \alpha + a_0 = 0$. Take the conjugate of both sides and use the properties of Lesson 28 ($\overline{u+v} = \bar{u} + \bar{v}$, $\overline{uv} = \bar{u} \bar{v}$, hence $\overline{\alpha^k} = \bar{\alpha}^k$):

$$\overline{a_n \alpha^n + \dots + a_1 \alpha + a_0} = \bar{0} \implies \bar{a}_n \bar{\alpha}^n + \dots + \bar{a}_1 \bar{\alpha} + \bar{a}_0 = 0.$$

Since each coefficient a_k is real, $\bar{a}_k = a_k$, so

$$a_n \bar{\alpha}^n + a_{n-1} \bar{\alpha}^{n-1} + \dots + a_1 \bar{\alpha} + a_0 = 0,$$

which says exactly $P(\bar{\alpha}) = 0$. ■

WARNING The hypothesis “real coefficients” is essential

When the coefficients are complex, the theorem fails: the roots of a quadratic with complex coefficients are generally not conjugates of each other. For example $z^2 - (3 + i)z + (2 + 2i) = 0$ has roots 2 and $1 + i$ (check!), which are not conjugates.

DID YOU KNOW? The Fundamental Theorem of Algebra

The Conjugate Root Theorem is a first taste of a deeper result, the Fundamental Theorem of Algebra (first proved rigorously by Gauss around 1799): every polynomial of degree n with complex coefficients has exactly n roots in $\mathbb{C}$, counted with multiplicity. This is why $\mathbb{C}$ is called algebraically closed — in $\mathbb{C}$, no polynomial equation is ever “impossible”.

3.5 Quadratic Equations with Complex Coefficients

The quadratic formula $z = \frac{-b \pm \sqrt{\Delta}}{2a}$ remains valid when $a, b, c \in \mathbb{C}$ — completing the square used only field operations. The new difficulty is computing $\sqrt{\Delta}$ when Δ is itself complex. For GCE purposes, $\sqrt{\Delta}$ is found by inspection (recognising a perfect square) or by the square-root method of Lesson 32.

WORKED EXAMPLE 9 A quadratic with complex coefficients

Solve $z^2 - (3 + i)z + (2 + 2i) = 0$.

SOLUTION

Solution. Compute the discriminant, expanding $(3 + i)^2$ in full:

$$\Delta = (3 + i)^2 - 4(2 + 2i) = (9 + 6i + i^2) - 8 - 8i = (8 + 6i) - 8 - 8i = -2i.$$

We need $\sqrt{-2i}$. By inspection, $(1 - i)^2 = 1 - 2i + i^2 = -2i$ ✓, so $\sqrt{\Delta} = \pm(1 - i)$. Then

$$z = \frac{(3 + i) \pm (1 - i)}{2} \implies z_1 = \frac{3 + i + 1 - i}{2} = \frac{4}{2} = 2, \quad z_2 = \frac{3 + i - 1 + i}{2} = \frac{2 + 2i}{2} = 1 + i.$$

Check: sum of roots $= 2 + (1 + i) = 3 + i = -b/a$ ✓; product $= 2(1 + i) = 2 + 2i = c/a$ ✓. Note the roots are not conjugates — the coefficients are not real, so the Conjugate Root Theorem does not apply.

WARNING Careful arithmetic with Δ

Most errors in this topic come from expanding $(p+qi)^2$ incorrectly. Remember $(p+qi)^2 = p^2 - q^2 + 2pqi$: the cross term carries the i , and $i^2 = -1$ flips the sign of q^2 . Write the expansion in full before simplifying, and always verify your candidate square root by squaring it again.

3.6 Factorisation, Sum and Product of Roots**PROPERTY** Factorisation and Vieta's relations in $\mathbb{C}$

Every quadratic $az^2 + bz + c$ ($a \neq 0$, coefficients real or complex) splits over $\mathbb{C}$ as

$$az^2 + bz + c = a(z - z_1)(z - z_2),$$

where z_1, z_2 are its roots. Expanding and comparing coefficients gives the **sum and product of roots**:

$$z_1 + z_2 = -\frac{b}{a}, \quad z_1 z_2 = \frac{c}{a}.$$

These relations remain valid in $\mathbb{C}$.

Indeed $a(z - z_1)(z - z_2) = az^2 - a(z_1 + z_2)z + az_1 z_2$, and matching with $az^2 + bz + c$ yields both formulas. For a real quadratic with $\Delta < 0$, the conjugate pair $z_1 = p + qi$, $z_2 = p - qi$ gives the nice real values $z_1 + z_2 = 2p$ and $z_1 z_2 = p^2 + q^2 = |z_1|^2$.

EXAMPLE Using sum and product

The roots of $z^2 - 2z + 5 = 0$ are $1 \pm 2i$: sum = $2 = -(-2)/1$ ✓, product = $(1 + 2i)(1 - 2i) = 1 + 4 = 5$ ✓. Conversely, a quadratic with roots $3i$ and $-3i$ is $z^2 - (0)z + (3i)(-3i) = z^2 + 9 = 0$.

METHOD “Show that α is a root, hence factorise completely” (GCE favourite)

Given a real polynomial P and a complex number α :

1. Verify $P(\alpha) = 0$ by direct substitution (compute powers of α carefully).
2. Conjugate Root Theorem: since the coefficients are real, $\bar{\alpha}$ is also a root.
3. Build the quadratic factor $(z - \alpha)(z - \bar{\alpha}) = z^2 - 2 \operatorname{Re}(\alpha)z + |\alpha|^2$, which has real coefficients.
4. Divide P by this quadratic (long division or inspection) to obtain the remaining factor, then solve it.

WORKED EXAMPLE 10 Exam-style: factorising a cubic over $\mathbb{C}$

Let $P(z) = z^3 - z^2 + 3z + 5$. Show that $1 + 2i$ is a root of P , and hence factorise P completely over $\mathbb{C}$.

SOLUTION

Solution. Step 1: compute powers: $(1 + 2i)^2 = 1 + 4i - 4 = -3 + 4i$; $(1 + 2i)^3 = (1 + 2i)(-3 + 4i) = -3 + 4i - 6i + 8i^2 = -11 - 2i$. Then

$$P(1 + 2i) = (-11 - 2i) - (-3 + 4i) + 3(1 + 2i) + 5 = -11 - 2i + 3 - 4i + 3 + 6i + 5 = 0. \checkmark$$


Step 2: coefficients are real, so $1 - 2i$ is also a root.

Step 3: $(z - 1 - 2i)(z - 1 + 2i) = (z - 1)^2 + 4 = z^2 - 2z + 5$.

Step 4: divide: $z^3 - z^2 + 3z + 5 = (z^2 - 2z + 5)(z + 1)$ (check: $(z^2 - 2z + 5)(z + 1) = z^3 - z^2 + 3z + 5$ $\checkmark$). Hence

$$P(z) = (z + 1)(z - (1 + 2i))(z - (1 - 2i)),$$

with roots $-1, 1 + 2i, 1 - 2i$.



Decision tree for solving $az^2 + bz + c = 0$ with real coefficients, according to the sign of the discriminant.

3.7 Consolidation Exercises

EXERCISE 4 Quadratics in $\mathbb{C}$

Solve in $\mathbb{C}$: (a) $z^2 + 4z + 13 = 0$; (b) $2z^2 - 2z + 1 = 0$; (c) $z^2 - (5 + i)z + (8 + i) = 0$ (find $\sqrt{\Delta}$ by inspection).

SOLUTION Exercise 1

(a) $\Delta = 16 - 52 = -36$, $\sqrt{\Delta} = 6i$: $z = \frac{-4 \pm 6i}{2} = -2 \pm 3i$. (b) $\Delta = 4 - 8 = -4$, $\sqrt{\Delta} = 2i$: $z = \frac{2 \pm 2i}{4} = \frac{1 \pm i}{2}$.
 (c) $\Delta = (5 + i)^2 - 4(8 + i) = (24 + 10i) - (32 + 4i) = -8 + 6i$. Inspection: $(1 + 3i)^2 = 1 + 6i - 9 = -8 + 6i$
 ✓. Hence $z = \frac{(5 + i) \pm (1 + 3i)}{2}$, giving $z_1 = 3 + 2i$, $z_2 = 2 - i$.

EXERCISE 5 Factorising over $\mathbb{C}$

Show that $2 + i$ is a root of $P(z) = z^3 - 3z^2 + z + 5$, and factorise P completely over $\mathbb{C}$.

SOLUTION Exercise 2

$(2 + i)^2 = 3 + 4i$; $(2 + i)^3 = (2 + i)(3 + 4i) = 2 + 11i$. Then $P(2 + i) = (2 + 11i) - 3(3 + 4i) + (2 + i) + 5 = 2 + 11i - 9 - 12i + 2 + i + 5 = 0$ ✓. Real coefficients $\Rightarrow 2 - i$ is a root. Quadratic factor: $(z - 2 - i)(z - 2 + i) = (z - 2)^2 + 1 = z^2 - 4z + 5$. Division: $P(z) = (z^2 - 4z + 5)(z + 1)$. Complete factorisation: $P(z) = (z + 1)(z - (2 + i))(z - (2 - i))$.

KEY POINTS Key points of this section

- Every non-zero complex number has square roots in $\mathbb{C}$: solving $z^2 = w$ is always possible.
- A linear equation $az + b = 0$ ($a \neq 0$) has the unique solution $z = -b/a$; divide using the conjugate.
- Real quadratic with $\Delta < 0$: two conjugate roots $z = \frac{-b \pm i\sqrt{|\Delta|}}{2a}$ — never “no solution”.
- Conjugate Root Theorem: real-coefficient polynomials have their non-real roots in conjugate pairs (proof examinable).
- Complex coefficients: the quadratic formula still works, but $\sqrt{\Delta}$ must be found in $\mathbb{C}$, and the roots are generally not conjugates.

- $az^2 + bz + c = a(z - z_1)(z - z_2)$ with $z_1 + z_2 = -b/a$, $z_1 z_2 = c/a$ — valid in $\mathbb{C}$.
- GCE technique: verify $P(\alpha) = 0$, deduce $\bar{\alpha}$, form the real quadratic factor, divide, finish.

4 THE ARGAND DIAGRAM, MODULUS AND ARGUMENT

In the previous section we learned how to solve quadratic equations in $\mathbb{C}$ and how to manipulate complex numbers algebraically. We now turn to a geometric viewpoint that will transform our understanding of complex numbers. By representing a complex number as a point or a vector in a plane, concepts like modulus and argument acquire a vivid visual meaning, and operations like multiplication and division become simple geometric transformations. This geometric representation, known as the **Argand diagram**, is the gateway to the polar and exponential forms that will simplify powers and roots enormously.

4.1 The Argand Diagram: Geometric Representation


A complex number $z = a + ib$ is completely determined by the ordered pair of real numbers (a, b) . It is therefore natural to associate z with a point M in a Cartesian coordinate system.

DEFINITION The Argand Diagram

The **Argand diagram** (or complex plane) is a Cartesian plane where:

- The horizontal axis (x -axis) is called the real axis and represents the real part $\operatorname{Re}(z) = a$.
- The vertical axis (y -axis) is called the imaginary axis and represents the imaginary part $\operatorname{Im}(z) = b$.

The complex number $z = a + ib$ is represented by the point $M(a, b)$ or by the position vector $\vec{OM}$.



The Argand diagram: $z = a + ib$ corresponds to point $M(a, b)$ or vector $\vec{OM}$.

KEY POINTS Key Geometric Correspondences

- $z = 0$ corresponds to the origin O .
- Real numbers ($b = 0$) lie on the real axis.
- Pure imaginary numbers ($a = 0$) lie on the imaginary axis.
- The complex conjugate $\bar{z} = a - ib$ is the reflection of M across the real axis.
- The opposite $-z = -a - ib$ is the point symmetric to M with respect to the origin (central symmetry).

DID YOU KNOW? Historical Note

The geometric representation of complex numbers was independently proposed by the Norwegian surveyor Caspar Wessel (1797), the Swiss mathematician Jean-Robert Argand (1806), and the French mathematician Adrien-Quentin Buée (1806). It was later popularised by Gauss, who coined the term “complex number” and established the notation i for $\sqrt{-1}$. This geometric insight turned complex numbers from an algebraic curiosity into a fundamental tool for analysis and physics.

4.2 The Modulus of a Complex Number

The distance from the origin O to the point $M(a, b)$ is a fundamental quantity.

DEFINITION Modulus

The **modulus** (or absolute value) of a complex number $z = a + ib$ is the length of the vector $\vec{OM}$ or the distance OM . It is denoted by $|z|$ and defined by:

$$|z| = \sqrt{a^2 + b^2}.$$

PROPERTY Properties of the Modulus

For any complex numbers z, z_1, z_2 :

1. $|z| \geq 0$, and $|z| = 0 \iff z = 0$.
2. $|z| = |\bar{z}| = |-z|$.
3. Multiplicative property: $|z_1 z_2| = |z_1| |z_2|$.
4. Quotient property: $\left| \frac{z_1}{z_2} \right| = \frac{|z_1|}{|z_2|}$ (for $z_2 \neq 0$).
5. Triangle inequality: $|z_1 + z_2| \leq |z_1| + |z_2|$.

EXAMPLE Computing Moduli

Find the modulus of $z_1 = 3 + 4i$, $z_2 = -5i$, and $z_3 = \frac{1+i}{1-i}$.

$$|z_1| = \sqrt{3^2 + 4^2} = \sqrt{25} = 5.$$

$$|z_2| = \sqrt{0^2 + (-5)^2} = 5.$$

$$|z_3| = \frac{|1+i|}{|1-i|} = \frac{\sqrt{1^2 + 1^2}}{\sqrt{1^2 + (-1)^2}} = \frac{\sqrt{2}}{\sqrt{2}} = 1.$$

4.3 The Argument of a Complex Number

While the modulus tells us how far the point is from the origin, the argument tells us in which direction.

DEFINITION Argument

Let $z = a + ib \neq 0$. An **argument** of z , denoted $\arg(z)$, is any real number θ such that:

$$\cos \theta = \frac{a}{|z|}, \quad \sin \theta = \frac{b}{|z|}.$$

Geometrically, θ is the oriented angle $(\vec{Ox}, \vec{OM})$, measured in radians, positive in the anti-clockwise direction.

Since adding 2π to an angle does not change its cosine and sine, the argument is defined modulo 2π : if θ is an argument, then $\theta + 2k\pi$ ($k \in \mathbb{Z}$) are also arguments. To have a unique value, we define the **principal argument**.

DEFINITION Principal Argument

The **principal argument** of $z \neq 0$, denoted $\text{Arg}(z)$ (capital A), is the unique argument θ satisfying:

$$-\pi < \theta \leq \pi.$$

WARNING Important Warnings

- Argument of zero is undefined. Never write $\arg(0)$ or $\text{Arg}(0)$; the point O has no well-defined direction.
- $\tan \theta = \frac{b}{a}$ is not enough. The equation $\tan \theta = \frac{b}{a}$ has two solutions in $(-\pi, \pi]$ differing by π . You must check the quadrant of the point $M(a, b)$ to choose the correct one.

4.4 Finding the Principal Argument: Quadrant by Quadrant

Let $z = a + ib \neq 0$ and $\alpha = \arctan \left| \frac{b}{a} \right| \in \left[0, \frac{\pi}{2} \right)$ (the acute angle with the real axis). The principal argument $\text{Arg}(z)$ depends on the signs of a and b :

Quadrant	Signs of (a, b)	$\tan \theta = b/a$	$\text{Arg}(z)$
I	$a > 0, b > 0$	> 0	$\alpha = \arctan(b/a)$
II	$a < 0, b > 0$	< 0	$\pi - \alpha = \pi - \arctan(b/a)$
III	$a < 0, b < 0$	> 0	$-\pi + \alpha = -\pi + \arctan(b/a)$
IV	$a > 0, b < 0$	< 0	$-\alpha = -\arctan(b/a)$

Determining the principal argument according to the quadrant of $M(a, b)$.

EXAMPLE Finding Principal ArgumentsFind $\text{Arg}(z)$ for:

1. $z_1 = 1 + i\sqrt{3}$: $a > 0, b > 0$ (QI). $\alpha = \arctan(\sqrt{3}/1) = \pi/3$. $\text{Arg}(z_1) = \pi/3$.
2. $z_2 = -2 + 2i$: $a < 0, b > 0$ (QII). $\alpha = \arctan(2/2) = \pi/4$. $\text{Arg}(z_2) = \pi - \pi/4 = 3\pi/4$.
3. $z_3 = -1 - i\sqrt{3}$: $a < 0, b < 0$ (QIII). $\alpha = \arctan(\sqrt{3}) = \pi/3$. $\text{Arg}(z_3) = -\pi + \pi/3 = -2\pi/3$.
4. $z_4 = 3 - 3i$: $a > 0, b < 0$ (QIV). $\alpha = \arctan(1) = \pi/4$. $\text{Arg}(z_4) = -\pi/4$.
5. $z_5 = -5$: Negative real axis. $\text{Arg}(z_5) = \pi$.
6. $z_6 = 4i$: Positive imaginary axis. $\text{Arg}(z_6) = \pi/2$.

PROPERTY Properties of the ArgumentFor $z, z_1, z_2 \neq 0$:

1. $\arg(\bar{z}) = -\arg(z) \pmod{2\pi}$.
2. $\arg(-z) = \arg(z) + \pi \pmod{2\pi}$.
3. Product: $\arg(z_1 z_2) = \arg(z_1) + \arg(z_2) \pmod{2\pi}$.
4. Quotient: $\arg\left(\frac{z_1}{z_2}\right) = \arg(z_1) - \arg(z_2) \pmod{2\pi}$.
5. Power: $\arg(z^n) = n \arg(z) \pmod{2\pi}$.

Note: For the principal argument, these equalities hold modulo 2π ; one may need to add or subtract 2π to bring the result back into $(-\pi, \pi]$.

4.5 Geometric Interpretation of Operations

The Argand diagram gives a beautiful geometric meaning to algebraic operations.


Addition and Subtraction: The Parallelogram Rule Let $z_1 = a_1 + ib_1$ and $z_2 = a_2 + ib_2$ be represented by points M_1, M_2 and vectors $\vec{OM}_1, \vec{OM}_2$.

$$z_1 + z_2 = (a_1 + a_2) + i(b_1 + b_2) \iff \vec{OM}_1 + \vec{OM}_2 = \vec{OM}_3$$

where M_3 is the fourth vertex of the parallelogram with vertices O, M_1, M_3, M_2 .

$$z_1 - z_2 = (a_1 - a_2) + i(b_1 - b_2) \iff \vec{OM}_1 - \vec{OM}_2 = \vec{M}_2\vec{M}_1.$$

Hence $|z_1 - z_2|$ is exactly the **distance** between the points M_1 and M_2 .



Parallelogram rule: $z_1 + z_2$ is the diagonal; $z_1 - z_2$ is the vector from M_2 to M_1 .

Conjugation and Opposite

- **Conjugate** $\bar{z}$: Reflection of $M(a, b)$ across the real axis $\rightarrow M'(a, -b)$. Modulus unchanged, argument changes sign.
- **Opposite** $-z$: Central symmetry about the origin $\rightarrow M'(-a, -b)$. Modulus unchanged, argument increased by π (or decreased by π).

4.6 Square Roots of a Complex Number (Lesson 32)

Every non-zero complex number has exactly two square roots, which are opposites of each other. To find them, we solve $(x + iy)^2 = a + ib$ with $x, y \in \mathbb{R}$.

METHOD Finding the Square Roots of $a + ib$

Given $z = a + ib \neq 0$, we seek $w = x + iy$ such that $w^2 = z$.

1. Expand: $(x + iy)^2 = (x^2 - y^2) + i(2xy) = a + ib$.

2. Equate real and imaginary parts:

$$\begin{cases} x^2 - y^2 = a & (1) \\ 2xy = b & (2) \end{cases}$$

3. Use the modulus: $|w^2| = |z| \Rightarrow (x^2 + y^2)^2 = a^2 + b^2 \Rightarrow x^2 + y^2 = \sqrt{a^2 + b^2} = |z|. \quad (3)$

4. Solve the system (1) and (3) for x^2 and y^2 :

$$x^2 = \frac{|z| + a}{2}, \quad y^2 = \frac{|z| - a}{2}.$$

5. Determine the signs of x and y using equation (2): x and y have the same sign if $b > 0$, opposite signs if $b < 0$.

6. The two square roots are $\pm(x + iy)$.

WORKED EXAMPLE 11 Square Roots of $3 + 4i$ and $7 - 24i$

Statement: Find the square roots of $3 + 4i$ and $7 - 24i$.

SOLUTION

Detailed Solution:

1. Square roots of $3 + 4i$. Here $a = 3, b = 4$. $|z| = \sqrt{3^2 + 4^2} = 5$.

$$x^2 = \frac{5+3}{2} = 4 \implies x = \pm 2, \quad y^2 = \frac{5-3}{2} = 1 \implies y = \pm 1.$$

Since $b = 4 > 0$, x and y have the same sign. The two square roots are $2 + i$ and $-2 - i$. Check:

$$(2 + i)^2 = 4 + 4i + i^2 = 3 + 4i. \equiv$$

2. Square roots of $7 - 24i$. Here $a = 7, b = -24$. $|z| = \sqrt{7^2 + (-24)^2} = \sqrt{49 + 576} = \sqrt{625} = 25$.

$$x^2 = \frac{25+7}{2} = 16 \implies x = \pm 4, \quad y^2 = \frac{25-7}{2} = 9 \implies y = \pm 3.$$

Since $b = -24 < 0$, x and y have opposite signs. The two square roots are $4 - 3i$ and $-4 + 3i$.

$$\text{Check: } (4 - 3i)^2 = 16 - 24i + 9i^2 = 7 - 24i. \equiv$$

WARNING Common Mistakes in Square Roots

- Forgetting that $x^2 + y^2 = |z|$ (not $|z|^2$).
- Taking $x = \pm\sqrt{\dots}$ and $y = \pm\sqrt{\dots}$ independently, yielding four candidates instead of two. Always use the sign of b (equation $2xy = b$) to pair the signs correctly.
- Writing $\sqrt{3 + 4i} = 2 + i$. The radical symbol $\sqrt{\cdot}$ denotes the principal square root (usually the one with non-negative real part, or argument in $(-\pi/2, \pi/2]$). It is safer to write: "The square roots of $3 + 4i$ are $2 + i$ and $-2 - i$."

4.7 Synthesis: Modulus–Argument Form

The modulus $r = |z|$ and an argument $\theta = \arg(z)$ give the **polar (trigonometric) form**:

$$z = r(\cos \theta + i \sin \theta), \quad r \geq 0, \theta \in \mathbb{R}.$$

This form makes the geometric properties of multiplication and division obvious:

$$z_1 z_2 = r_1 r_2 (\cos(\theta_1 + \theta_2) + i \sin(\theta_1 + \theta_2)), \quad \frac{z_1}{z_2} = \frac{r_1}{r_2} (\cos(\theta_1 - \theta_2) + i \sin(\theta_1 - \theta_2)).$$

We will exploit this fully in the next section with the exponential form $z = re^{i\theta}$ and De Moivre's theorem.

KEY POINTS Summary of Key Points

- Argand diagram: $z = a + ib \leftrightarrow M(a, b)$ or $\vec{OM}$.
- Modulus: $|z| = \sqrt{a^2 + b^2} = OM$. Properties: $|z_1 z_2| = |z_1| |z_2|$, $|z_1 / z_2| = |z_1| / |z_2|$, triangle inequality.
- Argument: $\arg(z)$ is the oriented angle $(\vec{Ox}, \vec{OM})$. Principal argument $\text{Arg}(z) \in (-\pi, \pi]$. Undefined for $z = 0$.
- Quadrant rule: Use signs of a, b to find $\text{Arg}(z)$ from $\alpha = \arctan |b/a|$.
- Geometry: Addition = parallelogram; $|z_1 - z_2| = M_1 M_2$; $\bar{z}$ = reflection in real axis; $-z$ = central symmetry.
- Square roots: Solve $x^2 - y^2 = a$, $2xy = b$, $x^2 + y^2 = |z|$. Two opposite roots $\pm(x + iy)$. Sign of x, y determined by sign of b .

EXERCISE 6 Practice Exercises

- Plot the following complex numbers on an Argand diagram and find their modulus and principal argument: $z_1 = -2\sqrt{3} + 2i$, $z_2 = -1 - i$, $z_3 = 4e^{i2\pi/3}$.
- Given $z_1 = 2(\cos \frac{\pi}{6} + i \sin \frac{\pi}{6})$ and $z_2 = 3(\cos \frac{-\pi}{3} + i \sin \frac{-\pi}{3})$, find the modulus and principal argument of $z_1 z_2$ and z_1 / z_2 without converting to algebraic form.
- Find the square roots of:
 - $5 + 12i$
 - $-8 - 6i$
 - $-7 + 24i$
- Let $z_1 = 1 + i\sqrt{3}$ and $z_2 = \sqrt{3} - i$. Represent $z_1, z_2, z_1 + z_2, z_1 - z_2$ on the same Argand diagram. Verify geometrically that $|z_1 + z_2|^2 + |z_1 - z_2|^2 = 2(|z_1|^2 + |z_2|^2)$ (parallelogram law).
- If $|z| = 2$ and $\arg(z) = \frac{2\pi}{3}$, find the modulus and principal argument of iz , $\frac{1}{z}$, and $\bar{z}$.

SOLUTION Exercise 1

- $z_1 = -2\sqrt{3} + 2i$: $|z_1| = \sqrt{12 + 4} = 4$. QII: $\alpha = \arctan(2/(2\sqrt{3})) = \pi/6$. $\text{Arg}(z_1) = \pi - \pi/6 =$

$$5\pi/6.$$

- $z_2 = -1 - i$: $|z_2| = \sqrt{2}$. QIII: $\alpha = \arctan(1) = \pi/4$. $\text{Arg}(z_2) = -\pi + \pi/4 = -3\pi/4$.
 - $z_3 = 4e^{i2\pi/3}$: $|z_3| = 4$, $\text{Arg}(z_3) = 2\pi/3$ (already in polar form).
2. $|z_1 z_2| = 2 \times 3 = 6$, $\arg(z_1 z_2) = \pi/6 + (-\pi/3) = -\pi/6 \in (-\pi, \pi]$. $|z_1/z_2| = 2/3$, $\arg(z_1/z_2) = \pi/6 - (-\pi/3) = \pi/2$.
3. (a) $5 + 12i$: $|z| = 13$. $x^2 = (13 + 5)/2 = 9 \Rightarrow x = \pm 3$, $y^2 = (13 - 5)/2 = 4 \Rightarrow y = \pm 2$. $b > 0 \Rightarrow$ same sign. Roots: $\pm(3 + 2i)$.
- (b) $-8 - 6i$: $|z| = 10$. $x^2 = (10 - 8)/2 = 1 \Rightarrow x = \pm 1$, $y^2 = (10 + 8)/2 = 9 \Rightarrow y = \pm 3$. $b < 0 \Rightarrow$ opposite signs. Roots: $\pm(1 - 3i)$.
- (c) $-7 + 24i$: $|z| = 25$. $x^2 = (25 - 7)/2 = 9 \Rightarrow x = \pm 3$, $y^2 = (25 + 7)/2 = 16 \Rightarrow y = \pm 4$. $b > 0 \Rightarrow$ same sign. Roots: $\pm(3 + 4i)$.
4. $z_1 = 1 + i\sqrt{3}$ ($|z_1| = 2$, $\arg = \pi/3$), $z_2 = \sqrt{3} - i$ ($|z_2| = 2$, $\arg = -\pi/6$). $z_1 + z_2 = (1 + \sqrt{3}) + i(\sqrt{3} - 1)$, $z_1 - z_2 = (1 - \sqrt{3}) + i(\sqrt{3} + 1)$. $|z_1 + z_2|^2 = (1 + \sqrt{3})^2 + (\sqrt{3} - 1)^2 = 1 + 3 + 2\sqrt{3} + 3 + 1 - 2\sqrt{3} = 8$. $|z_1 - z_2|^2 = (1 - \sqrt{3})^2 + (\sqrt{3} + 1)^2 = 1 + 3 - 2\sqrt{3} + 3 + 1 + 2\sqrt{3} = 8$. LHS = $8 + 8 = 16$. RHS = $2(4 + 4) = 16$. Verified.
5. $|z| = 2$, $\arg(z) = 2\pi/3$. iz : $|iz| = 2$, $\arg(iz) = 2\pi/3 + \pi/2 = 7\pi/6 \equiv -5\pi/6$ (principal). $1/z$: $|1/z| = 1/2$, $\arg(1/z) = -2\pi/3$ (principal). $\bar{z}$: $|\bar{z}| = 2$, $\arg(\bar{z}) = -2\pi/3$ (principal).

5

POLAR AND EXPONENTIAL FORMS

In the previous section we learned to locate a complex number in the Argand diagram using two pieces of information: its distance $r = |z|$ from the origin and the angle $\theta = \arg(z)$ that the line Oz makes with the positive real axis. We now exploit a beautiful idea: these two numbers r and θ do not merely describe the position of z — they can be used to write z itself. This gives two new ways of writing a complex number, the **polar form** and the **exponential form**, which turn the hardest operations of complex algebra (multiplication, division, powers, roots) into simple arithmetic on r and θ .

5.1 The Polar (Trigonometric) Form of a Complex Number

From geometry to algebra.

Let $z = a + ib$ be a non-zero complex number, represented by the point $M(a, b)$ in the Argand diagram. Let $r = |z| = \sqrt{a^2 + b^2}$ and $\theta = \arg(z)$. By the very definition of cosine and sine on the circle of radius r centred at O , the coordinates of M satisfy

$$a = r \cos \theta \quad \text{and} \quad b = r \sin \theta.$$

Substituting into $z = a + ib$ and factorising r :


$$z = r \cos \theta + i r \sin \theta = r(\cos \theta + i \sin \theta).$$

DEFINITION Polar form of a complex number

Let z be a non-zero complex number with modulus $r = |z| > 0$ and argument $\theta = \arg(z)$. The **polar form** (or **trigonometric form**) of z is

$$z = r(\cos \theta + i \sin \theta).$$

The number 0 has no polar form, since its argument is undefined. By convention, unless otherwise stated, θ denotes the **principal argument** $\text{Arg}(z) \in]-\pi, \pi]$.



One point, three names: the Cartesian, polar and exponential forms of z .

METHOD Converting $a + ib$ to polar form

1. Compute the modulus $r = \sqrt{a^2 + b^2}$ (always positive).
2. Find θ from the system $\cos \theta = \frac{a}{r}$, $\sin \theta = \frac{b}{r}$.
3. Use the signs of a and b to place θ in the correct quadrant (a calculator only gives $\arctan(b/a)$, which may be wrong by π). Recall the CAST rule:
 - $a > 0$, $b > 0$ (Q1): $\theta = \arctan(b/a)$
 - $a < 0$, $b > 0$ (Q2): $\theta = \pi + \arctan(b/a)$
 - $a < 0$, $b < 0$ (Q3): $\theta = -\pi + \arctan(b/a)$ (or $\pi + \arctan(b/a)$)
 - $a > 0$, $b < 0$ (Q4): $\theta = \arctan(b/a)$ (negative)
4. Write $z = r(\cos \theta + i \sin \theta)$ with $\theta \in]-\pi, \pi]$.

It is essential to memorise the standard angles, which appear constantly at the GCE:

$$\cos \frac{\pi}{6} = \frac{\sqrt{3}}{2}, \quad \sin \frac{\pi}{6} = \frac{1}{2}; \quad \cos \frac{\pi}{4} = \sin \frac{\pi}{4} = \frac{\sqrt{2}}{2}; \quad \cos \frac{\pi}{3} = \frac{1}{2}, \quad \sin \frac{\pi}{3} = \frac{\sqrt{3}}{2}.$$

EXAMPLE Cartesian to polar

Write $z = -1 + i\sqrt{3}$ in polar form.

$$r = \sqrt{(-1)^2 + (\sqrt{3})^2} = \sqrt{1+3} = 2.$$

Then $\cos \theta = -\frac{1}{2}$ and $\sin \theta = \frac{\sqrt{3}}{2}$. Since $a < 0$ and $b > 0$, θ lies in the second quadrant: $\theta = \frac{2\pi}{3}$. Hence

$$z = 2 \left(\cos \frac{2\pi}{3} + i \sin \frac{2\pi}{3} \right).$$

Conversely, polar to Cartesian is direct substitution: $2 \left(\cos \frac{\pi}{4} + i \sin \frac{\pi}{4} \right) = 2 \left(\frac{\sqrt{2}}{2} + i \frac{\sqrt{2}}{2} \right) = \sqrt{2} + i\sqrt{2}$.

EXAMPLE Quadrant determination practice

Write $z = -\sqrt{3} - i$ in polar form.

$$r = \sqrt{3+1} = 2, \quad \cos \theta = -\frac{\sqrt{3}}{2}, \quad \sin \theta = -\frac{1}{2}.$$

Both negative $\Rightarrow$ third quadrant. The reference angle is $\frac{\pi}{6}$, so $\theta = -\frac{5\pi}{6}$ (principal value). Thus

$$z = 2 \left(\cos \left(-\frac{5\pi}{6} \right) + i \sin \left(-\frac{5\pi}{6} \right) \right).$$

WARNING The modulus must be positive

A polar form requires $r > 0$. If a calculation produces something like $-2(\cos \frac{\pi}{6} + i \sin \frac{\pi}{6})$, this is not a polar form. Absorb the minus sign into the angle by adding π :

$$-2 \left(\cos \frac{\pi}{6} + i \sin \frac{\pi}{6} \right) = 2 \left(\cos \frac{7\pi}{6} + i \sin \frac{7\pi}{6} \right),$$

because $\cos(\theta + \pi) = -\cos \theta$ and $\sin(\theta + \pi) = -\sin \theta$. Always check that your final r is positive and $\theta \in]-\pi, \pi]$.

5.2 Multiplication, Division and Powers in Polar Form

Here lies the true power of the polar form. Take $z_1 = r_1(\cos \theta_1 + i \sin \theta_1)$ and $z_2 = r_2(\cos \theta_2 + i \sin \theta_2)$.

Multiplying:

$$\begin{aligned} z_1 z_2 &= r_1 r_2 [(\cos \theta_1 \cos \theta_2 - \sin \theta_1 \sin \theta_2) + i(\sin \theta_1 \cos \theta_2 + \cos \theta_1 \sin \theta_2)] \\ &= r_1 r_2 [\cos(\theta_1 + \theta_2) + i \sin(\theta_1 + \theta_2)], \end{aligned}$$

where we used the addition formulae $\cos(A+B) = \cos A \cos B - \sin A \sin B$ and $\sin(A+B) = \sin A \cos B + \cos A \sin B$.

PROPERTY Multiplication and division in polar form

For non-zero complex numbers $z_1 = r_1(\cos \theta_1 + i \sin \theta_1)$ and $z_2 = r_2(\cos \theta_2 + i \sin \theta_2)$:

$$z_1 z_2 = r_1 r_2 (\cos(\theta_1 + \theta_2) + i \sin(\theta_1 + \theta_2)), \quad \frac{z_1}{z_2} = \frac{r_1}{r_2} (\cos(\theta_1 - \theta_2) + i \sin(\theta_1 - \theta_2)).$$

In words: **moduli multiply (or divide), arguments add (or subtract)**. The proof of the product formula, shown above, is examinable; the quotient formula follows by multiplying numerator and denominator by the conjugate of z_2 .

Geometrically, multiplying by z_2 rotates the plane through the angle θ_2 and scales distances by the factor r_2 . This is why engineers and physicists love complex numbers: rotation becomes multiplication.

Applying the product rule repeatedly with the same number gives a preview of De Moivre's theorem (studied in the next section):

$$[r(\cos \theta + i \sin \theta)]^n = r^n (\cos n\theta + i \sin n\theta) \quad (n \in \mathbb{N}).$$

EXAMPLE A power made easy

Compute $(1 + i)^8$. In Cartesian form this would require the binomial theorem with nine terms. In polar form: $1 + i = \sqrt{2} \left(\cos \frac{\pi}{4} + i \sin \frac{\pi}{4} \right)$, so

$$(1 + i)^8 = (\sqrt{2})^8 \left(\cos \frac{8\pi}{4} + i \sin \frac{8\pi}{4} \right) = 16(\cos 2\pi + i \sin 2\pi) = 16.$$

EXPERIMENT Geometric interpretation of multiplication

On graph paper, plot $z_1 = 1 + i$ and $z_2 = \sqrt{3} + i$. Convert both to polar form, compute the product $z_1 z_2$ using the polar rule, and plot the result. Measure the angle and distance from the origin. You will see that the argument of the product is the sum of the arguments, and the modulus is the product of the moduli. This visual confirmation is worth a thousand algebraic proofs.

5.3 Euler's Formula and the Exponential Form

A remarkable observation.

Define, for real θ , the function $f(\theta) = \cos \theta + i \sin \theta$. The multiplication rule above says $f(\theta_1)f(\theta_2) = f(\theta_1 + \theta_2)$: f transforms addition into multiplication. But this is exactly the characteristic law of an exponential function, $e^{x_1}e^{x_2} = e^{x_1+x_2}$. Moreover, differentiating formally, $f'(\theta) = -\sin \theta + i \cos \theta = i(\cos \theta + i \sin \theta) = if(\theta)$, so f satisfies the differential equation $f' = if$ with $f(0) = 1$ — the same equation satisfied by $e^{i\theta}$. The great Swiss mathematician Leonhard Euler turned this observation into a definition.

PROPERTY Euler's formula

For every real number θ ,

$$e^{i\theta} = \cos \theta + i \sin \theta.$$


Consequently every non-zero complex number can be written in **exponential form**

$$z = re^{i\theta}, \quad r = |z| > 0, \quad \theta = \arg(z).$$

(The proof, via power series, is beyond the syllabus; the formula itself must be known and used fluently.)

WARNING $e^{i\theta}$ is not an ordinary exponential

The symbol $e^{i\theta}$ is a complex number of modulus 1; it is not the real exponential function. In particular you may not apply $\ln$ to it as if it were a positive real number, and $e^{i\theta}$ is never 0, never negative — it simply travels around the unit circle as θ varies.



As θ varies, $e^{i\theta} = \cos \theta + i \sin \theta$ describes the unit circle. At $\theta = \pi$ it passes through -1 .

Setting $\theta = \pi$ in Euler's formula gives $\cos \pi + i \sin \pi = -1 + 0i$, hence the most celebrated identity in all of mathematics.

KEY POINTS Euler's identity

$$e^{i\pi} + 1 = 0.$$

One short equation unites the five fundamental constants $0, 1, i, \pi, e$, together with the three basic operations (addition, multiplication, exponentiation). It is often called the most beautiful formula in mathematics.

DID YOU KNOW? Euler and the language of physics

Leonhard Euler (1707–1783) was the most prolific mathematician in history. The notation $e^{i\theta}$ that he introduced is today the working language of electrical engineering (alternating current is written $U = U_0 e^{i\omega t}$), of signal processing behind every mobile phone, and of quantum mechanics. The radio masts you see across Douala and Yaoundé are designed with calculations written in exponential form.

5.4 Algebraic Rules of the Exponential Form

All the polar rules become, in exponential notation, the familiar index laws — which is precisely why the notation $e^{i\theta}$ was chosen.


PROPERTY Rules of computation with $e^{i\theta}$

For real $\theta, \theta_1, \theta_2$ and non-zero $z_1 = r_1 e^{i\theta_1}, z_2 = r_2 e^{i\theta_2}$:

$$e^{i\theta_1} e^{i\theta_2} = e^{i(\theta_1+\theta_2)}, \quad \frac{1}{e^{i\theta}} = e^{-i\theta}, \quad \frac{z_1}{z_2} = \frac{r_1}{r_2} e^{i(\theta_1-\theta_2)}, \quad \overline{re^{i\theta}} = re^{-i\theta}, \quad (re^{i\theta})^n = r^n e^{in\theta}.$$

Also $|e^{i\theta}| = 1$ for every real θ .

These are exactly the polar rules rewritten: the conjugation rule, for instance, is just $\overline{r(\cos \theta + i \sin \theta)} = r(\cos \theta - i \sin \theta) = r(\cos(-\theta) + i \sin(-\theta)) = re^{-i\theta}$, since cosine is even and sine is odd.



Conversion flowchart between the three forms of a complex number.

WORKED EXAMPLE 12 Computing with the exponential form

Given $z_1 = 2e^{i\pi/3}$ and $z_2 = \sqrt{2}e^{-i\pi/4}$, determine in exponential form and then in Cartesian form: (a) $z_1 z_2$; (b) $\frac{z_1}{z_2}$; (c) z_1^3 .

SOLUTION

(a) Moduli multiply, arguments add:

$$z_1 z_2 = 2\sqrt{2} e^{i(\frac{\pi}{3} - \frac{\pi}{4})} = 2\sqrt{2} e^{i\pi/12}.$$

(b) Moduli divide, arguments subtract:

$$\frac{z_1}{z_2} = \frac{2}{\sqrt{2}} e^{i(\frac{\pi}{3} + \frac{\pi}{4})} = \sqrt{2} e^{i7\pi/12}.$$

(c) Power rule:

$$z_1^3 = 2^3 e^{i\pi} = 8(\cos \pi + i \sin \pi) = -8.$$

For the Cartesian form of (a): $\cos \frac{\pi}{12} = \frac{\sqrt{6}+\sqrt{2}}{4}$ and $\sin \frac{\pi}{12} = \frac{\sqrt{6}-\sqrt{2}}{4}$, so

$$z_1 z_2 = 2\sqrt{2} \left(\frac{\sqrt{6}+\sqrt{2}}{4} + i \frac{\sqrt{6}-\sqrt{2}}{4} \right) = \frac{2\sqrt{3}+2}{2} + i \frac{2\sqrt{3}-2}{2} = (\sqrt{3}+1) + i(\sqrt{3}-1).$$

METHOD GCE strategy: choosing the most convenient form

1. Addition and subtraction: use the Cartesian form $a + ib$ (real parts and imaginary parts combine separately).
2. Multiplication, division, powers, roots: convert to polar or exponential form first; the computation reduces to arithmetic on r and θ .
3. Conjugation and modulus: both forms work, but $\overline{re^{i\theta}} = re^{-i\theta}$ and $|re^{i\theta}| = r$ are instantaneous.
4. Final answer: give the form requested by the question; if none is requested, $a + ib$ with exact values is the safest.

WARNING Frequent errors at the GCE

- Writing $z = r(\cos \theta - i \sin \theta)$ when θ is in a lower quadrant instead of using the negative angle θ itself: the sign belongs to the angle, not to the formula.
- Forgetting to check the quadrant: $\arctan$ alone cannot distinguish $\frac{\pi}{3}$ from $\frac{4\pi}{3}$.
- Mixing forms inside one computation, e.g. adding $re^{i\theta}$ to $a + ib$ directly. Convert first.
- Claiming $e^{i\theta} > 0$ or solving $e^{i\theta} = 2$: impossible, since $|e^{i\theta}| = 1$.
- Forgetting to reduce the argument to the principal range $[-\pi, \pi]$ in the final answer.

EXERCISE 7 Practice

1. Write in polar and in exponential form: (a) $z = 1 - i$; (b) $z = -2\sqrt{3} - 2i$; (c) $z = -5i$.
2. Given $z_1 = 3e^{i\pi/6}$ and $z_2 = 2e^{i\pi/2}$, compute $z_1 z_2$, $\frac{z_1}{z_2}$ and z_2^4 , giving each answer in exponential and in Cartesian form.
3. Show that $(1 + i\sqrt{3})^6$ is a real number and find its value.
4. Simplify $\frac{e^{i\theta} - e^{-i\theta}}{2i}$ and $\frac{e^{i\theta} + e^{-i\theta}}{2}$. Which familiar functions do you recognise?
5. Express $\cos^3 \theta$ in terms of $\cos 3\theta$ and $\cos \theta$ using Euler's relations. (Hint: start from $2 \cos \theta = e^{i\theta} + e^{-i\theta}$ and cube both sides.)

SOLUTION Exercise 1

1. (a) $r = \sqrt{2}$, $\cos \theta = \frac{1}{\sqrt{2}}$, $\sin \theta = -\frac{1}{\sqrt{2}}$, so $\theta = -\frac{\pi}{4}$: $z = \sqrt{2} \left(\cos \frac{\pi}{4} - i \sin \frac{\pi}{4} \right) = \sqrt{2} e^{-i\pi/4}$. (b) $r = \sqrt{12 + 4} = 4$; $\cos \theta = -\frac{\sqrt{3}}{2}$, $\sin \theta = -\frac{1}{2}$, third quadrant: $\theta = -\frac{5\pi}{6}$ (or $\frac{7\pi}{6}$). Hence $z = 4e^{-5i\pi/6}$. (c) $r = 5$, $\theta = -\frac{\pi}{2}$: $z = 5e^{-i\pi/2}$.

2. $z_1 z_2 = 6e^{i(\pi/6 + \pi/2)} = 6e^{2i\pi/3} = 6 \left(-\frac{1}{2} + i\frac{\sqrt{3}}{2} \right) = -3 + 3i\sqrt{3}$. $\frac{z_1}{z_2} = \frac{3}{2} e^{i(\pi/6 - \pi/2)} = \frac{3}{2} e^{-i\pi/3} = \frac{3}{2} \left(\frac{1}{2} - i\frac{\sqrt{3}}{2} \right) = \frac{3}{4} - \frac{3\sqrt{3}}{4}i$. $z_2^4 = 16e^{2i\pi} = 16$.

3. $1 + i\sqrt{3} = 2e^{i\pi/3}$, so $(1 + i\sqrt{3})^6 = 2^6 e^{2i\pi} = 64(\cos 2\pi + i \sin 2\pi) = 64 \in \mathbb{R}$.

4. Since $e^{i\theta} = \cos \theta + i \sin \theta$ and $e^{-i\theta} = \cos \theta - i \sin \theta$, subtracting gives $e^{i\theta} - e^{-i\theta} = 2i \sin \theta$ and adding gives $e^{i\theta} + e^{-i\theta} = 2 \cos \theta$. Hence

$$\frac{e^{i\theta} - e^{-i\theta}}{2i} = \sin \theta, \quad \frac{e^{i\theta} + e^{-i\theta}}{2} = \cos \theta.$$

These are Euler's relations, which will be our main tool for expressing powers of $\cos x$ and $\sin x$ in terms of multiple angles later in this chapter.

5. $2 \cos \theta = e^{i\theta} + e^{-i\theta}$. Cubing: $8 \cos^3 \theta = (e^{i\theta} + e^{-i\theta})^3 = e^{3i\theta} + 3e^{i\theta} + 3e^{-i\theta} + e^{-3i\theta} = (e^{3i\theta} + e^{-3i\theta}) + 3(e^{i\theta} + e^{-i\theta}) = 2 \cos 3\theta + 6 \cos \theta$. Hence $\cos^3 \theta = \frac{1}{4} \cos 3\theta + \frac{3}{4} \cos \theta$.

KEY POINTS Key points of this section

- Polar form: $z = r(\cos \theta + i \sin \theta)$ with $r = |z| > 0$, $\theta = \arg(z) \in]-\pi, \pi]$.
- Euler's formula: $e^{i\theta} = \cos \theta + i \sin \theta$; exponential form $z = re^{i\theta}$; and $e^{i\pi} + 1 = 0$.
- Moduli multiply/divide, arguments add/subtract; $\overline{re^{i\theta}} = re^{-i\theta}$; $(re^{i\theta})^n = r^n e^{in\theta}$.
- Convert to exponential form for products, quotients and powers; stay in Cartesian form for sums.
- Euler's relations: $\cos \theta = \frac{e^{i\theta} + e^{-i\theta}}{2}$, $\sin \theta = \frac{e^{i\theta} - e^{-i\theta}}{2i}$.

6 DE MOIVRE'S THEOREM AND TRIGONOMETRIC APPLICATIONS

In the previous section we discovered that a complex number of modulus 1 can be written in the wonderfully compact form $e^{i\theta} = \cos \theta + i \sin \theta$, and that multiplication of such numbers simply adds their arguments. If we multiply $\cos \theta + i \sin \theta$ by itself n times, the argument θ is added to itself n times, giving $n\theta$. This simple observation is the content of one of the most beautiful theorems of the Upper Sixth programme: **De Moivre's theorem**. It will allow us to compute huge

powers of complex numbers in seconds, to find roots of unity, and to transform powers of $\cos x$ and $\sin x$ into multiple angles (and vice versa) — a skill you will use constantly in integration.

6.1 De Moivre's Theorem

EXPERIMENT A motivating computation

Let $z = \cos \theta + i \sin \theta$. Compute the first powers using the addition formulae:

$$z^2 = (\cos \theta + i \sin \theta)^2 = (\cos^2 \theta - \sin^2 \theta) + i(2 \sin \theta \cos \theta) = \cos 2\theta + i \sin 2\theta,$$

$$z^3 = z^2 \cdot z = (\cos 2\theta + i \sin 2\theta)(\cos \theta + i \sin \theta) = \cos 3\theta + i \sin 3\theta,$$

since multiplying two unit-modulus numbers adds their arguments. A pattern is emerging: $z^n = \cos n\theta + i \sin n\theta$. Let us prove it properly.

PROPERTY De Moivre's Theorem — proof examinable

For every real number θ and every integer $n \in \mathbb{Z}$,

$$(\cos \theta + i \sin \theta)^n = \cos n\theta + i \sin n\theta.$$

Equivalently, $(e^{i\theta})^n = e^{in\theta}$.

Proof for $n \in \mathbb{N}$ (by induction).

Let $P(n)$ be the statement " $(\cos \theta + i \sin \theta)^n = \cos n\theta + i \sin n\theta$ ".

Base case $n = 0$: $(\cos \theta + i \sin \theta)^0 = 1 = \cos 0 + i \sin 0$. So $P(0)$ holds. (The case $n = 1$ is also trivially true.)

Inductive step: assume $P(k)$ true for some $k \geq 0$. Then

$$\begin{aligned} (\cos \theta + i \sin \theta)^{k+1} &= (\cos k\theta + i \sin k\theta)(\cos \theta + i \sin \theta) \\ &= (\cos k\theta \cos \theta - \sin k\theta \sin \theta) + i(\sin k\theta \cos \theta + \cos k\theta \sin \theta) \\ &= \cos(k\theta + \theta) + i \sin(k\theta + \theta) = \cos(k+1)\theta + i \sin(k+1)\theta, \end{aligned}$$

using the addition formulae $\cos(A+B) = \cos A \cos B - \sin A \sin B$ and $\sin(A+B) = \sin A \cos B + \cos A \sin B$. Hence $P(k) \Rightarrow P(k+1)$, and by induction $P(n)$ holds for all $n \in \mathbb{N}$.

Extension to negative integers.


Let $n = -m$ with $m \in \mathbb{N}$, $m \geq 1$. Since $|\cos \theta + i \sin \theta| = 1$, its inverse equals its conjugate:

$$(\cos \theta + i \sin \theta)^{-1} = \cos \theta - i \sin \theta = \cos(-\theta) + i \sin(-\theta).$$

Therefore

$$(\cos \theta + i \sin \theta)^n = (\cos(-\theta) + i \sin(-\theta))^m = \cos(-m\theta) + i \sin(-m\theta) = \cos n\theta + i \sin n\theta,$$

applying the (already proved) result for the positive integer m to the angle $-\theta$. The theorem thus holds for all $n \in \mathbb{Z}$. ■



De Moivre on the unit circle: with $\theta = 45^\circ$, each multiplication by $z = \cos \theta + i \sin \theta$ rotates by a further θ , so z^n has argument $n\theta$.

WARNING Two classic traps

- $(\cos \theta + i \sin \theta)^n \neq \cos^n \theta + i \sin^n \theta$. De Moivre multiplies the angle by n ; it does not raise $\cos \theta$ and $\sin \theta$ to the power n .
- In its simple form the theorem is stated for **integer** n . For fractional powers (e.g. square roots, cube roots) several distinct values appear; this is the subject of the next section on n th roots.

6.2 Application: Computing Large Powers

METHOD Computing z^n via De Moivre

1. Write z in polar form: find $r = |z|$ and $\theta = \arg(z)$, so $z = r(\cos \theta + i \sin \theta)$.
2. Apply De Moivre: $z^n = r^n(\cos n\theta + i \sin n\theta)$.
3. Reduce $n\theta$ modulo 2π and convert back to Cartesian form if required.

WORKED EXAMPLE 13 Computing $(1+i)^{20}$ and $(\sqrt{3}+i)^{12}$

Compute (a) $(1+i)^{20}$ and (b) $(\sqrt{3}+i)^{12}$, giving exact answers in Cartesian form.

SOLUTION

(a) For $z = 1+i$: $r = \sqrt{1^2 + 1^2} = \sqrt{2}$ and $\theta = \arctan 1 = \frac{\pi}{4}$ (first quadrant). Hence

$$(1+i)^{20} = (\sqrt{2})^{20} \left(\cos \frac{20\pi}{4} + i \sin \frac{20\pi}{4} \right) = 2^{10} (\cos 5\pi + i \sin 5\pi) = 1024(-1 + 0i) = \boxed{-1024}.$$

(b) For $w = \sqrt{3}+i$: $r = \sqrt{3+1} = 2$ and $\theta = \arctan \frac{1}{\sqrt{3}} = \frac{\pi}{6}$. Hence

$$(\sqrt{3}+i)^{12} = 2^{12} \left(\cos \frac{12\pi}{6} + i \sin \frac{12\pi}{6} \right) = 4096(\cos 2\pi + i \sin 2\pi) = \boxed{4096}.$$

Notice how hopeless a direct binomial expansion of $(\sqrt{3}+i)^{12}$ would have been: polar form plus De Moivre reduces the problem to one line.

EXAMPLE Preview: roots of unity

Solve $z^3 = 1$ in $\mathbb{C}$. Write $z = \cos \theta + i \sin \theta$ (any cube root of 1 has modulus 1). By De Moivre, $z^3 = \cos 3\theta + i \sin 3\theta = 1$, so $3\theta = 2k\pi$, i.e. $\theta = \frac{2k\pi}{3}$. Taking $k = 0, 1, 2$ gives the three **cube roots of unity**:

$$1, \quad \cos \frac{2\pi}{3} + i \sin \frac{2\pi}{3} = -\frac{1}{2} + \frac{\sqrt{3}}{2}i, \quad \cos \frac{4\pi}{3} + i \sin \frac{4\pi}{3} = -\frac{1}{2} - \frac{\sqrt{3}}{2}i.$$

Further values of k repeat these. We shall generalise this to n th roots in the next section.

6.3 From Powers of cos and sin to Multiple Angles (Linearisation)

Set $z = \cos x + i \sin x = e^{ix}$, so that $|z| = 1$ and $z^{-1} = \cos x - i \sin x = \bar{z}$. Adding and subtracting,

$$z + \frac{1}{z} = 2 \cos x, \quad z - \frac{1}{z} = 2i \sin x.$$

Applying De Moivre with integer n , $z^n = \cos nx + i \sin nx$ and $z^{-n} = \cos nx - i \sin nx$, so:

PROPERTY The key pairing identities

With $z = \cos x + i \sin x$ and $n \in \mathbb{Z}$,

$$z^n + \frac{1}{z^n} = 2 \cos nx, \quad z^n - \frac{1}{z^n} = 2i \sin nx.$$

(Proof: immediate from De Moivre; quote it in the examination.)

n	$z^n + z^{-n} = 2 \cos nx$	$z^n - z^{-n} = 2i \sin nx$
1	$z + z^{-1} = 2 \cos x$	$z - z^{-1} = 2i \sin x$
2	$z^2 + z^{-2} = 2 \cos 2x$	$z^2 - z^{-2} = 2i \sin 2x$
3	$z^3 + z^{-3} = 2 \cos 3x$	$z^3 - z^{-3} = 2i \sin 3x$

The pairing identities for $n = 1, 2, 3$: conjugate pairs $z^{\pm n}$ recombine into a single cosine or sine of a multiple angle.

METHOD Linearising $\cos^n x$ or $\sin^n x$

1. Write $\cos x = \frac{1}{2} \left(z + \frac{1}{z} \right)$ or $\sin x = \frac{1}{2i} \left(z - \frac{1}{z} \right)$.
2. Raise to the power n and expand with the binomial theorem: $(A \pm B)^n = \sum_{k=0}^n \binom{n}{k} A^{n-k} (\pm B)^k$.
3. Regroup conjugate pairs $z^k + z^{-k}$ (or $z^k - z^{-k}$) and replace them by $2 \cos kx$ (or $2i \sin kx$).
4. Simplify the numerical factors.

WORKED EXAMPLE 14 Linearising $\cos^4 x$

Express $\cos^4 x$ as a sum of cosines of multiple angles.

SOLUTION

Let $z = \cos x + i \sin x$, so $\cos x = \frac{1}{2} (z + z^{-1})$. Then

$$\begin{aligned} \cos^4 x &= \frac{1}{16} \left(z + \frac{1}{z} \right)^4 = \frac{1}{16} \left(z^4 + 4z^2 + 6 + \frac{4}{z^2} + \frac{1}{z^4} \right) \\ &= \frac{1}{16} \left[\left(z^4 + \frac{1}{z^4} \right) + 4 \left(z^2 + \frac{1}{z^2} \right) + 6 \right] = \frac{1}{16} [2 \cos 4x + 8 \cos 2x + 6]. \end{aligned}$$

Hence $\cos^4 x = \frac{1}{8} \cos 4x + \frac{1}{2} \cos 2x + \frac{3}{8}$.

WORKED EXAMPLE 15 Linearising $\sin^5 x$

Express $\sin^5 x$ in terms of sines of multiple angles.

SOLUTION

With $\sin x = \frac{1}{2i} (z - z^{-1})$:

$$\begin{aligned}\sin^5 x &= \frac{1}{(2i)^5} \left(z - \frac{1}{z}\right)^5 = \frac{1}{32i} \left(z^5 - 5z^3 + 10z - \frac{10}{z} + \frac{5}{z^3} - \frac{1}{z^5}\right) \\ &= \frac{1}{32i} \left[\left(z^5 - \frac{1}{z^5}\right) - 5\left(z^3 - \frac{1}{z^3}\right) + 10\left(z - \frac{1}{z}\right)\right] \\ &= \frac{1}{32i} [2i \sin 5x - 10i \sin 3x + 20i \sin x].\end{aligned}$$

Hence $\sin^5 x = \frac{1}{16} \sin 5x - \frac{5}{16} \sin 3x + \frac{5}{8} \sin x$.

EXAMPLE Linearising $\sin^2 x \cos^2 x$

$$\begin{aligned}\sin^2 x \cos^2 x &= \frac{1}{4} \sin^2 2x = \frac{1}{4} \cdot \frac{1 - \cos 4x}{2} = \frac{1}{8} - \frac{1}{8} \cos 4x. \text{ Alternatively, directly with } z: \\ \sin^2 x \cos^2 x &= \frac{1}{(2i)^2 \cdot 2^2} (z - z^{-1})^2 (z + z^{-1})^2 = -\frac{1}{16} (z^2 - z^{-2})^2 = \frac{1}{8} - \frac{1}{8} \cos 4x.\end{aligned}$$

DID YOU KNOW? Why linearisation matters

Integrals such as $\int \cos^4 x \, dx$ cannot be done by substitution, but once linearised they are immediate: $\int \cos^4 x \, dx = \frac{1}{32} \sin 4x + \frac{1}{4} \sin 2x + \frac{3}{8} x + C$. These expansions are examined regularly in the Pure and Further papers.

6.4 From Multiple Angles to Powers of cos and sin

The reverse direction uses De Moivre together with the **binomial theorem**: expand $(\cos x + i \sin x)^n$, then equate real and imaginary parts with $\cos nx + i \sin nx$.

METHOD Expanding $\cos nx$ and $\sin nx$

1. Write $\cos nx + i \sin nx = (\cos x + i \sin x)^n$ (De Moivre).
2. Expand the right-hand side with the binomial theorem, writing $c = \cos x$, $s = \sin x$:

$$(c + is)^n = \sum_{k=0}^n \binom{n}{k} c^{n-k} (is)^k.$$

3. Equate real parts to obtain $\cos nx$, and imaginary parts to obtain $\sin nx$.
4. Use $i^2 = -1$ to simplify, and $\sin^2 x = 1 - \cos^2 x$ (or $\cos^2 x = 1 - \sin^2 x$) if a single-variable polynomial is wanted.

WORKED EXAMPLE 16 The triple-angle formulae

Prove that $\cos 3x = 4 \cos^3 x - 3 \cos x$ and $\sin 3x = 3 \sin x - 4 \sin^3 x$.

SOLUTION

By De Moivre and the binomial theorem, with $c = \cos x$, $s = \sin x$:

$$\cos 3x + i \sin 3x = (c + is)^3 = c^3 + 3c^2(is) + 3c(is)^2 + (is)^3 = (c^3 - 3cs^2) + i(3c^2s - s^3).$$

Equating real parts: $\cos 3x = c^3 - 3cs^2 = c^3 - 3c(1 - c^2) = 4c^3 - 3c$, i.e.

$$\cos 3x = 4 \cos^3 x - 3 \cos x.$$

Equating imaginary parts: $\sin 3x = 3c^2s - s^3 = 3(1 - s^2)s - s^3 = 3s - 4s^3$, i.e.

$$\sin 3x = 3 \sin x - 4 \sin^3 x. \quad \blacksquare$$

EXAMPLE Obtaining $\tan nx$

Dividing the expansions of $\sin nx$ and $\cos nx$ and then dividing numerator and denominator by $\cos^n x$ expresses $\tan nx$ in terms of $t = \tan x$. For $n = 3$:

$$\tan 3x = \frac{3c^2s - s^3}{c^3 - 3cs^2} = \frac{3t - t^3}{1 - 3t^2}, \quad t = \tan x.$$

The same technique gives $\tan 2x = \frac{2t}{1 - t^2}$, a formula you already know — now derived from De Moivre.

WARNING Common mistakes in expansions

- Forgetting that $(is)^2 = -s^2$ and $(is)^3 = -is^3$: the signs of the real part alternate.
- Mixing the two directions: to linearise $\cos^n x$ start from $z + z^{-1}$; to expand $\cos nx$ start from $(c + is)^n$.
- When equating parts, remember $i \sin nx$ is the imaginary part of the expansion, so

$\sin nx$ equals the coefficient of i .

EXERCISE 8 Practice

1. Compute $(1 - i\sqrt{3})^{15}$ in Cartesian form.
2. Express $\cos^5 x$ as a sum of cosines of multiple angles.
3. Express $\sin^4 x$ as a sum of cosines of multiple angles, and hence evaluate $\int_0^{\pi/2} \sin^4 x \, dx$.
4. Prove that $\cos 4x = 8 \cos^4 x - 8 \cos^2 x + 1$ and find the corresponding expression for $\tan 4x$ in terms of $t = \tan x$.

SOLUTION Exercise 1

1. $1 - i\sqrt{3}$ has modulus 2 and argument $-\frac{\pi}{3}$. Hence $(1 - i\sqrt{3})^{15} = 2^{15} (\cos(-5\pi) + i \sin(-5\pi)) = 32768(-1) = \boxed{-32768}$.

$$2. \quad \cos^5 x = \frac{1}{32} (z + z^{-1})^5 = \frac{1}{32} [(z^5 + z^{-5}) + 5(z^3 + z^{-3}) + 10(z + z^{-1})] = \frac{1}{16} \cos 5x + \frac{5}{16} \cos 3x + \frac{5}{8} \cos x.$$

$$3. \quad \sin^4 x = \frac{1}{16} (z - z^{-1})^4 = \frac{1}{16} [(z^4 + z^{-4}) - 4(z^2 + z^{-2}) + 6] = \frac{1}{8} \cos 4x - \frac{1}{2} \cos 2x + \frac{3}{8}. \text{ Then } \int_0^{\pi/2} \sin^4 x \, dx = \left[\frac{1}{32} \sin 4x - \frac{1}{4} \sin 2x + \frac{3}{8} x \right]_0^{\pi/2} = \boxed{\frac{3\pi}{16}}.$$

4. $(c + is)^4 = (c^4 - 6c^2s^2 + s^4) + i(4c^3s - 4cs^3)$. Real part: $\cos 4x = c^4 - 6c^2(1 - c^2) + (1 - c^2)^2 = 8c^4 - 8c^2 + 1$, i.e. $\cos 4x = 8 \cos^4 x - 8 \cos^2 x + 1$. Dividing imaginary by real parts and then

$$\text{by } c^4: \tan 4x = \frac{4t - 4t^3}{1 - 6t^2 + t^4}, \text{ i.e. } \tan 4x = \frac{4 \tan x - 4 \tan^3 x}{1 - 6 \tan^2 x + \tan^4 x}.$$

KEY POINTS Key points of the section

- De Moivre: $(\cos \theta + i \sin \theta)^n = \cos n\theta + i \sin n\theta$ for all $n \in \mathbb{Z}$ (proved by induction, extended to negative n via the conjugate).
- Large powers: convert to polar form, apply De Moivre, reduce the angle modulo 2π .
- With $z = e^{ix}$: $z^n + z^{-n} = 2 \cos nx$ and $z^n - z^{-n} = 2i \sin nx$ — the engine of linearisation.

- $\cos nx$ and $\sin nx$ are obtained by expanding $(\cos x + i \sin x)^n$ binomially and equating real and imaginary parts; $\tan nx$ follows by division.

7 ROOTS OF COMPLEX NUMBERS: NTH ROOTS AND CUBE ROOTS

In the previous section, De Moivre's theorem taught us how to raise a complex number to a power: $(re^{i\theta})^n = r^n e^{in\theta}$. We now ask the reverse question, which is far richer: given a complex number w , can we find all the numbers z such that $z^n = w$? In the real numbers, the equation $x^2 = 4$ has two solutions and $x^2 = -4$ has none. In $\mathbb{C}$, the situation is beautifully complete: **every** non-zero complex number has **exactly** n distinct n th roots, and they are arranged with perfect symmetry in the Argand diagram. This section solves the problem completely, then studies in detail the most important special case, the cube roots, which appear constantly at the GCE Advanced Level.

7.1 The n th Roots of a Complex Number

Setting up the problem. Let w be a non-zero complex number. We seek all $z \in \mathbb{C}$ such that $z^n = w$. Write both numbers in exponential form:

$$w = Re^{i\varphi} \quad (R > 0), \quad z = re^{i\theta}.$$

Then $z^n = w$ becomes $r^n e^{in\theta} = Re^{i\varphi}$. Two complex numbers in exponential form are equal if and only if their moduli are equal and their arguments differ by a multiple of 2π . Hence

$$r^n = R \quad \text{and} \quad n\theta = \varphi + 2k\pi \quad (k \in \mathbb{Z}).$$

Since r is a positive real number, $r = R^{1/n}$ (the ordinary positive real n th root). The arguments are $\theta = \frac{\varphi + 2k\pi}{n}$. Taking $k = 0, 1, \dots, n-1$ gives n distinct values; any other integer k repeats one of these, because increasing k by n adds 2π to θ .

PROPERTY The n th roots of a complex number

Every non-zero complex number $w = Re^{i\varphi}$ has exactly n distinct n th roots, given by

$$z_k = R^{1/n} e^{i(\varphi + 2k\pi)/n}, \quad k = 0, 1, \dots, n-1.$$

The derivation above is examinable: you may be asked to show that these are the only solutions.

WARNING Do not forget the $2k\pi$ term

The most frequent error at the GCE is to write only $\theta = \varphi/n$, which yields just one root. The equation $z^n = w$ has n solutions: the term $2k\pi$ in $n\theta = \varphi + 2k\pi$ is what produces them all.

WARNING The modulus of the roots

$R^{1/n}$ is the positive real n th root of the modulus R (for example $8^{1/3} = 2$). It is an ordinary real number, not a complex root.

PROPERTY Geometric property: regular polygon

The n roots $z_0, z_1, \dots, z_{n-1}$ all have the same modulus $R^{1/n}$, and consecutive roots differ in argument by $\frac{2\pi}{n}$. Therefore their images in the Argand diagram lie on the circle of centre O and radius $R^{1/n}$, at the vertices of a **regular n -gon**.

METHOD Solving $z^n = w$

1. Write w in exponential form $w = Re^{i\varphi}$ (modulus, then argument).
2. Compute the common modulus $R^{1/n}$ of the roots.
3. Write the n arguments $\theta_k = \frac{\varphi + 2k\pi}{n}$ for $k = 0, 1, \dots, n-1$.
4. State the roots $z_k = R^{1/n}e^{i\theta_k}$, then convert each to the form requested (often $a + ib$).

WORKED EXAMPLE 17 Fourth roots of -16

Solve $z^4 = -16$, giving the roots in the form $a + ib$.

SOLUTION

Solution. $-16 = 16e^{i\pi}$, so $R = 16$, $\varphi = \pi$, and $R^{1/4} = 16^{1/4} = 2$. The arguments are

$$\theta_k = \frac{\pi + 2k\pi}{4}, \quad k = 0, 1, 2, 3 : \quad \frac{\pi}{4}, \frac{3\pi}{4}, \frac{5\pi}{4}, \frac{7\pi}{4}.$$

Hence

$$z_0 = 2e^{i\pi/4} = \sqrt{2} + i\sqrt{2},$$

$$z_1 = 2e^{3i\pi/4} = -\sqrt{2} + i\sqrt{2},$$

$$z_2 = 2e^{5i\pi/4} = -\sqrt{2} - i\sqrt{2},$$

$$z_3 = 2e^{7i\pi/4} = \sqrt{2} - i\sqrt{2}.$$

Check: $(\sqrt{2} + i\sqrt{2})^2 = 4i$, so $(\sqrt{2} + i\sqrt{2})^4 = -16$. ✓


7.2 Roots of Unity

DEFINITION Roots of unity

The solutions of $z^n = 1$ are called the **n th roots of unity**. Since $1 = e^{i \cdot 0}$, they are

$$\omega_k = e^{2ik\pi/n}, \quad k = 0, 1, \dots, n-1,$$

the vertices of a regular n -gon inscribed in the unit circle, with one vertex at 1.



The five 5th roots of unity: vertices of a regular pentagon on the unit circle.

PROPERTY Sum of the roots of unity

The sum of the n th roots of unity is zero:

$$1 + \omega + \omega^2 + \dots + \omega^{n-1} = 0, \quad \text{where } \omega = e^{2i\pi/n}.$$

Proof (examinable): this is a geometric progression with ratio $\omega \neq 1$, so the sum is $\frac{1 - \omega^n}{1 - \omega} = \frac{1 - 1}{1 - \omega} = 0$, since $\omega^n = 1$.

Geometrically this says the “centre of mass” of the regular polygon is the origin — a satisfying confirmation of the symmetry.

7.3 The Cube Roots of a Complex Number

The case $n = 3$ deserves a detailed study, both because it is the most frequent at the GCE and because it introduces the celebrated number j . Solving $z^3 = w$ with $w = Re^{i\varphi}$ gives three roots

$$z_k = R^{1/3} e^{i(\varphi + 2k\pi)/3}, \quad k = 0, 1, 2,$$

spaced by $\frac{2\pi}{3}$ on the circle of radius $R^{1/3}$: an equilateral triangle.


DEFINITION The number j

The cube roots of unity are the solutions of $z^3 = 1$:

$$1, \quad j = e^{2i\pi/3} = -\frac{1}{2} + i\frac{\sqrt{3}}{2}, \quad j^2 = e^{4i\pi/3} = -\frac{1}{2} - i\frac{\sqrt{3}}{2} = \bar{j}.$$

They satisfy the fundamental identities

$$j^3 = 1, \quad 1 + j + j^2 = 0, \quad j^2 = \bar{j} = \frac{1}{j}.$$



The cube roots of unity $1, j, j^2$: an equilateral triangle on the unit circle.

EXAMPLE Factorising with j

Since $j^3 = 1$, we have $a^3 + b^3 = (a + b)(a + jb)(a + j^2b)$. Indeed, expanding $(a + jb)(a + j^2b) = a^2 + (j + j^2)ab + j^3b^2 = a^2 - ab + b^2$ (using $1 + j + j^2 = 0$ and $j^3 = 1$), and $(a + b)(a^2 - ab + b^2) = a^3 + b^3$. Similarly $a^3 - b^3 = (a - b)(a - jb)(a - j^2b)$.

WORKED EXAMPLE 18 Solving $z^3 = -8$ and $z^3 = i$

(a) Solve $z^3 = -8$. (b) Solve $z^3 = i$, expressing the roots in the form $a + ib$.

SOLUTION


Solution. (a) $-8 = 8e^{i\pi}$, so $R^{1/3} = 2$ and $\theta_k = \frac{\pi + 2k\pi}{3}$, giving $\theta = \frac{\pi}{3}, \pi, \frac{5\pi}{3}$. Hence

$$z_0 = 2e^{i\pi/3} = 1 + i\sqrt{3}, \quad z_1 = 2e^{i\pi} = -2, \quad z_2 = 2e^{5i\pi/3} = 1 - i\sqrt{3}.$$

Quick alternative: $z^3 = -8 \iff \left(\frac{z}{-2}\right)^3 = 1$, so $z = -2, -2j, -2j^2$, which are the same three numbers.

(b) $i = e^{i\pi/2}$, so $R = 1$ and $\theta_k = \frac{\pi/2 + 2k\pi}{3} = \frac{\pi}{6}, \frac{5\pi}{6}, \frac{3\pi}{2}$. Therefore

$$z_0 = e^{i\pi/6} = \frac{\sqrt{3}}{2} + \frac{1}{2}j, \quad z_1 = e^{5i\pi/6} = -\frac{\sqrt{3}}{2} + \frac{1}{2}j, \quad z_2 = e^{3i\pi/2} = -i.$$



The three cube roots of $8i$: $\sqrt{3} + i$, $-\sqrt{3} + i$, $-2i$, on the circle of radius 2.

EXAMPLE Cube roots of $8i$ and $-8i$

For $8i = 8e^{i\pi/2}$: $R^{1/3} = 2$, $\theta_k = \frac{\pi/2 + 2k\pi}{3} = \frac{\pi}{6}, \frac{5\pi}{6}, \frac{3\pi}{2}$. The roots are

$$2e^{i\pi/6} = \sqrt{3} + i, \quad 2e^{5i\pi/6} = -\sqrt{3} + i, \quad 2e^{3i\pi/2} = -2i.$$

For $-8i = 8e^{-i\pi/2}$: $\theta_k = \frac{-\pi/2 + 2k\pi}{3} = -\frac{\pi}{6}, \frac{\pi}{2}, \frac{7\pi}{6}$. The roots are

$$2e^{-i\pi/6} = \sqrt{3} - i, \quad 2e^{i\pi/2} = 2i, \quad 2e^{7i\pi/6} = -\sqrt{3} - i.$$

Both families form an equilateral triangle of radius 2; only the rotation differs. The figure above illustrates the roots of $8i$.

7.4 The Complete Picture and Examination Advice

The programme on roots is now complete. The square-root method of Lesson 32 (solving $z^2 = w$ algebraically) is exactly the case $n = 2$ of the general formula: the two square roots of $Re^{i\varphi}$ are $\pm\sqrt{R}e^{i\varphi/2}$, diametrically opposite on the circle of radius $\sqrt{R}$. Whatever the degree, the strategy is identical: exponential form, root formula, conversion.

WARNING GCE exam extra: convert to $a + ib$

The GCE frequently asks, after the roots have been found in exponential form, to “express the roots in the form $a+ib$ ”. You must then evaluate the cosines and sines exactly (standard angles $\frac{\pi}{6}, \frac{\pi}{4}, \frac{\pi}{3}, \frac{2\pi}{3}$, etc.). Leaving answers as $2e^{i\pi/6}$ when $a+ib$ is requested costs marks.

KEY POINTS Key points

- $w = Re^{i\varphi} \neq 0$ has exactly n n th roots: $z_k = R^{1/n} e^{i(\varphi+2k\pi)/n}$, $k = 0, \dots, n-1$.
- They form a regular n -gon on the circle of radius $R^{1/n}$; consecutive roots differ by $\frac{2\pi}{n}$.
- The n th roots of unity sum to 0.
- $j = e^{2i\pi/3} = -\frac{1}{2} + i\frac{\sqrt{3}}{2}$ satisfies $j^3 = 1$, $1+j+j^2 = 0$, $j^2 = \bar{j}$.
- $z^3 = a^3$ has solutions a, aj, aj^2 — a powerful shortcut.

EXERCISE 9 Practice

1. Solve $z^5 = 1$ and verify that the sum of the roots is 0.
2. Solve $z^3 = 27$, then $z^3 = -27i$, giving all roots in the form $a+ib$.
3. Show that $(1+j)^2 = j$ and deduce $(1+j)^6$.
4. Find the fourth roots of $-8 - 8\sqrt{3}i$ in exponential form, then in the form $a+ib$.

SOLUTION Exercise 1

1. $z_k = e^{2ik\pi/5}$, $k = 0, \dots, 4$. Sum = $\frac{1-\omega^5}{1-\omega} = 0$ with $\omega = e^{2i\pi/5}$. 2. $z^3 = 27$: $z = 3, 3j, 3j^2$, i.e. $3, -\frac{3}{2} + \frac{3\sqrt{3}}{2}j, -\frac{3}{2} - \frac{3\sqrt{3}}{2}j$. For $z^3 = -27i = 27e^{-i\pi/2}$: modulus 3, arguments $-\frac{\pi}{6}, \frac{\pi}{2}, \frac{7\pi}{6}$: roots $\frac{3\sqrt{3}}{2} - \frac{3}{2}i, 3i, -\frac{3\sqrt{3}}{2} - \frac{3}{2}i$. 3. $(1+j)^2 = 1+2j+j^2 = (1+j+j^2)+j = 0+j = j$ (since $1+j+j^2 = 0$). Hence $(1+j)^6 = ((1+j)^2)^3 = j^3 = 1$. 4. $-8 - 8\sqrt{3}i = 16e^{-2i\pi/3}$ (modulus 16, argument $-\frac{2\pi}{3}$). Roots: $2e^{i(-2\pi/3+2k\pi)/4}$, i.e. $2e^{-i\pi/6} = \sqrt{3} - i, 2e^{i\pi/3} = 1 + i\sqrt{3}, 2e^{5i\pi/6} = -\sqrt{3} + i, 2e^{4i\pi/3} = -1 - i\sqrt{3}$.

8

LOCI IN THE COMPLEX PLANE AND SYNTHESIS

In the previous section we learnt how to find all the n th roots of a complex number, and we saw

a beautiful fact: those roots are always the vertices of a regular polygon inscribed in a circle. In other words, the equation $z^n = w$ describes a set of points in the plane with a precise geometric shape. This final section generalises that idea. A condition on a complex number z — an equation or an inequality involving $|z - a|$ or $\arg(z - a)$ — picks out a curve or a region of the Argand diagram. Such a set of points is called a **locus** (plural: loci). Loci questions are among the most frequent and most rewarding questions in the GCE Advanced Level paper, because they test simultaneously your algebra, your geometry and your understanding of the modulus and the argument.

8.1 Loci Defined by the Modulus

The circle. Let a be a fixed complex number, represented by the point A , and let z be a variable complex number, represented by the point M . The number $z - a$ is represented by the vector $\vec{AM}$, so $|z - a|$ is nothing other than the distance AM . The condition $|z - a| = r$ therefore says: “ M is at distance r from A ” — which is exactly the definition of a circle.

PROPERTY Circle and perpendicular bisector


Let $a, b \in \mathbb{C}$ with images A, B , and let $r > 0$. Then:

- $|z - a| = r \iff M(z)$ lies on the **circle** of centre $A(a)$ and radius r ;
- $|z - a| = |z - b| \iff M(z)$ lies on the **perpendicular bisector** of the segment $[AB]$.

The second statement is the classical fact that the points equidistant from A and B form the perpendicular bisector of $[AB]$, since $|z - a| = AM$ and $|z - b| = BM$.

EXAMPLE Reading a locus directly

The equation $|z - (1 + 2i)| = 3$ describes the circle of centre $(1, 2)$ and radius 3. The equation $|z - 1| = |z + i|$, rewritten as $|z - 1| = |z - (-i)|$, describes the perpendicular bisector of the segment joining $A(1, 0)$ and $B(0, -1)$.



The circle $|z - (1 + 2i)| = 3$ and the perpendicular bisector $|z - 1| = |z + i|$.

METHOD From a locus to a Cartesian equation

To obtain the Cartesian equation of a locus:

1. Replace z by $x + iy$ with $x, y \in \mathbb{R}$.
2. Compute each modulus using $|u + iv| = \sqrt{u^2 + v^2}$.
3. Square both sides to eliminate the square roots.
4. Simplify; recognise the curve (circle, line, etc.).

WORKED EXAMPLE 19 Cartesian equation of a bisector

Find the Cartesian equation of the locus $|z - 1| = |z + i|$ and identify it.

SOLUTION

Set $z = x + iy$. Then $z - 1 = (x - 1) + iy$ and $z + i = x + i(y + 1)$, so

$$\sqrt{(x - 1)^2 + y^2} = \sqrt{x^2 + (y + 1)^2}.$$

Squaring: $(x - 1)^2 + y^2 = x^2 + (y + 1)^2$, that is

$$x^2 - 2x + 1 + y^2 = x^2 + y^2 + 2y + 1 \iff -2x = 2y \iff y = -x.$$

The locus is the straight line $y = -x$, the perpendicular bisector of the segment joining $(1, 0)$ and $(0, -1)$ — exactly as the figure shows.

8.2 Loci Defined by the Argument

The number $\arg(z - a)$ is the angle that the vector $\vec{AM}$ makes with the positive real axis. Fixing this angle forces M onto a ray starting at A .

PROPERTY Half-line locus

Let $a \in \mathbb{C}$ with image A , and $\theta \in \mathbb{R}$. Then

$\arg(z - a) = \theta \iff M(z)$ lies on the half-line from A making angle θ with the positive real axis, the point A itself being excluded.

WARNING The origin of the ray is excluded

The point a is never part of the locus $\arg(z - a) = \theta$, because at $z = a$ we would need $\arg(0)$, which is undefined. Mark A with an open (hollow) dot on your diagram. Similarly, in $\arg\left(\frac{z - a}{z - b}\right) = \theta$, both a and b are excluded.

The Thales locus. A quotient of complex numbers has argument


$$\arg\left(\frac{z - a}{z - b}\right) = \arg(z - a) - \arg(z - b) = \text{angle}(\vec{BM}, \vec{AM}) = \hat{AMB}.$$

Requiring this angle to be $\pm \frac{\pi}{2}$ means the angle $\hat{AMB}$ is a right angle. By the theorem of Thales, M lies on the circle of diameter $[AB]$.

PROPERTY Circle of diameter $[AB]$

$\arg\left(\frac{z - a}{z - b}\right) = \pm \frac{\pi}{2} \pmod{\pi} \iff M(z)$ lies on the circle of diameter $[AB]$, A and B excluded.

With a single sign, $\arg\left(\frac{z - a}{z - b}\right) = \frac{\pi}{2}$ (principal value), only one semicircle is obtained.



The locus $\arg\left(\frac{z-1}{z+1}\right) = \frac{\pi}{2}$: the upper semicircle of diameter $[-1, 1]$ (solid), endpoints excluded. The dashed semicircle corresponds to $-\frac{\pi}{2}$.

EXAMPLE Checking the Thales locus

Take $z = i$. Then $\frac{z-1}{z+1} = \frac{-1+i}{1+i} = \frac{(-1+i)(1-i)}{(1+i)(1-i)} = \frac{2i}{2} = i$, whose argument is $\frac{\pi}{2}$. Indeed i lies on the circle of diameter $[-1, 1]$, since $|i| = 1$.

8.3 Inequalities and Regions of the Plane

An inequality involving the modulus describes a region rather than a curve:

- $|z - a| \leq r$: the closed **disc** of centre a , radius r (boundary circle included, drawn solid);
- $|z - a| < r$: the open disc (boundary excluded, drawn dashed);
- $r_1 \leq |z| \leq r_2$: an **annulus** centred at the origin;
- $\alpha \leq \arg z \leq \beta$: a **sector** (wedge) from the origin.

Conditions can be combined: the intersection of an annulus and a sector is a “piece of cake” region.

WARNING Solid versus dashed boundaries


For strict inequalities ($<$, $>$), draw the boundary dashed: it is not part of the locus. For non-strict inequalities ($\leq$, $\geq$), draw it solid. Examiners award marks for this convention.

METHOD Sketching a region

1. Sketch the boundary curve(s) first, using the equality cases.
2. Choose one convenient test point (e.g. $z = 0$ or $z = 1$) and check whether it satisfies

the inequality.

3. Shade the side containing the test point if it works, the other side otherwise.
4. Apply the solid/dashed convention and mark excluded points with hollow dots.



The region $1 \leq |z| \leq 2$ and $0 \leq \arg z \leq \frac{\pi}{3}$ (shaded): intersection of an annulus and a sector.

8.4 Synthesis: GCE-Style Problems

Examination questions typically chain several ideas: a locus condition, a conversion to Cartesian form, and a computation involving powers, roots or De Moivre's theorem.

WORKED EXAMPLE 20 GCE-style synthesis

Let $z = x + iy$.

1. Show that the locus $|z - 4i| = 2|z - 1|$ is a circle, and find its centre and radius.
2. Find the complex number(s) on this locus with $\arg z = \frac{\pi}{2}$.

SOLUTION

1. $|x + i(y - 4)| = 2|(x - 1) + iy|$ gives, after squaring,

$$x^2 + (y - 4)^2 = 4[(x - 1)^2 + y^2].$$

Expanding: $x^2 + y^2 - 8y + 16 = 4x^2 - 8x + 4 + 4y^2$, so

$$3x^2 + 3y^2 - 8x + 8y - 12 = 0 \iff x^2 + y^2 - \frac{8}{3}x + \frac{8}{3}y - 4 = 0.$$

Completing the squares:

$$\left(x - \frac{4}{3}\right)^2 + \left(y + \frac{4}{3}\right)^2 = 4 + \frac{16}{9} + \frac{16}{9} = \frac{68}{9}.$$

This is a circle of centre $\frac{4}{3} - \frac{4}{3}i$ and radius $\frac{\sqrt{68}}{3} = \frac{2\sqrt{17}}{3}$.

2. $\arg z = \frac{\pi}{2}$ means $z = iy$ with $y > 0$. Substituting $x = 0$:

$$y^2 + \frac{8}{3}y - 4 = 0 \iff 3y^2 + 8y - 12 = 0 \iff y = \frac{-8 \pm \sqrt{64 + 144}}{6} = \frac{-8 \pm 4\sqrt{13}}{6}.$$

Only the positive root is acceptable: $z = \frac{-4 + 2\sqrt{13}}{3}i$.

WORKED EXAMPLE 21 Locus and roots combined

1. Sketch the locus $|z| = 1$ and mark on it the cube roots of -8 .
2. Verify that each cube root of -8 lies on the circle $|z| = 2$, not $|z| = 1$.

SOLUTION

1. $|z| = 1$ is the unit circle centred at O .
2. Write $-8 = 8e^{i\pi}$. The cube roots are

$$z_k = 2e^{i(\pi+2k\pi)/3}, \quad k = 0, 1, 2,$$

that is $z_0 = 2e^{i\pi/3} = 1 + i\sqrt{3}$, $z_1 = 2e^{i\pi} = -2$, $z_2 = 2e^{i5\pi/3} = 1 - i\sqrt{3}$. Each has modulus 2, so all three lie on the circle $|z| = 2$ — they form an equilateral triangle inscribed in that circle, not on the unit circle. This illustrates the general principle: the n th roots of w lie on the circle $|z| = \sqrt[n]{|w|}$.

8.5 Chapter Revision Map: Choosing the Right Form

Throughout this chapter you have met three faces of a complex number. Choosing the right one is half the battle in the examination.

Form	Best for	Typical tasks
Cartesian $z = x + iy$	Addition, subtraction, conjugates; converting loci to Cartesian equations	Simplifying expressions, solving equations with real/imaginary parts, locus equations
Polar $r(\cos \theta + i \sin \theta)$	Multiplication, division, arguments, loci involving arg	Products and quotients, argument conditions, Thales-type loci
Exponential $re^{i\theta}$	Powers, roots, De Moivre, trigonometric identities	Computing z^n , n th roots, expressing $\cos^n \theta$ in multiple angles and conversely

KEY POINTS Key points of the section

- $|z - a| = r$: circle, centre a , radius r . $|z - a| = |z - b|$: perpendicular bisector of $[AB]$.
- $\arg(z - a) = \theta$: half-line from a (a excluded). $\arg\left(\frac{z - a}{z - b}\right) = \pm \frac{\pi}{2}$: circle of diameter $[AB]$.
- Inequalities give regions: discs, annuli, sectors; test one interior point; dashed boundary for strict inequalities.
- Cartesian equation: set $z = x + iy$, compute moduli, square, simplify.
- Powers and roots: switch to exponential form and use De Moivre.

EXERCISE 10 Practice

1. Find and sketch the locus $|z + 2 - i| = 3$; give its Cartesian equation.
2. Show that $|z - 3| = |z + 3i|$ is a line and find its equation.
3. Sketch the region defined by $|z| < 2$ and $\frac{\pi}{4} \leq \arg z \leq \frac{3\pi}{4}$.
4. Describe the locus $\arg\left(\frac{z - 2i}{z - 2}\right) = \frac{\pi}{2}$.
5. Find the points of the circle $|z - 1| = 2$ where $\arg(z - 1) = \frac{\pi}{3}$, giving them in Cartesian form.

SOLUTION Exercise 1

1. Circle of centre $-2 + i$, radius 3: $(x + 2)^2 + (y - 1)^2 = 9$.

2. Bisector of $(3, 0)$ and $(0, -3)$: squaring gives $-6x = 6y$, i.e. $y = -x$.
3. Open disc of radius 2 (dashed circle) intersected with the sector between the rays at $\frac{\pi}{4}$ and $\frac{3\pi}{4}$ (solid rays, origin excluded).
4. Semicircle of diameter joining $2i$ and 2 , endpoints excluded.
5. $z = 1 + 2e^{i\pi/3} = 1 + 2\left(\frac{1}{2} + i\frac{\sqrt{3}}{2}\right) = 2 + i\sqrt{3}$.

DID YOU KNOW?**Why loci matter beyond the classroom**

Locus thinking with complex numbers is the seed of conformal mapping, a tool engineers use to study airflow around a wing or the electric field around a conductor: complicated regions of the plane are transformed into discs or half-planes where the equations become easy. The same mathematics governs the stability criteria used when designing control systems — a modern echo of the humble circle $|z - a| = r$ you have just mastered.

9 INTEGRATION ACTIVITY

9.1 Aims of the activity

This integration activity is designed to consolidate your mastery of complex numbers by placing you in a realistic engineering context. By the end of this activity, you should be able to:

- Perform algebraic operations (addition, multiplication, division) on complex numbers in Cartesian form and interpret the results physically.
- Convert fluently between Cartesian, polar (trigonometric), and exponential forms.
- Apply De Moivre's theorem to compute powers of complex numbers efficiently.
- Interpret the modulus as a magnitude (impedance magnitude) and the argument as a phase shift in an AC circuit.
- Sketch and describe loci in the Argand diagram, linking geometric descriptions to algebraic equations.
- Communicate mathematical reasoning clearly, justifying each step as required in the GCE Advanced Level examination.

9.2 Situation

Context: You are a team of junior engineers attached to the Direction de la Distribution at ENEO (Energy of Cameroon) in Yaoundé. Your unit is analysing a section of the low-voltage alternating current (AC) network supplying the Mfoundi district. In AC circuit theory, opposition to current is not a simple resistance but a complex impedance $Z = R + iX$, where R is the resistance (real part) and X is the reactance (imaginary part). The modulus $|Z|$ gives the magnitude of the impedance (in ohms, Ω), and the argument $\arg(Z)$ gives the phase difference between voltage and current.

Two series branches in the network have been modelled with the following impedances:

$$Z_1 = 3 + 4i \, \Omega, \quad Z_2 = 1 - 2i \, \Omega.$$

The supply voltage across the combination is given in exponential form as $V = 220 e^{i\pi/3}$ volts (RMS value).

Your team must prepare a technical note for the senior engineer, answering the questions below. All calculations must be shown step by step, and final answers given in the requested forms. Where an Argand diagram is required, draw it accurately to scale on graph paper (or using geometry software) and include it in your report.

9.3 Tasks

1. Series and parallel combinations.

- (a) Compute the total impedance $Z_{\text{series}} = Z_1 + Z_2$ when the two branches are connected in series. Express your answer in the form $a + ib$.

- (b) Compute the equivalent impedance $Z_{\text{parallel}} = \frac{Z_1 Z_2}{Z_1 + Z_2}$ when the two branches are connected in parallel. Express your answer in the form $a + ib$ (simplify the fraction completely).

2. **Polar and exponential forms of Z_1 .**

- (a) Calculate the modulus $|Z_1|$ and the principal argument $\arg(Z_1)$ (in radians, to three significant figures).
 (b) Write Z_1 in polar (trigonometric) form: $r(\cos \theta + i \sin \theta)$.
 (c) Write Z_1 in exponential form: $re^{i\theta}$.
 (d) Interpret physically: what do $|Z_1|$ and $\arg(Z_1)$ represent in the AC circuit?

3. **Current calculation using exponential form.** Given the supply voltage $V = 220 e^{i\pi/3}$ V across Z_1 alone, use the exponential forms to compute the current $I = \frac{V}{Z_1}$. Give your answer in exponential form $I = I_0 e^{i\phi}$, stating the magnitude I_0 (in amperes) and the phase ϕ (in radians, to three significant figures). Explain why the exponential form makes this division particularly simple.

4. **De Moivre's theorem and Z_1^3 .**

- (a) Use De Moivre's theorem to compute Z_1^3 directly from the polar/exponential form of Z_1 . Give the result in both polar and Cartesian ($a + ib$) forms.
 (b) If the same voltage V were applied across a hypothetical impedance Z_1^3 , how would the magnitude of the current compare to that in Task 3? Explain without recalculating the current.

5. **Locus on the Argand diagram.**

- (a) On an Argand diagram, sketch the locus of all points representing complex impedances Z such that $|Z| = |Z_1|$. Use a scale of 1 cm per ohm. Clearly mark the positions of Z_1 , Z_2 , Z_{series} , and Z_{parallel} on the same diagram.
 (b) Describe the locus in words and give its Cartesian equation.
 (c) Which of the four impedances (Z_1 , Z_2 , Z_{series} , Z_{parallel}) lie exactly on this locus? Justify your answer numerically.

9.4 Model answer

WORKED EXAMPLE 22 Task 1: Series and parallel combinations

1(a) **Series impedance.** In series, impedances add. Add the real parts together and the imaginary parts together:

$$Z_{\text{series}} = Z_1 + Z_2 = (3 + 4i) + (1 - 2i) = (3 + 1) + i(4 - 2) = 4 + 2i \, \Omega.$$

1(b) Parallel impedance. First compute the product $Z_1 Z_2$, expanding term by term:

$$Z_1 Z_2 = (3 + 4i)(1 - 2i) = 3(1) + 3(-2i) + 4i(1) + 4i(-2i) = 3 - 6i + 4i - 8i^2.$$

Since $i^2 = -1$, we have $-8i^2 = +8$. Hence

$$Z_1 Z_2 = (3 + 8) + i(-6 + 4) = 11 - 2i.$$

From part (a), $Z_1 + Z_2 = 4 + 2i$. Therefore

$$Z_{\text{parallel}} = \frac{Z_1 Z_2}{Z_1 + Z_2} = \frac{11 - 2i}{4 + 2i}.$$

To write this in the form $a + ib$, multiply numerator and denominator by the complex conjugate of the denominator, $4 - 2i = 4 - 2i$:

$$Z_{\text{parallel}} = \frac{(11 - 2i)(4 - 2i)}{(4 + 2i)(4 - 2i)}.$$

Denominator (product of conjugates, giving a real number):

$$(4 + 2i)(4 - 2i) = 4^2 + 2^2 = 16 + 4 = 20.$$

Numerator:

$$(11 - 2i)(4 - 2i) = 44 - 22i - 8i + 4i^2 = 44 - 30i - 4 = 40 - 30i.$$

Thus

$$Z_{\text{parallel}} = \frac{40 - 30i}{20} = \frac{40}{20} - \frac{30}{20}i = 2 - 1.5i \, \Omega.$$

WORKED EXAMPLE 23 Task 2: Polar and exponential forms of Z_1

2(a) Modulus and argument.

$$|Z_1| = \sqrt{3^2 + 4^2} = \sqrt{9 + 16} = \sqrt{25} = 5 \, \Omega.$$

Since $Z_1 = 3 + 4i$ lies in the first quadrant (both real and imaginary parts positive), the principal argument is

$$\arg(Z_1) = \arctan\left(\frac{4}{3}\right) \approx 0.927 \text{ rad (to three significant figures)}.$$

2(b) Polar (trigonometric) form.

$$Z_1 = 5(\cos 0.927 + i \sin 0.927) \, \Omega.$$

(Exact version: since $\cos \theta = \frac{3}{5}$ and $\sin \theta = \frac{4}{5}$, we may write $Z_1 = 5\left(\frac{3}{5} + i\frac{4}{5}\right)$, which is of course just $3 + 4i$ again.)

2(c) Exponential form.

$$Z_1 = 5 e^{0.927i} \Omega.$$

2(d) Physical interpretation.

- The modulus $|Z_1| = 5 \Omega$ is the magnitude of the impedance. It is the ratio of the RMS voltage across the branch to the RMS current through it: $|Z_1| = V_{\text{rms}}/I_{\text{rms}}$. It quantifies the total opposition to the flow of alternating current.
- The argument $\arg(Z_1) \approx 0.927$ rad (about 53.1°) is the phase angle by which the voltage leads the current in this branch. Because the reactance is positive ($X = 4 \Omega$, inductive), the voltage reaches its maximum before the current does.

WORKED EXAMPLE 24 Task 3: Current calculation using exponential form

We have $V = 220 e^{i\pi/3}$ V and $Z_1 = 5 e^{0.927i} \Omega$. Using the quotient rule for exponential forms (divide the moduli, subtract the arguments):

$$I = \frac{V}{Z_1} = \frac{220 e^{i\pi/3}}{5 e^{0.927i}} = \frac{220}{5} e^{i(\pi/3 - 0.927)}.$$

Magnitude: $I_0 = \frac{220}{5} = 44$ A.

Phase: $\frac{\pi}{3} \approx 1.0472$ rad, so

$$\phi = 1.0472 - 0.9273 = 0.1199 \approx 0.120 \text{ rad (to three significant figures).}$$

Hence

$$I = 44 e^{0.120i} \text{ A.}$$

Why the exponential form simplifies the division: in exponential form, division reduces to dividing the moduli and subtracting the arguments — two ordinary real-number operations. This avoids the algebraic manipulation of multiplying numerator and denominator by the complex conjugate, which is required in Cartesian form. It is especially efficient when several impedances are combined, or when powers and roots are needed (as in Task 4).

WORKED EXAMPLE 25 Task 4: De Moivre's theorem and Z_1^3

4(a) Computing Z_1^3 . De Moivre's theorem states that for $n \in \mathbb{Z}$,

$$(re^{i\theta})^n = r^n e^{in\theta}.$$

With $Z_1 = 5 e^{0.9273i}$ (keeping extra precision in the angle to avoid rounding error):

$$Z_1^3 = 5^3 e^{i(3 \times 0.9273)} = 125 e^{2.782i} \Omega^3.$$

Since $3 \times 0.9273 = 2.7819$ rad lies in $(-\pi, \pi]$, this is already the principal argument. The polar form is

$$Z_1^3 = 125 (\cos 2.782 + i \sin 2.782).$$

Converting to Cartesian form with $\cos 2.782 \approx -0.9365$ and $\sin 2.782 \approx 0.3508$:

$$Z_1^3 \approx 125(-0.9365 + 0.3508i) \approx -117 + 43.8i \Omega^3.$$

Exact check by direct multiplication (recommended in the examination when the Cartesian form is simple):

$$Z_1^2 = (3 + 4i)^2 = 9 + 24i + 16i^2 = -7 + 24i,$$

$$Z_1^3 = (-7 + 24i)(3 + 4i) = -21 - 28i + 72i + 96i^2 = -21 + 44i - 96 = -117 + 44i.$$

So the exact answer is

$$Z_1^3 = -117 + 44i \Omega^3 \quad (\text{Cartesian}), \quad Z_1^3 = 125 e^{2.782i} \Omega^3 \quad (\text{exponential}).$$

(The small discrepancy between $44i$ and $43.8i$ comes from rounding the argument to 0.927 ; the exact Cartesian computation confirms $-117 + 44i$.)

4(b) Current magnitude comparison. By De Moivre's theorem, $|Z_1^3| = |Z_1|^3 = 5^3 = 125 \Omega$. With the same voltage applied,

$$I' = \frac{|V|}{|Z_1^3|} = \frac{220}{125} = 1.76 \text{ A}.$$

In Task 3 the current magnitude was $I_0 = 44 \text{ A}$. Since the impedance magnitude has been multiplied by $\frac{|Z_1^3|}{|Z_1|} = \frac{125}{5} = 25$, the current magnitude is divided by 25: indeed $\frac{44}{25} = 1.76$

A. In general, the current magnitude scales as $\frac{1}{|Z_1|^n}$ when the impedance is raised to the power n .

WORKED EXAMPLE 26 Task 5: Locus on the Argand diagram


5(a) Sketch. Draw axes with the horizontal axis = Real part (resistance R) and the vertical axis = Imaginary part (reactance X), using a scale of 1 cm per ohm. The locus $|Z| = |Z_1| = 5$ is the circle centred at the origin with radius 5. Plot the four points:

$$Z_1 = 3 + 4i \rightarrow (3, 4),$$

$$Z_2 = 1 - 2i \rightarrow (1, -2),$$

$$Z_{\text{series}} = 4 + 2i \rightarrow (4, 2),$$

$$Z_{\text{parallel}} = 2 - 1.5i \rightarrow (2, -1.5).$$



Argand diagram: the locus $|Z| = 5$ (circle, centre O , radius 5) and the four impedances. Only Z_1 lies on the circle.

5(b) Description and equation. The locus is the set of all points in the complex plane at a fixed distance 5 from the origin: a circle centred at the origin with radius 5. Writing $Z = x + iy$, the condition $|Z| = 5$ becomes $\sqrt{x^2 + y^2} = 5$, i.e.

$$x^2 + y^2 = 25.$$

5(c) Which impedances lie on the locus? A point lies on the locus if and only if its modulus equals 5. Computing each modulus:

$$|Z_1| = \sqrt{3^2 + 4^2} = \sqrt{25} = 5 \quad \checkmark \text{ (on the locus)}$$

$$|Z_2| = \sqrt{1^2 + (-2)^2} = \sqrt{5} \approx 2.24 \neq 5$$

$$|Z_{\text{series}}| = \sqrt{4^2 + 2^2} = \sqrt{20} \approx 4.47 \neq 5$$

$$|Z_{\text{parallel}}| = \sqrt{2^2 + (-1.5)^2} = \sqrt{6.25} = 2.5 \neq 5$$

Only Z_1 lies exactly on the locus; the other three impedances lie strictly inside the circle since their moduli are all less than 5.

WARNING Common errors to avoid in this type of problem

- Forgetting that $i^2 = -1$ when expanding products: a frequent sign error in $Z_1 Z_2$ and in Z_1^3 .
- Dividing by a complex number without multiplying by the conjugate: $\frac{11 - 2i}{4 + 2i}$ is not $\frac{11}{4} - \frac{2i}{2i}$.
- Rounding the argument too early: using $\theta = 0.93$ instead of 0.9273 in Task 4 shifts the Cartesian result noticeably. Keep at least 4 significant figures in intermediate steps and round only at the end.
- Confusing the locus $|Z| = 5$ (a circle) with loci such as $|Z - Z_1| = |Z - Z_2|$ (a perpendicular bisector) or $\arg(Z - Z_1) = \theta$ (a half-line). Read the condition carefully before sketching.
- Giving the argument in degrees when the question asks for radians (or vice versa). State the unit explicitly.

KEY POINTS Key synthesis points for the examination

- Cartesian form $(a + ib)$ is best for addition and subtraction (series/parallel combinations).
- Polar/Exponential form $(re^{i\theta})$ is best for multiplication, division, powers and roots (De Moivre's theorem): multiply/divide the moduli, add/subtract the arguments.
- Modulus = magnitude (impedance magnitude, voltage/current ratio). Argument = phase shift (voltage leads current if $\arg(Z) > 0$).
- Locus $|Z| = k$ is the circle centred at the origin with radius k ; its Cartesian equation is $x^2 + y^2 = k^2$. To test whether a given complex number lies on a locus, compute its modulus (or substitute into the Cartesian equation).
- In GCE answers: show all steps, give exact values where possible (e.g. $\arg Z_1 = \arctan \frac{4}{3}$), and round only at the final step (usually to 3 significant figures for angles).

10 METHODS AND WORKED EXAMPLES

10.1 Skill 1: Performing Algebraic Operations in $\mathbb{C}$

Every complex number can be written uniquely in the **algebraic form** $z = a + ib$, where $a = \operatorname{Re}(z)$ is the **real part** and $b = \operatorname{Im}(z)$ the **imaginary part** (note: b is a real number). All the usual rules of algebra (commutativity, associativity, distributivity, remarkable identities) remain valid in $\mathbb{C}$; the only new ingredient is the fundamental relation $i^2 = -1$.

METHOD Adding, Subtracting and Multiplying Complex Numbers

To compute with complex numbers written in **algebraic form** $z = a + ib$ ($a, b \in \mathbb{R}$):

1. Treat i as an ordinary letter and expand using the usual rules of algebra (distributivity, identities such as $(a + b)^2 = a^2 + 2ab + b^2$).
2. Replace every occurrence of i^2 by -1 , then $i^3 = -i$, $i^4 = 1$, and use the cycle of powers of i for higher exponents.
3. Group the **real parts** together and the **imaginary parts** together.
4. Write the final answer in the standard form $a + ib$, with $a, b \in \mathbb{R}$.

Reflex: never leave i^2 in a final answer; for instance $2 + 3i^2$ must be simplified to $2 - 3 = -1$.

KEY POINTS The Cycle of Powers of i

$$i^1 = i, \quad i^2 = -1, \quad i^3 = -i, \quad i^4 = 1, \quad i^{n+4} = i^n.$$

To evaluate i^n , divide n by 4 and keep the remainder: $i^n = i^r$ where $n = 4q + r$, $r \in \{0, 1, 2, 3\}$.

WORKED EXAMPLE 27 Computing with Complex Numbers

Given $z_1 = 3 + 2i$ and $z_2 = 1 - 4i$, express each of the following in the form $a + ib$:

- (a) $z_1 + z_2$ (b) $z_1 - 2z_2$ (c) $z_1 z_2$ (d) z_1^2 (e) i^{2023} .

SOLUTION

Solution.

- (a) Add real parts and imaginary parts separately:

$$z_1 + z_2 = (3 + 2i) + (1 - 4i) = (3 + 1) + (2 - 4)i = 4 - 2i.$$

(b) First compute $2z_2 = 2 - 8i$, then:

$$z_1 - 2z_2 = (3 + 2i) - (2 - 8i) = (3 - 2) + (2 + 8)i = 1 + 10i.$$

(c) Expand as with ordinary brackets:

$$\begin{aligned} z_1 z_2 &= (3 + 2i)(1 - 4i) = 3(1) + 3(-4i) + 2i(1) + 2i(-4i) \\ &= 3 - 12i + 2i - 8i^2. \end{aligned}$$

Since $i^2 = -1$, we have $-8i^2 = +8$, so

$$z_1 z_2 = 3 + 8 + (-12 + 2)i = 11 - 10i.$$

(d) Using the identity $(a + b)^2 = a^2 + 2ab + b^2$:

$$z_1^2 = (3 + 2i)^2 = 9 + 12i + 4i^2 = 9 - 4 + 12i = 5 + 12i.$$

(e) The powers of i cycle with period 4. Dividing 2023 by 4: $2023 = 4 \times 505 + 3$, hence

$$i^{2023} = i^{4 \times 505 + 3} = (i^4)^{505} \cdot i^3 = 1 \cdot (-i) = -i.$$

Check (c): $(3+2i)(1-4i)$: real part = $3 \times 1 - 2 \times (-4) = 3 + 8 = 11$ ✓; imaginary part = $3 \times (-4) + 2 \times 1 = -10$ ✓.

10.2 Skill 2: Dividing Complex Numbers Using the Conjugate

Addition and multiplication of complex numbers behave exactly as in $\mathbb{R}$. Division is the first genuinely new operation: a quotient $\frac{z_1}{z_2}$ is not immediately in the form $a + ib$, because its denominator contains i . The remedy is the **complex conjugate**.

DEFINITION Complex Conjugate

The **conjugate** of $z = a + ib$ ($a, b \in \mathbb{R}$) is the complex number

$$\bar{z} = a - ib.$$

Geometrically, $\bar{z}$ is the reflection of z in the real axis. Immediate properties: $z + \bar{z} = 2a = 2\operatorname{Re}(z)$, $z - \bar{z} = 2ib = 2i\operatorname{Im}(z)$, and

$$z \bar{z} = (a + ib)(a - ib) = a^2 + b^2 = |z|^2,$$

which is always a non-negative real number. Moreover z is real if and only if $z = \bar{z}$, and z is purely imaginary if and only if $z = -\bar{z}$ (with $z \neq 0$).

METHOD Quotient of Two Complex Numbers

To write $\frac{z_1}{z_2}$ (with $z_2 = c + id \neq 0$) in the form $a + ib$:

1. Write down the **conjugate** of the denominator: $\overline{z_2} = c - id$ (change only the sign of the imaginary part).
2. Multiply numerator and denominator by $\overline{z_2}$:

$$\frac{z_1}{z_2} = \frac{z_1 \overline{z_2}}{z_2 \overline{z_2}}.$$

3. The denominator becomes the real number $z_2 \overline{z_2} = c^2 + d^2 = |z_2|^2$.

4. Expand the numerator, simplify, and split into real and imaginary parts.

Key formula: $(c + id)(c - id) = c^2 + d^2$ (a sum of squares — always real and positive when $z_2 \neq 0$).

WORKED EXAMPLE 28 Division via the Conjugate

Express $\frac{5+i}{2-3i}$ in the form $a + ib$, where $a, b \in \mathbb{R}$.

SOLUTION

Solution. The conjugate of the denominator $2 - 3i$ is $2 + 3i$. Multiply top and bottom by $2 + 3i$:

$$\frac{5+i}{2-3i} = \frac{(5+i)(2+3i)}{(2-3i)(2+3i)}.$$

Denominator:

$$(2-3i)(2+3i) = 2^2 + 3^2 = 4 + 9 = 13.$$

Numerator:

$$(5+i)(2+3i) = 10 + 15i + 2i + 3i^2 = 10 + 17i - 3 = 7 + 17i.$$

Therefore:

$$\frac{5+i}{2-3i} = \frac{7+17i}{13} = \frac{7}{13} + \frac{17}{13}i.$$

Check: multiply the answer by the denominator: $\left(\frac{7}{13} + \frac{17}{13}i\right)(2-3i) = \frac{1}{13}(14 - 21i + 34i - 51i^2) = \frac{1}{13}(14 + 51 + 13i) = \frac{65+13i}{13} = 5 + i$ ✓.

KEY POINTS Algebraic Properties of the Conjugate

For all $z_1, z_2 \in \mathbb{C}$ (with $z_2 \neq 0$ for the quotient):

$$\overline{z_1 + z_2} = \bar{z}_1 + \bar{z}_2, \quad \overline{z_1 z_2} = \bar{z}_1 \bar{z}_2, \quad \overline{\left(\frac{z_1}{z_2}\right)} = \frac{\bar{z}_1}{\bar{z}_2}, \quad \overline{z^n} = \bar{z}^n, \quad \bar{\bar{z}} = z.$$

These properties are frequently examined: they justify, for example, why non-real roots of real polynomials come in conjugate pairs.

10.3 Skill 3: Solving Equations in $\mathbb{C}$

One of the historical motivations for inventing $\mathbb{C}$ was precisely to give every quadratic equation a solution. In $\mathbb{C}$, the quadratic formula remains valid even when the discriminant is negative.

METHOD Quadratic Equations with Negative Discriminant

To solve $az^2 + bz + c = 0$ ($a, b, c \in \mathbb{R}, a \neq 0$) in $\mathbb{C}$:

1. Compute the discriminant $\Delta = b^2 - 4ac$.
2. If $\Delta < 0$, write $\Delta = -|\Delta|$ so that $\sqrt{\Delta} = i\sqrt{|\Delta|}$.
3. Apply the quadratic formula:

$$z = \frac{-b \pm i\sqrt{|\Delta|}}{2a}.$$

4. The two roots are always **conjugates** of each other when the coefficients are real.

Reflex: for equations of the type $z = x + iy$ with conditions (e.g. z^2 real, or $\frac{z-1}{z+1}$ purely imaginary), substitute $z = x + iy$, expand, and equate real and imaginary parts separately to obtain simultaneous equations in x and y . This is legitimate because two complex numbers are equal if and only if they have the same real part and the same imaginary part.

WORKED EXAMPLE 29 Solving a Quadratic and an Equation with Unknown Real and Imaginary Parts

- (a) Solve in $\mathbb{C}$: $z^2 - 4z + 13 = 0$.
- (b) Find the complex number z such that $z + 2\bar{z} = 6 - 3i$.

SOLUTION

Solution (a). Here $a = 1$, $b = -4$, $c = 13$:

$$\Delta = (-4)^2 - 4(1)(13) = 16 - 52 = -36 < 0.$$

Hence $\sqrt{\Delta} = i\sqrt{36} = 6i$, and

$$z = \frac{4 \pm 6i}{2} = 2 \pm 3i.$$

The solution set is $S = \{2 - 3i, 2 + 3i\}$. Note the roots are conjugates, as expected since the coefficients are real.

Solution (b). Write $z = x + iy$ with $x, y \in \mathbb{R}$; then $\bar{z} = x - iy$. Substituting:

$$(x + iy) + 2(x - iy) = 6 - 3i \implies 3x - iy = 6 - 3i.$$

Equating real parts: $3x = 6$, so $x = 2$. Equating imaginary parts: $-y = -3$, so $y = 3$.

$$z = 2 + 3i$$

Check: $z + 2\bar{z} = (2 + 3i) + 2(2 - 3i) = 2 + 3i + 4 - 6i = 6 - 3i$ ✓.

WARNING Square Roots of a Complex Number

To find the **square roots** of a complex number w (i.e. to solve $z^2 = w$), do not write “ $z = \sqrt{w}$ ” — the symbol $\sqrt{}$ is only defined for non-negative reals. Instead set $z = x + iy$, expand $z^2 = (x^2 - y^2) + 2ixy = w$, equate real and imaginary parts, and use the extra relation $x^2 + y^2 = |w|$ (obtained by taking moduli). You will always obtain exactly two opposite solutions z and $-z$.

10.4 Skill 4: Modulus, Argument and Polar Form

A complex number $z = a + ib$ is represented in the **Argand diagram** by the point $M(a, b)$, called the **affix** (or image) of z . The distance $OM = \sqrt{a^2 + b^2}$ is the **modulus** $|z|$, and the angle θ between the positive real axis and $[OM]$ is an **argument** of z , defined modulo 2π . The **principal argument**, written $\text{Arg}(z)$, is the unique argument in $(-\pi, \pi]$.

METHOD Converting $z = a + ib$ to Polar Form $r(\cos \theta + i \sin \theta)$

1. Compute the **modulus**: $r = |z| = \sqrt{a^2 + b^2}$ (always $r \geq 0$).
2. Find an **argument** θ from

$$\cos \theta = \frac{a}{r}, \quad \sin \theta = \frac{b}{r}.$$

Use both equations to fix the quadrant (a calculator gives only $\tan \theta = b/a$, which is ambiguous).

3. Write $z = r(\cos \theta + i \sin \theta)$, choosing the **principal argument** in $(-\pi, \pi]$ if required.

Reflex: sketch the point on the Argand diagram to confirm the quadrant. Remember:

$|z_1 z_2| = |z_1| |z_2|$, $\left| \frac{z_1}{z_2} \right| = \frac{|z_1|}{|z_2|}$, $\arg(z_1 z_2) = \arg z_1 + \arg z_2$ and $\arg\left(\frac{z_1}{z_2}\right) = \arg z_1 - \arg z_2$ (all modulo 2π).

WORKED EXAMPLE 30 From Algebraic Form to Polar Form

Given $z = -1 + i\sqrt{3}$:

- Find $|z|$ and the principal argument of z .
- Write z in polar form and in exponential form.
- Hence write $\frac{z}{1+i}$ in polar form.

SOLUTION

Solution (a). Modulus:

$$r = |z| = \sqrt{(-1)^2 + (\sqrt{3})^2} = \sqrt{1+3} = \sqrt{4} = 2.$$

Argument: we need θ with

$$\cos \theta = \frac{-1}{2}, \quad \sin \theta = \frac{\sqrt{3}}{2}.$$

Cosine negative and sine positive place θ in the second quadrant. The reference angle is $\frac{\pi}{3}$, so

$$\theta = \pi - \frac{\pi}{3} = \frac{2\pi}{3}.$$

Solution (b). Polar form and exponential form:

$$z = 2 \left(\cos \frac{2\pi}{3} + i \sin \frac{2\pi}{3} \right) = 2e^{i\frac{2\pi}{3}}.$$

Solution (c). For $w = 1 + i$: $|w| = \sqrt{1^2 + 1^2} = \sqrt{2}$, and $\arg w = \frac{\pi}{4}$ (first quadrant, $\cos \theta = \sin \theta = \frac{1}{\sqrt{2}}$). Using the quotient rules:

$$\left| \frac{z}{w} \right| = \frac{|z|}{|w|} = \frac{2}{\sqrt{2}} = \sqrt{2}, \quad \arg \frac{z}{w} = \frac{2\pi}{3} - \frac{\pi}{4} = \frac{8\pi - 3\pi}{12} = \frac{5\pi}{12}.$$

Therefore

$$\frac{z}{1+i} = \sqrt{2} \left(\cos \frac{5\pi}{12} + i \sin \frac{5\pi}{12} \right).$$

Since $\frac{5\pi}{12} \in (-\pi, \pi]$, this is already the principal argument.

10.5 Skill 5: Applying De Moivre's Theorem

Computing $(a + ib)^n$ by repeated multiplication is hopeless for large n . The polar form turns multiplication into addition of angles, which is the content of De Moivre's theorem.

PROPERTY De Moivre's Theorem

For every real number θ and every integer $n \in \mathbb{Z}$:

$$(\cos \theta + i \sin \theta)^n = \cos(n\theta) + i \sin(n\theta).$$

Consequently, if $z = r(\cos \theta + i \sin \theta)$, then $z^n = r^n(\cos(n\theta) + i \sin(n\theta))$. (Proof by induction on $n \geq 0$ using the addition formulae; extension to negative n via $z^{-1} = \bar{z}/|z|^2$. The proof is short and may be asked.)

METHOD Powers of Complex Numbers via De Moivre

To compute z^n for large n :

1. Convert z to polar form $z = r(\cos \theta + i \sin \theta)$.
2. Apply **De Moivre's theorem**:

$$z^n = r^n(\cos(n\theta) + i \sin(n\theta)).$$

3. Reduce $n\theta$ modulo 2π to express the result with a standard angle, then convert back to algebraic form if required.

Reflex: never expand $(a + ib)^n$ by the binomial theorem for large n — De Moivre is always faster and safer.

WORKED EXAMPLE 31 Computing a High Power

Let $z = 1 + i\sqrt{3}$. Compute z^{12} , giving your answer in the form $a + ib$.

SOLUTION

Solution. Step 1 — Polar form.

$$r = |z| = \sqrt{1+3} = 2; \quad \cos \theta = \frac{1}{2}, \sin \theta = \frac{\sqrt{3}}{2} \implies \theta = \frac{\pi}{3}.$$

$$\text{So } z = 2\left(\cos \frac{\pi}{3} + i \sin \frac{\pi}{3}\right).$$

Step 2 — De Moivre.

$$z^{12} = 2^{12}\left(\cos \frac{12\pi}{3} + i \sin \frac{12\pi}{3}\right) = 4096(\cos 4\pi + i \sin 4\pi).$$

Step 3 — Reduce the angle. Since 4π is a multiple of 2π :

$$\cos 4\pi = 1, \quad \sin 4\pi = 0.$$

Therefore

$$z^{12} = 4096(1 + 0i) = 4096.$$

The result is a positive real number — consistent with the fact that $\arg z = \frac{\pi}{3}$ and $12 \times \frac{\pi}{3} = 4\pi \equiv 0 \pmod{2\pi}$.

10.6 Skill 6: Trigonometric Applications of De Moivre

De Moivre's theorem works in both directions: it converts powers of $\cos x$ and $\sin x$ into multiple angles (linearisation, useful for integration), and conversely it expands $\cos nx$ and $\sin nx$ as polynomials in $\cos x$ and $\sin x$.

METHOD Powers of $\cos x$ and $\sin x$ into Multiple Angles (and conversely)

(A) Powers $\rightarrow$ multiple angles. Set $z = \cos x + i \sin x$, so $z + z^{-1} = 2 \cos x$ and $z - z^{-1} = 2i \sin x$.

1. Write $\cos^n x = \left(\frac{z + z^{-1}}{2}\right)^n$ (or $\sin^n x = \left(\frac{z - z^{-1}}{2i}\right)^n$).

2. Expand with the binomial theorem and group symmetric terms $z^k + z^{-k} = 2 \cos kx$.

(B) Multiple angles $\rightarrow$ powers. Expand $(\cos x + i \sin x)^n$ by the binomial theorem and equate real parts (for $\cos nx$) or imaginary parts (for $\sin nx$).

WORKED EXAMPLE 32 Linearising $\cos^4 x$ and Expanding $\cos 3x$

(a) Express $\cos^4 x$ as a sum of cosines of multiples of x .

(b) Express $\cos 3x$ in terms of powers of $\cos x$.

SOLUTION

Solution (a). Let $z = \cos x + i \sin x$, so $z + z^{-1} = 2 \cos x$ and $z^k + z^{-k} = 2 \cos kx$. Then

$$(2 \cos x)^4 = (z + z^{-1})^4 = z^4 + 4z^2 + 6 + 4z^{-2} + z^{-4}.$$

Grouping symmetric terms:

$$16 \cos^4 x = (z^4 + z^{-4}) + 4(z^2 + z^{-2}) + 6 = 2 \cos 4x + 8 \cos 2x + 6.$$

Dividing by 16:

$$\cos^4 x = \frac{1}{8} \cos 4x + \frac{1}{2} \cos 2x + \frac{3}{8}.$$

Check at $x = 0$: $\text{RHS} = \frac{1}{8} + \frac{1}{2} + \frac{3}{8} = 1 = \cos^4 0$ ✓.

Solution (b). By De Moivre and the binomial theorem:

$$(\cos x + i \sin x)^3 = \cos^3 x + 3i \cos^2 x \sin x + 3i^2 \cos x \sin^2 x + i^3 \sin^3 x.$$

The real part is $\cos 3x$:

$$\cos 3x = \cos^3 x - 3 \cos x \sin^2 x = \cos^3 x - 3 \cos x (1 - \cos^2 x).$$

Hence

$$\cos 3x = 4 \cos^3 x - 3 \cos x.$$

Check at $x = \frac{\pi}{3}$: $\cos \pi = -1$ and $4\left(\frac{1}{2}\right)^3 - 3\left(\frac{1}{2}\right) = \frac{1}{2} - \frac{3}{2} = -1$ ✓.

10.7 Skill 7: Finding the n th Roots of a Complex Number

In $\mathbb{R}$, the equation $x^n = a$ has at most two solutions. In $\mathbb{C}$, the equation $z^n = w$ (with $w \neq 0$) always has **exactly n distinct solutions**: this is one of the great strengths of the complex number system.

METHOD The n th Roots of $w = re^{i\theta}$

1. Write the number in polar/exponential form: $w = r(\cos \theta + i \sin \theta)$.
2. The n roots are given by

$$z_k = r^{1/n} \left(\cos \frac{\theta + 2k\pi}{n} + i \sin \frac{\theta + 2k\pi}{n} \right), \quad k = 0, 1, 2, \dots, n-1.$$

3. List the roots for each value of k ; stop at $k = n-1$ (further values repeat earlier roots).
4. Geometry: the roots lie on the circle of radius $r^{1/n}$, equally spaced at angles $\frac{2\pi}{n}$ — they are the vertices of a regular n -gon.

Special case (cube roots of unity): the roots of $z^3 = 1$ are $1, \omega = e^{2i\pi/3} = -\frac{1}{2} + i\frac{\sqrt{3}}{2}, \omega^2 = \bar{\omega}$, with $1 + \omega + \omega^2 = 0$ and $\omega^3 = 1$.

WORKED EXAMPLE 33 Cube Roots of a Complex Number

Find all the cube roots of $z = -8$, giving them in algebraic form, and represent them on an Argand diagram.

SOLUTION

Solution. Step 1 — Polar form. The number -8 lies on the negative real axis:

$$-8 = 8(\cos \pi + i \sin \pi), \quad r = 8, \theta = \pi.$$

Step 2 — Apply the formula with $n = 3$, $r^{1/3} = 8^{1/3} = 2$:

$$z_k = 2 \left(\cos \frac{\pi + 2k\pi}{3} + i \sin \frac{\pi + 2k\pi}{3} \right), \quad k = 0, 1, 2.$$

Step 3 — List the roots.


$$k = 0 : z_0 = 2 \left(\cos \frac{\pi}{3} + i \sin \frac{\pi}{3} \right) = 2 \left(\frac{1}{2} + i \frac{\sqrt{3}}{2} \right) = 1 + i\sqrt{3}.$$

$$k = 1 : z_1 = 2(\cos \pi + i \sin \pi) = -2.$$

$$k = 2 : z_2 = 2 \left(\cos \frac{5\pi}{3} + i \sin \frac{5\pi}{3} \right) = 2 \left(\frac{1}{2} - i \frac{\sqrt{3}}{2} \right) = 1 - i\sqrt{3}.$$

Check: $(-2)^3 = -8$ ✓; $(1 + i\sqrt{3})^2 = 1 + 2i\sqrt{3} - 3 = -2 + 2i\sqrt{3}$, and $(1 + i\sqrt{3})^3 = (-2 + 2i\sqrt{3})(1 + i\sqrt{3}) = -2 - 2i\sqrt{3} + 2i\sqrt{3} + 6i^2 = -2 - 6 = -8$ ✓.

The three roots have modulus 2 and arguments $\frac{\pi}{3}, \pi, \frac{5\pi}{3}$: they form an equilateral triangle inscribed in the circle of radius 2 centred at the origin.



The cube roots of -8 : vertices of an equilateral triangle on the circle $|z| = 2$.

10.8 Skill 8: Loci in the Complex Plane

A **locus** is the set of points $M(z)$ satisfying a given condition. Because $|z - a|$ measures the distance between the points of affixes z and a , and $\arg(z - a)$ measures a direction, conditions on z translate directly into geometry.

METHOD Identifying and Sketching Loci

Translate the given condition on $z = x + iy$ into geometry:

1. $|z - a| = r$: **circle**, centre a , radius r .
2. $|z - a| = |z - b|$: **perpendicular bisector** of the segment joining a and b (points equidistant from a and b).
3. $\arg(z - a) = \theta$: **half-line** (ray) from a (the point a itself excluded) making angle θ with the positive real axis.
4. $|z - a| = k|z - b|$ with $k \neq 1$: circle of Apollonius — substitute $z = x + iy$ and rearrange to recognise centre and radius.

Reflex: if the geometric meaning is unclear, set $z = x + iy$, square the moduli, and simplify to a Cartesian equation.

WORKED EXAMPLE 34 A Perpendicular Bisector and a Circle of Apollonius

- (a) Sketch the locus of points z satisfying $|z - 2i| = |z - 4|$ and find its Cartesian equation.
 (b) Show that the locus $|z| = 2|z - 3|$ is a circle; find its centre and radius.

SOLUTION

Solution (a). The condition says z is equidistant from $A = 2i$ (point $(0, 2)$) and $B = 4$ (point $(4, 0)$): the locus is the perpendicular bisector of $[AB]$. Algebraically, with $z = x + iy$:

$$|x + i(y - 2)|^2 = |(x - 4) + iy|^2 \implies x^2 + (y - 2)^2 = (x - 4)^2 + y^2.$$

Expanding:

$$x^2 + y^2 - 4y + 4 = x^2 - 8x + 16 + y^2 \implies 8x - 4y = 12 \implies 2x - y = 3.$$

The locus is the straight line $y = 2x - 3$ (it passes through the midpoint $(2, 1)$ of $[AB]$ ✓).

Solution (b). Set $z = x + iy$ and square both sides:

$$|z|^2 = 4|z - 3|^2 \implies x^2 + y^2 = 4[(x - 3)^2 + y^2].$$

Expanding the right-hand side:

$$x^2 + y^2 = 4x^2 - 24x + 36 + 4y^2 \implies 3x^2 + 3y^2 - 24x + 36 = 0.$$

Divide by 3:

$$x^2 + y^2 - 8x + 12 = 0 \implies (x - 4)^2 - 16 + y^2 + 12 = 0 \implies (x - 4)^2 + y^2 = 4.$$

This is a circle of centre $(4, 0)$, i.e. the affix 4, and radius 2.

Check with a point on the locus: $z = 2$ gives $|z| = 2$ and $2|z - 3| = 2 \times 1 = 2$ ✓; indeed $(2 - 4)^2 + 0 = 4$ ✓.

WARNING Frequent Errors at the GCE

- Forgetting that $\sqrt{\Delta}$ for $\Delta < 0$ requires i : writing $\sqrt{-36} = -6$ is wrong; $\sqrt{-36} = 6i$.
- Using only $\tan \theta = b/a$ to find the argument: this confuses opposite quadrants. Always use both $\cos \theta = a/r$ and $\sin \theta = b/r$.
- Giving only one n th root: there are always exactly n distinct roots, for $k = 0, 1, \dots, n - 1$.
- In locus problems with $\arg(z - a) = \theta$, the point a itself is excluded (the argument of 0 is undefined).
- Mixing degrees and radians: at Advanced Level, arguments are expected in radians.

11 EXERCISES

11.1 I check my knowledge

EXERCISE 11 Multiple choice questions

For each question, only one answer is correct. Write down the letter of the correct answer.

1. The value of i^{2023} is:
(a) i (b) $-i$ (c) 1 (d) -1
2. If $z = 3 - 4i$, then $|z|$ equals:
(a) 5 (b) 7 (c) 1 (d) 25
3. The conjugate of $z = -2 + 5i$ is:
(a) $2 - 5i$ (b) $-2 - 5i$ (c) $2 + 5i$ (d) $5 - 2i$
4. The exponential form of $z = 2\left(\cos \frac{\pi}{3} + i \sin \frac{\pi}{3}\right)$ is:
(a) $2e^{i\pi/3}$ (b) $e^{2i\pi/3}$ (c) $2e^{3i\pi}$ (d) $2e^{-i\pi/3}$

EXERCISE 12 True or false

State whether each statement is true or false, justifying your answer briefly.

1. For every complex number z , $z + \bar{z}$ is a real number.
2. If $z = i$, then $\arg(z) = 0$.
3. The product of two complex conjugates is always a non-negative real number.
4. The equation $z^2 + 4 = 0$ has no solution in $\mathbb{C}$.
5. If $|z| = 0$, then $z = 0$.

EXERCISE 13 Definitions and vocabulary

1. Define the **modulus** and the **argument** of a non-zero complex number $z = a + ib$.
2. State **De Moivre's theorem**.

3. What is meant by the **principal argument** of a complex number? In which interval is it taken?
4. Explain what an **Argand diagram** is and state what the axes represent.

EXERCISE 14 Direct calculations

1. Write each of the following in the form $a + ib$, where $a, b \in \mathbb{R}$:
 - (a) $(2 + 3i) + (5 - 7i)$;
 - (b) $(1 - 2i)(3 + 4i)$;
 - (c) $\frac{3 + i}{1 - 2i}$.
2. Find the modulus and the principal argument of $z = 1 - i$.
3. Write $z = -2i$ in polar form and in exponential form.
4. Compute $(1 + i)^2$ and deduce the square roots of $2i$.

11.2 I practise**EXERCISE 15** Algebra of complex numbers

Given $z_1 = 2 + i$ and $z_2 = 1 - 3i$, compute each of the following in the form $a + ib$:

1. $z_1 z_2$;
2. $\frac{z_1}{z_2}$;
3. $z_1^2 - 2\bar{z}_2$;
4. $\frac{z_1 + z_2}{z_1 - z_2}$.

EXERCISE 16 Quadratic equations in $\mathbb{C}$

1. Solve in $\mathbb{C}$ the equation $z^2 - 4z + 13 = 0$.
2. Represent the two roots z_1 and z_2 on an Argand diagram.

3. State the modulus and the principal argument of each root.
4. Verify that $z_1 + z_2 = 4$ and $z_1 z_2 = 13$.

EXERCISE 17 Square roots of a complex number

1. Find, in the form $a + ib$, the two square roots of $5 + 12i$.
2. Hence solve in $\mathbb{C}$ the equation

$$z^2 - (3 + i)z + (2 - 2i) = 0.$$

EXERCISE 18 Loci in the complex plane

The complex number z is represented by the point M in the Argand diagram.

1. Describe and sketch the locus of M in each case:
 - (a) $|z - 2 + i| = 3$;
 - (b) $|z - 1| = |z + 3i|$;
 - (c) $\arg(z - 2) = \frac{\pi}{4}$.
2. Find the Cartesian equation of the locus in part (b).

11.3 I prepare for the GCE**EXERCISE 19** Polynomial with a complex root — GCE style

Consider the polynomial $P(z) = z^3 - 5z^2 + 8z - 6$.

1. Show that $1 + i$ is a root of $P(z)$. (3 marks)
2. Write down, without further calculation, another complex root of $P(z)$, justifying your answer. (2 marks)
3. Hence find all the roots of $P(z) = 0$. (4 marks)
4. Represent the three roots on an Argand diagram and show that they form an isosceles triangle. (4 marks)

EXERCISE 20 Polar form, De Moivre and powers — GCE style

Let $z = -1 + i\sqrt{3}$.

1. Find the modulus and the principal argument of z , and write z in polar form and in exponential form. (4 marks)
2. Using De Moivre's theorem, compute z^{15} in the form $a + ib$. (4 marks)
3. Use De Moivre's theorem to prove that

$$\cos 3x = 4 \cos^3 x - 3 \cos x.$$

(4 marks)

4. Express $\cos^4 x$ as a sum of cosines of multiple angles. (4 marks)

EXERCISE 21 Roots of unity and loci — GCE style

Let $j = e^{2i\pi/3}$.

1. Prove that $j^3 = 1$ and that $1 + j + j^2 = 0$. (4 marks)
2. Hence solve in $\mathbb{C}$ the equation $z^3 = 8i$, giving all the roots in the form $a + ib$. (5 marks)
3. Find the four 4th roots of -16 in exponential form, plot them on an Argand diagram, and show that they are the vertices of a square. (5 marks)
4. On the same diagram, shade the region defined by

$$1 \leq |z| \leq 3 \quad \text{and} \quad -\frac{\pi}{4} \leq \arg z \leq \frac{\pi}{4},$$

and find the exact area of this region. (4 marks)

12 SOLUTIONS TO THE EXERCISES

SOLUTION Exercise 1 — Multiple choice questions

- (b) $-i$. The powers of i are periodic with period 4: $i^1 = i$, $i^2 = -1$, $i^3 = -i$, $i^4 = 1$, then the cycle repeats. Dividing 2023 by 4: $2023 = 4 \times 505 + 3$, so $i^{2023} = i^{4 \times 505} \cdot i^3 = (i^4)^{505} \cdot i^3 = 1^{505} \cdot (-i) = -i$.
- (a) 5. For $z = 3 - 4i$, $|z| = \sqrt{3^2 + (-4)^2} = \sqrt{9 + 16} = \sqrt{25} = 5$.
- (b) $-2 - 5i$. The conjugate of $z = a + ib$ is $\bar{z} = a - ib$: only the sign of the imaginary part changes. Here $a = -2$ and $b = 5$, so $\bar{z} = -2 - 5i$.
- (a) $2e^{i\pi/3}$. The polar form $r(\cos \theta + i \sin \theta)$ corresponds, by Euler's formula, to the exponential form $re^{i\theta}$. Here $r = 2$ and $\theta = \pi/3$, so $z = 2e^{i\pi/3}$.

SOLUTION Exercise 2 — True or false

- True. Let $z = a + ib$ with $a, b \in \mathbb{R}$. Then $\bar{z} = a - ib$, so $z + \bar{z} = (a + ib) + (a - ib) = 2a \in \mathbb{R}$. In fact $z + \bar{z} = 2 \operatorname{Re}(z)$.
- False. $z = i$ corresponds to the point $(0, 1)$ on the positive imaginary axis. Its modulus is $|i| = 1$ and its argument is $\frac{\pi}{2}$ (i.e. 90°), not 0. An argument of 0 characterises positive real numbers.
- True. If $z = a + ib$, then $\bar{z} = a - ib$ and

$$z\bar{z} = (a + ib)(a - ib) = a^2 - (ib)^2 = a^2 + b^2 = |z|^2 \geq 0,$$

a non-negative real number.

- False. The equation $z^2 + 4 = 0$ gives $z^2 = -4$, hence $z = \pm\sqrt{-4} = \pm 2i$. These are perfectly valid complex solutions: in $\mathbb{C}$ every quadratic equation has solutions.
- True. $|z| = \sqrt{a^2 + b^2} = 0 \iff a^2 + b^2 = 0$. Since a sum of squares of real numbers is zero only when each term is zero, this is equivalent to $a = 0$ and $b = 0$, i.e. $z = 0$.

SOLUTION Exercise 3 — Definitions and vocabulary

- For a non-zero complex number $z = a + ib$ ($a, b \in \mathbb{R}$):

- The **modulus** of z , denoted $|z|$, is the distance from the origin O to the image point $M(a, b)$ in the Argand diagram: $|z| = \sqrt{a^2 + b^2}$.
- An **argument** of z , denoted $\arg(z)$, is any angle (in radians) that the vector $\vec{OM}$ makes with the positive real axis, measured anticlockwise. It is defined only up to the addition of multiples of 2π .

2. **De Moivre's theorem**: for any integer n and any real number θ ,

$$(\cos \theta + i \sin \theta)^n = \cos(n\theta) + i \sin(n\theta).$$

Equivalently, if $z = r(\cos \theta + i \sin \theta)$, then $z^n = r^n(\cos(n\theta) + i \sin(n\theta))$.

3. The **principal argument** of a non-zero complex number z , denoted $\text{Arg}(z)$, is the unique value of $\arg(z)$ lying in the interval $(-\pi, \pi]$.
4. An **Argand diagram** is a geometric representation of complex numbers as points of a plane equipped with an orthonormal frame. The horizontal axis (the real axis) carries the real part $\text{Re}(z)$ and the vertical axis (the imaginary axis) carries the imaginary part $\text{Im}(z)$. The complex number $z = a + ib$ is represented by the point $M(a, b)$, called the image of z , or equivalently by the vector $\vec{OM}$.

SOLUTION Exercise 4 — Direct calculations

1. (a) $(2 + 3i) + (5 - 7i) = (2 + 5) + i(3 - 7) = 7 - 4i$.

(b) $(1 - 2i)(3 + 4i) = 3 + 4i - 6i - 8i^2 = 3 - 2i - 8(-1) = 11 - 2i$.

(c) Multiply numerator and denominator by the conjugate of the denominator:

$$\frac{3 + i}{1 - 2i} = \frac{(3 + i)(1 + 2i)}{(1 - 2i)(1 + 2i)} = \frac{3 + 6i + i + 2i^2}{1^2 + 2^2} = \frac{3 + 7i - 2}{5} = \frac{1 + 7i}{5} = \frac{1}{5} + \frac{7}{5}i.$$

2. For $z = 1 - i$: $|z| = \sqrt{1^2 + (-1)^2} = \sqrt{2}$. The image point $(1, -1)$ lies in the fourth quadrant, and $\tan \theta = \frac{-1}{1} = -1$, so the principal argument is $\text{Arg}(z) = -\frac{\pi}{4}$.

3. $z = -2i$: modulus $|z| = \sqrt{0^2 + (-2)^2} = 2$. The image point $(0, -2)$ lies on the negative imaginary axis, so $\text{Arg}(z) = -\frac{\pi}{2}$. Polar form: $z = 2\left(\cos\left(-\frac{\pi}{2}\right) + i \sin\left(-\frac{\pi}{2}\right)\right)$. Exponential form: $z = 2e^{-i\pi/2}$.

4. $(1 + i)^2 = 1 + 2i + i^2 = 1 + 2i - 1 = 2i$. Hence $1 + i$ is a square root of $2i$, and the two square roots of $2i$ are $\pm(1 + i)$, i.e. $1 + i$ and $-1 - i$.

SOLUTION Exercise 5 — Algebra of complex numbers

Given $z_1 = 2 + i$ and $z_2 = 1 - 3i$.

- $z_1 z_2 = (2 + i)(1 - 3i) = 2 - 6i + i - 3i^2 = 2 - 5i + 3 = 5 - 5i$.
- $\frac{z_1}{z_2} = \frac{2 + i}{1 - 3i} = \frac{(2 + i)(1 + 3i)}{(1 - 3i)(1 + 3i)} = \frac{2 + 6i + i + 3i^2}{1^2 + 3^2} = \frac{2 + 7i - 3}{10} = \frac{-1 + 7i}{10} = -0.1 + 0.7i$.
- $z_1^2 = (2 + i)^2 = 4 + 4i + i^2 = 3 + 4i$. Also $\bar{z}_2 = \overline{1 - 3i} = 1 + 3i$, so $2\bar{z}_2 = 2 + 6i$. Therefore

$$z_1^2 - 2\bar{z}_2 = (3 + 4i) - (2 + 6i) = 1 - 2i.$$

- $z_1 + z_2 = (2 + i) + (1 - 3i) = 3 - 2i$ and $z_1 - z_2 = (2 + i) - (1 - 3i) = 1 + 4i$. Then

$$\frac{z_1 + z_2}{z_1 - z_2} = \frac{3 - 2i}{1 + 4i} = \frac{(3 - 2i)(1 - 4i)}{(1 + 4i)(1 - 4i)} = \frac{3 - 12i - 2i + 8i^2}{1^2 + 4^2} = \frac{3 - 14i - 8}{17} = \frac{-5 - 14i}{17} = -\frac{5}{17} - \frac{14}{17}i.$$

SOLUTION Exercise 6 — Quadratic equations in $\mathbb{C}$

- Solve $z^2 - 4z + 13 = 0$. The discriminant is


$$\Delta = (-4)^2 - 4(1)(13) = 16 - 52 = -36 = (6i)^2.$$

Since $\Delta < 0$, the equation has two complex conjugate roots:

$$z = \frac{-(-4) \pm 6i}{2(1)} = \frac{4 \pm 6i}{2} = 2 \pm 3i.$$

So $z_1 = 2 + 3i$ and $z_2 = 2 - 3i$.

- The images are the points $A(2, 3)$ and $B(2, -3)$. They have the same real part and opposite imaginary parts, so they are symmetric with respect to the real axis — as expected for conjugate roots.



Images of the conjugate roots $z_1 = 2 + 3i$ and $z_2 = 2 - 3i$: symmetry about the real axis.

3. For $z_1 = 2 + 3i$: $|z_1| = \sqrt{2^2 + 3^2} = \sqrt{13}$. The point $(2, 3)$ is in the first quadrant, so $\text{Arg}(z_1) = \arctan\left(\frac{3}{2}\right) \approx 0.983$ rad. For $z_2 = 2 - 3i$: $|z_2| = \sqrt{13}$ and, by conjugation, $\text{Arg}(z_2) = -\arctan\left(\frac{3}{2}\right) \approx -0.983$ rad. Note that $|z_1| = |z_2|$ and $\text{Arg}(z_2) = -\text{Arg}(z_1)$, as always for conjugates.

4. Sum and product of the roots:

$$z_1 + z_2 = (2 + 3i) + (2 - 3i) = 4, \quad z_1 z_2 = (2 + 3i)(2 - 3i) = 2^2 + 3^2 = 13.$$

These match the coefficients of the equation: for $z^2 - 4z + 13 = 0$ the sum of roots is 4 and the product is 13. Verified.

SOLUTION Exercise 7 — Square roots of a complex number

1. Find the square roots of $5 + 12i$. Let $x + iy$ ($x, y \in \mathbb{R}$) satisfy $(x + iy)^2 = 5 + 12i$. Expanding, $x^2 - y^2 + 2ixy = 5 + 12i$, and equating real and imaginary parts:

$$x^2 - y^2 = 5 \quad (1), \quad 2xy = 12 \Rightarrow xy = 6 \quad (2).$$

Taking moduli of $(x + iy)^2 = 5 + 12i$ gives $x^2 + y^2 = |5 + 12i| = \sqrt{25 + 144} = 13 \quad (3)$. Adding (1) and (3): $2x^2 = 18 \Rightarrow x^2 = 9 \Rightarrow x = \pm 3$. Subtracting: $2y^2 = 8 \Rightarrow y^2 = 4 \Rightarrow y = \pm 2$. Since $xy = 6 > 0$, x and y have the same sign. The two square roots are

$$3 + 2i \quad \text{and} \quad -3 - 2i.$$

Check: $(3 + 2i)^2 = 9 + 12i + 4i^2 = 5 + 12i$. ✓

2. Solve $z^2 - (3 + i)z + (2 - 2i) = 0$. The discriminant is

$$\Delta = (3 + i)^2 - 4(1)(2 - 2i) = (9 + 6i + i^2) - 8 + 8i = (8 + 6i) - 8 + 8i = 14i.$$

We need a square root of $\Delta = 14i$. Observe that $(1 + i)^2 = 2i$, so

$$(\sqrt{7}(1 + i))^2 = 7(1 + i)^2 = 7(2i) = 14i.$$

Thus $\sqrt{\Delta} = \pm\sqrt{7}(1 + i) = \pm(\sqrt{7} + i\sqrt{7})$. The roots are

$$z = \frac{(3 + i) \pm (\sqrt{7} + i\sqrt{7})}{2},$$

that is

$$z_1 = \frac{3 + \sqrt{7}}{2} + i \frac{1 + \sqrt{7}}{2}, \quad z_2 = \frac{3 - \sqrt{7}}{2} + i \frac{1 - \sqrt{7}}{2}.$$

SOLUTION Exercise 8 — Loci in the complex plane

- (a) $|z - 2 + i| = 3 \iff |z - (2 - i)| = 3$. The distance from the image of z to the point $(2, -1)$ is constantly 3: the locus is the circle with centre $2 - i$ (point $(2, -1)$) and radius 3.

(b) $|z - 1| = |z + 3i| \iff |z - 1| = |z - (-3i)|$. The image of z is equidistant from the points $A(1, 0)$ and $B(0, -3)$: the locus is the perpendicular bisector of the segment $[AB]$. Its midpoint is $(\frac{1}{2}, -\frac{3}{2})$; the gradient of $[AB]$ is $\frac{-3-0}{0-1} = 3$, so the perpendicular gradient is $-\frac{1}{3}$. Equation: $y + \frac{3}{2} = -\frac{1}{3}(x - \frac{1}{2})$.

(c) $\arg(z - 2) = \frac{\pi}{4}$. Writing $w = z - 2$, the condition $\arg w = \frac{\pi}{4}$ describes a half-line (ray) starting from the point 2 (i.e. $(2, 0)$), making an angle $\frac{\pi}{4}$ with the positive real axis. The point $(2, 0)$ itself is excluded, because $\arg(0)$ is undefined.

2. Cartesian equation for (b): let $z = x + iy$. Squaring both sides of $|z - 1| = |z + 3i|$:

$$(x - 1)^2 + y^2 = x^2 + (y + 3)^2.$$

Expanding: $x^2 - 2x + 1 + y^2 = x^2 + y^2 + 6y + 9$. Cancelling $x^2 + y^2$:

$$-2x + 1 = 6y + 9 \Rightarrow -2x - 6y = 8 \Rightarrow x + 3y + 4 = 0.$$

This is indeed the straight line found geometrically in (b): substituting the midpoint $(\frac{1}{2}, -\frac{3}{2})$ gives $\frac{1}{2} - \frac{9}{2} + 4 = 0$. ✓

SOLUTION Exercise 9 — Polynomial with a complex root — GCE style

1. Show that $1 + i$ is a root. Substitute $z = 1 + i$ into $P(z) = z^3 - 5z^2 + 8z - 6$. First compute the powers:

$$(1 + i)^2 = 1 + 2i + i^2 = 2i, \quad (1 + i)^3 = (1 + i)(1 + i)^2 = (1 + i)(2i) = 2i + 2i^2 = -2 + 2i.$$

Then

$$P(1 + i) = (-2 + 2i) - 5(2i) + 8(1 + i) - 6 = (-2 + 8 - 6) + (2i - 10i + 8i) = 0 + 0i = 0.$$

Hence $1 + i$ is a root of P . (3 marks)

2. Another root. The coefficients of P are all real, so by the **conjugate root theorem** the complex roots occur in conjugate pairs. Therefore $\overline{1 + i} = 1 - i$ is also a root. (2 marks)

3. Find all the roots. From the two roots $1 + i$ and $1 - i$ we build a real quadratic factor:


$$(z - (1 + i))(z - (1 - i)) = z^2 - ((1 + i) + (1 - i))z + (1 + i)(1 - i) = z^2 - 2z + 2.$$

Since P is monic of degree 3, the remaining factor is linear: $P(z) = (z^2 - 2z + 2)(z - a)$. Comparing constant terms: $-6 = 2 \times (-a)$, so $a = 3$. Check by expansion:

$$(z^2 - 2z + 2)(z - 3) = z^3 - 3z^2 - 2z^2 + 6z + 2z - 6 = z^3 - 5z^2 + 8z - 6. \checkmark$$

The three roots are $z = 1 + i$, $z = 1 - i$ and $z = 3$. (4 marks)

4. Argand diagram and isosceles triangle. The images are $A(1, 1)$, $B(1, -1)$ and $C(3, 0)$.



Triangle formed by the images of the three roots of P .

Distances:

$$AB = |1 - (-1)| = 2, \quad AC = \sqrt{(3 - 1)^2 + (0 - 1)^2} = \sqrt{5}, \quad BC = \sqrt{(3 - 1)^2 + (0 - (-1))^2} = \sqrt{5}.$$

Since $AC = BC = \sqrt{5}$, the triangle ABC is isosceles with apex C . (4 marks)

Mark scheme / Examiner expectations:

- Part (a): correct values of $(1+i)^2$ and $(1+i)^3$ (2 marks), substitution and simplification to 0 (1 mark).
- Part (b): explicit statement of the conjugate root theorem (1 mark), root $1-i$ (1 mark).
- Part (c): quadratic factor $z^2 - 2z + 2$ (1 mark), correct division or comparison of coefficients (2 marks), third root $z = 3$ (1 mark).
- Part (d): correct plot (1 mark), correct distance computations (2 marks), conclusion isosceles (1 mark).

SOLUTION Exercise 10 — Polar form, De Moivre and powers — GCE style

Let $z = -1 + i\sqrt{3}$.

1. Modulus and argument. $|z| = \sqrt{(-1)^2 + (\sqrt{3})^2} = \sqrt{1+3} = 2$. The image point $(-1, \sqrt{3})$ lies in the second quadrant (negative real part, positive imaginary part). We have $\cos \theta = \frac{-1}{2}$ and $\sin \theta = \frac{\sqrt{3}}{2}$, so the principal argument is $\theta = \pi - \frac{\pi}{3} = \frac{2\pi}{3}$. Polar form:

$$z = 2\left(\cos \frac{2\pi}{3} + i \sin \frac{2\pi}{3}\right), \quad \text{exponential form: } z = 2e^{2i\pi/3}.$$

(4 marks)

2. Compute z^{15} using De Moivre's theorem.

$$z^{15} = 2^{15} \left(\cos \left(15 \times \frac{2\pi}{3} \right) + i \sin \left(15 \times \frac{2\pi}{3} \right) \right) = 32768 (\cos(10\pi) + i \sin(10\pi)).$$

Since 10π is an even multiple of π , $\cos(10\pi) = 1$ and $\sin(10\pi) = 0$. Therefore $z^{15} = 32768$, a positive real number.

(4 marks)

3. Prove that $\cos 3x = 4 \cos^3 x - 3 \cos x$. By De Moivre's theorem with $n = 3$:

$$\cos 3x + i \sin 3x = (\cos x + i \sin x)^3.$$

Expanding the right-hand side with the binomial theorem:

$$(\cos x + i \sin x)^3 = \cos^3 x + 3i \cos^2 x \sin x + 3i^2 \cos x \sin^2 x + i^3 \sin^3 x = \cos^3 x + 3i \cos^2 x \sin x - 3 \cos x \sin^2 x - i \sin^3 x$$

Equating the real parts:

$$\cos 3x = \cos^3 x - 3 \cos x \sin^2 x = \cos^3 x - 3 \cos x (1 - \cos^2 x) = 4 \cos^3 x - 3 \cos x. \quad \blacksquare$$

(4 marks)

4. Express $\cos^4 x$ as a sum of cosines of multiple angles. From Euler's formulae, $2 \cos x = e^{ix} + e^{-ix}$. Raising to the fourth power and expanding binomially:

$$2^4 \cos^4 x = (e^{ix} + e^{-ix})^4 = e^{4ix} + 4e^{2ix} + 6 + 4e^{-2ix} + e^{-4ix}.$$

Grouping conjugate terms and using $e^{ikx} + e^{-ikx} = 2 \cos kx$:

$$16 \cos^4 x = (e^{4ix} + e^{-4ix}) + 4(e^{2ix} + e^{-2ix}) + 6 = 2 \cos 4x + 8 \cos 2x + 6.$$

Hence

$$\cos^4 x = \frac{1}{8} \cos 4x + \frac{1}{2} \cos 2x + \frac{3}{8}.$$

(4 marks)

Mark scheme / Examiner expectations:

- Part (a): correct modulus (1 mark), correct quadrant identified and argument $\frac{2\pi}{3}$ (2 marks), correct polar and exponential forms (1 mark).
- Part (b): correct application of De Moivre (2 marks), reduction of the angle 10π (1 mark), final value 32768 (1 mark).
- Part (c): De Moivre stated for $n = 3$ (1 mark), correct binomial expansion (1 mark), equating real parts and using $\sin^2 x = 1 - \cos^2 x$ (2 marks).
- Part (d): use of $2 \cos x = e^{ix} + e^{-ix}$ (1 mark), correct expansion of $(e^{ix} + e^{-ix})^4$ (2 marks), simplification to the required form (1 mark).

SOLUTION Exercise 11 — Roots of unity and loci — GCE style

Let $j = e^{2i\pi/3}$.

1. Prove that $j^3 = 1$ and $1 + j + j^2 = 0$. By the laws of exponents:

$$j^3 = (e^{2i\pi/3})^3 = e^{2i\pi} = \cos 2\pi + i \sin 2\pi = 1.$$

Since $j \neq 1$ (indeed $j = -\frac{1}{2} + i\frac{\sqrt{3}}{2}$), factorising $j^3 - 1 = 0$ gives

$$j^3 - 1 = (j - 1)(j^2 + j + 1) = 0 \Rightarrow j^2 + j + 1 = 0,$$

because the factor $j - 1$ is non-zero. Hence $1 + j + j^2 = 0$.

(4 marks)

2. Solve $z^3 = 8i$. Write the right-hand side in exponential form: $8i = 8e^{i\pi/2}$. The three cube roots are

$$z_k = \sqrt[3]{8} e^{i(\pi/2 + 2k\pi)/3} = 2 e^{i(\pi/6 + 2k\pi/3)}, \quad k = 0, 1, 2.$$

Computing each root in Cartesian form:

$$k = 0 : z_0 = 2e^{i\pi/6} = 2 \left(\cos \frac{\pi}{6} + i \sin \frac{\pi}{6} \right) = 2 \left(\frac{\sqrt{3}}{2} + \frac{1}{2}i \right) = \sqrt{3} + i,$$

$$k = 1 : z_1 = 2e^{i5\pi/6} = 2 \left(\cos \frac{5\pi}{6} + i \sin \frac{5\pi}{6} \right) = 2 \left(-\frac{\sqrt{3}}{2} + \frac{1}{2}i \right) = -\sqrt{3} + i,$$

$$k = 2 : z_2 = 2e^{i3\pi/2} = 2 \left(\cos \frac{3\pi}{2} + i \sin \frac{3\pi}{2} \right) = 2(0 - i) = -2i.$$


The three roots are $\sqrt{3} + i$, $-\sqrt{3} + i$ and $-2i$.

(5 marks)

3. Fourth roots of -16 . Write $-16 = 16e^{i\pi}$. The four fourth roots are

$$z_k = \sqrt[4]{16} e^{i(\pi+2k\pi)/4} = 2 e^{i(\pi/4+k\pi/2)}, \quad k = 0, 1, 2, 3,$$


that is $z_0 = 2e^{i\pi/4}$, $z_1 = 2e^{i3\pi/4}$, $z_2 = 2e^{i5\pi/4}$, $z_3 = 2e^{i7\pi/4}$.



The four fourth roots of -16 : vertices of a square inscribed in the circle of radius 2.

All four points lie on the circle of radius 2 centred at the origin, and consecutive arguments differ by exactly $\frac{\pi}{2}$. Hence the four images are the vertices of a square (a regular quadrilateral) inscribed in that circle. (5 marks)

4. Region defined by $1 \leq |z| \leq 3$ and $-\frac{\pi}{4} \leq \arg z \leq \frac{\pi}{4}$. The condition $1 \leq |z| \leq 3$ describes the annulus between the circles of radii 1 and 3 centred at the origin; the condition on the argument restricts to the sector between the rays $\arg z = -\frac{\pi}{4}$ and $\arg z = \frac{\pi}{4}$. The locus is therefore a sector of an annulus, of angle $\frac{\pi}{4} - \left(-\frac{\pi}{4}\right) = \frac{\pi}{2}$.



Sector of an annulus: $1 \leq |z| \leq 3$ and $|\arg z| \leq \pi/4$.

The area of a sector of angle α of an annulus of radii r and R is $\frac{1}{2}\alpha(R^2 - r^2)$. Here:


$$\text{Area} = \frac{1}{2} \times \frac{\pi}{2} \times (3^2 - 1^2) = \frac{\pi}{4}(9 - 1) = 2\pi \text{ square units.}$$

(4 marks)

Mark scheme / Examiner expectations:

- Part (a): $j^3 = 1$ obtained from the laws of exponents (2 marks), factorisation of $j^3 - 1$ and conclusion $1 + j + j^2 = 0$ with the justification $j \neq 1$ (2 marks).
- Part (b): $8i$ written in exponential form (1 mark), correct formula for the cube roots (2 marks), the three roots given in $a + ib$ form (2 marks).
- Part (c): -16 written in exponential form (1 mark), the four roots in exponential form (2 marks), correct plot (1 mark), justification of the square (equal moduli, arguments differing by $\frac{\pi}{2}$) (1 mark).
- Part (d): region correctly described (1 mark), correct sketch (1 mark), area formula for a sector of an annulus (1 mark), correct value 2π (1 mark).

13 SUMMARY SHEET



Mind map of the chapter Complex Numbers.

FICHE BILAN L'essentiel à connaître pour l'examen

Key definitions

- A **complex number** is $z = a + ib$, $a, b \in \mathbb{R}$, where $i^2 = -1$; $a = \operatorname{Re}(z)$, $b = \operatorname{Im}(z)$. If $b = 0$, z is real; if $a = 0$, z is pure imaginary.
- **Conjugate**: $\bar{z} = a - ib$; reflection of z in the real axis.
- **Modulus**: $|z| = \sqrt{a^2 + b^2}$ (distance from O). **Argument**: $\arg z = \theta$ with $\cos \theta = \frac{a}{r}$, $\sin \theta = \frac{b}{r}$; principal value $-\pi < \theta \leq \pi$.
- **Polar form**: $z = r(\cos \theta + i \sin \theta)$; **exponential form**: $z = re^{i\theta}$.

Laws, formulas and theorems

- Powers of i cycle: $i^1 = i$, $i^2 = -1$, $i^3 = -i$, $i^4 = 1$.
- $z\bar{z} = |z|^2$; $\overline{z_1 \pm z_2} = \bar{z}_1 \pm \bar{z}_2$; $\overline{z_1 z_2} = \bar{z}_1 \bar{z}_2$; $\overline{\left(\frac{z_1}{z_2}\right)} = \frac{\bar{z}_1}{\bar{z}_2}$.
- $z + \bar{z} = 2\operatorname{Re}(z)$, $z - \bar{z} = 2i \operatorname{Im}(z)$; z real $\iff z = \bar{z}$.

- Division: multiply numerator and denominator by the conjugate of the denominator.
- $|z_1 z_2| = |z_1| |z_2|$; $\left| \frac{z_1}{z_2} \right| = \frac{|z_1|}{|z_2|}$; $\arg(z_1 z_2) = \arg z_1 + \arg z_2$; $\arg\left(\frac{z_1}{z_2}\right) = \arg z_1 - \arg z_2 \pmod{2\pi}$.
- **De Moivre**: $(\cos \theta + i \sin \theta)^n = \cos n\theta + i \sin n\theta$, $n \in \mathbb{Z}$ (proof by induction for $n \in \mathbb{N}$ is examinable).
- **n th roots**: $z^{1/n} = r^{1/n} \left(\cos \frac{\theta + 2k\pi}{n} + i \sin \frac{\theta + 2k\pi}{n} \right)$, $k = 0, 1, \dots, n-1$; the roots lie on a circle, vertices of a regular n -gon.
- Euler: $\cos \theta = \frac{e^{i\theta} + e^{-i\theta}}{2}$, $\sin \theta = \frac{e^{i\theta} - e^{-i\theta}}{2i}$ (to express $\cos^n \theta$, $\sin^n \theta$ in multiple angles, and conversely).
- Quadratic with real coefficients: non-real roots occur in conjugate pairs; $z = \frac{-b \pm i\sqrt{4ac - b^2}}{2a}$ when $\Delta < 0$.

Methods

- Argument: use $\tan \theta = \frac{b}{a}$ plus the quadrant of (a, b) ; sketch the point first.
- Square roots of $a + ib$: set $(x + iy)^2 = a + ib$, equate parts, use $x^2 + y^2 = \sqrt{a^2 + b^2}$.
- Multiple angles: expand $(\cos \theta + i \sin \theta)^n$ by the binomial theorem, then equate real/imaginary parts.
- Powers to multiple angles: write $z = e^{i\theta}$, expand $\left(z + \frac{1}{z}\right)^n$ or $\left(z - \frac{1}{z}\right)^n$.
- Loci: $|z - a| = r$ circle; $|z - a| = |z - b|$ perpendicular bisector; $\arg(z - a) = \theta$ half-line; $|z - a| = k|z - b|$ circle of Apollonius.

Common mistakes

- Writing $\arg z = \tan^{-1}(b/a)$ without checking the quadrant (e.g. $-1 + i$ has $\arg = \frac{3\pi}{4}$, not $-\frac{\pi}{4}$).
- Forgetting the $2k\pi$ in n th roots, hence finding only one root.
- Dividing without multiplying by the conjugate of the whole denominator.
- Confusing $|z|^2 = z\bar{z}$ with z^2 .
- Mixing degrees and radians; GCE answers are expected in radians, exact form.

GCE tips

- State answers in exact form ($\pi/3$, $\sqrt{2}$, $e^{i\pi/6}$); no decimals unless asked.
- For loci questions, always identify, describe and sketch the locus on an Argand diagram.
- Show the binomial expansion step in De Moivre applications — method marks are awarded for it.

- Check roots by substitution or by verifying the product/sum relations.



Signed • OnBuch+

ONBUCH+ TEACHING TEAM
FOLLOWS THE OFFICIAL MINESEC SYLLABUS

OnBuch+