Scope of Work

SWITCHGEAR AND PROTECTIVE RELAY MAINTENANCE SPECIFICATIONS

2027-2031 Annual Maintenance Contract

ROBERT W. HITE TREATMENT FACILITY (RWHTF)
AND SOUTH THORNTON LIFT STATION

TABLE OF CONTENTS

1. General Requirements
2. Planning, Scheduling and Coordination
3. Safety Requirements
4. Maintenance Levels and Scope Definitions
5. General Inspection and Testing Requirements
6. Switchgear Assemblies
7. Protective Relays
8. Medium-Voltage Circuit Breakers
9. Medium-Voltage Interrupter and Disconnect Switches
10. Medium-Voltage Cable Systems
11. Power and Control Transformers
12. Low-Voltage Power Circuit Breakers
13. Instrument Transformers
14. Additional Electrical Equipment
15. Deficiencies, Repairs and Corrective Work
16. Documentation and Test Reports
17. Completion and Acceptance of Work
Appendix A - Five-Year Maintenance Schedule, 2027-2031
Appendix B - RWHTF and South Thornton Lift Station Equipment Schedule

1. GENERAL REQUIREMENTS

1.1 Purpose and Scope

These specifications establish requirements for inspection, preventive maintenance, testing, servicing, and documentation of designated electrical distribution equipment located at Metro Water Recovery's Robert W. Hite Treatment Facility (RWHTF) and South Thornton Lift Station. The Contractor shall provide all qualified personnel, supervision, labor, test equipment, tools, materials, temporary protective equipment, and other resources necessary to complete the work identified in these specifications and the applicable annual equipment schedule.

Work under this Contract is limited to equipment identified within the RWHTF and South Thornton Lift Station equipment schedules and the approved annual maintenance program for the 2027-2031 contract period.

1.2 Contract Term

The planned maintenance program covers calendar years 2027 through 2031. Annual work shall be performed in accordance with Appendix A and the equipment identified in Appendix B, subject to Metro-approved outage schedules and written direction.

1.3 Applicable Standards and References

- ANSI/NETA MTS-2023, Standard for Maintenance Testing Specifications for Electrical Power Equipment and Systems, as referenced by the equipment schedule.
- Manufacturer instructions and published maintenance recommendations applicable to the equipment being serviced.
- Metro Water Recovery Contractor, Vendor and Visitor Safety Manual - Construction Activities RWHTF, revised February 4, 2026.
- Applicable OSHA requirements, including control of hazardous energy.
- NFPA 70E requirements applicable to electrical safe work practices and qualified persons.

1.4 Definitions and Abbreviations

RWHTF: Robert W. Hite Treatment Facility.

STL: South Thornton Lift Station.

EIT: Electrical/Instrumentation Technician. A Metro Water Recovery Electrical Maintenance employee responsible for electrical and instrumentation maintenance activities.

Full VME: Full Visual, Mechanical, and Electrical maintenance/testing applicable to the scheduled equipment.

V&M Only: Visual and Mechanical inspection/maintenance only. Electrical testing is not included unless specifically directed in writing by Metro.

Contractor: The firm awarded the maintenance/testing contract, including its qualified employees and approved subcontractors.

Metro: Metro Water Recovery.

1.5 Contractor Qualifications

The Contractor shall provide personnel qualified and experienced in maintenance and testing of the equipment included in Appendix B. Personnel performing electrical work shall meet applicable qualification, licensing, and training requirements. Testing shall be performed by personnel competent in the specific equipment and test methods being used.

1.6 Contractor Personnel and Supervision

The Contractor shall provide sufficient qualified personnel and onsite supervision to complete each approved outage within the allotted time. Contractor staffing shall not be based upon the availability of Metro EIT personnel to supplement the Contractor's workforce.

1.7 Equipment, Labor, Tools and Test Equipment

The Contractor shall furnish all labor, test instruments, tools, lifting/handling equipment, temporary protective grounding equipment, PPE, consumables, cleaning materials, contractor locks and tags, and other resources required to complete the scope. Test instruments shall have current calibration traceable to recognized standards and shall be suitable for the measurements performed.

1.8 Metro Water Recovery Responsibilities

Metro EIT personnel will perform or coordinate facility switching necessary to establish and restore the approved electrical outage. Metro may also respond to operational or electrical issues affecting equipment outside or downstream of the Contractor's immediate work scope when determined necessary by Metro.

1.9 Contractor Responsibilities

Following completion of Metro's required switching activities and establishment of the approved outage boundary, the Contractor shall be fully responsible for execution of the contracted maintenance and testing scope. Metro EIT personnel shall not be considered part of the Contractor's planned workforce and shall not be relied upon for routine testing, maintenance, equipment handling, racking, cleaning, adjustment, disassembly, reassembly, or other activities included within the Contractor's scope.

2. PLANNING, SCHEDULING AND COORDINATION

2.1 Annual Maintenance Schedule

The Contractor shall plan work around the annual rotation in Appendix A. Exact dates and outage windows will be coordinated with Metro and Operations.

2.2 Pre-Mobilization Requirements

Before mobilization, the Contractor shall provide required safety documentation, personnel information, calibration records when requested, planned staffing, and a work plan appropriate to the scheduled outage.

2.3 Pre-Construction / Safety Meeting

Contractor representatives shall participate in required pre-construction and safety coordination with Metro project representatives and EHS before work begins.

2.4 Outage Planning and Coordination

The Contractor shall coordinate sequencing, expected durations, equipment access, required clearances, and restoration milestones with Metro before each outage. Work shall not begin until Metro authorizes the outage.

2.5 Metro Switching Responsibilities

Metro EIT personnel will perform or coordinate facility switching required to place the electrical system in the approved configuration for Contractor work.

2.6 Contractor Work Following Switching

Once switching and required Metro hazardous-energy controls are established, the Contractor shall verify the applicable isolation, apply required contractor LOTO, establish an electrically safe work condition appropriate to the task, and independently execute the contracted work.

2.7 Equipment Restoration and Return to Service

The Contractor shall complete reassembly, remove temporary grounds and work equipment, perform final checks, remove Contractor LOTO in accordance with the approved process, and notify Metro when equipment is ready for restoration. Metro will perform or coordinate facility restoration switching.

2.8 Downstream Equipment and Operational Issues

Metro may troubleshoot operational or electrical issues affecting equipment outside or downstream of the Contractor's immediate work scope. Such support does not transfer responsibility for the Contractor's work to Metro.

2.9 Schedule Changes and Emergency Conditions

Metro may suspend, postpone, re-sequence, or terminate outage work when plant conditions, safety, reliability, weather, or operational requirements require restoration of equipment.

3. SAFETY REQUIREMENTS

The Contractor shall comply with the current Metro Water Recovery Contractor, Vendor and Visitor Safety Manual - Construction Activities RWHTF, applicable Metro EHS requirements, and applicable federal, state, and local safety regulations. The Contractor remains responsible for the safety of its personnel and subcontractors.

3.1 Metro Contractor Safety Requirements

Contractor personnel shall complete required Metro safety awareness training/acknowledgment and comply with site access and badge requirements before work.

3.2 Electrical Safety

Electrical work shall be performed de-energized unless specifically authorized through the applicable Metro process. Only qualified persons shall perform electrical work.

3.3 Lockout/Tagout

Metro employees are responsible for shutdown and isolation of equipment or processes under Metro's Control of Hazardous Energy program. Contractor personnel performing service, repair, inspection, testing, or maintenance shall provide and apply their own personal locks and tags as required by Metro's LOTO program.

3.4 Verification of Electrically Safe Work Condition

Before beginning work, the Contractor shall verify proper energy isolation and absence of voltage using appropriately rated and verified test equipment. Metro switching or LOTO does not relieve the Contractor of this verification responsibility.

3.5 Temporary Protective Grounding

The Contractor shall furnish, inspect, apply, and remove temporary protective grounds when required for the work. Grounds shall be appropriately rated and installed by qualified personnel.

3.6 Arc-Flash and Electrical PPE

The Contractor shall provide their personnel with arc-rated PPE and other electrical protective equipment appropriate to the task and hazard.

3.7 Personal Protective Equipment

The Contractor shall provide their personnel with all PPE required by Metro safety requirements, applicable regulations, and the hazards of the work.

3.8 Barricades and Work-Area Control

The Contractor shall establish and maintain barriers, danger/caution controls, and housekeeping necessary to protect personnel and maintain safe access and egress.

3.9 Hazardous Locations

Portable tools and equipment used in classified or hazardous locations shall meet Metro requirements applicable to the area.

3.10 Incident and Emergency Reporting

The Contractor shall immediately report injuries, close calls, property damage, spills, releases, and emergencies in accordance with Metro requirements.

4. MAINTENANCE LEVELS AND SCOPE DEFINITIONS

4.1 General

The annual schedule identifies equipment assigned Full VME or V&M-only maintenance. Equipment-specific activities shall follow the applicable NETA MTS-2023 section identified in Appendix B and manufacturer requirements.

4.2 Full VME Maintenance

Full VME includes the applicable visual inspection, mechanical inspection/maintenance, and electrical testing required by the referenced NETA MTS-2023 section and these specifications. The Contractor shall document as-found and as-left conditions and all test results.

4.3 V&M-Only Maintenance

V&M-only work includes applicable visual and mechanical inspection/maintenance required by the referenced NETA MTS-2023 section and these specifications. Electrical testing is excluded unless specifically identified in the annual scope or authorized in writing by Metro.

4.4 Equipment Included in Scheduled Maintenance

The equipment included in each scheduled location is identified in Appendix B.

4.5 Equipment Not Included in Scope

Equipment not identified in the applicable annual schedule or Appendix B is excluded unless added by written authorization.

4.6 Additional Work and Repairs

Work beyond the equipment included in Appendix B shall not proceed without Metro authorization, except actions necessary to place equipment in a safe condition. Deficiencies shall be reported promptly in accordance with Section 15. District personnel may authorize minor repairs that can be completed onsite and with very minimal time and materials on a case-by-case basis. No repairs or replacements of any type shall be conducted without Metro personnel authorization.

5. GENERAL INSPECTION AND TESTING REQUIREMENTS

5.1 ANSI/NETA Requirements

Perform maintenance and testing in accordance with the NETA MTS-2023 section listed for each equipment item in Appendix B. Where the workbook does not identify a NETA section, the Contractor shall not assume a test requirement and shall request direction from Metro.

5.2 Manufacturer Requirements

Follow applicable manufacturer instructions and maintenance recommendations where they do not conflict with the Contract Documents.

5.3 Test Equipment Calibration

Provide calibrated test equipment suitable for the test performed. Calibration documentation shall be available to Metro upon request and included with final reporting when required.

5.4 Existing Conditions and Pre-Test Inspection

Document visible damage, contamination, loose or missing hardware, abnormal indications, and other significant as-found conditions before maintenance or testing.

5.5 As-Found Testing

Where applicable, obtain and record as-found values before adjustment or corrective maintenance.

5.6 Cleaning, Inspection and Maintenance

Clean, inspect, exercise, lubricate, torque, adjust, and service equipment as required by the applicable maintenance level, NETA section, and manufacturer requirements.

5.7 Electrical Testing

Perform applicable electrical tests using approved methods and record measured values, test parameters, and acceptance criteria.

5.8 Mechanical Inspection and Operation

Inspect operating mechanisms, interlocks, shutters, racking mechanisms, primary/secondary contacts, hardware, and mechanical operation as applicable.

5.9 As-Left Testing

Following maintenance or adjustment, perform applicable as-left verification sufficient to demonstrate that equipment is ready for return to service.

5.10 Acceptance Criteria

Evaluate results using applicable NETA MTS-2023 acceptance criteria, manufacturer requirements, and approved settings or baseline information provided by Metro.

5.11 Abnormal or Failed Test Results

Immediately notify Metro of results indicating unsafe, failed, or potentially unreliable equipment. Do not energize or represent failed equipment as acceptable without Metro direction.

6. SWITCHGEAR ASSEMBLIES

Switchgear assemblies identified in Appendix B shall receive the maintenance level scheduled for the applicable year. Perform applicable inspection, cleaning, mechanical checks, electrical checks, and documentation under the NETA section identified in Appendix B.

7. PROTECTIVE RELAYS

Protective relays shall be inspected and tested in accordance with the NETA section identified in Appendix B. Verify applicable measured quantities, protection functions, logic/interlocks, indications, and outputs appropriate to the scheduled scope. Do not change settings without Metro authorization.

8. MEDIUM-VOLTAGE CIRCUIT BREAKERS

Medium-voltage circuit breakers shall be inspected, serviced, operated, tested, and documented in accordance with the applicable NETA section identified in Appendix B and manufacturer requirements. Contractor responsibility includes equipment handling/racking necessary for its scope unless specifically directed otherwise by Metro.

9. MEDIUM-VOLTAGE INTERRUPTER AND DISCONNECT SWITCHES

Perform applicable visual, mechanical, and electrical maintenance/testing of listed switches in accordance with the NETA section identified in Appendix B.

10. MEDIUM-VOLTAGE CABLE SYSTEMS

Perform applicable inspection and testing of listed cable systems in accordance with the NETA section identified in Appendix B. Coordinate cable isolation, grounding, test boundaries, and restoration with Metro switching activities.

11. POWER AND CONTROL TRANSFORMERS

Perform applicable maintenance/testing of listed power and control transformers in accordance with the NETA section(s) identified in Appendix B. Transformer oil sampling/testing is included only where specifically identified or authorized.

12. LOW-VOLTAGE POWER CIRCUIT BREAKERS

Perform applicable inspection, maintenance, operation, trip-unit verification/testing, and documentation in accordance with the NETA section identified in Appendix B. Contractor responsibility includes equipment handling/racking necessary for its scope unless specifically directed otherwise by Metro.

13. INSTRUMENT TRANSFORMERS

Current transformers and potential transformers identified in Appendix B shall be inspected/tested in accordance with the listed NETA section and the scheduled maintenance level.

14. ADDITIONAL ELECTRICAL EQUIPMENT

Additional listed equipment, including MCOV/surge protective devices, neutral grounding resistors, meters, control power transformers, and other device types appearing in Appendix B, shall be maintained/tested in accordance with the NETA section identified for the item.

15. DEFICIENCIES, REPAIRS AND CORRECTIVE WORK

15.1 Immediate Notification Requirements

Immediately notify Metro of conditions that affect personnel safety, equipment integrity, plant reliability, or the ability to restore equipment.

15.2 Equipment Found Unsafe or Unserviceable

Do not return unsafe or unserviceable equipment to service without Metro direction.

15.3 Minor Adjustments During Maintenance

Routine adjustments inherent to the specified maintenance may be completed and documented. Material repairs or changes require Metro authorization.

15.4 Repairs Requiring Metro Authorization

Provide a clear description of the deficiency, recommended corrective action, effect on serviceability, and supporting test data before proceeding with additional repair work.

15.5 Additional Work Authorization

Additional work shall be performed only after authorization through the Contract's approved change/additional-work process.

15.6 Retesting Following Repairs

Retest affected functions after authorized repairs and document final as-left results.

16. DOCUMENTATION AND TEST REPORTS

16.1 Daily Documentation

Maintain daily records of equipment serviced, work completed, deficiencies, and status of equipment restoration.

16.2 Equipment Identification

Reports shall identify equipment using the applicable tag name, description, section/note, and other identifying information available in Appendix B.

16.3 Test Results
Provide measured results, test parameters, acceptance criteria, and pass/fail or condition assessment as applicable.

16.4 As-Found and As-Left Conditions
Clearly distinguish as-found conditions from final as-left conditions.

16.5 Deficiency Reporting
Provide a concise deficiency summary identifying items requiring corrective action, additional monitoring, or follow-up.

16.6 Photographs
Include photographs when useful to document defects, damage, unusual conditions, repairs, or final condition.

16.7 Test Equipment Calibration Documentation
Provide calibration information for test equipment used when required by Metro or the applicable test method.

16.8 Draft Report
Submit a draft electronic report for Metro review within fifteen (15) calendar days after completion of the applicable outage unless otherwise approved.

16.9 Final Report
Submit a corrected final report incorporating Metro comments and including all required test data, deficiencies, repairs, and supporting documentation.

16.10 Electronic Deliverables
Provide reports and supporting test files electronically in a format acceptable to Metro. Original electronic test data shall be retained and provided when requested.

17. COMPLETION AND ACCEPTANCE OF WORK

17.1 Contractor Final Inspection
Before release for restoration, verify all work is complete, covers/guards are installed, connections are restored, tools/materials are removed, and equipment is ready for service.

17.2 Removal of Grounds, Tools and Contractor LOTO
Remove temporary grounds and Contractor equipment and release Contractor LOTO in accordance with Metro's approved process.

17.3 Equipment Ready-for-Service Notification
Notify the Metro representative when the Contractor has completed its scope and the equipment is ready for restoration.

17.4 Metro Restoration Switching
Metro EIT personnel will perform or coordinate required facility switching to restore the electrical system to the approved operating configuration.

17.5 Final Acceptance
Final acceptance is subject to completion of the scheduled work, satisfactory restoration, delivery of required documentation, and resolution or documented disposition of deficiencies.

APPENDIX A FIVE-YEAR MAINTENANCE SCHEDULE, 2027–2031

The following schedule establishes the planned annual maintenance rotation for the Robert W. Hite Treatment Facility (RWHTF) and South Thornton Lift Station.

Maximum Allowable Outage Durations

The following durations establish the **maximum allowable outage** for scheduled maintenance. The Contractor shall provide sufficient qualified personnel, supervision, equipment, and resources to complete the required work within these limits:

- **901 Bus 1 & Bus 2 – Full VME Maintenance:** Maximum **four (4) consecutive calendar days** per scheduled outage.
- **901 Bus 1 & Bus 2 – V&M Maintenance Only:** Maximum **two (2) consecutive calendar days** per scheduled outage.
- **902, 903, 904, and 905 – Bus 1 & Bus 2:** Maximum **two (2) calendar day per location/outage**.
- **All Other Locations Identified in Appendix A:** Maximum **one (1) calendar day per location/outage.**

2027

- 901 Bus 1 - **Full VME**
  - H-207 ADMIN (901 52-15), this outage is consecutive with 901 Bus 1.
- 901 Bus 2 - **V&M only**
- 905 Bus 1
- 905 Bus 2
- H-270-XMR-8201-01 (TU-4)
- H-280-XMR-8201-01 (TU-20)
- H-953-XMR-8201-01 (TU-12A)
- H-953-XMR-8201-02 (TU-12B)
- H-971-XMR-8201-01
- H-971-XMR-8201-02
- T-STL-XMR-8201-01 (South Thornton Lift Station)
- T-STL-XMR-8201-02 (South Thornton Lift Station)

2028

- 901 Bus 1 - V&M only
- 901 Bus 2 - Full VME
- 904 Bus 1
- 904 Bus 2
- H-274-XMR-8201-01
- H-528-XMR-8201-01 (TU-37A)
- H-528-XMR-8201-02 (TU-37B)
- H-538-XMR-8201-01 (TU-38A)
- H-538-XMR-8201-02 (TU-38B)
- H-832-XMR-8201-01 (TU-13A)
- H-832-XMR-8201-02 (TU-13B)
- H-911-XMR-8201-01
- H-911-XMR-8201-02
- H-913-XMR-8201-01
- H-913-XMR-8201-02
- H-926-XMR-8201-02 (TU-36)
- H-983-XMR-8201-02 (TU-39B)
- H-983-XMR-8201-01 (TU-39A)

2029

- 901 Bus 1 - Full VME

- 901 Bus 2 - V&M only
- 902 Bus 1
- 902 Bus 2
- H-202-E-XMR-8201-01
- H-312-E-XMR-8201-01 (TU-40A)
- H-312-E-XMR-8201-02 (TU-40B)
- H-514-E-XMR-8201-01 (TU-34A)
- H-514-E-XMR-8201-02 (TU-34B)
- H-514-E-XMR-8202-01 (TU-35A)
- H-514-E-XMR-8202-02 (TU-35B)
- H-902-E-XMR-8201-01 (TU-30A)
- H-902-E-XMR-8201-02 (TU-30B)
- H-902-E-XMR-8202-01 (TU-31A)
- H-902-E-XMR-8202-02 (TU-31B)
- H-902-E-XMR-8203-01 (TU-32A)
- H-902-E-XMR-8203-02 (TU-32B)
- H-902-E-XMR-8250-01 (TU-33A)
- H-902-E-XMR-8250-02 (TU-33B)
- H-902-E-XMR-8250-03 (TU-33C)

2030

- 901 Bus 1 - V&M only
- 901 Bus 2 - Full VME
- 903 Bus 1
- 903 Bus 2
- H-260-XMR-8201-01 (TU-43)
- H-527-XMR-8201-01
- H-527-XMR-8201-02
- H-527-XMR-8251-01
- H-527-XMR-8251-02
- H-840-XMR-8201-01 (TU-41A)
- H-840-XMR-8201-02 (TU-41B)
- H-840-XMR-8202-01 (TU-42A)
- H-840-XMR-8202-02 (TU-42B)
- H-931-XMR-8201-01 (TU-8A)
- H-931-XMR-8201-02 (TU-8B)
- H-951-XMR-8201-01 (TU-7A)
- H-951-XMR-8201-02 (TU-7B)

2031

- 901 Bus 1 - Full VME
  - H-207 ADMIN (901 52-15), this outage is consecutive with 901 Bus 1.
- 901 Bus 2 - V&M only
- 905 Bus 1
- 905 Bus 2
- H-270-XMR-8201-01 (TU-4)
- H-280-XMR-8201-01 (TU-20)
- H-953-XMR-8201-01 (TU-12A)
- H-953-XMR-8201-02 (TU-12B)
- H-971-XMR-8201-01
- H-971-XMR-8201-02
- T-STL-XMR-8201-01 (South Thornton Lift Station)
- T-STL-XMR-8201-02 (South Thornton Lift Station)

APPENDIX B RWHTF AND SOUTH THORNTON LIFT STATION EQUIPMENT SCHEDULE

2027 Maintenance Group

901 Bus 1

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
MCOV		76KV MCOV (TO XCEL SWYD BAY1)		7.19.2
GOAB Switch	H-901-GSW-8010-01	89-01 GOAB 1200A (TO XCEL SWYD BAY1)		7.5.1.3
Potential Transformer		LINE-1 PT 115kV 600/1000:1		7.10.2
Meter		MET T-1 SEL-735		7.11.2
Current Transformer		800:5 SR 0.15SB1.8	TO MET T-1	7.10.1
Current Transformer		2000:5 MR 2000:5 TAP C800	TO 87T-1	7.10.1
Protective Relay		87T-1 SEL-487E		7.9.2
Current Transformer		2000:5 MR 2000:5 TAP C800	TO 51-T1	7.10.1
Protective Relay		51-T1 SEL-351S		7.9.2
Circuit Breaker	H-901-BKR-8020-01	52-01 115kV 1200A		7.6.4
Current Transformer		2000:5 MR 2000:5 TAP C800	TO XCEL SWYD 87BT1S/115KV	7.10.1
Current Transformer		2000:5 MR 2000:5 TAP C800	TO XCEL SWYD 87BT1P/115KV	7.10.1
MCOV		76KV MCOV		7.19.2
Power Transformer	H-901-XMR-8001-01	T-1 115-13.2/7.6kV 25/33/42MVA KNAN/KNAF LTC ±10% Z=9.36% @25MVA		7.2.2, 7.12.3
Current Transformer		1200:5 MR 1200:5 TAP C800	TO 51-01	7.10.1
Neutral Grounding Resistor	H-901-NGR-8001-01	NGR-1 400A 20kA 10s 0.4 OHM		7.20.4
MCOV		12.7kV MCOV		7.19.2
GOAB Switch	H-901-GSW-8030-01	89-M1 GOAB 2000A		7.5.1.3
Station Service Transformer	H-901-XMR-8201-01	BUS-1 SST 13.2kV-480/277V 150kVA		7.2.2
Switchgear Assembly	H-901-SWG-8001-01	13.2kV BUS 1 2000A Continuous 25kA 95kV BIL (TYP.)		7.1
MCOV		12.7kV MCOV		7.19.2
Potential Transformer		BUS-1 PT2 7.6kV-120V 63.5:1	101A	7.10.2
Current Transformer		2000:5 MR 2000:5 TAP C200	M1A TO 87B-1	7.10.1
Protective Relay		87B-1 SEL-587Z		7.9.2
Current Transformer		2000:5 MR 2000:5 TAP C200	M1B TO 50AF-1	7.10.1

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Protective Relay		50AF-1 SEL-751		7.9.2
Current Transformer		2000:5 MR 2000:5 TAP C200	51-M1	7.10.1
Protective Relay		51-M1 SEL-351S 101B	101B	7.9.2
Circuit Breaker	52-M1	52-M1 15kV 2000A Eaton Type 15VCP-W25 101B	101B	7.6.3
Current Transformer		2000:5 MR 2000:5 TAP C400	101B TO 87T-1	7.10.1
Potential Transformer		BUS-1 PT1 7.6kV-120V 63.5:1	102A	7.10.2
Current Transformer		1200:5 MR 1200:5 TAP C200	TO 51-11	7.10.1
Protective Relay		51-11 SEL-351S	103A	7.9.2
Circuit Breaker	903 BUS 1	52-11 15kV 1200A Eaton Type 15VCP-W25 103A	103A	7.6.3
Current Transformer		2000:5 MR 2000:5 TAP C400	103A TO 87B-1	7.10.1
MCOV		12.7kV MCOV 103A	103A	7.19.2
Current Transformer		1200:5 MR 1200:5 TAP C200	103B TO 51-12	7.10.1
Protective Relay		51-12 SEL-351S	103B	7.9.2
Circuit Breaker	905 BUS 1	52-12 15kV 1200A Eaton Type 15VCP-W25 103B	103B	7.6.3
Current Transformer		2000:5 MR 2000:5 TAP C400	103B TO 87B-1	7.10.1
MCOV		12.7kV MCOV 103B	103B	7.19.2
Current Transformer		1200:5 MR 1200:5 TAP C200	TO 51-13	7.10.1
Protective Relay		51-13 SEL-351S	104A	7.9.2
Circuit Breaker	902 BUS 1	52-13 15kV 1200A Eaton Type 15VCP-W25 104A	104A	7.6.3
Current Transformer		2000:5 MR 2000:5 TAP C400	TO 87B-1	7.10.1
MCOV		12.7kV MCOV 104A	104A	7.19.2
Current Transformer		1200:5 MR 1200:5 TAP C200	TO 51-14	7.10.1
Protective Relay		51-14 SEL-351S	104B	7.9.2
Circuit Breaker	904 BUS 1	52-14 15kV 1200A Eaton Type 15VCP-W25 104B	104B	7.6.3
Current Transformer		2000:5 MR 2000:5 TAP C400	TO 87B-1	7.10.1
MCOV		12.7kV MCOV 104B	104B	7.19.2
Current Transformer		1200:5 MR 1200:5 TAP C200	TO 51-15	7.10.1
Protective Relay		51-15 SEL-351S	105A	7.9.2
Circuit Breaker	H-207-XMR-8201-01	52-15 15kV 1200A Eaton Type 15VCP-W25 105A	105A	7.6.3
Current Transformer		2000:5 MR 2000:5 TAP C400	TO 87B-1	7.10.1
MCOV		12.7kV MCOV 105A	105A	7.19.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Current Transformer		1200:5 MR 1200:5 TAP C200	TO 51-16	7.10.1
Protective Relay		51-16 SEL-351S	105B	7.9.2
Circuit Breaker	SPARE	52-16 15kV 1200A Eaton Type 15VCP-W25 105B	105B	7.6.3
Current Transformer		2000:5 MR 2000:5 TAP C400	TO 87B-1	7.10.1
MCOV		12.7kV MCOV (SPARE) 105B	105B	7.19.2
Current Transformer		1200:5 MR 1200:5 TAP C200	TO 51-17	7.10.1
Protective Relay		51-17 SEL-351S	106A	7.9.2
Circuit Breaker	SPARE	52-17 15kV 1200A Eaton Type 15VCP-W25 106A	106A	7.6.3
Current Transformer		2000:5 MR 2000:5 TAP C400	TO 87B-1	7.10.1
MCOV		12.7kV MCOV (SPARE) 106A	106A	7.19.2
Current Transformer		1200:5 MR 1200:5 TAP C200	TO 51-18	7.10.1
Protective Relay		51-18 SEL-351S	106B	7.9.2
Circuit Breaker	SPARE	52-18 15kV 1200A Eaton Type 15VCP-W25 106B	106B	7.6.3
Current Transformer		2000:5 MR 2000:5 TAP C400	TO 87B-1	7.10.1
MCOV		12.7kV MCOV (SPARE) 106B	106B	7.19.2
Current Transformer		2000:5 MR 2000:5 TAP C400	T1A TO 87B-2	7.10.1
Circuit Breaker	TIE 1	52-T1 15kV 2000A Eaton Type 15VCP-W25 102B	102B	7.6.3
Current Transformer		2000:5 MR 2000:5 TAP C200	TO 51-T1	7.10.1
Protective Relay		51-T1 SEL-351S	102B	7.9.2
Current Transformer		2000:5 MR 2000:5 TAP C400	T1B TO 50AF-1	7.10.1
MCOV		12.7kV MCOV (TO H-901-SWG-8001-02 52-T2 bus tie/section) 102B	102B	7.19.2

H-207 ADMIN (901 52-15)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable		13.2kV SHIELDED 3/C (FROM 901 52-15 CUBICLE 105A)		7.3.3
MCOV		12.7kV MCOV		7.19.2
Power Transformer	H-207-XMR-8201-01	207 ADMIN BUILDING PADMOUNT 13.2kV-480V, 500kVA		7.2.2, 7.12.3

901 Bus 2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
MCOV		76KV MCOV (TO XCEL SWYD BAY2)		7.19.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
GOAB Switch	H-901-GSW-8010-02	89-02 GOAB 1200A (TO XCEL SWYD BAY2)		7.5.1.3
Potential Transformer		LINE-2 PT 115kV 600/1000:1		7.10.2
Meter		MET T-2 SEL-735		7.11.2
Current Transformer		800:5 SR 0.15SB1.8	TO MET T-2	7.10.1
Current Transformer		2000:5 MR 2000:5 TAP C800	TO 87T-2	7.10.1
Protective Relay		87T-2 SEL-487E		7.9.2
Current Transformer		2000:5 MR 2000:5 TAP C800	TO 51-T2	7.10.1
Protective Relay		51-T2 SEL-351S		7.9.2
Circuit Breaker	H-901-BKR-8020-02	52-02 115kV 1200A		7.6.4
Current Transformer		2000:5 MR 2000:5 TAP C800	TO XCEL SWYD 87BT2S/115KV	7.10.1
Current Transformer		2000:5 MR 2000:5 TAP C800	TO XCEL SWYD 87BT2P/115KV	7.10.1
MCOV		76KV MCOV		7.19.2
Power Transformer	H-901-XMR-8001-02	T-2 115-13.2/7.6kV 25/33/42MVA KNAN/KNAF LTC ±10% Z=9.16% @25MVA		7.2.2, 7.12.3
Current Transformer		1200:5 MR 1200:5 TAP C800	TO 51-02	7.10.1
Neutral Grounding Resistor	H-901-NGR-8001-02	NGR-2 400A 20kA 10s 0.4 OHM		7.20.4
MCOV		12.7kV MCOV		7.19.2
GOAB Switch	H-901-GSW-8030-02	89-M2 GOAB 2000A		7.5.1.3
Station Service Transformer	H-901-XMR-8201-02	BUS-2 SST 13.2kV-480/277V 150kVA		7.2.2
Switchgear Assembly	H-901-SWG-8001-02	13.2kV BUS 2 2000A Continuous 25kA 95kV BIL (TYP.)		7.1
MCOV		12.7kV MCOV		7.19.2
Potential Transformer		BUS-2 PT2 7.6kV-120V 63.5:1	201A	7.10.2
Current Transformer		2000:5 MR 2000:5 TAP C200	M2A TO 87B-2	7.10.1
Protective Relay		87B-2 SEL-587Z	202A	7.9.2
Current Transformer		2000:5 MR 2000:5 TAP C200	M2B TO 50AF-2	7.10.1
Protective Relay		50AF-2 SEL-751	201A	7.9.2
Current Transformer		2000:5 MR 2000:5 TAP C200	51-M2	7.10.1
Protective Relay		51-M2 SEL-351S 201B	201B	7.9.2
Circuit Breaker	52-M2	52-M2 15kV 2000A Eaton Type 15VCP-W25 201B	201B	7.6.3
Current Transformer		2000:5 MR 2000:5 TAP C400	TO 87T-2	7.10.1

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Potential Transformer		BUS-2 PT1 7.6kV-120V 63.5:1	202A	7.10.2
Current Transformer		2000:5 MR 2000:5 TAP C400	T2A TO 87B-1	7.10.1
Circuit Breaker	TIE 2	52-T2 15kV 2000A Eaton Type 15VCP-W25 202B	202B	7.6.3
Current Transformer		2000:5 MR 2000:5 TAP C200	TO 51-T2	7.10.1
Protective Relay		51-T2 SEL-351S	202B	7.9.2
Current Transformer		2000:5 MR 2000:5 TAP C400	T2B TO 50AF-2	7.10.1
MCOV		12.7kV MCOV 202B	202B	7.19.2
Current Transformer		1200:5 MR 1200:5 TAP C200	TO 51-28	7.10.1
Protective Relay		51-28 SEL-351S	206B	7.9.2
Circuit Breaker	SPARE	52-28 15kV 1200A Eaton Type 15VCP-W25 206B	206B	7.6.3
Current Transformer		2000:5 MR 2000:5 TAP C400	TO 87B-2	7.10.1
MCOV		12.7kV MCOV (SPARE) 206B	206B	7.19.2
Current Transformer		1200:5 MR 1200:5 TAP C200	TO 51-27	7.10.1
Protective Relay		51-27 SEL-351S	206A	7.9.2
Circuit Breaker	SPARE	52-27 15kV 1200A Eaton Type 15VCP-W25 206A	206A	7.6.3
Current Transformer		2000:5 MR 2000:5 TAP C400	TO 87B-2	7.10.1
MCOV		12.7kV MCOV (SPARE) 206A	206A	7.19.2
Current Transformer		1200:5 MR 1200:5 TAP C200	TO 51-26	7.10.1
Protective Relay		51-26 SEL-351S	205B	7.9.2
Circuit Breaker	SPARE	52-26 15kV 1200A Eaton Type 15VCP-W25 205B	205B	7.6.3
Current Transformer		2000:5 MR 2000:5 TAP C400	TO 87B-2	7.10.1
MCOV		12.7kV MCOV (SPARE) 205B	205B	7.19.2
Current Transformer		1200:5 MR 1200:5 TAP C200	TO 51-25	7.10.1
Protective Relay		51-25 SEL-351S	205A	7.9.2
Circuit Breaker	SPARE	52-25 15kV 1200A Eaton Type 15VCP-W25 205A	205A	7.6.3
Current Transformer		2000:5 MR 2000:5 TAP C400	TO 87B-2	7.10.1
MCOV		12.7kV MCOV (SPARE) 205A	205A	7.19.2
Current Transformer		1200:5 MR 1200:5 TAP C200	TO 51-24	7.10.1
Protective Relay		51-24 SEL-351S	204B	7.9.2
Circuit Breaker	904 BUS 2	52-24 15kV 1200A Eaton Type 15VCP-W25 204B	204B	7.6.3
Current Transformer		2000:5 MR 2000:5 TAP C400	TO 87B-2	7.10.1

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
MCOV		12.7kV MCOV 204B	204B	7.19.2
Current Transformer		1200:5 MR 1200:5 TAP C200	TO 51-23	7.10.1
Protective Relay		51-23 SEL-351S	204A	7.9.2
Circuit Breaker	902 BUS 2	52-23 15kV 1200A Eaton Type 15VCP-W25 204A	204A	7.6.3
Current Transformer		2000:5 MR 2000:5 TAP C400	TO 87B-2	7.10.1
MCOV		12.7kV MCOV 204A	204A	7.19.2
Current Transformer		1200:5 MR 1200:5 TAP C200	TO 51-22	7.10.1
Protective Relay		51-22 SEL-351S	203B	7.9.2
Circuit Breaker	905 BUS 2	52-22 15kV 1200A Eaton Type 15VCP-W25 203B	203B	7.6.3
Current Transformer		2000:5 MR 2000:5 TAP C400	TO 87B-2	7.10.1
MCOV		12.7kV MCOV 203B	203B	7.19.2
Current Transformer		1200:5 MR 1200:5 TAP C200	TO 51-21	7.10.1
Protective Relay		51-21 SEL-351S	203A	7.9.2
Circuit Breaker	903 BUS 2	52-21 15kV 1200A Eaton Type 15VCP-W25 203A	203A	7.6.3
Current Transformer		2000:5 MR 2000:5 TAP C400	TO 87B-2	7.10.1
MCOV		12.7kV MCOV 203A	203A	7.19.2

905 Bus 1

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Switchgear Assembly	H-905-SWG-8101-01	15kV METACLAD 1200A Continuous 25kA 95kV BIL (TYP.)		7.1
Medium Voltage Cable		13.2kV SHIELDED (FROM H-901-SWG-8001-01 52-12)		7.3.3
MCOV		15kV MCOV (FROM H-901-SWG-8001-01 52-12)	105A	7.19.2
Potential Transformer		BUS-1 PT2 7.6kV-120V 63.5:1	105A TO 51-MAIN-1	7.10.2
Current Transformer		1200:5 C400	105A M1 TO 87B-1	7.10.1
Current Transformer		1200:5 MR 1200:5 TAP C200	105B TO 51-MAIN-1	7.10.1
Protective Relay		51-MAIN-1 SEL-351S	105B	7.9.2
Circuit Breaker	52-MAIN-1	52-MAIN-1 15kV 1200A Eaton Type 15VCP-W25 (FROM H-901-SWG-8001-01 52-12)	105B	7.6.3
Protective Relay		87B-1 SEL-587Z	105A	7.9.2
Potential Transformer		BUS-1 PT1 7.6kV-120V 63.5:1	105A	7.10.2
Control Power Transformer		BUS-1 CPT1 13.2kV-480V 45kVA 3PH (TO H-905-UDS-8410-01 PRIMARY)	101B	7.2.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Circuit Breaker		FD 35k 70A	101B	7.6.1.1
Current Transformer		600:5 MR 600:5 TAP C200	102B TO 51-16	7.10.1
Protective Relay		51-16 SEL-351	102B	7.9.2
Circuit Breaker	H-953-XMR-8201-01 (TU-12A)	52-16 15kV 1200A Eaton Type 15VCP-W25	102B	7.6.3
Current Transformer		1200:5 C400	102B TO 87B-1	7.10.1
MCOV		15kV MCOV	102B	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	102A TO 51-15	7.10.1
Protective Relay		51-15 SEL-351	102A	7.9.2
Circuit Breaker	SPARE	52-15 15kV 1200A Eaton Type 15VCP-W25	102A	7.6.3
Current Transformer		1200:5 C400	102A TO 87B-1	7.10.1
MCOV		15kV MCOV	102A	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	103B TO 51-14	7.10.1
Protective Relay		51-14 SEL-351	103B	7.9.2
Circuit Breaker	H-280-XMR-8201-01 (TU-20)	52-14 15kV 1200A Eaton Type 15VCP-W25	103B	7.6.3
Current Transformer		1200:5 C400	103B TO 87B-1	7.10.1
MCOV		15kV MCOV	103B	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	103A TO 51-13	7.10.1
Protective Relay		51-13 SEL-351	103A	7.9.2
Circuit Breaker	H-525-BLW-7007-01 / H-525-CAP-7007-01	52-13 15kV 1200A Eaton Type 15VCP-W25	103A	7.6.3
Current Transformer		1200:5 C400	103A TO 87B-1	7.10.1
MCOV		15kV MCOV	103A	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	104B TO 51-12	7.10.1
Protective Relay		51-12 SEL-351	104B	7.9.2
Circuit Breaker	H-971-XMR-8201-01	52-12 15kV 1200A Eaton Type 15VCP-W25	104B	7.6.3
Current Transformer		1200:5 C400	104B TO 87B-1	7.10.1
MCOV		15kV MCOV	104B	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	104A TO 51-11	7.10.1
Protective Relay		51-11 SEL-351	104A	7.9.2
Circuit Breaker	SPARE	52-11 15kV 1200A Eaton Type 15VCP-W25	104A	7.6.3
Current Transformer		1200:5 C400	104A TO 87B-1	7.10.1

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
MCOV		15kV MCOV	104A	7.19.2
Protective Relay		25-TIE BE1-25	106A	7.9.2
Protective Relay		SEL-2411 BAY CONTROL (TIE / 52-11 LOWER DOOR)	106A	7.9.2
Current Transformer		1200:5 C400	106B T1 TO 87B-2	7.10.1
Circuit Breaker	52-T1	52-T1 15kV 1200A Eaton Type 15VCP-W25	106B	7.6.3
Current Transformer		1200:5 C400	106B T2 TO 87B-1	7.10.1

905 Bus 2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Protective Relay		25-TIE BE1-25	106A	7.9.2
Protective Relay		SEL-2411 BAY CONTROL	106A	7.9.2
Current Transformer		1200:5 C400	106B T1 TO 87B-2	7.10.1
Circuit Breaker	52-T1	52-T1 15kV 1200A Eaton Type 15VCP-W25	106B	7.6.3
Current Transformer		1200:5 C400	106B T2 TO 87B-1	7.10.1
Medium Voltage Cable		13.2kV SHIELDED (FROM H-901-SWG-8001-02 52-22)		7.3.3
MCOV		15kV MCOV (FROM H-901-SWG-8001-02 52-22)	106B	7.19.2
Potential Transformer		BUS-2 PT2 7.6kV-120V 63.5:1	106B	7.10.2
Current Transformer		1200:5 C400	107B M2 TO 87B-2	7.10.1
Current Transformer		1200:5 MR 1200:5 TAP C200	107B TO 51-MAIN-2	7.10.1
Protective Relay		51-MAIN-2 SEL-351S	107B	7.9.2
Circuit Breaker	52-MAIN-2	52-MAIN-2 15kV 1200A Eaton Type 15VCP-W25 (FROM H-901-SWG-8001-02 52-22)	107B	7.6.3
Protective Relay		87B-2 SEL-587Z	107A	7.9.2
Potential Transformer		BUS-2 PT1 7.6kV-120V 63.5:1	107A	7.10.2
Current Transformer		600:5 MR 600:5 TAP C200	108A TO 51-17	7.10.1
Protective Relay		51-21 SEL-351	108A	7.9.2
Circuit Breaker	SPARE	52-21 15kV 1200A Eaton Type 15VCP-W25	108A	7.6.3
Current Transformer		1200:5 C400	108A TO 87B-2	7.10.1
MCOV		15kV MCOV	108A	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	108B TO 51-20	7.10.1
Protective Relay		51-22 SEL-351	108B	7.9.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Circuit Breaker	H-971-XMR-8201-02	52-22 15kV 1200A Eaton Type 15VCP-W25	108B	7.6.3
Current Transformer		1200:5 C400	108B TO 87B-2	7.10.1
MCOV		15kV MCOV	108B	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	109A TO 51-23	7.10.1
Protective Relay		51-23 SEL-351	109A	7.9.2
Circuit Breaker	H-270-XMR-8201-01 (TU-4)	52-23 15kV 1200A Eaton Type 15VCP-W25	109A	7.6.3
Current Transformer		1200:5 C400	109A TO 87B-2	7.10.1
MCOV		15kV MCOV	109A	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	109B TO 51-24	7.10.1
Protective Relay		51-24 SEL-351	109B	7.9.2
Circuit Breaker	H-953-XMR-8201-02 (TU-12B)	52-24 15kV 1200A Eaton Type 15VCP-W25	109B	7.6.3
Current Transformer		1200:5 C400	109B TO 87B-2	7.10.1
MCOV		15kV MCOV	109B	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	110A TO 51-21	7.10.1
Protective Relay		51-25 SEL-351	110A	7.9.2
Circuit Breaker	SPARE	52-25 15kV 1200A Eaton Type 15VCP-W25	110A	7.6.3
Current Transformer		1200:5 C400	110A TO 87B-2	7.10.1
MCOV		15kV MCOV	110A	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	110B TO 51-22	7.10.1
Protective Relay		51-26 SEL-351	110B	7.9.2
Circuit Breaker	SPARE	52-26 15kV 1200A Eaton Type 15VCP-W25	110B	7.6.3
Current Transformer		1200:5 C400	110B TO 87B-2	7.10.1
MCOV		15kV MCOV	110B	7.19.2
Control Power Transformer		BUS-2 CPT1 13.2kV-480V 45kVA 3PH (TO H-905-UDS-8410-01 SECONDARY)	111B	7.2.2
Circuit Breaker		FD 35k 70A	111B	7.6.1.1

H-270-XMR-8201-01 (TU-4)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable		13.2kV SHIELDED 3/C (FROM 905 52-23 CUBICLE 109A TO H-270-E-XMR-8201-01 TU-4 PADMOUNT)		7.3.3
MCOV		15kV MCOV (TRANSFORMER PRIMARY — ALSO ON 905 109A)		7.19.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Power Transformer	H-270-XMR-8201-01	TU-4 PADMOUNT 13.2kV-480V	Primary TO ATS	7.2.2, 7.12.3
Low Voltage Cable		480V 3Ø (TRANSFORMER TO LC MAIN)		7.3.2

H-280-XMR-8201-01 (TU-20)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
MCOV		13.2kV LA / MCOV (TRANSFORMER PRIMARY)		7.19.2
MV Interrupter Switch	HV-SW-WMS-01	200A HV SWITCH / FU-80E 15kV FUSED (TU-20)		7.5.1.3
Power Transformer	H-280-XMR-8201-01	TU-20 T1 1000 kVA OAFA 13.2kV-480Y/277V MINERAL		7.2.2, 7.12.3
Low Voltage Cable		480V 3Ø (TRANSFORMER TO LC MAIN)		7.3.2
MCOV		480V LA (TRANSFORMER SECONDARY)		7.19.2
Load Center	LC-WMS-19	480Y/277V 3Ø 4W 2000A 50kAIC (SINGLE-ENDED)		7.1
Low Voltage Circuit Breaker	52-MAIN LC-WMS-19	2000AF 2000AT (N.C.)		7.6.1.2
Low Voltage Circuit Breaker	52-WSB DIST PANEL WSB	800AF 800AT (WSB-E101)		7.6.1.2
Low Voltage Circuit Breaker	52-WSA DIST PANEL WSA	800AF 800AT (WSB-E102)		7.6.1.2
Low Voltage Circuit Breaker	52-MCC-WMS-1	800AF 800AT (MCC-WMS-1 WAREHOUSE / MAINT SHOPS)		7.6.1.2
Low Voltage Circuit Breaker	52-HT LIGHTING	800AF 400AT (HT LIGHTING PANEL)		7.6.1.2
Low Voltage Circuit Breaker	52-VEHICLE / SITE LIGHTS	800AF 400AT (VEHICLE SERVICE / SITE POLE LIGHTS)		7.6.1.2
Low Voltage Circuit Breaker	52-SPARE 200AT	800AF 200AT (SPARE)		7.6.1.2
Low Voltage Circuit Breaker	52-BLDG LIGHTS	800AF 400AT (BLDG MOUNTED LIGHTS)		7.6.1.2
Low Voltage Circuit Breaker	52-SPARE 200AT-2	800AF 200AT (SPARE)		7.6.1.2

H-953-XMR-8201-01 (TU-12A)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
MV Interrupter Switch		100E 15.5kV 50kAIC (TU-12A)		7.5.1.3
Power Transformer	H-953-XMR-8201-01	TU-12A 2500kVA 13.2kV-480V		7.2.2, 7.12.3
Low Voltage Cable		480V 3Ø (TRANSFORMER TO LC MAIN)		7.3.2
Medium Voltage Cable	EBB-E1000	480V SECONDARY (TRANSFORMER TO LC MAIN 104C)		7.3.3
Neutral Grounding Resistor		HRG TU-12A 2-480V 2.5A CONT. (SE-330 / ER-600VC) 5:5 / 200:5 CT	103B	7.20.4

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Current Transformer		5:5	103B TO SE-330 / AMMETER	7.10.1
Current Transformer		200:5	103B TO SE-330	7.10.1
Protective Relay		SE-330 NGR MONITOR (AM / 73 / 50G)	103B	7.9.2
Load Center		TU-12 480V 3Ø 3W 3200A 65kAIC (A BUS / MTM)		7.1
Low Voltage Circuit Breaker	MAIN A	3200AF 3000AT LSI (N.C.)	104C	7.6.1.2
Low Voltage Circuit Breaker	BLOWER 8	1600AF 1600AT LSI (BLOWER NO. 8 CONTROL PANEL)	104A	7.6.1.2
Low Voltage Circuit Breaker	MCC AC4-2	1600AF 1600AT LSI (AERATION SECONDARY CONTROL BLDG NO. 4)	103D	7.6.1.2
Low Voltage Circuit Breaker	SPARE	1600AF 1600AT LSI (SPARE) / MCC EBB-1 EAST BLOWER PER OL-1203	103C	7.6.1.2
Low Voltage Circuit Breaker	TIE	3200AF 3000AT LSI (N.O.) (BUS A–BUS B TIE)	102C	7.6.1.2

H-953-XMR-8201-02 (TU-12B)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	EBB-E011	13.2kV SHIELDED 3/C (FROM 905 52-24 CUBICLE 109B)		7.3.3
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
MV Interrupter Switch		100E 15.5kV 50kAIC (TU-12B)		7.5.1.3
Power Transformer	H-953-XMR-8201-02	TU-12B 2500kVA 13.2kV-480V		7.2.2, 7.12.3
Low Voltage Cable		480V 3Ø (TRANSFORMER TO LC MAIN)		7.3.2
Neutral Grounding Resistor		HRG TU-12B 2-480V 2.5A CONT. (SE-330 / ER-600VC) 5:5 / 200:5 CT	102B	7.20.4
Current Transformer		5:5	102B TO SE-330 / AMMETER	7.10.1
Current Transformer		200:5	102B TO SE-330	7.10.1
Protective Relay		SE-330 NGR MONITOR (AM / 73 / 50G)	102B	7.9.2
Load Center		TU-12 480V 3Ø 3W 3200A 65kAIC (B BUS / MTM)		7.1
Low Voltage Circuit Breaker	MAIN B	3200AF 3000AT LSI (N.C.)	101C	7.6.1.2
Low Voltage Circuit Breaker	MCC AC3-2	1600AF 1600AT LSI (AERATION SECONDARY CONTROL BLDG NO. 3)	102A	7.6.1.2
Low Voltage Circuit Breaker	MCC EBB-1	1600AF 1600AT LSI (EAST BLOWER BUILDING)	102D	7.6.1.2
Low Voltage Circuit Breaker	LP-TU-12	800AF 200AT LSI (LP-TU-12 480-208/120V)	103A	7.6.1.2
Low Voltage Circuit Breaker	TIE	3200AF 3000AT LSI (N.O.) (BUS A–BUS B TIE)	102C	7.6.1.2

H-971-XMR-8201-01

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	905-E0101	13.2kV SHIELDED 3/C (FROM 905 52-12 CUBICLE 104B)		7.3.3
MCOV		13.2kV LA / MCOV (TRANSFORMER PRIMARY)		7.19.2
Power Transformer	H-971-XMR-8201-01	1000/1150 kVA KNAN/KNAF 13.2kV-480V		7.2.2, 7.12.3
Medium Voltage Cable	971-E0103	480V SECONDARY (TRANSFORMER TO LC MAIN 101C)		7.3.3
Neutral Grounding Resistor	H-971-HRG-8201-01	HRG 277V 2.5A CONT. 5:5 / 5:0.05 CT (971-E0114 / 971-E0116)	101C	7.20.4
Current Transformer		5:5	TO 50G / AMMETER	7.10.1
Current Transformer		5:0.05	TO 50G	7.10.1
Protective Relay		50G / 73 NGR MONITOR (AM / 73 / 50G)	101C	7.9.2
Load Center		480V 3Ø 3W 1200A 42kAIC (BUS 1 / ATO)		7.1
Low Voltage Circuit Breaker	MAIN 1	1600AF 1200AT EO (N.C.)	101C	7.6.1.2
Control Power Transformer		5kVA CPT 480-120V (FU 600V 10A CLF TD / 250V 20A FNM)	101B	7.2.1
Low Voltage Circuit Breaker	MCC CCB-1/2	800AF 600AT (CHLORINE ELECTRICAL BUILDING)	102A	7.6.1.2
Low Voltage Circuit Breaker	PWC PUMP NO. 2 VFD	800AF 600AT (PWC ELECTRICAL FACILITY)	102B	7.6.1.2
Low Voltage Circuit Breaker	MCC DIS-1	800AF 800AT (DISINFECTION BUILDING)	102C	7.6.1.2
Low Voltage Circuit Breaker	MCC AFF-1	800AF 200AT (AMMONIA FEED BUILDING)	102D	7.6.1.2
Low Voltage Circuit Breaker	TIE 1	1600AF 1200AT EO (N.O.) (ATO / BUS DUCT TO 800kW GEN)	103B	7.6.1.2

H-971-XMR-8201-02

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	905-E0201	13.2kV SHIELDED 3/C (FROM 905 52-20 CUBICLE 108B)		7.3.3
MCOV		13.2kV LA / MCOV (TRANSFORMER PRIMARY)		7.19.2
Power Transformer	H-971-XMR-8201-02	1000/1150 kVA KNAN/KNAF 13.2kV-480V		7.2.2, 7.12.3
Medium Voltage Cable	971-E0104	480V SECONDARY (TRANSFORMER TO LC MAIN 105C)		7.3.3
Neutral Grounding Resistor	H-971-HRG-8201-02	HRG 277V 2.5A CONT. 5:5 / 5:0.05 CT (971-E0115 / 971-E0117)	105C	7.20.4
Current Transformer		5:5	TO 50G / AMMETER	7.10.1
Current Transformer		5:0.05	TO 50G	7.10.1
Protective Relay		50G / 73 NGR MONITOR (AM / 73 / 50G)	105C	7.9.2
Load Center	H-971-LDC-8201-01	480V 3Ø 3W 1200A 42kAIC (BUS 2 / ATO)		7.1

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Low Voltage Circuit Breaker	52-105C MAIN 2	1600AF 1200AT EO (N.C.)	105C	7.6.1.2
Control Power Transformer		5kVA CPT 480-120V (FU 600V 10A CLF TD / 250V 20A FNM)	104A	7.2.1
Low Voltage Circuit Breaker	MCC DIS-2	800AF 800AT (DISINFECTION BUILDING)	104C	7.6.1.2
Low Voltage Circuit Breaker	MCC CCB-3/4	800AF 600AT (CHLORINE ELECTRICAL BUILDING)	104D	7.6.1.2
Low Voltage Circuit Breaker	PWC PUMP NO. 5 VFD	800AF 600AT (PWC ELECTRICAL FACILITY)	105A	7.6.1.2
Low Voltage Circuit Breaker	MCC AFF-2	800AF 200AT (AMMONIA FEED BUILDING)	105D	7.6.1.2
Low Voltage Circuit Breaker	TIE 2	1600AF 1200AT EO (N.O.) (ATO / BUS DUCT TO 800kW GEN)	104B	7.6.1.2

T-STL-XMR-8201-01 - South Thornton Lift Station

Device Type	Tag Name	Description	Section/Note	NETA MTS 2023 Spec
Medium Voltage Cable	STL-E001	13.2kV (XCEL MAPLETON 1754 TO T-STL-SWG-8101-01)		7.3.3
MV Interrupter Switch	T-STL-SWG-8101-01	600A 15kV PADMOUNT SWITCH (50/51) STL-E003 TO XFMR		7.5.2
MCOV		LA (TRANSFORMER PRIMARY)		7.19.2
Power Transformer	T-STL-XMR-8201-01	1000/1150 kVA KNAN/KNAF 13.2kV-480V		7.2.2, 7.12.3
Medium Voltage Cable	STL-E103	480V SECONDARY (XFMR TO LC MAIN 101B)		7.3.3
Neutral Grounding Resistor	T-STL-HRG-8201-01	HRG 277V 2.5A CONT. 5:5 / 5:0.05 CT	101C	7.20.4
Current Transformer		5:5	101C TO 50G / AMMETER	7.10.1
Current Transformer		5:0.05	101C TO 50G	7.10.1
Protective Relay		50G / 73 NGR MONITOR (AM / 73 / 50G)	101C	7.9.2
Protective Relay		SEL-751 50/51/59/27/47/25	101A	7.9.2
Protective Relay		BE1-25 25T1	103A	7.9.2
Load Center	T-STL-LDC-8201-01	480V 3Ø 3W 2000A 65kAIC (BUS A / ATO) OFFSITE STL		7.1
Low Voltage Circuit Breaker	MAIN A T-STL-LDC-8201-01	2000AF 2000AT (N.C.)	101B	7.6.1.2
Low Voltage Circuit Breaker	T-STL-PMP-2550-01	800AF 300AT (PUMP-1 / VFD-2550-01 / STL-E109)	102A	7.6.1.2
Low Voltage Circuit Breaker	T-STL-MCC-8300-01	800AF 600AT (STL-E105)	102B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 300AT (SPARE)	102C	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 600AT (SPARE)	102D	7.6.1.2
Low Voltage Circuit Breaker	T-STL-PMP-2550-03	800AF 300AT (PUMP-3 / VFD-2550-03 / STL-E111)	103C	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 800AT (SPARE)	103D	7.6.1.2
Low Voltage Circuit Breaker	TIE A	2000AF 2000AT (N.O.) (BUS A TIE)	103B	7.6.1.2
Low Voltage Circuit Breaker	TIE B	2000AF 2000AT (N.O.) (BUS B TIE)	105B	7.6.1.2

T-STL-XMR-8201-02 - South Thornton Lift Station

Device Type	Tag Name	Description	Section/Note	NETA MTS 2023 Spec
Medium Voltage Cable	STL-E002	13.2kV (XCEL DERBY 1653 TO T-STL-SWG-8101-02)		7.3.3
MV Interrupter Switch	T-STL-SWG-8101-02	600A 15kV PADMOUNT SWITCH (50/51) STL-E004 TO XFMR		7.5.2
MCOV		LA (TRANSFORMER PRIMARY)		7.19.2
Power Transformer	T-STL-XMR-8201-02	1000/1150 kVA KNAN/KNAF 13.2kV-480V		7.2.2, 7.12.3
Medium Voltage Cable	STL-E104	480V SECONDARY (XFMR TO LC MAIN 107B)		7.3.3
Neutral Grounding Resistor	T-STL-HRG-8201-02	HRG 277V 2.5A CONT. 5:5 / 5:0.05 CT	107C	7.20.4
Current Transformer		5:5	107C TO 50G / AMMETER	7.10.1
Current Transformer		5:0.05	107C TO 50G	7.10.1
Protective Relay		50G / 73 NGR MONITOR (AM / 73 / 50G)	107C	7.9.2
Protective Relay		SEL-751 50/51/59/27/47/25	107A	7.9.2
Protective Relay		BE1-25 25T2	105A	7.9.2
Load Center	T-STL-LDC-8201-01	480V 3Ø 3W 2000A 65kAIC (BUS B / ATO) OFFSITE STL		7.1
Low Voltage Circuit Breaker	MAIN B T-STL-LDC-8201-01	2000AF 2000AT (N.C.)	107B	7.6.1.2
Low Voltage Circuit Breaker	T-STL-PMP-2550-02	800AF 300AT (PUMP-2 / VFD-2550-02 / STL-E110)	105C	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 800AT (SPARE)	105D	7.6.1.2
Low Voltage Circuit Breaker	T-STL-PMP-2550-04	800AF 300AT (PUMP-4 / VFD-2550-04 / STL-E112)	106A	7.6.1.2
Low Voltage Circuit Breaker	T-STL-MCC-8300-02	800AF 600AT (STL-E106)	106B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 300AT (SPARE)	106C	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 600AT (SPARE)	106D	7.6.1.2
Low Voltage Circuit Breaker	TIE A	2000AF 2000AT (N.O.) (BUS A TIE)	103B	7.6.1.2
Low Voltage Circuit Breaker	TIE B	2000AF 2000AT (N.O.) (BUS B TIE)	105B	7.6.1.2
Low Voltage Circuit Breaker	T-STL-GEN-8201-01	2000AF 2000AT (1000kW 480V GEN / STL-E005)	104C	7.6.1.2
Protective Relay		SEL-700G (GENERATOR)	104B	7.9.2
Neutral Grounding Resistor	T-STL-HRG-8201-03	HRG 277V 2.5A CONT. 5:5 / 5:0.05 CT (GENERATOR)	104D	7.20.4

2028 Maintenance Group

901 Bus 1-See 2027 Maintenance Group

901 Bus 2-See 2027 Maintenance Group

904 Bus 1

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Switchgear Assembly	H-904-SWG-8101-01	13.2kV BUS 1 1200A Continuous (TYP.)		7.1
Medium Voltage Cable		13.2kV SHIELDED (FROM H-901-SWG-8001-01 52-14)		7.3.3
MCOV		12.7kV MCOV (FROM H-901-SWG-8001-01 52-14)	106	7.19.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Potential Transformer		1 PT 63.5:1	106	7.10.2
Current Transformer		1200/5 FR	106 TO 87B Bus 1	7.10.1
Current Transformer		1200/5 MR	106 TO 51-MAIN-1	7.10.1
Protective Relay		51-MAIN-1 SEL-351S	106	7.9.2
Circuit Breaker	52-MAIN-1	52-MAIN-1 15kV 1200A Eaton Type 15VCP-W25 (FROM H-901-SWG-8001-01 52-14)	106	7.6.3
Potential Transformer		3 PTs 63.5:1	106	7.10.2
Protective Relay		87B-1 SEL-587Z	106	7.9.2
Control Power Transformer		SST-1 75kVA 7620/13200V GRDY-120/240V OUTDOOR PAD MOUNT #1	108	7.2.2
Circuit Breaker		FD 350A 2P	108	7.6.1.1
Current Transformer		1200/5 FR	108 TO 87B Bus 1	7.10.1
Current Transformer		1200/5 MR	101B TO 51-19	7.10.1
Protective Relay		51-19 SEL-351	101B	7.9.2
Circuit Breaker	H-983-XMR-8201-01 (TU-39A)	52-19 15kV 1200A Eaton Type 15VCP-W25	101B	7.6.3
Current Transformer		1200/5 MR	101B TO 87B Bus 1	7.10.1
MCOV		12.7kV MCOV	101B	7.19.2
Current Transformer		1200/5 MR	101A TO 51-18	7.10.1
Protective Relay		51-18 SEL-351-6	101A	7.9.2
Circuit Breaker	H-528-XMR-8201-01 (TU-37A)	52-18 15kV 1200A Eaton Type 15VCP-W25	101A	7.6.3
Current Transformer		1200/5 FR	101A TO 87B Bus 1	7.10.1
MCOV		12.7kV MCOV	101A	7.19.2
Current Transformer		1200/5 MR	102B TO 51-17	7.10.1
Protective Relay		51-17 SEL-351-6	102B	7.9.2
Circuit Breaker	H-913-XMR-8201-01	52-17 15kV 1200A Eaton Type 15VCP-W25 (FUTURE PAR 1395)	102B	7.6.3
Current Transformer		1200/5 FR	102B TO 87B Bus 1	7.10.1
MCOV		12.7kV MCOV	102B	7.19.2
Current Transformer		1200/5 MR	102A TO 51-16	7.10.1
Protective Relay		51-16 SEL-351-6	102A	7.9.2
Circuit Breaker	SPARE	52-16 15kV 1200A Eaton Type 15VCP-W25	102A	7.6.3
Current Transformer		1200/5 FR	102A TO 87B Bus 1	7.10.1

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
MCOV		12.7kV MCOV	102A	7.19.2
Current Transformer		1200/5 MR	103B TO 51-15	7.10.1
Protective Relay		51-15 SEL-351	103B	7.9.2
Circuit Breaker	H-832-XMR-8201-01 (TU-13A)	52-15 15kV 1200A Eaton Type 15VCP-W25	103B	7.6.3
Current Transformer		1200/5 FR	103B TO 87B Bus 1	7.10.1
MCOV		12.7kV MCOV	103B	7.19.2
Current Transformer		1200/5 MR	103A TO 51-14	7.10.1
Protective Relay		51-14 SEL-351-6	103A	7.9.2
Circuit Breaker	H-538-XMR-8201-01 (TU-38A)	52-14 15kV 1200A Eaton Type 15VCP-W25	103A	7.6.3
Current Transformer		1200/5 FR	103A TO 87B Bus 1	7.10.1
MCOV		12.7kV MCOV	103A	7.19.2
Current Transformer		1200/5 MR	104A TO 51-13	7.10.1
Protective Relay		51-13 SEL-351-6	104A	7.9.2
Circuit Breaker	H-911-XMR-8201-01	52-13 15kV 1200A Eaton Type 15VCP-W25 (FUTURE PAR 1395)	104A	7.6.3
Current Transformer		1200/5 FR	104A TO 87B Bus 1	7.10.1
MCOV		12.7kV MCOV	104A	7.19.2
Potential Transformer		1 PT 63.5:1 (FUTURE COGEN METERING)	104B	7.10.2
Meter		WH METER (FUTURE)	104B	7.11.2
Current Transformer		1200/5 MR	105B TO 51-12	7.10.1
Protective Relay		51-12 SEL-351-6	105B	7.9.2
Circuit Breaker	H-926-XMR-8201-02 (TU-36)	52-12 15kV 1200A Eaton Type 15VCP-W25	105B	7.6.3
Current Transformer		1200/5 FR	105B TO 87B Bus 1	7.10.1
MCOV		12.7kV MCOV	105B	7.19.2
Current Transformer		1200/5 MR	105A TO 51-11	7.10.1
Protective Relay		51-11 SEL-351	105A	7.9.2
Circuit Breaker	902 SW ATO INTERCONNECT M3	52-11 15kV 1200A Eaton Type 15VCP-W25	105A	7.6.3
Current Transformer		1200/5 FR	105A TO 87B Bus 1	7.10.1
MCOV		12.7kV MCOV	105A	7.19.2
Protective Relay		25-TIE	108	7.9.2
Protective Relay		SEL-3350	108	7.9.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Protective Relay		SEL-2407	108	7.9.2
Current Transformer		1200/5 FR	108 TO 87B Bus 2	7.10.1
Circuit Breaker	52-T1	52-TIE 15kV 1200A Eaton Type 15VCP-W25	108	7.6.3
Current Transformer		1200/5 FR	108 TO 87B Bus 1	7.10.1

904 Bus 2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Protective Relay		25-TIE	108	7.9.2
Protective Relay		SEL-3350	108	7.9.2
Protective Relay		SEL-2407	108	7.9.2
Current Transformer		1200/5 FR	108 TO 87B Bus 2	7.10.1
Circuit Breaker	52-T1	52-TIE 15kV 1200A Eaton Type 15VCP-W25	108	7.6.3
Current Transformer		1200/5 FR	108 TO 87B Bus 1	7.10.1
Medium Voltage Cable		13.2kV SHIELDED (FROM H-901-SWG-8001-02 52-24)		7.3.3
MCOV		12.7kV MCOV (FROM H-901-SWG-8001-02 52-24)	110	7.19.2
Potential Transformer		1 PT 63.5:1	110 TO 51-MAIN-2	7.10.2
Current Transformer		1200/5 FR	110 TO 87B Bus 2	7.10.1
Current Transformer		1200/5 MR	110 TO 51-MAIN-2	7.10.1
Protective Relay		51-MAIN-2 SEL-351S	110	7.9.2
Circuit Breaker	52-MAIN-2	52-MAIN-2 15kV 1200A Eaton Type 15VCP-W25 (FROM H-901-SWG-8001-02 52-24)	110	7.6.3
Potential Transformer		3 PTs 63.5:1	110	7.10.2
Protective Relay		87B-2 SEL-587Z	110	7.9.2
Control Power Transformer		SST-2 75kVA 7620/13200V GRDY-120/240V OUTDOOR PAD MOUNT #2	110	7.2.2
Circuit Breaker		FD 350A 2P	110	7.6.1.1
Automatic Transfer Switch		400A ATS (TO SWITCHGEAR BUILDING LOADS LP ISS-1)	110	7.22.3
Current Transformer		1200/5 FR	110 TO 87B Bus 2	7.10.1
Current Transformer		1200/5 MR	111A TO 51-21	7.10.1
Protective Relay		51-21 SEL-351-6	111A	7.9.2
Circuit Breaker	H-538-XMR-8201-02 (TU-38B)	52-21 15kV 1200A Eaton Type 15VCP-W25	111A	7.6.3

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Current Transformer		1200/5 FR	111A TO 87B Bus 2	7.10.1
MCOV		12.7kV MCOV	111A	7.19.2
Current Transformer		1200/5 MR	111B TO 51-22	7.10.1
Protective Relay		51-22 SEL-351-6	111B	7.9.2
Circuit Breaker	SPARE	52-22 15kV 1200A Eaton Type 15VCP-W25	111B	7.6.3
Current Transformer		1200/5 FR	111B TO 87B Bus 2	7.10.1
MCOV		12.7kV MCOV	111B	7.19.2
Current Transformer		1200/5 MR	112A TO 51-23	7.10.1
Protective Relay		51-23 SEL-351-6	112A	7.9.2
Circuit Breaker	H-911-XMR-8201-02	52-23 15kV 1200A Eaton Type 15VCP-W25 (FUTURE PAR 1395)	112A	7.6.3
Current Transformer		1200/5 FR	112A TO 87B Bus 2	7.10.1
MCOV		12.7kV MCOV	112A	7.19.2
Potential Transformer		1 PT 63.5:1 (FUTURE COGEN METERING)	112B	7.10.2
Meter		WH METER (FUTURE)	112B	7.11.2
Current Transformer		1200/5 MR	113A TO 51-24	7.10.1
Protective Relay		51-24 SEL-351	113A	7.9.2
Circuit Breaker	H-902-XMR-8250-02 (TU-33B)	52-24 15kV 1200A Eaton Type 15VCP-W25	113A	7.6.3
Current Transformer		1200/5 FR	113A TO 87B Bus 2	7.10.1
MCOV		12.7kV MCOV	113A	7.19.2
Current Transformer		1200/5 MR	113B TO 51-25	7.10.1
Protective Relay		51-25 SEL-351	113B	7.9.2
Circuit Breaker	H-832-XMR-8201-02 (TU-13B)	52-25 15kV 1200A Eaton Type 15VCP-W25	113B	7.6.3
Current Transformer		1200/5 FR	113B TO 87B Bus 2	7.10.1
MCOV		12.7kV MCOV	113B	7.19.2
Current Transformer		1200/5 MR	114A TO 51-26	7.10.1
Protective Relay		51-26 SEL-351-6	114A	7.9.2
Circuit Breaker	H-274-XMR-8201-01	52-26 15kV 1200A Eaton Type 15VCP-W25	114A	7.6.3
Current Transformer		1200/5 FR	114A TO 87B Bus 2	7.10.1
MCOV		12.7kV MCOV	114A	7.19.2
Current Transformer		1200/5 MR	114B TO 51-27	7.10.1

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Protective Relay		51-27 SEL-351-6	114B	7.9.2
Circuit Breaker	H-913-XMR-8201-02	52-27 15kV 1200A Eaton Type 15VCP-W25 (FUTURE PAR 1395)	114B	7.6.3
Current Transformer		1200/5 FR	114B TO 87B Bus 2	7.10.1
MCOV		12.7kV MCOV	114B	7.19.2
Current Transformer		1200/5 MR	115A TO 51-28	7.10.1
Protective Relay		51-28 SEL-351-6	115A	7.9.2
Circuit Breaker	H-528-XMR-8201-02 (TU-37B)	52-28 15kV 1200A Eaton Type 15VCP-W25	115A	7.6.3
Current Transformer		1200/5 FR	115A TO 87B Bus 2	7.10.1
MCOV		12.7kV MCOV	115A	7.19.2
Current Transformer		1200/5 MR	115B TO 51-29	7.10.1
Protective Relay		51-29 SEL-351-6	115B	7.9.2
Circuit Breaker	H-983-XMR-8201-02 (TU-39B)	52-29 15kV 1200A Eaton Type 15VCP-W25	115B	7.6.3
Current Transformer		1200/5 FR	115B TO 87B Bus 2	7.10.1
MCOV		12.7kV MCOV	115B	7.19.2

H-274-XMR-8201-01

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable		13.2kV SHIELDED 3/C (FROM 904 52-26 CUBICLE 114A)		7.3.3
MCOV		12.7kV MCOV (TRANSFORMER PRIMARY — ALSO ON 904 114A)		7.19.2
Power Transformer	H-274-XMR-8201-01	VTC 1000/1150kVA 13.2kV-480V S/N 441000A059W-WN395C		7.2.2, 7.12.3

H-528-XMR-8201-01 (TU-37A)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	ISS-E401	13.2kV SHIELDED 3/C (FROM 904 52-18 CUBICLE 101A)		7.3.3
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
MV Interrupter Switch		125E 15.5kV 50kAIC (TU-37A)		7.5.1.3
Power Transformer	H-528-XMR-8201-01	TU-37A 2000/2250 kVA 13.2kV-480V		7.2.2, 7.12.3
Metal-Enclosed Busway		3200A BUSWAY 600V 3Ø 3W (TRANSFORMER TO LC MAIN 101B)		7.4
Neutral Grounding Resistor		HRG 2-480V 2.5A CONT. 5:5 / 200:5 CT (SSR1-E1300 / SSR1-E1301)	101C	7.20.4

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Current Transformer		5:5	101C TO 50G / AMMETER	7.10.1
Current Transformer		200:5	101C TO 50G	7.10.1
Protective Relay		50G / 73 NGR MONITOR (AM / 73 / 50G)	101C	7.9.2
Load Center		TU-37 480V 3Ø 3W 3200A 65kAIC (BUS A / MTM)		7.1
Low Voltage Circuit Breaker	MAIN A	3200AF 3200AT LSI (N.C.)	101B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	1600AF 1200AT LSI (SPARE)	102A	7.6.1.2
Low Voltage Circuit Breaker	MCC SSR1-1	1600AF 1200AT LSI (SOUTH SECONDARY RAS PUMP STATION)	102B	7.6.1.2
Low Voltage Circuit Breaker	MCC SS-1	800AF 225AT LSI (SOUTH SECONDARY CLARIFIERS)	102C	7.6.1.2
Low Voltage Circuit Breaker	TIE	3200AF 3200AT LSI (N.O.) (BUS A–BUS B TIE)	103B	7.6.1.2

H-528-XMR-8201-02 (TU-37B)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	ISS-E402	13.2kV SHIELDED 3/C (FROM 904 52-28 CUBICLE 115A)		7.3.3
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
MV Interrupter Switch		125E 15.5kV 50kAIC (TU-37B)		7.5.1.3
Power Transformer	H-528-XMR-8201-02	TU-37B 2000/2250 kVA 13.2kV-480V		7.2.2, 7.12.3
Metal-Enclosed Busway		3200A BUSWAY 600V 3Ø 3W (TRANSFORMER TO LC MAIN 105B)		7.4
Neutral Grounding Resistor		HRG 2-480V 2.5A CONT. 5:5 / 200:5 CT (SSR1-E1310 / SSR1-E1311)	105C	7.20.4
Current Transformer		5:5	105C TO 50G / AMMETER	7.10.1
Current Transformer		200:5	105C TO 50G	7.10.1
Protective Relay		50G / 73 NGR MONITOR (AM / 73 / 50G)	105C	7.9.2
Load Center		TU-37 480V 3Ø 3W 3200A 65kAIC (BUS B / MTM)		7.1
Low Voltage Circuit Breaker	MAIN B	3200AF 3200AT LSI (N.C.)	105B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	1600AF 1200AT LSI (SPARE)	104A	7.6.1.2
Low Voltage Circuit Breaker	MCC SSR1-2	1600AF 1200AT LSI (SOUTH SECONDARY RAS PUMP STATION)	104B	7.6.1.2
Low Voltage Circuit Breaker	MCC SS-3	800AF 225AT LSI (SOUTH SECONDARY CLARIFIERS)	104C	7.6.1.2
Low Voltage Circuit Breaker	TIE	3200AF 3200AT LSI (N.O.) (BUS A–BUS B TIE)	103B	7.6.1.2

H-538-XMR-8201-01 (TU-38A)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	ISS-E403	13.2kV SHIELDED 3/C (FROM 904 52-14 CUBICLE 103A)		7.3.3
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
MV Interrupter Switch		150E 15.5kV 50kAIC (TU-38A)		7.5.1.3
Power Transformer	H-538-XMR-8201-01	TU-38A 2500 kVA 13.2kV-480V		7.2.2, 7.12.3
Metal-Enclosed Busway		3200A BUSWAY 600V 3Ø 3W (TRANSFORMER TO LC MAIN 101B)		7.4
Neutral Grounding Resistor		HRG 2-480V 2.5A CONT. 5:5 / 200:5 CT (SSR2-E1300 / SSR2-E1301)	101C	7.20.4
Current Transformer		5:5	101C TO 50G / AMMETER	7.10.1
Current Transformer		200:5	101C TO 50G	7.10.1
Protective Relay		50G / 73 NGR MONITOR (AM / 73 / 50G)	101C	7.9.2
Load Center		TU-38 480V 3Ø 3W 3200A 65kAIC (BUS A / MTM)		7.1
Low Voltage Circuit Breaker	MAIN A	3200AF 3200AT LSI (N.C.)	101B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	1600AF 1200AT LSI (SPARE)	102A	7.6.1.2
Low Voltage Circuit Breaker	MCC SSR2-1	1600AF 1600AT LSI (SOUTH SECONDARY RAS PUMP STATION)	102B	7.6.1.2
Low Voltage Circuit Breaker	MCC SS-2	800AF 225AT LSI (SOUTH SECONDARY CLARIFIERS)	102C	7.6.1.2
Low Voltage Circuit Breaker	TIE	3200AF 3200AT LSI (N.O.) (BUS A–BUS B TIE)	103B	7.6.1.2

H-538-XMR-8201-02 (TU-38B)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	ISS-E404	13.2kV SHIELDED 3/C (FROM 904 52-21 CUBICLE 111A)		7.3.3
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
MV Interrupter Switch		150E 15.5kV 50kAIC (TU-38B)		7.5.1.3
Power Transformer	H-538-XMR-8201-02	TU-38B 2500 kVA 13.2kV-480V		7.2.2, 7.12.3
Metal-Enclosed Busway		3200A BUSWAY 600V 3Ø 3W (TRANSFORMER TO LC MAIN 105B)		7.4
Neutral Grounding Resistor		HRG 2-480V 2.5A CONT. 5:5 / 200:5 CT (SSR2-E1310 / SSR2-E1311)	105C	7.20.4
Current Transformer		5:5	105C TO 50G / AMMETER	7.10.1
Current Transformer		200:5	105C TO 50G	7.10.1
Protective Relay		50G / 73 NGR MONITOR (AM / 73 / 50G)	105C	7.9.2
Load Center		TU-38 480V 3Ø 3W 3200A 65kAIC (BUS B / MTM)		7.1

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Low Voltage Circuit Breaker	MAIN B	3200AF 3200AT LSI (N.C.)	105B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	1600AF 1200AT LSI (SPARE)	104A	7.6.1.2
Low Voltage Circuit Breaker	MCC SSR2-2	1600AF 1600AT LSI (SOUTH SECONDARY RAS PUMP STATION)	104B	7.6.1.2
Low Voltage Circuit Breaker	MCC SS-4	800AF 225AT LSI (SOUTH SECONDARY CLARIFIERS)	104C	7.6.1.2
Low Voltage Circuit Breaker	TIE	3200AF 3200AT LSI (N.O.) (BUS A–BUS B TIE)	103B	7.6.1.2

H-832-XMR-8201-01 (TU-13A)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable		13.2kV SHIELDED 3/C (FROM 904 52-15 CUBICLE 103B)		7.3.3
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
Power Transformer	H-832-XMR-8201-01	TU-13A 1500/1725 kVA 13.2kV-480V Z=5.75%		7.2.2, 7.12.3
Low Voltage Cable		480V 3Ø (TRANSFORMER TO LC MAIN)		7.3.2
Neutral Grounding Resistor		HRG 2-480V 2.5A CONT. 5:5 / 200:5 CT (DIG-E020 / DIG-E021)	101B	7.20.4
Current Transformer		5:5	101B TO 50G / AMMETER	7.10.1
Current Transformer		200:5	101B TO 50G	7.10.1
Protective Relay		50G / 73 NGR MONITOR (AM / 73 / 50G)	101B	7.9.2
Load Center	1-832-LDC-8201-01	480V 3Ø 3W 2000A 65kAIC (BUS A / MTM)		7.1
Low Voltage Circuit Breaker	MAIN A	2000AF 2000AT (N.C.)	101C	7.6.1.2
Low Voltage Circuit Breaker	1-832-ATS-8300-01	800AF 800AT (STANDBY / 832-E0002)	102B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 600AT (SPARE)	102C	7.6.1.2
Low Voltage Circuit Breaker	MCC-DCB-3	800AF 600AT (MCC DCB-3 / DIG-E072 / 1000A BUS DUCT)	102D	7.6.1.2
Low Voltage Circuit Breaker	MCC-DCB-1	1600AF 400AT (MCC DCB-1 / DIG-E070)	103C	7.6.1.2
Low Voltage Circuit Breaker	MCC-DCB-5	800AF 400AT (MCC DCB-5 / DIG-E074)	103D	7.6.1.2
Low Voltage Circuit Breaker	TIE	2000AF 2000AT (N.O.) (BUS A–BUS B TIE)	104C	7.6.1.2

H-832-XMR-8201-02 (TU-13B)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable		13.2kV SHIELDED 3/C (FROM 904 52-25 CUBICLE 113B)		7.3.3

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
Power Transformer	H-832-XMR-8201-02	TU-13B 1500/1725 kVA 13.2kV-480V Z=5.75%		7.2.2, 7.12.3
Low Voltage Cable		480V 3Ø (TRANSFORMER TO LC MAIN)		7.3.2
Neutral Grounding Resistor		HRG 2-480V 2.5A CONT. 5:5 / 200:5 CT (DIG-E020 / DIG-E021)	107B	7.20.4
Current Transformer		5:5	107B TO 50G / AMMETER	7.10.1
Current Transformer		200:5	107B TO 50G	7.10.1
Protective Relay		50G / 73 NGR MONITOR (AM / 73 / 50G)	107B	7.9.2
Load Center	1-832-LDC-8201-01	480V 3Ø 3W 2000A 65kAIC (BUS B / MTM)		7.1
Low Voltage Circuit Breaker	MAIN B	2000AF 2000AT (N.C.)	107C	7.6.1.2
Low Voltage Circuit Breaker	MCC-DCB-2	800AF 400AT (MCC DCB-2 / DIG-E071)	105C	7.6.1.2
Low Voltage Circuit Breaker	MCC-DCB-4	1600AF 400AT (MCC DCB-4 / DIG-E073)	105D	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 600AT (SPARE)	105B	7.6.1.2
Low Voltage Circuit Breaker	1-832-ATS-8300-01	800AF 800AT (PRIMARY)	106B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 400AT (SPARE)	106C	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 200AT (SPARE)	106D	7.6.1.2
Low Voltage Circuit Breaker	TIE	2000AF 2000AT (N.O.) (BUS A–BUS B TIE)	104C	7.6.1.2

H-911-XMR-8201-01

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	911-E0110	13.2kV SHIELDED 3/C (FROM 904 PAR 1395 52-13 CUBICLE 104A)		7.3.3
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
Power Transformer	H-911-XMR-8201-01	2500/3125 kVA KNAN/KNAF 13.2kV-480V Z=5.75%		7.2.2, 7.12.3
Low Voltage Cable		480V SECONDARY (TRANSFORMER TO LC MAIN 101B)		7.3.2
Neutral Grounding Resistor	H-911-HRG-8201-01	HRG 2-480V 2.5A CONT. 5:5 / 5:0.5 CT	101C	7.20.4
Current Transformer		5:5	101C TO 50G / AMMETER	7.10.1
Current Transformer		5:0.5	101C TO 50G	7.10.1
Protective Relay		50G / 73 NGR MONITOR (AM / 73 / 50G)	101C	7.9.2
Protective Relay		SEL-751A 59/27	101A	7.9.2
Load Center	H-911-LDC-8201-01	480V 3Ø 3W 4000A 65kAIC (BUS 1 / ATO)		7.1

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Low Voltage Circuit Breaker	MAIN 1 H-911-LDC-8201-01	4000AF 4000AT LSI (N.C.)	101B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	2000AF 1600AT LSI (SPARE)	102B	7.6.1.2
Low Voltage Circuit Breaker	H-911-MCC-8301-01	1600AF 1200AT LSI (N.C.) (911-E0086) (KIRK 2-OF-3 W/ TIE)	102C	7.6.1.2
Low Voltage Circuit Breaker	H-911-MTS-8302-02	1600AF 1200AT LSI (AMINE SYSTEM MCC-02)	102D	7.6.1.2
Low Voltage Circuit Breaker	SPARE	1600AF 1200AT LSI (SPARE)	103B	7.6.1.2
Low Voltage Circuit Breaker	H-911-VFD-4021-01	2000AF 1600AT LSI (HEAT PUMP 1 / 911-E0007)	103C	7.6.1.2
Low Voltage Circuit Breaker	H-911-MTS-8302-01	1600AF 1200AT LSI (AMINE SYSTEM MCC-01 / 911-E0001)	103D	7.6.1.2
Low Voltage Circuit Breaker	TIE	4000AF 4000AT LSI (N.O.) (BUS 1–BUS 2 TIE / ATO) (KIRK 2-OF-3)	104C	7.6.1.2

H-911-XMR-8201-02

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	911-E0050	13.2kV SHIELDED 3/C (FROM 904 PAR 1395 52-23 CUBICLE 112A)		7.3.3
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
Power Transformer	H-911-XMR-8201-02	2500/3125 kVA KNAN/KNAF 13.2kV-480V Z=5.75%		7.2.2, 7.12.3
Low Voltage Cable		480V SECONDARY (TRANSFORMER TO LC MAIN 107B)		7.3.2
Neutral Grounding Resistor	H-911-HRG-8201-02	HRG 2-480V 2.5A CONT. 5:5 / 5:0.5 CT	107C	7.20.4
Current Transformer		5:5	107C TO 50G / AMMETER	7.10.1
Current Transformer		5:0.5	107C TO 50G	7.10.1
Protective Relay		50G / 73 NGR MONITOR (AM / 73 / 50G)	107C	7.9.2
Protective Relay		SEL-751A 59/27	107A	7.9.2
Load Center	H-911-LDC-8201-01	480V 3Ø 3W 4000A 65kAIC (BUS 2 / ATO)		7.1
Low Voltage Circuit Breaker	MAIN 2 H-911-LDC-8201-01	4000AF 4000AT LSI (N.C.)	107B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	2000AF 1600AT LSI (SPARE)	105B	7.6.1.2
Low Voltage Circuit Breaker	H-911-VFD-4021-02	2000AF 1600AT LSI (HEAT PUMP 2 / 911-E0151)	105C	7.6.1.2
Low Voltage Circuit Breaker	H-911-MTS-8302-02	1600AF 1200AT LSI (AMINE SYSTEM MCC-02 / 911-E0508)	105D	7.6.1.2
Low Voltage Circuit Breaker	SPARE	2000AF 1600AT LSI (SPARE)	106B	7.6.1.2
Low Voltage Circuit Breaker	H-911-MCC-8301-02	1600AF 1200AT LSI (N.C.) (911-E0099) (KIRK 2-OF-3 W/ TIE)	106C	7.6.1.2
Low Voltage Circuit Breaker	H-911-MTS-8302-01	1600AF 1200AT LSI (AMINE SYSTEM MCC-01)	106D	7.6.1.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Low Voltage Circuit Breaker	TIE	4000AF 4000AT LSI (N.O.) (BUS 1–BUS 2 TIE / ATO) (KIRK 2-OF-3)	104C	7.6.1.2

H-913-XMR-8201-01

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable		13.2kV SHIELDED 3/C (FROM 904 PAR 1395 52-17 CUBICLE 102B)		7.3.3
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
Power Transformer	H-913-XMR-8201-01	1500/1725 kVA KNAN/KNAF 13.2kV-480V Z=5.75%		7.2.2, 7.12.3
Low Voltage Cable		480V SECONDARY (TRANSFORMER TO LC MAIN 101B)		7.3.2
Neutral Grounding Resistor	H-913-HRG-8201-01	HRG 2-480V 2.5A CONT. 5:5 / 5:0.05 CT	101C	7.20.4
Current Transformer		5:5	101C TO 50G / AMMETER	7.10.1
Current Transformer		5:0.05	101C TO 50G	7.10.1
Protective Relay		50G / 73 NGR MONITOR (AM / 73 / 50G)	101C	7.9.2
Protective Relay		SEL-751A 59/27	101A	7.9.2
Load Center	H-913-LDC-8201-01	480V 3Ø 3W 3200A 65kAIC (BUS 1 / ATO)		7.1
Low Voltage Circuit Breaker	MAIN 1 H-913-LDC-8201-01	3200AF 2500AT (N.C.)	101B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	1600AF 1200AT (SPARE)	102B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	1600AF 1600AT (SPARE)	102C	7.6.1.2
Low Voltage Circuit Breaker	H-913-MCC-8301-01	1600AF 1200AT (913-E0070)	102D	7.6.1.2
Low Voltage Circuit Breaker	TIE	3200AF 2500AT (N.O.) (BUS 1–BUS 2 TIE / ATO)	103C	7.6.1.2

H-913-XMR-8201-02

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable		13.2kV SHIELDED 3/C (FROM 904 PAR 1395 52-27 CUBICLE 114B)		7.3.3
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
Power Transformer	H-913-XMR-8201-02	1500/1725 kVA KNAN/KNAF 13.2kV-480V Z=5.75%		7.2.2, 7.12.3
Low Voltage Cable		480V SECONDARY (TRANSFORMER TO LC MAIN 105B)		7.3.2
Neutral Grounding Resistor	H-913-HRG-8201-02	HRG 2-480V 2.5A CONT. 5:5 / 5:0.05 CT	105C	7.20.4
Current Transformer		5:5	105C TO 50G / AMMETER	7.10.1
Current Transformer		5:0.05	105C TO 50G	7.10.1

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Protective Relay		50G / 73 NGR MONITOR (AM / 73 / 50G)	105C	7.9.2
Protective Relay		SEL-751A 59/27	105A	7.9.2
Load Center	H-913-LDC-8201-01	480V 3Ø 3W 3200A 65kAIC (BUS 2 / ATO)		7.1
Low Voltage Circuit Breaker	MAIN 2 H-913-LDC-8201-01	3200AF 2500AT (N.C.)	105B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	1600AF 1600AT (SPARE)	104B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	1600AF 1200AT (SPARE)	104C	7.6.1.2
Low Voltage Circuit Breaker	H-913-MCC-8301-02	1600AF 1200AT (913-E0080)	104D	7.6.1.2
Low Voltage Circuit Breaker	TIE	3200AF 2500AT (N.O.) (BUS 1–BUS 2 TIE / ATO)	103C	7.6.1.2

H-926-XMR-8201-02 (TU-36)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable		13.2kV SHIELDED 3/C (FROM 904 52-12 CUBICLE 105B)		7.3.3
MCOV		13.2kV MCOV 100E 15.5kV (TRANSFORMER PRIMARY)		7.19.2
Power Transformer	H-926-XMR-8201-02	TU-36 750 kVA 13.2kV-480Y/277V (RR&R ELECTRICAL BUILDING) — SOLID GND 3Ø 4W		7.2.2, 7.12.3
Low Voltage Cable		480V 3Ø (TRANSFORMER TO LC MAIN)		7.3.2
Current Transformer		4 CTs 2000:5	102C TO MAIN / PK-2	7.10.1
Load Center	LC-36	TU-36 LC 480V 3Ø 4W 2000A 65kAIC (SINGLE-ENDED)		7.1
Low Voltage Circuit Breaker	TU-36 MAIN	1600AF 1200AT LSI (N.C.)	102C	7.6.1.2
Low Voltage Circuit Breaker	PP-1 RR&R O&M	800AF 400AT LSI (RRC-E021)	101A	7.6.1.2
Low Voltage Circuit Breaker	MCC-1	800AF 200AT LSI (RR&R ELECTRICAL BUILDING)	101B	7.6.1.2
Low Voltage Circuit Breaker	HPA	800AF 200AT LSI (RR&R SERVICES)	101C	7.6.1.2
Low Voltage Circuit Breaker	SPACE	SPACE	102B	7.6.1.2
Low Voltage Circuit Breaker	SPACE	SPACE	102D	7.6.1.2
Low Voltage Circuit Breaker	SPACE	SPACE	101D	7.6.1.2

H-983-XMR-8201-02 (TU-39B)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	ISS-E502	13.2kV SHIELDED 3/C (FROM 904 52-29 CUBICLE 115B)		7.3.3

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
MCOV		13.2kV MCOV 100E 15.5kV 50kAIC (TRANSFORMER PRIMARY)		7.19.2
Power Transformer	H-983-XMR-8201-02	TU-39B 1500/1875 kVA 13.2kV-480V (H-983 DIGESTER COMPLEX)		7.2.2, 7.12.3
Low Voltage Cable		480V 3Ø (TRANSFORMER TO LC MAIN)		7.3.2
Neutral Grounding Resistor		HRG 2-480V 2.5A CONT. 200:5 / 5:5 CT (RK-325)	105C	7.20.4
Current Transformer		200:5	105C TO RK-325 / 50G	7.10.1
Current Transformer		5:5	105C TO AMMETER	7.10.1
Protective Relay		RK-325 NGR MONITOR (AM / 73 / 50G)	105C	7.9.2
Load Center	H-983-LDC-8201-01	480V 3Ø 3W 3200A 65kAIC (BUS B / MTM)		7.1
Low Voltage Circuit Breaker	TU-39B MAIN	3200AF 3200AT LSI (N.C.)	105B	7.6.1.2
Low Voltage Circuit Breaker	MCC DCB-7	1600AF 1200AT LSI (DIGESTER ELECTRICAL BUILDING / DCB-E1349)	104B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	1600AF 1200AT LSI (SPARE)	104C	7.6.1.2
Low Voltage Circuit Breaker	SPARE	1600AF 1200AT LSI (SPARE)	104D	7.6.1.2
Low Voltage Circuit Breaker	TIE	3200AF 3200AT LSI (N.O.) (BUS A–BUS B TIE)	103C	7.6.1.2

H-983-XMR-8201-01 (TU-39A)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	ISS-E501	13.2kV SHIELDED 3/C (FROM 904 52-19 CUBICLE 101B)		7.3.3
MCOV		13.2kV MCOV 100E 15.5kV 50kAIC (TRANSFORMER PRIMARY)		7.19.2
Power Transformer	H-983-XMR-8201-01	TU-39A 1500/1875 kVA 13.2kV-480V (H-983 DIGESTER COMPLEX)		7.2.2, 7.12.3
Low Voltage Cable		480V 3Ø (TRANSFORMER TO LC MAIN)		7.3.2
Neutral Grounding Resistor		HRG 2-480V 2.5A CONT. 200:5 / 5:5 CT (RK-325)	101C	7.20.4
Current Transformer		200:5	101C TO RK-325 / 50G	7.10.1
Current Transformer		5:5	101C TO AMMETER	7.10.1
Protective Relay		RK-325 NGR MONITOR (AM / 73 / 50G)	101C	7.9.2
Load Center	H-983-LDC-8201-01	480V 3Ø 3W 3200A 65kAIC (BUS A / MTM)		7.1
Low Voltage Circuit Breaker	TU-39A MAIN	3200AF 3200AT LSI (N.C.)	101B	7.6.1.2
Low Voltage Circuit Breaker	MCC DCB-8	1600AF 1200AT LSI (DIGESTER ELECTRICAL BUILDING / DCB-E1331)	102B	7.6.1.2
Low Voltage Circuit Breaker	MCC DCB-6	1600AF 1200AT LSI (DIGESTERS 11 & 12 BUILDING / DCB-E1329)	102C	7.6.1.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Low Voltage Circuit Breaker	SPARE	1600AF 1200AT LSI (SPARE)	102D	7.6.1.2
Low Voltage Circuit Breaker	TIE	3200AF 3200AT LSI (N.O.) (BUS A–BUS B TIE)	103C	7.6.1.2

2029 Maintenance Group

901 Bus 1-See 2027 Maintenance Group

901 Bus 2-See 2027 Maintenance Group

902 Bus 1

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Switchgear Assembly		902 Southwest Switchgear 13.2kV BUS 1 1200A		7.1
Medium Voltage Cable		13.2kV SHIELDED (FROM H-901-SWG-8001-01 52-13)		7.3.3
MCOV		12.7kV MCOV (FROM H-901-SWG-8001-01 52-13)		7.19.2
Potential Transformer		3 PTs 70:1	107B TO 51-MAIN-1	7.10.2
Current Transformer		1200/5 FR	107B TO 87B Bus 1	7.10.1
Protective Relay		87-B1 SEL-587Z	107B	7.9.2
Current Transformer		1200/5 MR	107A TO 51-MAIN-1	7.10.1
Protective Relay		51-MAIN-1 SEL-351S	107A	7.9.2
Circuit Breaker	52-MAIN-1	52-MAIN-1 15kV 1200A Eaton Type 15VCP-W25 (FROM H-901-SWG-8001-01 52-13)	107A	7.6.3
Potential Transformer		3 PTs 70:1	103A	7.10.2
Current Transformer		1200/5 MR	100A TO 51-19	7.10.1
Protective Relay		51-19 SEL-351	100A	7.9.2
Circuit Breaker	SPARE	52-19 15kV 1200A Eaton Type 15VCP-W25	100A	7.6.3
Current Transformer		1200/5 FR	100A TO 87B Bus 1	7.10.1
Current Transformer		1200/5 MR	102B TO 51-18	7.10.1
Protective Relay		51-18 SEL-351	102B	7.9.2
Circuit Breaker	H-312-XMR-8201-01 (TU-40A)	52-18 15kV 1200A Eaton Type 15VCP-W25	102B	7.6.3
Current Transformer		1200/5 FR	102B TO 87B Bus 1	7.10.1
MCOV		12.7kV MCOV	102B	7.19.2
Current Transformer		1200/5 MR	102A TO 51-17	7.10.1

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Protective Relay		51-17 SEL-351	102A	7.9.2
Circuit Breaker	SPARE	52-17 15kV 1200A Eaton Type 15VCP-W25	102A	7.6.3
Current Transformer		1200/5 FR	102A TO 87B Bus 1	7.10.1
MCOV		12.7kV MCOV	102A	7.19.2
Current Transformer		1200/5 MR	103B TO 51-16	7.10.1
Protective Relay		51-16 SEL-351	103B	7.9.2
Circuit Breaker	H-514-XMR-8201-01 (TU-34A)	52-16 15kV 1200A Eaton Type 15VCP-W25	103B	7.6.3
Current Transformer		1200/5 FR	103B TO 87B Bus 1	7.10.1
MCOV		12.7kV MCOV	103B	7.19.2
Current Transformer		1200/5 MR	104B TO 51-15	7.10.1
Protective Relay		51-15 SEL-351	104B	7.9.2
Circuit Breaker	H-514-XMR-8202-01 (TU-35A)	52-15 15kV 1200A Eaton Type 15VCP-W25	104B	7.6.3
Current Transformer		1200/5 FR	104B TO 87B Bus 1	7.10.1
MCOV		12.7kV MCOV	104B	7.19.2
Current Transformer		1200/5 MR	104A TO 51-14	7.10.1
Protective Relay		51-14 SEL-351	104A	7.9.2
Circuit Breaker	H-902-XMR-8203-01 (TU-32A)	52-14 15kV 1200A Eaton Type 15VCP-W25	104A	7.6.3
Current Transformer		1200/5 FR	104A TO 87B Bus 1	7.10.1
MCOV		12.7kV MCOV	104A	7.19.2
Current Transformer		1200/5 MR	105B TO 51-13	7.10.1
Protective Relay		51-13 SEL-351	105B	7.9.2
Circuit Breaker	H-902-XMR-8201-01 (TU-30A)	52-13 15kV 1200A Eaton Type 15VCP-W25	105B	7.6.3
Current Transformer		1200/5 FR	105B TO 87B Bus 1	7.10.1
MCOV		12.7kV MCOV	105B	7.19.2
Current Transformer		1200/5 MR	105A TO 51-12	7.10.1
Protective Relay		51-12 SEL-351	105A	7.9.2
Circuit Breaker	H-902-XMR-8202-01 (TU-31A)	52-12 15kV 1200A Eaton Type 15VCP-W25	105A	7.6.3
Current Transformer		1200/5 FR	105A TO 87B Bus 1	7.10.1
MCOV		12.7kV MCOV	105A	7.19.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Current Transformer		1200/5 MR	106A TO 87-11	7.10.1
Protective Relay		87-11 SEL-787	106A	7.9.2
Circuit Breaker	H-902-XMR-8250-01 (TU-33A)	52-11 15kV 1200A Eaton Type 15VCP-W25	106A	7.6.3
Current Transformer		1200/5 FR	106A TO 87B Bus 1	7.10.1
MCOV		12.7kV MCOV	106A	7.19.2
Protective Relay		25-TIE-1	109B	7.9.2
Current Transformer		1200/5 FR	109B TO 87B Bus 2	7.10.1
Circuit Breaker	TIE 1	52-TIE-1 15kV 1200A Eaton Type 15VCP-W25	109B	7.6.3
Current Transformer		1200/5 FR	109B TO 87B Bus 1	7.10.1

902 Bus 2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Protective Relay		25-TIE-1	109B	7.9.2
Current Transformer		1200/5 FR	109B TO 87B Bus 2	7.10.1
Circuit Breaker	TIE 1	52-TIE-1 15kV 1200A Eaton Type 15VCP-W25	109B	7.6.3
Current Transformer		1200/5 FR	109B TO 87B Bus 1	7.10.1
Switchgear Assembly		902 Southwest Switchgear 13.2kV BUS 2 1200A		7.1
Medium Voltage Cable		13.2kV SHIELDED (FROM H-901-SWG-8001-02 52-23)		7.3.3
MCOV		12.7kV MCOV	111B	7.19.2
Potential Transformer		3 PTs 70:1	111B	7.10.2
Current Transformer		1200/5 FR	111B TO 87B Bus 2	7.10.1
Protective Relay		51-MAIN-2 SEL-351S	110A	7.9.2
Circuit Breaker	52-MAIN-2	52-MAIN-2 15kV 1200A Eaton Type 15VCP-W25	110A	7.6.3
Current Transformer		1200/5 MR	110A TO 51-MAIN-2	7.10.1
Protective Relay		87-B2 SEL-587Z	110B	7.9.2
Potential Transformer		3 PTs 70:1	115A	7.10.2
Current Transformer		1200/5 MR	113B TO 51-22	7.10.1
Protective Relay		51-22 SEL-351	113B	7.9.2
Circuit Breaker	H-902-XMR-8201-02 (TU-30B)	52-22 15kV 1200A Eaton Type 15VCP-W25	113B	7.6.3

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Current Transformer		1200/5 FR	113B TO 87B Bus 2	7.10.1
MCOV		12.7kV MCOV	113B	7.19.2
Current Transformer		1200/5 MR	113A TO 51-23	7.10.1
Protective Relay		51-23 SEL-351	113A	7.9.2
Circuit Breaker	H-902-XMR-8202-02 (TU-31B)	52-23 15kV 1200A Eaton Type 15VCP-W25	113A	7.6.3
Current Transformer		1200/5 FR	113A TO 87B Bus 2	7.10.1
MCOV		12.7kV MCOV	113A	7.19.2
Current Transformer		1200/5 MR	114B TO 51-24	7.10.1
Protective Relay		51-24 SEL-351	114B	7.9.2
Circuit Breaker	H-514-XMR-8201-02 (TU-34B)	52-24 15kV 1200A Eaton Type 15VCP-W25	114B	7.6.3
Current Transformer		1200/5 FR	114B TO 87B Bus 2	7.10.1
MCOV		12.7kV MCOV	114B	7.19.2
Current Transformer		1200/5 MR	114A TO 51-25	7.10.1
Protective Relay		51-25 SEL-351	114A	7.9.2
Circuit Breaker	H-902-XMR-8203-02 (TU-32B)	52-25 15kV 1200A Eaton Type 15VCP-W25	114A	7.6.3
Current Transformer		1200/5 FR	114A TO 87B Bus 2	7.10.1
MCOV		12.7kV MCOV	114A	7.19.2
Current Transformer		1200/5 MR	115B TO 51-26	7.10.1
Protective Relay		51-26 SEL-351	115B	7.9.2
Circuit Breaker	H-514-XMR-8202-02 (TU-35B)	52-26 15kV 1200A Eaton Type 15VCP-W25	115B	7.6.3
Current Transformer		1200/5 FR	115B TO 87B Bus 2	7.10.1
MCOV		12.7kV MCOV	115B	7.19.2
Current Transformer		1200/5 MR	116B TO 51-27	7.10.1
Protective Relay		51-27 SEL-351	116B	7.9.2
Circuit Breaker	H-312-XMR-8201-02 (TU-40B)	52-27 15kV 1200A Eaton Type 15VCP-W25	116B	7.6.3
Current Transformer		1200/5 FR	116B TO 87B Bus 2	7.10.1
MCOV		12.7kV MCOV	116B	7.19.2
Current Transformer		1200/5 MR	116A TO 51-28	7.10.1
Protective Relay		51-28 SEL-351	116A	7.9.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Circuit Breaker	H-202-XMR-8201-01	52-28 15kV 1200A Eaton Type 15VCP-W25	116A	7.6.3
Current Transformer		1200/5 FR	116A TO 87B Bus 2	7.10.1
MCOV		12.7kV MCOV	116A	7.19.2
Current Transformer		1200/5 MR	117B TO 87-29	7.10.1
Protective Relay		87-29 SEL-787	117A	7.9.2
Circuit Breaker	H-902-XMR-8250-02 (TU-33B)	52-29 15kV 1200A Eaton Type 15VCP-W25	117B	7.6.3
Current Transformer		1200/5 FR	117B TO 87B Bus 2	7.10.1
MCOV		12.7kV MCOV	117B	7.19.2
Protective Relay		25-TIE-2	118B	7.9.2
Current Transformer		1200/5 FR	118B TO 87B Bus 3	7.10.1
Circuit Breaker	TIE 2	52-TIE-2 15kV 1200A Eaton Type 15VCP-W25 (N.O.)	118B	7.6.3
Current Transformer		1200/5 FR	118B TO 87B Bus 2	7.10.1
Switchgear Assembly		902 Southwest Switchgear 13.2kV BUS 3 1200A		7.1
Current Transformer		1200/5 MR	119A TO 87-31	7.10.1
Protective Relay		87-31 SEL-787 (TU-33C DIFF)	119A	7.9.2
Circuit Breaker	H-902-XMR-8250-03 (TU-33C)	52-31 15kV 1200A Eaton Type 15VCP-W25	119A	7.6.3
Current Transformer		1200/5 FR	119A TO 87B Bus 3	7.10.1
MCOV		12.7kV MCOV	119A	7.19.2
Potential Transformer		3 PTs 70:1	120A	7.10.2
Current Transformer		1200/5 MR	120B TO 51-MAIN-3	7.10.1
Protective Relay		51-MAIN-3 SEL-351	120B	7.9.2
Circuit Breaker	TO 904 SWITCHGEAR	52-MAIN-3 15kV 1200A Eaton Type 15VCP-W25	120B	7.6.3
Current Transformer		1200/5 FR	120A TO 87B Bus 3	7.10.1

H-202-E-XMR-8201-01

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable		13.2kV SHIELDED 3/C (FROM 902 52-28 CUBICLE 116A)		7.3.3
MCOV		12.7kV MCOV (TRANSFORMER PRIMARY — ALSO ON 902 116A)		7.19.2
Power Transformer	H-202-XMR-8201-01	GUARD HOUSE SOUTH PADMOUNT 13.2kV-480V, 75kVA		7.2.2, 7.12.3

H-312-E-XMR-8201-01 (TU-40A)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	SWB-E1013	13.2kV SHIELDED 3/C (FROM 902 52-18 SW SWITCHGEAR BUS A)		7.3.3
Power Transformer	H-312-XMR-8201-01	TU-40A EATON 2000/2250kVA 13.2kV-480V S/N 18JC07450002		7.2.2, 7.12.3
Low Voltage Cable		480V 3Ø (TRANSFORMER TO LC MAIN)		7.3.2
Neutral Grounding Resistor		HRG 2×480V 2.5A CONT. 110.8Ω OUTDOOR (SE-325 / ER-600VC)	TU-40A HRG PANEL	7.20.4
Current Transformer		200:5	TU-40A NGR TO SE-325	7.10.1
Current Transformer		5:5	TU-40A NGR AMMETER	7.10.1
Protective Relay		SE-325 NGR MONITOR (GF TRIP 0.5A)	TU-40A HRG PANEL	7.9.2
Load Center	LC-40	TU-40 LC 480V 3Ø 3W 3200A 65kAIC (A BUS / MTM)		7.1
Low Voltage Circuit Breaker	TU-40A MAIN	EATON MDS632 3200AF 3000AT LSI (N.C.)	LC-40 101B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	EATON MDS616 1200AF 1200AT LSIG	LC-40 102A	7.6.1.2
Low Voltage Circuit Breaker	SPARE	EATON MDS608 800AF 400AT LSIG	LC-40 102B	7.6.1.2
Low Voltage Circuit Breaker	SGRT MCC-1	EATON MDS608 800AF 800AT LSIG	LC-40 102C	7.6.1.2
Low Voltage Circuit Breaker	SBAR MCC-1	EATON MDS608 800AF 400AT LSIG	LC-40 102D	7.6.1.2
Low Voltage Circuit Breaker	SPARE	EATON MDS616 1200AF 1200AT LSIG	LC-40 103A	7.6.1.2
Low Voltage Circuit Breaker	SGRT MCC-3	EATON MDS608 800AF 300AT LSIG	LC-40 103B	7.6.1.2
Low Voltage Circuit Breaker	GRSP MCC-1	EATON MDS616 1200AF 800AT LSIG	LC-40 104C	7.6.1.2
Low Voltage Circuit Breaker	SHEL MCC-1	EATON MDS616 1200AF 1000AT LSIG	LC-40 104D	7.6.1.2
Low Voltage Circuit Breaker	TU-40A TIE	EATON MDS632 3200AF 3000AT LSI (N.O.)	LC-40 104B	7.6.1.2

H-312-E-XMR-8201-02 (TU-40B)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	SWB-E1014	13.2kV SHIELDED 3/C (FROM 902 52-27 SW SWITCHGEAR BUS B)		7.3.3
Power Transformer	H-312-XMR-8201-02	TU-40B EATON 2000/2250kVA 13.2kV-480V S/N 18JC07450001		7.2.2, 7.12.3
Low Voltage Cable		480V 3Ø (TRANSFORMER TO LC MAIN)		7.3.2
Neutral Grounding Resistor		HRG 2×480V 2.5A CONT. 110.8Ω OUTDOOR (SE-325 / ER-600VC)	TU-40B HRG PANEL	7.20.4
Current Transformer		200:5	TU-40B NGR TO SE-325	7.10.1

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Current Transformer		5:5	TU-40B NGR AMMETER	7.10.1
Protective Relay		SE-325 NGR MONITOR (GF TRIP 0.5A)	TU-40B HRG PANEL	7.9.2
Load Center	LC-40	TU-40 LC 480V 3Ø 3W 3200A 65kAIC (B BUS / MTM)		7.1
Low Voltage Circuit Breaker	TU-40B MAIN	EATON MDS632 3200AF 3000AT LSI (N.C.)	LC-40 109B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	EATON MDS616 1200AF 1200AT LSIG	LC-40 108A	7.6.1.2
Low Voltage Circuit Breaker	SPSP MCC-1	EATON MDS608 800AF 600AT LSIG	LC-40 108B	7.6.1.2
Low Voltage Circuit Breaker	SGRT MCC-2	EATON MDS608 800AF 800AT LSIG	LC-40 108C	7.6.1.2
Low Voltage Circuit Breaker	SBAR MCC-2	EATON MDS608 800AF 400AT LSIG	LC-40 108D	7.6.1.2
Low Voltage Circuit Breaker	SPARE	EATON MDS616 1200AF 1200AT LSIG	LC-40 107A	7.6.1.2
Low Voltage Circuit Breaker	SPARE	EATON MDS608 800AF 300AT LSIG	LC-40 107B	7.6.1.2
Low Voltage Circuit Breaker	GRSP MCC-2	EATON MDS616 1200AF 800AT LSIG	LC-40 106C	7.6.1.2
Low Voltage Circuit Breaker	SHEL MCC-2	EATON MDS616 1200AF 1000AT LSIG	LC-40 106D	7.6.1.2
Low Voltage Circuit Breaker	TU-40B TIE	EATON MDS632 3200AF 2500AT LSI (N.O.)	LC-40 106B	7.6.1.2

H-514-E-XMR-8201-01 (TU-34A)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	SWB-E1009	13.2kV SHIELDED 3/C (FROM 902 52-16 SW SWITCHGEAR BUS 1)		7.3.3
MCOV		13.2kV MCOV 100E 15.5kV 50kAIC		7.19.2
MV Interrupter Switch		EATON MVS 15kV (TU-34A)		7.5.1.3
Power Transformer	H-514-XMR-8201-01	TU-34A EATON 1500/1725kVA 13.2kV-480V S/N 12JC564440002		7.2.2, 7.12.3
Metal-Enclosed Busway		3200A BUSWAY 600V 3Ø 3W (TRANSFORMER TO LC MAIN)		7.4
Neutral Grounding Resistor		HRG 2×480V 2.5A CONT. 110.8Ω OUTDOOR (SE-325 / ER-600VC)	TU-34A HRG PANEL 102C	7.20.4
Current Transformer		200:5	TU-34A NGR TO SE-325	7.10.1
Current Transformer		5:5	TU-34A NGR AMMETER	7.10.1
Protective Relay		SE-325 NGR MONITOR (GF TRIP 0.5A)	TU-34A HRG PANEL 102C	7.9.2
Load Center	LC-34	TU-34 LC 480V 3Ø 3W 3200A 65kAIC (A BUS / MTM)		7.1
Low Voltage Circuit Breaker	TU-34A MAIN	EATON MDS632 3200AF 2500AT LSI (N.C.)	LC-34 102B	7.6.1.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Low Voltage Circuit Breaker	MCC SAC2-1	EATON MDS616 1600AF 1200AT LSI (SOUTH SECONDARY AERATION / SAC2-E1000)	LC-34 101A	7.6.1.2
Low Voltage Circuit Breaker	SPARE	EATON MDS616 1600AF 1200AT LSI (SPARE)	LC-34 101B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	EATON MDS616 1600AF 1200AT LSI (SPARE)	LC-34 101C	7.6.1.2
Low Voltage Circuit Breaker	TU-34 TIE	EATON MDS632 3200AF 2500AT LSI (N.O.)	LC-34 103B	7.6.1.2

H-514-E-XMR-8201-02 (TU-34B)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	SWB-E1010	13.2kV SHIELDED 3/C (FROM 902 52-24 SW SWITCHGEAR BUS 2)		7.3.3
MCOV		13.2kV MCOV 100E 15.5kV 50kAIC		7.19.2
MV Interrupter Switch		EATON MVS 15kV (TU-34B)		7.5.1.3
Power Transformer	H-514-XMR-8201-02	TU-34B EATON 1500/1725kVA 13.2kV-480V S/N 12JC561940001		7.2.2, 7.12.3
Metal-Enclosed Busway		3200A BUSWAY 600V 3Ø 3W (TRANSFORMER TO LC MAIN)		7.4
Neutral Grounding Resistor		HRG 2×480V 2.5A CONT. 110.8Ω OUTDOOR (SE-325 / ER-600VC)	TU-34B HRG PANEL 104C	7.20.4
Current Transformer		200:5	TU-34B NGR TO SE-325	7.10.1
Current Transformer		5:5	TU-34B NGR AMMETER	7.10.1
Protective Relay		SE-325 NGR MONITOR (GF TRIP 0.5A)	TU-34B HRG PANEL 104C	7.9.2
Load Center	LC-34	TU-34 LC 480V 3Ø 3W 3200A 65kAIC (B BUS / MTM)		7.1
Low Voltage Circuit Breaker	TU-34B MAIN	EATON MDS632 3200AF 2500AT LSI (N.C.)	LC-34 104B	7.6.1.2
Low Voltage Circuit Breaker	MCC SAC2-2	EATON MDS616 1600AF 1200AT LSI (SOUTH SECONDARY AERATION / SAC2-E1001)	LC-34 105A	7.6.1.2
Low Voltage Circuit Breaker	1-268-ATS-8300-01 ATS-RRS-HP	EATON MDS616 1600AF 400AT LSI (ATS-RRS-HP / SAC2-E1920) (WAS 1200AT SPARE)	LC-34 105B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	EATON MDS616 1600AF 1200AT LSI (SPARE)	LC-34 105C	7.6.1.2
Low Voltage Circuit Breaker	TU-34 TIE	EATON MDS632 3200AF 2500AT LSI (N.O.)	LC-34 103B	7.6.1.2

H-514-E-XMR-8202-01 (TU-35A)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	SWB-E1011	13.2kV SHIELDED 3/C (FROM 902 52-15 SW SWITCHGEAR BUS 1)		7.3.3
MCOV		13.2kV MCOV 100E 15.5kV 50kAIC		7.19.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
MV Interrupter Switch		EATON MVS 15kV (TU-35A)		7.5.1.3
Power Transformer	H-514-XMR-8202-01	TU-35A EATON 1500/1725kVA 13.2kV-480V S/N 12JC564440001		7.2.2, 7.12.3
Metal-Enclosed Busway		3200A BUSWAY 600V 3Ø 3W (TRANSFORMER TO LC MAIN)		7.4
Neutral Grounding Resistor		HRG 2×480V 2.5A CONT. 110.8Ω OUTDOOR (SE-325 / ER-600VC)	TU-35A HRG PANEL 102C	7.20.4
Current Transformer		200:5	TU-35A NGR TO SE-325	7.10.1
Current Transformer		5:5	TU-35A NGR AMMETER	7.10.1
Protective Relay		SE-325 NGR MONITOR (GF TRIP 0.5A)	TU-35A HRG PANEL 102C	7.9.2
Load Center	LC-35	TU-35 LC 480V 3Ø 3W 3200A 65kAIC (A BUS / MTM)		7.1
Low Voltage Circuit Breaker	TU-35A MAIN	EATON MDS632 3200AF 2500AT LSI (N.C.)	LC-35 102B	7.6.1.2
Low Voltage Circuit Breaker	MCC SAC2-3	EATON MDS616 1600AF 1200AT LSI (SOUTH SECONDARY AERATION / SAC2-E1010)	LC-35 101A	7.6.1.2
Low Voltage Circuit Breaker	1-268-ATS-8300-01 ATS-RRS-HP	EATON MDS616 1600AF 400AT LSI (ATS-RRS-HP / SAC2-E1921) (WAS 1200AT SPARE)	LC-35 101B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	EATON MDS616 1600AF 1200AT LSI (SPARE)	LC-35 101C	7.6.1.2
Low Voltage Circuit Breaker	TU-35 TIE	EATON MDS632 3200AF 2500AT LSI (N.O.)	LC-35 103B	7.6.1.2

H-514-E-XMR-8202-02 (TU-35B)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	SWB-E1012	13.2kV SHIELDED 3/C (FROM 902 52-26 SW SWITCHGEAR BUS 2)		7.3.3
MCOV		13.2kV MCOV 100E 15.5kV 50kAIC		7.19.2
MV Interrupter Switch		EATON MVS 15kV (TU-35B)		7.5.1.3
Power Transformer	H-514-XMR-8202-02	TU-35B EATON 1500/1725kVA 13.2kV-480V S/N 12JC561940003		7.2.2, 7.12.3
Metal-Enclosed Busway		3200A BUSWAY 600V 3Ø 3W (TRANSFORMER TO LC MAIN)		7.4
Neutral Grounding Resistor		HRG 2×480V 2.5A CONT. 110.8Ω OUTDOOR (SE-325 / ER-600VC)	TU-35B HRG PANEL 104C	7.20.4
Current Transformer		200:5	TU-35B NGR TO SE-325	7.10.1
Current Transformer		5:5	TU-35B NGR AMMETER	7.10.1
Protective Relay		SE-325 NGR MONITOR (GF TRIP 0.5A)	TU-35B HRG PANEL 104C	7.9.2
Load Center	LC-35	TU-35 LC 480V 3Ø 3W 3200A 65kAIC (B BUS / MTM)		7.1
Low Voltage Circuit Breaker	TU-35B MAIN	EATON MDS632 3200AF 2500AT LSI (N.C.)	LC-35 104B	7.6.1.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Low Voltage Circuit Breaker	MCC SAC2-4	EATON MDS616 1600AF 1200AT LSI (SOUTH SECONDARY AERATION / SAC2-E1011)	LC-35 105A	7.6.1.2
Low Voltage Circuit Breaker	SPARE	EATON MDS616 1600AF 1200AT LSI (SPARE)	LC-35 105B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	EATON MDS616 1600AF 1200AT LSI (SPARE)	LC-35 105C	7.6.1.2
Low Voltage Circuit Breaker	TU-35 TIE	EATON MDS632 3200AF 2500AT LSI (N.O.)	LC-35 103B	7.6.1.2

H-902-E-XMR-8201-01 (TU-30A)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	SWB-E1000	13.2kV SHIELDED 3/C (FROM 902 52-13 SW SWITCHGEAR BUS 1)		7.3.3
MCOV		13.2kV MCOV 150E 15.5kV 50kAIC		7.19.2
MV Interrupter Switch		EATON MVS 15kV (TU-30A)		7.5.1.3
Power Transformer	H-902-XMR-8201-01	TU-30A EATON 2500/3125kVA 13.2kV-480V S/N 12JC561920002		7.2.2, 7.12.3
Metal-Enclosed Busway		3200A BUSWAY 600V 3Ø 3W (TRANSFORMER TO LC MAIN)		7.4
Neutral Grounding Resistor		HRG 2×480V 2.5A CONT. 110.8Ω OUTDOOR (SE-325 / ER-600VC)	TU-30A HRG PANEL 101C	7.20.4
Current Transformer		200:5	TU-30A NGR TO SE-325	7.10.1
Current Transformer		5:5	TU-30A NGR AMMETER	7.10.1
Protective Relay		SE-325 NGR MONITOR (GF TRIP 0.5A)	TU-30A HRG PANEL 101C	7.9.2
Load Center	LC-30	TU-30 LC 480V 3Ø 3W 4000A 65kAIC (A BUS / MTM)		7.1
Low Voltage Circuit Breaker	TU-30A MAIN	EATON MDS840 4000AF 4000AT LSI (N.C.)	LC-30 101B	7.6.1.2
Low Voltage Circuit Breaker	MCC SAC1-1	EATON MDS608 800AF 800AT LSI	LC-30 102A	7.6.1.2
Low Voltage Circuit Breaker	MCC SAC1-5	EATON MDS608 800AF 800AT LSI	LC-30 102B	7.6.1.2
Low Voltage Circuit Breaker	PE PUMP NO. 5 VFD	EATON MDS616 1600AF 800AT LSI (FUTURE)	LC-30 102C	7.6.1.2
Low Voltage Circuit Breaker	TU-30 TIE	EATON MDS840 4000AF 4000AT LSI (N.O.)	LC-30 103C	7.6.1.2

H-902-E-XMR-8201-02 (TU-30B)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	SWB-E1001	13.2kV SHIELDED 3/C (FROM 902 52-22 SW SWITCHGEAR BUS 2)		7.3.3
MCOV		13.2kV MCOV 150E 15.5kV 50kAIC		7.19.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
MV Interrupter Switch		EATON MVS 15kV (TU-30B)		7.5.1.3
Power Transformer	H-902-XMR-8201-02	TU-30B EATON 2500/3125kVA 13.2kV-480V S/N 12JC561920003		7.2.2, 7.12.3
Metal-Enclosed Busway		3200A BUSWAY 600V 3Ø 3W (TRANSFORMER TO LC MAIN)		7.4
Neutral Grounding Resistor		HRG 2×480V 2.5A CONT. 110.8Ω OUTDOOR (SE-325 / ER-600VC)	TU-30B HRG PANEL 105C	7.20.4
Current Transformer		200:5	TU-30B NGR TO SE-325	7.10.1
Current Transformer		5:5	TU-30B NGR AMMETER	7.10.1
Protective Relay		SE-325 NGR MONITOR (GF TRIP 0.5A)	TU-30B HRG PANEL 105C	7.9.2
Load Center	LC-30	TU-30 LC 480V 3Ø 3W 4000A 65kAIC (B BUS / MTM)		7.1
Low Voltage Circuit Breaker	TU-30B MAIN	EATON MDS840 4000AF 4000AT LSI (N.C.)	LC-30 105B	7.6.1.2
Low Voltage Circuit Breaker	MCC SAC1-2	EATON MDS608 800AF 800AT LSI	LC-30 104A	7.6.1.2
Low Voltage Circuit Breaker	PP-1	EATON MDS608 800AF 400AT LSI	LC-30 104B	7.6.1.2
Low Voltage Circuit Breaker	PE PUMP NO. 6 VFD	EATON MDS616 1600AF 800AT LSI	LC-30 104C	7.6.1.2
Low Voltage Circuit Breaker	TU-30 TIE	EATON MDS840 4000AF 4000AT LSI (N.O.)	LC-30 103C	7.6.1.2

H-902-E-XMR-8202-01 (TU-31A)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	SWB-E1002	13.2kV SHIELDED 3/C (FROM 902 52-12 SW SWITCHGEAR BUS 1)		7.3.3
MCOV		13.2kV MCOV 150E 15.5kV 50kAIC		7.19.2
MV Interrupter Switch		EATON MVS 15kV (TU-31A)		7.5.1.3
Power Transformer	H-902-XMR-8202-01	TU-31A EATON 2500/3125kVA 13.2kV-480V S/N 12JC561920004		7.2.2, 7.12.3
Metal-Enclosed Busway		3200A BUSWAY 600V 3Ø 3W (TRANSFORMER TO LC MAIN)		7.4
Neutral Grounding Resistor		HRG 2×480V 2.5A CONT. 110.8Ω OUTDOOR (SE-325 / ER-600VC)	TU-31A HRG PANEL 101C	7.20.4
Current Transformer		200:5	TU-31A NGR TO SE-325	7.10.1
Current Transformer		5:5	TU-31A NGR AMMETER	7.10.1
Protective Relay		SE-325 NGR MONITOR (GF TRIP 0.5A)	TU-31A HRG PANEL 101C	7.9.2
Load Center	LC-31	TU-31 LC 480V 3Ø 3W 4000A 65kAIC (A BUS / MTM)		7.1
Low Voltage Circuit Breaker	TU-31A MAIN	EATON MDS840 4000AF 4000AT LSI (N.C.)	LC-31 101B	7.6.1.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Low Voltage Circuit Breaker	MCC SAC1-3	EATON MDS608 800AF 800AT LSI	LC-31 102A	7.6.1.2
Low Voltage Circuit Breaker	SPARE	EATON MDS616 1600AF 1200AT LSI	LC-31 102B	7.6.1.2
Low Voltage Circuit Breaker	PE PUMP NO. 3 VFD	EATON MDS616 1600AF 800AT LSI	LC-31 102C	7.6.1.2
Low Voltage Circuit Breaker	TU-31 TIE	EATON MDS840 4000AF 4000AT LSI (N.O.)	LC-31 103C	7.6.1.2

H-902-E-XMR-8202-02 (TU-31B)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	SWB-E1003	13.2kV SHIELDED 3/C (FROM 902 52-23 SW SWITCHGEAR BUS 2)		7.3.3
MCOV		13.2kV MCOV 150E 15.5kV 50kAIC		7.19.2
MV Interrupter Switch		EATON MVS 15kV (TU-31B)		7.5.1.3
Power Transformer	H-902-XMR-8202-02	TU-31B EATON 2500/3125kVA 13.2kV-480V S/N 12JC561920005		7.2.2, 7.12.3
Metal-Enclosed Busway		3200A BUSWAY 600V 3Ø 3W (TRANSFORMER TO LC MAIN)		7.4
Neutral Grounding Resistor		HRG 2×480V 2.5A CONT. 110.8Ω OUTDOOR (SE-325 / ER-600VC)	TU-31B HRG PANEL 105C	7.20.4
Current Transformer		200:5	TU-31B NGR TO SE-325	7.10.1
Current Transformer		5:5	TU-31B NGR AMMETER	7.10.1
Protective Relay		SE-325 NGR MONITOR (GF TRIP 0.5A)	TU-31B HRG PANEL 105C	7.9.2
Load Center	LC-31	TU-31 LC 480V 3Ø 3W 4000A 65kAIC (B BUS / MTM)		7.1
Low Voltage Circuit Breaker	TU-31B MAIN	EATON MDS840 4000AF 4000AT LSI (N.C.)	LC-31 105B	7.6.1.2
Low Voltage Circuit Breaker	MCC SAC1-4	EATON MDS608 800AF 800AT LSI (FUTURE)	LC-31 104A	7.6.1.2
Low Voltage Circuit Breaker	MCC SAC1-6	EATON MDS608 800AF 800AT LSI	LC-31 104B	7.6.1.2
Low Voltage Circuit Breaker	PE PUMP NO. 4 VFD	EATON MDS616 1600AF 800AT LSI	LC-31 104C	7.6.1.2
Low Voltage Circuit Breaker	TU-31 TIE	EATON MDS840 4000AF 4000AT LSI (N.O.)	LC-31 103C	7.6.1.2

H-902-E-XMR-8203-01 (TU-32A)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	SWB-E1004	13.2kV SHIELDED 3/C (FROM 902 52-14 SW SWITCHGEAR BUS 1)		7.3.3
MCOV		13.2kV MCOV 150E 15.5kV 50kAIC		7.19.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
MV Interrupter Switch		EATON MVS 15kV (TU-32A)		7.5.1.3
Power Transformer	H-902-XMR-8203-01	TU-32A EATON 2500/3125kVA 13.2kV-480V S/N 12JC561920006		7.2.2, 7.12.3
Metal-Enclosed Busway		3200A BUSWAY 600V 3Ø 3W (TRANSFORMER TO LC MAIN)		7.4
Neutral Grounding Resistor		HRG 2×480V 2.5A CONT. 110.8Ω OUTDOOR (SE-325 / ER-600VC)	TU-32A HRG PANEL 101C	7.20.4
Current Transformer		200:5	TU-32A NGR TO SE-325	7.10.1
Current Transformer		5:5	TU-32A NGR AMMETER	7.10.1
Protective Relay		SE-325 NGR MONITOR (GF TRIP 0.5A)	TU-32A HRG PANEL 101C	7.9.2
Load Center	LC-32	TU-32 LC 480V 3Ø 3W 4000A 65kAIC (A BUS / MTM)		7.1
Low Voltage Circuit Breaker	TU-32A MAIN	EATON MDS840 4000AF 4000AT LSI (N.C.)	LC-32 101B	7.6.1.2
Low Voltage Circuit Breaker	MCC SWB-1	EATON MDS616 1600AF 1200AT LSI	LC-32 102A	7.6.1.2
Low Voltage Circuit Breaker	SPARE	EATON MDS616 1600AF 1200AT LSI	LC-32 102B	7.6.1.2
Low Voltage Circuit Breaker	PE PUMP NO. 1 VFD	EATON MDS616 1600AF 800AT LSI	LC-32 102C	7.6.1.2
Low Voltage Circuit Breaker	TU-32 TIE	EATON MDS840 4000AF 4000AT LSI (N.O.)	LC-32 103B	7.6.1.2

H-902-E-XMR-8203-02 (TU-32B)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	SWB-E1005	13.2kV SHIELDED 3/C (FROM 902 52-25 SW SWITCHGEAR BUS 2)		7.3.3
MCOV		13.2kV MCOV 150E 15.5kV 50kAIC		7.19.2
MV Interrupter Switch		EATON MVS 15kV (TU-32B)		7.5.1.3
Power Transformer	H-902-XMR-8203-02	TU-32B EATON 2500/3125kVA 13.2kV-480V S/N 12JC561920007		7.2.2, 7.12.3
Metal-Enclosed Busway		3200A BUSWAY 600V 3Ø 3W (TRANSFORMER TO LC MAIN)		7.4
Neutral Grounding Resistor		HRG 2×480V 2.5A CONT. 110.8Ω OUTDOOR (SE-325 / ER-600VC)	TU-32B HRG PANEL 105C	7.20.4
Current Transformer		200:5	TU-32B NGR TO SE-325	7.10.1
Current Transformer		5:5	TU-32B NGR AMMETER	7.10.1
Protective Relay		SE-325 NGR MONITOR (GF TRIP 0.5A)	TU-32B HRG PANEL 105C	7.9.2
Load Center	LC-32	TU-32 LC 480V 3Ø 3W 4000A 65kAIC (B BUS / MTM)		7.1
Low Voltage Circuit Breaker	TU-32B MAIN	EATON MDS840 4000AF 4000AT LSI (N.C.)	LC-32 105B	7.6.1.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Low Voltage Circuit Breaker	MCC SWB-2	EATON MDS616 1600AF 1200AT LSI	LC-32 104A	7.6.1.2
Low Voltage Circuit Breaker	SPARE	EATON MDS616 1600AF 1200AT LSI	LC-32 104B	7.6.1.2
Low Voltage Circuit Breaker	PE PUMP NO. 2 VFD	EATON MDS616 1600AF 800AT LSI	LC-32 104C	7.6.1.2
Low Voltage Circuit Breaker	TU-32 TIE	EATON MDS840 4000AF 4000AT LSI (N.O.)	LC-32 103B	7.6.1.2

H-902-E-XMR-8250-01 (TU-33A)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	SWB-E1006	13.2kV SHIELDED 3/C (FROM 902 52-11 SW SWITCHGEAR BUS 1)		7.3.3
MCOV		12.7kV MCOV (TRANSFORMER PRIMARY)		7.19.2
MV Interrupter Switch		EATON MVS 15kV (TU-33A)		7.5.1.3
Power Transformer	H-902-XMR-8250-01	TU-33A CUTLER-HAMMER 7500/9375kVA 13.2kV-4.16kV S/N AS40229-001		7.2.2, 7.12.3
Metal-Enclosed Busway		2000A BUSWAY 4160V 3Ø 3W (TRANSFORMER TO LC MAIN)		7.4
MCOV		5.1kV MCOV (TRANSFORMER SECONDARY)	TO 4.16kV BUS 1	7.19.2
Neutral Grounding Resistor		LRG 4160/2402V 400A 6Ω OUTDOOR (SE-325 / ER-5KV) — NO GF CT	TU-33A LRG PANEL	7.20.4
Protective Relay		SE-325 NGR MONITOR (RES FAULT ONLY; GF TRIP 4.0A)	TU-33A LRG PANEL	7.9.2
Switchgear Assembly		TU-33 4.16kV 2000A 3Ø W/ GND MV NONSEG BUS		7.1
Potential Transformer		3 PTs 40:1		7.10.2
Current Transformer		2000:5 MR	TO 51-MAIN-1	7.10.1
Protective Relay		51-MAIN-1 SEL-351	100A	7.9.2
Circuit Breaker	52-MAIN-1	52-MAIN-1 4.16kV 2000A	100A	7.6.3
Current Transformer		2000:5 FR	TO 87T / 902 52-11 DIFF	7.10.1
Protective Relay		87B-1		7.9.2
Current Transformer		1200:5 MR	TO 51-11	7.10.1
Protective Relay		51-11 SEL-351		7.9.2
Circuit Breaker	SPARE	52-11 4.16kV 1200A		7.6.3
MCOV		5.1kV MCOV		7.19.2
Current Transformer		1200:5 MR	TO 51-12	7.10.1
Protective Relay		51-12 SEL-351		7.9.2
Circuit Breaker	FUTURE AERATION BLOWER NO. 6 RVSS	52-12 4.16kV 1200A		7.6.3

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
MCOV		5.1kV MCOV		7.19.2
Current Transformer		1200:5 MR	TO 51-13	7.10.1
Protective Relay		51-13 SEL-351		7.9.2
Circuit Breaker	AERATION BLOWER NO. 5 RVSS	52-13 4.16kV 1200A		7.6.3
MCOV		5.1kV MCOV		7.19.2
Current Transformer		2000:5 FR	TIE-1 TO 87B-2	7.10.1
Circuit Breaker	52-TIE-1	52-TIE-1 4.16kV 2000A (N.O.) (BUS 1–BUS 2 TIE)		7.6.3

H-902-E-XMR-8250-02 (TU-33B)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	SWB-E1007	13.2kV SHIELDED 3/C (FROM 902 52-29 SW SWITCHGEAR BUS 2)		7.3.3
MCOV		12.7kV MCOV (TRANSFORMER PRIMARY)		7.19.2
MV Interrupter Switch		EATON MVS 15kV (TU-33B)		7.5.1.3
Power Transformer	H-902-XMR-8250-02	TU-33B CUTLER-HAMMER 7500/9375kVA 13.2kV-4.16kV S/N AS40229-002		7.2.2, 7.12.3
Metal-Enclosed Busway		2000A BUSWAY 4160V 3Ø 3W (TRANSFORMER TO LC MAIN)		7.4
MCOV		5.1kV MCOV (TRANSFORMER SECONDARY)	TO 4.16kV BUS 2	7.19.2
Neutral Grounding Resistor		LRG 4160/2402V 400A 6Ω OUTDOOR (SE-325 / ER-5KV) — NO GF CT	TU-33B LRG PANEL	7.20.4
Protective Relay		SE-325 NGR MONITOR (RES FAULT ONLY; GF TRIP 4.0A)	TU-33B LRG PANEL	7.9.2
Switchgear Assembly		TU-33 4.16kV 2000A 3Ø W/ GND MV NONSEG BUS		7.1
Potential Transformer		3 PTs 40:1		7.10.2
Current Transformer		2000:5 MR	TO 51-MAIN-2	7.10.1
Protective Relay		51-MAIN-2 SEL-351	106A	7.9.2
Circuit Breaker	52-MAIN-2	52-MAIN-2 4.16kV 2000A	106A	7.6.3
Current Transformer		2000:5 FR	TO 87T / 902 52-29 DIFF	7.10.1
Protective Relay		87B-2		7.9.2
Current Transformer		1200:5 MR	TO 51-21	7.10.1
Protective Relay		51-21 SEL-351		7.9.2
Circuit Breaker	AERATION BLOWER NO. 4 RVSS	52-21 4.16kV 1200A		7.6.3
MCOV		5.1kV MCOV		7.19.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Current Transformer		1200:5 MR	TO 51-22	7.10.1
Protective Relay		51-22 SEL-351		7.9.2
Circuit Breaker	SPARE	52-22 4.16kV 1200A		7.6.3
MCOV		5.1kV MCOV		7.19.2
Current Transformer		1200:5 MR	TO 51-23	7.10.1
Protective Relay		51-23 SEL-351		7.9.2
Circuit Breaker	AERATION BLOWER NO. 3 RVSS	52-23 4.16kV 1200A		7.6.3
MCOV		5.1kV MCOV		7.19.2
Circuit Breaker	52-TIE-1	52-TIE-1 4.16kV 2000A (N.O.) (BUS 1–BUS 2 TIE)		7.6.3
Circuit Breaker	52-TIE-2	52-TIE-2 4.16kV 2000A (N.O.) (BUS 2–BUS 3 TIE)		7.6.3

H-902-E-XMR-8250-03 (TU-33C)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	SWB-E1008	13.2kV SHIELDED 3/C (FROM 902 52-31 SW SWITCHGEAR BUS 3 TO TU-33C)		7.3.3
MCOV		12.7kV MCOV (TRANSFORMER PRIMARY)		7.19.2
MV Interrupter Switch		EATON MVS 15kV (TU-33C)		7.5.1.3
Power Transformer	H-902-XMR-8250-03	TU-33C CUTLER-HAMMER 7500/9375kVA 13.2kV-4.16kV S/N AS40229-003		7.2.2, 7.12.3
Metal-Enclosed Busway		2000A BUSWAY 4160V 3Ø 3W (TRANSFORMER TO LC MAIN)		7.4
MCOV		5.1kV MCOV (TRANSFORMER SECONDARY)	TO 4.16kV BUS 3	7.19.2
Neutral Grounding Resistor		LRG 4160/2402V 400A 6Ω OUTDOOR (SE-325 / ER-5KV) — NO GF CT	TU-33C LRG PANEL	7.20.4
Protective Relay		SE-325 NGR MONITOR (RES FAULT ONLY; GF TRIP 4.0A)	TU-33C LRG PANEL	7.9.2
Switchgear Assembly		TU-33 4.16kV 2000A 3Ø W/ GND MV NONSEG BUS		7.1
Potential Transformer		3 PTs 40:1		7.10.2
Current Transformer		2000:5 MR	TO 51-MAIN-3	7.10.1
Protective Relay		51-MAIN-3 SEL-351	110A	7.9.2
Circuit Breaker	52-MAIN-3	52-MAIN-3 4.16kV 2000A (N.C.)	110A	7.6.3
Current Transformer		2000:5 FR	TO 87T / 902 52-31 DIFF	7.10.1
Protective Relay		87B-3		7.9.2
Current Transformer		1200:5 MR	TO 51-31	7.10.1
Protective Relay		51-31 SEL-351		7.9.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Circuit Breaker	AERATION BLOWER NO. 2 RVSS	52-31 4.16kV 1200A		7.6.3
MCOV		5.1kV MCOV		7.19.2
Current Transformer		1200:5 MR	TO 51-32	7.10.1
Protective Relay		51-32 SEL-351		7.9.2
Circuit Breaker	AERATION BLOWER NO. 1 RVSS	52-32 4.16kV 1200A		7.6.3
MCOV		5.1kV MCOV		7.19.2
Current Transformer		2000:5 FR	TIE-2 TO 87B-2	7.10.1
Circuit Breaker	52-TIE-2	52-TIE-2 4.16kV 2000A (N.O.) (BUS 2–BUS 3 TIE)		7.6.3

2030 Maintenance Group

901 Bus 1-See 2027 Maintenance Group

901 Bus 2-See 2027 Maintenance Group

903 Bus 1

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Switchgear Assembly	H-903-SWG-8101-01	15kV METACLAD 1200A Continuous 25kA 95kV BIL (TYP.)		7.1
Medium Voltage Cable		13.2kV SHIELDED (FROM H-901-SWG-8001-01 52-11)		7.3.3
MCOV		12.7kV MCOV (FROM H-901-SWG-8001-01 52-11)	107A	7.19.2
Potential Transformer		BUS-1 PT2 7.6kV-120V 63.5:1	107B	7.10.2
Current Transformer		1200:5 C400	107A M1 TO 87B-1	7.10.1
Current Transformer		1200:5 MR 1200:5 TAP C200	106A TO 51-MAIN-1	7.10.1
Protective Relay		51-MAIN-1 SEL-351S	106B	7.9.2
Circuit Breaker	52-MAIN-1	52-MAIN-1 15kV 1200A Eaton Type 15VCP-W25 (N.C.) (FROM H-901-SWG-8001-01 52-11)	106B	7.6.3
Protective Relay		87B-1 SEL-587Z	106A	7.9.2
Potential Transformer		BUS-1 PT1 7.6kV-120V 63.5:1	106A	7.10.2
Control Power Transformer		BUS-1 CPT1 13.2kV-480V 45kVA 3PH (TO H-903-UDS-8410-01 PRIMARY)	101B	7.2.2
Circuit Breaker		FD 35k 70A	101A	7.6.1.1
Current Transformer		600:5 MR 600:5 TAP C200	102B TO 51-18	7.10.1
Protective Relay		51-18 SEL-351	102B	7.9.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Circuit Breaker	SPARE	52-18 15kV 1200A Eaton Type 15VCP-W25 (FUTURE PAR 1411)	102B	7.6.3
Current Transformer		1200:5 C400	102B TO 87B-1	7.10.1
MCOV		12.7kV MCOV (TO H-523-XMR-8250-01 TU-5A N. SECONDARY WEST BLOWER)	102B	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	102A TO 51-17	7.10.1
Protective Relay		51-17 SEL-351	102A	7.9.2
Circuit Breaker	H-527-XMR-8201-01	52-17 15kV 1200A Eaton Type 15VCP-W25 (FUTURE PAR 1411)	102A	7.6.3
Current Transformer		1200:5 C400	102A TO 87B-1	7.10.1
MCOV		12.7kV MCOV	102A	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	103B TO 51-16	7.10.1
Protective Relay		51-16 SEL-351	103B	7.9.2
Circuit Breaker	H-931-XMR-8201-01 (TU-8A)	52-16 15kV 1200A Eaton Type 15VCP-W25	103B	7.6.3
Current Transformer		1200:5 C400	103B TO 87B-1	7.10.1
MCOV		12.7kV MCOV	103B	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	103A TO 51-15	7.10.1
Protective Relay		51-15 SEL-351	103A	7.9.2
Circuit Breaker	H-527-XMR-8251-01	52-15 15kV 1200A Eaton Type 15VCP-W25 (FUTURE PAR 1411)	103A	7.6.3
Current Transformer		1200:5 C400	103A TO 87B-1	7.10.1
MCOV		12.7kV MCOV	103A	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	104B TO 51-14	7.10.1
Protective Relay		51-14 SEL-351	104B	7.9.2
Circuit Breaker	H-951-XMR-8201-01 (TU-7A)	52-14 15kV 1200A Eaton Type 15VCP-W25	104B	7.6.3
Current Transformer		1200:5 C400	104B TO 87B-1	7.10.1
MCOV		12.7kV MCOV	104B	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	104A TO 51-13	7.10.1
Protective Relay		51-13 SEL-351	104A	7.9.2
Circuit Breaker	H-840-XMR-8202-01 (TU-42A)	52-13 15kV 1200A Eaton Type 15VCP-W25	104A	7.6.3
Current Transformer		1200:5 C400	104A TO 87B-1	7.10.1
MCOV		12.7kV MCOV	104A	7.19.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Current Transformer		600:5 MR 600:5 TAP C200	105B TO 51-12	7.10.1
Protective Relay		51-12 SEL-351	105B	7.9.2
Circuit Breaker	H-260-XMR-8201-01 (TU-43)	52-12 15kV 1200A Eaton Type 15VCP-W25	105B	7.6.3
Current Transformer		1200:5 C400	105B TO 87B-1	7.10.1
MCOV		12.7kV MCOV	105B	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	105A TO 51-11	7.10.1
Protective Relay		51-11 SEL-351	105A	7.9.2
Circuit Breaker	H-840-XMR-8201-01 (TU-41A)	52-11 15kV 1200A Eaton Type 15VCP-W25	105A	7.6.3
Current Transformer		1200:5 C400	105A TO 87B-1	7.10.1
MCOV		12.7kV MCOV	105A	7.19.2
Protective Relay		25-TIE BE1-25	107A	7.9.2
Circuit Breaker	52-T1	52-T1 15kV 1200A Eaton Type 15VCP-W25	107A	7.6.3
Current Transformer		1200:5 C400	107A T1 TO 87B-2	7.10.1
Current Transformer		1200:5 C400	107A T2 TO 87B-1	7.10.1

903 Bus 2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Protective Relay		25-TIE BE1-25	107A	7.9.2
Circuit Breaker	52-T1	52-T1 15kV 1200A Eaton Type 15VCP-W25	107A	7.6.3
Current Transformer		1200:5 C400	107A T1 TO 87B-2	7.10.1
Current Transformer		1200:5 C400	107A T2 TO 87B-1	7.10.1
Potential Transformer		BUS-2 PT2 7.6kV-120V 63.5:1	108A	7.10.2
Protective Relay		87B-2 SEL-587Z	108A	7.9.2
Potential Transformer		BUS-2 PT1 7.6kV-120V 63.5:1	108A	7.10.2
Medium Voltage Cable		13.2kV SHIELDED (FROM H-901-SWG-8001-02 52-21)		7.3.3
MCOV		12.7kV MCOV (FROM H-901-SWG-8001-02 52-21)	108B	7.19.2
Current Transformer		1200:5 C400	108B M2 TO 87B-2	7.10.1
Current Transformer		1200:5 MR 1200:5 TAP C200	108B TO 51-MAIN-2	7.10.1
Protective Relay		51-MAIN-2 SEL-351S	108B	7.9.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Circuit Breaker	52-MAIN-2	52-MAIN-2 15kV 1200A Eaton Type 15VCP-W25 (FROM H-901-SWG-8001-02 52-21)	108B	7.6.3
Current Transformer		600:5 MR 600:5 TAP C200	109A TO 51-21	7.10.1
Protective Relay		51-21 SEL-351	109A	7.9.2
Circuit Breaker	H-840-XMR-8201-02 (TU-41B)	52-21 15kV 1200A Eaton Type 15VCP-W25	109A	7.6.3
Current Transformer		1200:5 C400	109A TO 87B-2	7.10.1
MCOV		12.7kV MCOV	109A	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	109B TO 51-22	7.10.1
Protective Relay		51-22 SEL-351	109B	7.9.2
Circuit Breaker	SPARE	52-22 15kV 1200A Eaton Type 15VCP-W25	109B	7.6.3
Current Transformer		1200:5 C400	109B TO 87B-2	7.10.1
MCOV		12.7kV MCOV	109B	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	110A TO 51-23	7.10.1
Protective Relay		51-23 SEL-351	110A	7.9.2
Circuit Breaker	H-840-XMR-8202-02 (TU-42B)	52-23 15kV 1200A Eaton Type 15VCP-W25	110A	7.6.3
Current Transformer		1200:5 C400	110A TO 87B-2	7.10.1
MCOV		12.7kV MCOV	110A	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	110B TO 51-24	7.10.1
Protective Relay		51-24 SEL-351	110B	7.9.2
Circuit Breaker	H-951-XMR-8201-02 (TU-7B)	52-24 15kV 1200A Eaton Type 15VCP-W25	110B	7.6.3
Current Transformer		1200:5 C400	110B TO 87B-2	7.10.1
MCOV		12.7kV MCOV	110B	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	111A TO 51-25	7.10.1
Protective Relay		51-25 SEL-351	111A	7.9.2
Circuit Breaker	H-527-XMR-8251-02	52-25 15kV 1200A Eaton Type 15VCP-W25 (FUTURE PAR 1411)	111A	7.6.3
Current Transformer		1200:5 C400	111A TO 87B-2	7.10.1
MCOV		12.7kV MCOV	111A	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	111B TO 51-26	7.10.1
Protective Relay		51-26 SEL-351	111B	7.9.2
Circuit Breaker	H-931-XMR-8201-02 (TU-8B)	52-26 15kV 1200A Eaton Type 15VCP-W25	111B	7.6.3

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Current Transformer		1200:5 C400	111B TO 87B-2	7.10.1
MCOV		12.7kV MCOV	111B	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	112A TO 51-27	7.10.1
Protective Relay		51-27 SEL-351	112A	7.9.2
Circuit Breaker	H-527-XMR-8201-02	52-27 15kV 1200A Eaton Type 15VCP-W25 (FUTURE PAR 1411)	112A	7.6.3
Current Transformer		1200:5 C400	112A TO 87B-2	7.10.1
MCOV		12.7kV MCOV	112A	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	112B TO 51-28	7.10.1
Protective Relay		51-28 SEL-351	112B	7.9.2
Circuit Breaker	SPARE	52-28 15kV 1200A Eaton Type 15VCP-W25 (FUTURE PAR 1411)	112B	7.6.3
Current Transformer		1200:5 C400	112B TO 87B-2	7.10.1
MCOV		12.7kV MCOV	112B	7.19.2
Control Power Transformer		BUS-2 CPT1 13.2kV-480V 45kVA 3PH (TO H-903-UDS-8410-01 STANDBY)	113A	7.2.2
Circuit Breaker		FD 35k 70A	113A	7.6.1.1

H-260-XMR-8201-01 (TU-43)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable		13.2kV SHIELDED 3/C (FROM 903 52-12 CUBICLE 105B)		7.3.3
MCOV		12.7kV MCOV (TRANSFORMER PRIMARY — ALSO ON 903 105B)		7.19.2
Power Transformer	H-260-XMR-8201-01	TU-43 TMV-OSB 750 kVA 13.2kV-480Y/277V		7.2.2, 7.12.3

H-527-XMR-8201-01

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	527-E2005	13.2kV SHIELDED 3/C (FROM 903 52-17 CUBICLE 102A)		7.3.3
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
Power Transformer	H-527-XMR-8201-01	2500/3125 kVA KNAN/KNAF 13.2kV-480V		7.2.2, 7.12.3
Low Voltage Cable	527-E2028	480V SECONDARY (TRANSFORMER TO LC MAIN 101B)		7.3.2
Neutral Grounding Resistor	H-527-HRG-8201-01	HRG 277V 2.5A CONT. 5:5 / 5:0.05 CT (527-E2030 / 527-E2031 / 527-E2032)	101C	7.20.4
Current Transformer		5:5	101C TO 50G / AMMETER	7.10.1

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Current Transformer		5:0.05	101C TO 50G	7.10.1
Protective Relay		50G / 73 NGR MONITOR (AM / 73 / 50G)	101C	7.9.2
Load Center	H-527-LDC-8201-01	480V 3200A 3Ø 3W 65kAIC (BUS 1 / MTM)		7.1
Low Voltage Circuit Breaker	MAIN 1	3200AF 3200AT LSI (N.C.)	101B	7.6.1.2
Low Voltage Circuit Breaker	H-597-PPL-8420-01	800AF 250AT LSI (H-597-PJB-8601-01 CARBON ADDITION) 527-E2086	102B	7.6.1.2
Low Voltage Circuit Breaker	H-527-MCC-8301-01	1200AF 1200AT LSI (N. SECONDARY BLOWER FACILITY) 527-E2038	102C	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 225AT LSI (SPARE)	102D	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 800AT LSI (SPARE)	103A	7.6.1.2
Low Voltage Circuit Breaker	H-527-UDS-8430-01 STANDBY	800AF 200AT LSI (N. SECONDARY BLOWER / LPL-8439-01)	103B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 800AT LSI (SPARE)	103C	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 800AT LSI (SPARE)	103D	7.6.1.2
Low Voltage Circuit Breaker	SPARE	1600AF 1600AT LSI (SPARE)	104A	7.6.1.2
Low Voltage Circuit Breaker	TIE	3200AF 3200AT LSI (N.O.) (BUS 1–BUS 2 TIE)	104B	7.6.1.2

H-527-XMR-8201-02

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	527-E2006	13.2kV SHIELDED 3/C (FROM 903 52-27 CUBICLE 112A)		7.3.3
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
Power Transformer	H-527-XMR-8201-02	2500/3125 kVA KNAN/KNAF 13.2kV-480V		7.2.2, 7.12.3
Low Voltage Cable	527-E2029	480V SECONDARY (TRANSFORMER TO LC MAIN 107A)		7.3.2
Neutral Grounding Resistor	H-527-HRG-8201-02	HRG 277V 2.5A CONT. 5:5 / 10:5 CT (527-E2034 / 527-E2035 / 527-E2036)	107C	7.20.4
Current Transformer		5:5	107C TO 50G / AMMETER	7.10.1
Current Transformer		10:5	107C TO 50G	7.10.1
Protective Relay		50G / 73 NGR MONITOR (AM / 73 / 50G)	107C	7.9.2
Load Center	H-527-LDC-8201-01	480V 3200A 3Ø 3W 65kAIC (BUS 2 / MTM)		7.1
Low Voltage Circuit Breaker	MAIN 2	3200AF 3200AT LSI (N.C.)	107A	7.6.1.2
Low Voltage Circuit Breaker	H-527-MCC-8301-02	1200AF 1200AT LSI (N. SECONDARY BLOWER FACILITY) 527-E2039	106C	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 200AT LSI (SPARE)	106B	7.6.1.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Low Voltage Circuit Breaker	SPARE	800AF 200AT LSI (SPARE)	105D	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 200AT LSI (SPARE)	105C	7.6.1.2
Low Voltage Circuit Breaker	H-527-UDS-8430-01 PRIMARY	800AF 200AT LSI (N. SECONDARY BLOWER) 527-E2041	105B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 800AT LSI (SPARE)	105A	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 800AT LSI (SPARE)	104D	7.6.1.2
Low Voltage Circuit Breaker	SPARE	1600AF 1600AT LSI (SPARE)	104C	7.6.1.2
Low Voltage Circuit Breaker	TIE	3200AF 3200AT LSI (N.O.) (BUS 1–BUS 2 TIE)	104B	7.6.1.2

H-527-XMR-8251-01

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable		13.2kV SHIELDED 3/C (FROM 903 52-15 CUBICLE 103A)		7.3.3
MCOV		7.2kV MCOV (TRANSFORMER H-527-XMR-8251-01)		7.19.2
Power Transformer	H-527-XMR-8251-01	5000/6250 kVA OA/FA 13.2kV-4160V Z=5.42%		7.2.2, 7.12.3
Medium Voltage Cable		4160 V SHIELDED		7.3.3
Neutral Grounding Resistor	H-527-LRG-8251-01	LRG 400A 300:5 (600:5 MR @ 200:5 TAP C200, 1 CT)		7.20.4
Current Transformer		600:5 MR 200:5 TAP C200	LRG-8251-01 TO 50G-1	7.10.1
Protective Relay		50G-1 SE-330X3	101B	7.9.2
Switchgear Assembly	H-527-LDC-8251-01	5kV METAL CLAD 1200A 29kA (BUS 1)		7.1
MCOV		12.7kV MCOV (FROM H-527-XMR-8251-01)	101B	7.19.2
Potential Transformer		PT-L1 4.16kV-120V 34.7:1 3Ø	101A TO 51-M1	7.10.2
Current Transformer		1200:5 C400	101B M1 TO 87B-1	7.10.1
Current Transformer		1200:5 MR 1200:5 TAP C200	101B TO 51-M1	7.10.1
Protective Relay		51-M1 SEL-351S	101B	7.9.2
Circuit Breaker	52-M1	52-M1 5kV 1200A (N.C.) (FROM H-527-XMR-8251-01)	101B	7.6.3
Protective Relay		87B-1 SEL-587Z	103B	7.9.2
Potential Transformer		PT-B1 4.16kV-120V 34.7:1 3Ø	101A	7.10.2
Current Transformer		600:5 MR 600:5 TAP C200	101B TO 903 52-15 / 87T-15	7.10.1
Current Transformer		600:5 MR 600:5 TAP C200	102B TO 51-12	7.10.1

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Protective Relay		51-12 SEL-351	102B	7.9.2
Circuit Breaker	H-527-VFD-2101-01	52-12 5kV 1200A	102B	7.6.3
Current Transformer		1200:5 C400	102B TO 87B-1	7.10.1
MCOV		12.7kV MCOV	102B	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	102A TO 51-11	7.10.1
Protective Relay		51-11 SEL-351	102A	7.9.2
Circuit Breaker	H-527-VFD-2101-03	52-11 5kV 1200A	102A	7.6.3
Current Transformer		1200:5 C400	102A TO 87B-1	7.10.1
MCOV		12.7kV MCOV	102A	7.19.2
Protective Relay		25-T1 BE1-25	103A	7.9.2
Circuit Breaker	52-T1	52-T1 5kV 1200A (N.O.) (BUS 1–BUS 3 TIE)	103A	7.6.3
Current Transformer		1200:5 C400	103A T1 TO 87B-1	7.10.1
Potential Transformer		PT-B3 4.16kV-120V 34.7:1 3Ø	104A	7.10.2
Protective Relay		87B-3 SEL-587Z	106B	7.9.2
Current Transformer		600:5 MR 600:5 TAP C200	104B TO 51-34	7.10.1
Protective Relay		51-34 SEL-351	104B	7.9.2
Circuit Breaker	H-527-VFD-2101-05	52-34 5kV 1200A	104B	7.6.3
Current Transformer		1200:5 C400	104B TO 87B-3	7.10.1
MCOV		12.7kV MCOV	104B	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	105B TO 51-32	7.10.1
Protective Relay		51-32 SEL-351	105B	7.9.2
Circuit Breaker	H-527-VFD-2101-06	52-32 5kV 1200A	105B	7.6.3
Current Transformer		1200:5 C400	105B TO 87B-3	7.10.1
MCOV		12.7kV MCOV	105B	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	105A TO 51-31	7.10.1
Protective Relay		51-31 SEL-351	105A	7.9.2
Circuit Breaker	SPARE	52-31 5kV 1200A	105A	7.6.3
Current Transformer		1200:5 C400	105A TO 87B-3	7.10.1
MCOV		12.7kV MCOV	105A	7.19.2
Current Transformer		1200:5 C400	103A T1 TO 87B-3	7.10.1
Current Transformer		1200:5 C400	106A T2 TO 87B-3	7.10.1

H-527-XMR-8251-02

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable		13.2kV SHIELDED 3/C (FROM 903 52-25 CUBICLE 111A)		7.3.3
MCOV		7.2kV MCOV (TRANSFORMER H-527-XMR-8251-02)		7.19.2
Power Transformer	H-527-XMR-8251-02	5000/6250 kVA OA/FA 13.2kV-4160V Z=5.43%		7.2.2, 7.12.3
Medium Voltage Cable		4160 V SHIELDED		7.3.3
Neutral Grounding Resistor	H-527-LRG-8251-02	LRG 400A 300:5 (600:5 MR @ 200:5 TAP C200, 1 CT)		7.20.4
Current Transformer		600:5 MR 200:5 TAP C200	LRG-8251-02 TO 50G-2	7.10.1
Protective Relay		50G-2 SE-330X3	108B	7.9.2
Switchgear Assembly	H-527-LDC-8251-01	5kV METAL CLAD 1200A 29kA (BUS 2)		7.1
MCOV		12.7kV MCOV (FROM H-527-XMR-8251-02)	108B	7.19.2
Potential Transformer		PT-L2 4.16kV-120V 34.7:1 3Ø	108A TO 51-M2	7.10.2
Current Transformer		1200:5 C400	108B M2 TO 87B-2	7.10.1
Current Transformer		1200:5 MR 1200:5 TAP C200	108B TO 51-M2	7.10.1
Protective Relay		51-M2 SEL-351S	108B	7.9.2
Circuit Breaker	52-M2	52-M2 5kV 1200A (N.C.) (FROM H-527-XMR-8251-02)	108B	7.6.3
Protective Relay		87B-2 SEL-587Z	106B	7.9.2
Potential Transformer		PT-B2 4.16kV-120V 34.7:1 3Ø	108A	7.10.2
Current Transformer		600:5 MR 600:5 TAP C200	108B TO 903 52-25 / 87T-25	7.10.1
Current Transformer		600:5 MR 600:5 TAP C200	107B TO 51-22	7.10.1
Protective Relay		51-22 SEL-351	107B	7.9.2
Circuit Breaker	H-527-VFD-2101-02	52-22 5kV 1200A	107B	7.6.3
Current Transformer		1200:5 C400	107B TO 87B-2	7.10.1
MCOV		12.7kV MCOV	107B	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	107A TO 51-21	7.10.1
Protective Relay		51-21 SEL-351	107A	7.9.2
Circuit Breaker	H-527-VFD-2101-04	52-21 5kV 1200A	107A	7.6.3
Current Transformer		1200:5 C400	107A TO 87B-2	7.10.1
MCOV		12.7kV MCOV	107A	7.19.2
Protective Relay		25-T2 BE1-25	106A	7.9.2
Circuit Breaker	52-T2	52-T2 5kV 1200A (N.C.) (BUS 3–BUS 2 TIE)	106A	7.6.3

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Current Transformer		1200:5 C400	106A T2 TO 87B-2	7.10.1
Potential Transformer		PT-B3 4.16kV-120V 34.7:1 3Ø	104A	7.10.2
Protective Relay		87B-3 SEL-587Z	106B	7.9.2
Current Transformer		600:5 MR 600:5 TAP C200	104B TO 51-34	7.10.1
Protective Relay		51-34 SEL-351	104B	7.9.2
Circuit Breaker	H-527-VFD-2101-05	52-34 5kV 1200A	104B	7.6.3
Current Transformer		1200:5 C400	104B TO 87B-3	7.10.1
MCOV		12.7kV MCOV	104B	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	105B TO 51-32	7.10.1
Protective Relay		51-32 SEL-351	105B	7.9.2
Circuit Breaker	H-527-VFD-2101-06	52-32 5kV 1200A	105B	7.6.3
Current Transformer		1200:5 C400	105B TO 87B-3	7.10.1
MCOV		12.7kV MCOV	105B	7.19.2
Current Transformer		600:5 MR 600:5 TAP C200	105A TO 51-31	7.10.1
Protective Relay		51-31 SEL-351	105A	7.9.2
Circuit Breaker	SPARE	52-31 5kV 1200A	105A	7.6.3
Current Transformer		1200:5 C400	105A TO 87B-3	7.10.1
MCOV		12.7kV MCOV	105A	7.19.2
Current Transformer		1200:5 C400	103A T1 TO 87B-3	7.10.1
Current Transformer		1200:5 C400	106A T2 TO 87B-3	7.10.1

H-951-XMR-8201-01 (TU-7A)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	951-E0107 / 951-E0109	13.2kV SHIELDED 3/C (FROM 903 52-14 CUBICLE 104B)		7.3.3
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
MV Interrupter Switch		EATON WFS9078A40G19 15kV (TU-7A)		7.5.1.3
Power Transformer	H-951-XMR-8201-01	TU-7A GE 2500kVA KNAN 13.2kV-480Y/277V S/N S2549-01-001		7.2.2, 7.12.3
Low Voltage Cable		480V 3Ø (TRANSFORMER TO LC MAIN)		7.3.2
Neutral Grounding Resistor	H-951-HRG-8201-01	HRG 277V 2.5A CONT. (SE-325) 5:5 / 5:0.05 CT	TU-7A HRG PANEL 101C	7.20.4
Current Transformer		5:5	101C TO SE-325 / AMMETER	7.10.1

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Current Transformer		5:0.05	101C TO SE-325	7.10.1
Protective Relay		SE-325 NGR MONITOR (AM / 73 / 50G)	LC-7 101C	7.9.2
Load Center	H-951-LDC-8201-01	LC-7 480V 3Ø 3W 3000A 65kAIC (A BUS / MTM)		7.1
Low Voltage Circuit Breaker	TU-7A MAIN	EATON MDS632 3200AF 3000AT LSI (N.C.)	LC-7 101C	7.6.1.2
Low Voltage Circuit Breaker	H-413-MCC-8301-01	EATON MDS616 1600AF 200AT LSI (N. PRIMARY PUMP STATION 2)	LC-7 101A	7.6.1.2
Low Voltage Circuit Breaker	H-523-PJB-8201-01	EATON MDS616 1600AF 400AT LSI	LC-7 101D	7.6.1.2
Low Voltage Circuit Breaker	H-583-MCC-8201-01	EATON MDS616 1600AF 1600AT LSI (N. AERATION CTRL FAC 2 / SCUM 2)	LC-7 102A	7.6.1.2
Low Voltage Circuit Breaker	TU-7 TIE	EATON MDS632 3200AF 3000AT LSI (N.O.)	LC-7 102C	7.6.1.2

H-951-XMR-8201-02 (TU-7B)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	951-E0108 / 951-E0110	13.2kV SHIELDED 3/C (FROM 903 52-22 CUBICLE 110B)		7.3.3
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
MV Interrupter Switch		EATON WFS9078A40G19 15kV (TU-7B)		7.5.1.3
Power Transformer	H-951-XMR-8201-02	TU-7B GE 2500kVA KNAN 13.2kV-480Y/277V S/N S2550-01-001		7.2.2, 7.12.3
Low Voltage Cable		480V 3Ø (TRANSFORMER TO LC MAIN)		7.3.2
Neutral Grounding Resistor	H-951-HRG-8201-02	HRG 277V 2.5A CONT. (SE-325) 5:5 / 5:0.05 CT	TU-7B HRG PANEL 103B	7.20.4
Current Transformer		5:5	103B TO SE-325 / AMMETER	7.10.1
Current Transformer		5:0.05	103B TO SE-325	7.10.1
Protective Relay		SE-325 NGR MONITOR (AM / 73 / 50G)	LC-7 103B	7.9.2
Load Center	H-951-LDC-8201-01	LC-7 480V 3Ø 3W 3000A 65kAIC (B BUS / MTM)		7.1
Low Voltage Circuit Breaker	TU-7B MAIN	EATON MDS632 3200AF 3000AT LSI (N.C.)	LC-7 104C	7.6.1.2
Low Voltage Circuit Breaker	H-523-PJB-8201-01	EATON MDS616 1600AF 1600AT LSI (N. SECONDARY WEST BLOWER)	LC-7 102D	7.6.1.2
Low Voltage Circuit Breaker	H-523-MCC-8301-01	EATON MDS616 1600AF 400AT LSI (N. SECONDARY WEST BLOWER)	LC-7 103A	7.6.1.2
Low Voltage Circuit Breaker	H-411-MCC-8301-01	EATON MDS616 1600AF 400AT LSI (N. PRIMARY PUMP STATION 1)	LC-7 103C	7.6.1.2
Low Voltage Circuit Breaker	H-581-MCC-8201-01	EATON MDS616 1600AF 1600AT LSI (N. SECONDARY SCUM PUMP STATION 1)	LC-7 103D	7.6.1.2
Low Voltage Circuit Breaker	SPARE	EATON MDS616 1600AF 400AT LSI	LC-7 104D	7.6.1.2
Low Voltage Circuit Breaker	H-951-PPL-8410-01	EATON MDS608 800AF 200AT LSI (UDS/PPL/LPL 208/120V)	LC-7 104A	7.6.1.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Low Voltage Circuit Breaker	TU-7 TIE	EATON MDS632 3200AF 3000AT LSI (N.O.)	LC-7 102C	7.6.1.2

H-840-XMR-8201-01 (TU-41A)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable		13.2kV SHIELDED 3/C (FROM 903 52-11 CUBICLE 105A)		7.3.3
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
Power Transformer	H-840-XMR-8201-01	TU-41A 2500-3125/2800-3500 kVA 13.2kV-480V		7.2.2, 7.12.3
Low Voltage Cable		480V 3Ø (TRANSFORMER TO LC MAIN)		7.3.2
Neutral Grounding Resistor	H-840-HRG-8201-01	HRG 2-480V 2.5A CONT. 5:5 / 200:5 CT	101C	7.20.4
Current Transformer		5:5	101C TO 50G / AMMETER	7.10.1
Current Transformer		200:5	101C TO 50G	7.10.1
Protective Relay		50G / 73 NGR MONITOR (AM / 73 / 50G)	101C	7.9.2
Load Center	H-840-LDC-8201-01	480V 3Ø 3W 4000A 85kAIC (BUS A / MTM)		7.1
Low Voltage Circuit Breaker	MAIN A	4000AF 4000AT LSI (N.C.)	101B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 400AT LSI (SPARE / EXISTING PNLBD CPB1 TEMP)	101G	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 800AT LSI (SPARE / MCC DSS-1 TEMP)	101H	7.6.1.2
Low Voltage Circuit Breaker	H-840-CFG-2110-13	800AF 300AT LSI (CENTRIFUGE 1-3 FUTURE)	102A	7.6.1.2
Low Voltage Circuit Breaker	H-840-MCC-8300-01	800AF 800AT LSI (BIOSOLIDS DEWATERING AND STORAGE)	102B	7.6.1.2
Low Voltage Circuit Breaker	H-840-CFG-2110-12	800AF 300AT LSI (CENTRIFUGE 1-2)	102C	7.6.1.2
Low Voltage Circuit Breaker	H-840-CFG-2110-11	800AF 300AT LSI (CENTRIFUGE 1-1)	102D	7.6.1.2
Low Voltage Circuit Breaker	H-827-MCC-8300-01	800AF 800AT LSI (SLUDGE HOLDING TANKS)	103B	7.6.1.2
Low Voltage Circuit Breaker	TIE	4000AF 4000AT LSI (N.O.) (BUS A–BUS B TIE)	103C	7.6.1.2

H-840-XMR-8201-02 (TU-41B)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable		13.2kV SHIELDED 3/C (FROM 903 52-21 CUBICLE 109A)		7.3.3
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
Power Transformer	H-840-XMR-8201-02	TU-41B 2500-3125/2800-3500 kVA 13.2kV-480V		7.2.2, 7.12.3
Low Voltage Cable		480V 3Ø (TRANSFORMER TO LC MAIN)		7.3.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Neutral Grounding Resistor	H-840-HRG-8201-02	HRG 2-480V 2.5A CONT. 5:5 / 200:5 CT	105G	7.20.4
Current Transformer		5:5	105G TO 50G / AMMETER	7.10.1
Current Transformer		200:5	105G TO 50G	7.10.1
Protective Relay		50G / 73 NGR MONITOR (AM / 73 / 50G)	105G	7.9.2
Load Center	H-840-LDC-8201-01	480V 3Ø 3W 4000A 85kAIC (BUS B / MTM)		7.1
Low Voltage Circuit Breaker	MAIN B	4000AF 4000AT LSI (N.C.)	105B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 300AT LSI (SPARE)	105C	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 800AT LSI (SPARE / MCC DSS-2 TEMP)	105D	7.6.1.2
Low Voltage Circuit Breaker	H-840-MCC-8300-02	800AF 800AT LSI (BIOSOLIDS DEWATERING AND STORAGE)	104A	7.6.1.2
Low Voltage Circuit Breaker	H-840-CFG-2110-22	800AF 300AT LSI (CENTRIFUGE 2-2)	104B	7.6.1.2
Low Voltage Circuit Breaker	H-840-CFG-2110-23	800AF 300AT LSI (CENTRIFUGE 2-3 FUTURE)	104C	7.6.1.2
Low Voltage Circuit Breaker	H-840-CFG-2110-21	800AF 300AT LSI (CENTRIFUGE 2-1)	104D	7.6.1.2
Low Voltage Circuit Breaker	H-827-MCC-8300-02	800AF 800AT LSI (SLUDGE HOLDING TANKS)	103D	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 300AT LSI (SPARE)	103F	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 800AT LSI (SPARE)	103H	7.6.1.2
Low Voltage Circuit Breaker	TIE	4000AF 4000AT LSI (N.O.) (BUS A–BUS B TIE)	103C	7.6.1.2

H-840-XMR-8202-01 (TU-42A)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable		13.2kV SHIELDED 3/C (FROM 903 52-13 CUBICLE 104A)		7.3.3
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
Power Transformer	H-840-XMR-8202-01	TU-42A 2500-3125/2800-3500 kVA 13.2kV-480V		7.2.2, 7.12.3
Low Voltage Cable		480V 3Ø (TRANSFORMER TO LC MAIN)		7.3.2
Neutral Grounding Resistor	H-840-HRG-8202-01	HRG 2-480V 2.5A CONT. 5:5 / 200:5 CT	101C	7.20.4
Current Transformer		5:5	101C TO 50G / AMMETER	7.10.1
Current Transformer		200:5	101C TO 50G	7.10.1
Protective Relay		50G / 73 NGR MONITOR (AM / 73 / 50G)	101C	7.9.2
Load Center	H-840-LDC-8202-01	480V 3Ø 3W 4000A 85kAIC (BUS A / MTM)		7.1

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Low Voltage Circuit Breaker	MAIN A	4000AF 4000AT LSI (N.C.)	101B	7.6.1.2
Low Voltage Circuit Breaker	H-847-MCC-8300-01	800AF 800AT LSI (SLUDGE PROCESSING FACILITY)	101G	7.6.1.2
Low Voltage Circuit Breaker	H-270-XMR-8300-01	800AF 800AT LSI (TECHNICAL SERVICES BLDG / H-270-SWB-8300-01)	101H	7.6.1.2
Low Voltage Circuit Breaker	H-840-CFG-2110-33	800AF 300AT LSI (CENTRIFUGE 3-3 FUTURE)	102A	7.6.1.2
Low Voltage Circuit Breaker	H-840-MCC-8300-03	800AF 800AT LSI (BIOSOLIDS DEWATERING AND STORAGE)	102B	7.6.1.2
Low Voltage Circuit Breaker	H-840-CFG-2110-32	800AF 300AT LSI (CENTRIFUGE 3-2)	102C	7.6.1.2
Low Voltage Circuit Breaker	H-840-CFG-2110-31	800AF 300AT LSI (CENTRIFUGE 3-1)	102D	7.6.1.2
Low Voltage Circuit Breaker	H-840-ATS-8300-01	800AF 800AT LSI (STANDBY)	103B	7.6.1.2
Low Voltage Circuit Breaker	TIE	4000AF 4000AT LSI (N.O.) (BUS A–BUS B TIE)	103C	7.6.1.2

H-840-XMR-8202-02 (TU-42B)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable		13.2kV SHIELDED 3/C (FROM 903 52-23 CUBICLE 110A)		7.3.3
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
Power Transformer	H-840-XMR-8202-02	TU-42B 2500-3125/2800-3500 kVA 13.2kV-480V		7.2.2, 7.12.3
Low Voltage Cable		480V 3Ø (TRANSFORMER TO LC MAIN)		7.3.2
Neutral Grounding Resistor	H-840-HRG-8202-02	HRG 2-480V 2.5A CONT. 5:5 / 200:5 CT	105G	7.20.4
Current Transformer		5:5	105G TO 50G / AMMETER	7.10.1
Current Transformer		200:5	105G TO 50G	7.10.1
Protective Relay		50G / 73 NGR MONITOR (AM / 73 / 50G)	105G	7.9.2
Load Center	H-840-LDC-8202-01	480V 3Ø 3W 4000A 85kAIC (BUS B / MTM)		7.1
Low Voltage Circuit Breaker	MAIN B	4000AF 4000AT LSI (N.C.)	105B	7.6.1.2
Low Voltage Circuit Breaker	H-847-MCC-8300-02	800AF 800AT LSI (SLUDGE PROCESSING FACILITY)	105C	7.6.1.2
Low Voltage Circuit Breaker	H-840-ATS-8300-01	800AF 800AT LSI (PRIMARY / H-847-MCC-8300-03)	105D	7.6.1.2
Low Voltage Circuit Breaker	H-840-MCC-8300-04	800AF 600AT LSI (BIOSOLIDS DEWATERING AND STORAGE)	104A	7.6.1.2
Low Voltage Circuit Breaker	H-840-CFG-2110-42	800AF 300AT LSI (CENTRIFUGE 4-2)	104B	7.6.1.2
Low Voltage Circuit Breaker	H-840-CFG-2110-43	800AF 300AT LSI (CENTRIFUGE 4-3 FUTURE)	104C	7.6.1.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Low Voltage Circuit Breaker	H-840-CFG-2110-41	800AF 300AT LSI (CENTRIFUGE 4-1)	104D	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 800AT LSI (SPARE)	103D	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 300AT LSI (SPARE)	103F	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 300AT LSI (SPARE)	103H	7.6.1.2
Low Voltage Circuit Breaker	SPARE	4000AF 4000AT LSI (N.O.) (BUS A–BUS B TIE)	103C	7.6.1.2

H-931-XMR-8201-02 (TU-8B)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	931-E002	13.2kV SHIELDED 3/C (FROM 903 52-26 CUBICLE 111B)		7.3.3
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
Power Transformer	H-931-XMR-8201-02	TU-8B 2000/2300 kVA KNAN/KNAF 13.2kV-480V		7.2.2, 7.12.3
Low Voltage Cable	931-E102	480V SECONDARY (TRANSFORMER TO LC MAIN 109B)		7.3.2
Neutral Grounding Resistor	H-931-HRG-8201-02	HRG 277V 2.5A CONT. (SE-330) 5:5 / 5:0.05 CT	109C	7.20.4
Current Transformer		5:5	109C TO SE-330 / AMMETER	7.10.1
Current Transformer		5:0.05	109C TO SE-330	7.10.1
Protective Relay		SE-330 NGR MONITOR (AM / 73 / 50G)	109C	7.9.2
Load Center	H-931-LDC-8201-01	LC-8 480V 3Ø 3W 3200A 65kAIC (B BUS / MTM)		7.1
Low Voltage Circuit Breaker	MAIN B	3200AF 3200AT LSI (N.C.)	109B	7.6.1.2
Low Voltage Circuit Breaker	H-931-MCC-8300-01	800AF 400AT LSI (N. PRELIMINARY LOAD CENTER FACILITY)	108C	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 400AT LSI (SPARE / FUTURE GRAVITY THICKENERS MCC)	108D	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 800AT LSI (SPARE)	108B	7.6.1.2
Low Voltage Circuit Breaker	H-311-ATS-8300-02	800AF 400AT LSI (N. HEADWORKS ELECTRICAL FACILITY)	107D	7.6.1.2
Low Voltage Circuit Breaker	H-810-MCC-8300-02	800AF 400AT LSI (GRAVITY THICKENERS FACILITY)	107C	7.6.1.2
Low Voltage Circuit Breaker	H-809-ATS-8300-04	800AF 600AT LSI (DAF PRIMARY)	107B	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 800AT LSI (SPARE / FUTURE ODOR CONTROL MCC)	107A	7.6.1.2
Low Voltage Circuit Breaker	H-809-ATS-8300-03	800AF 600AT LSI (DAF STANDBY)	106D	7.6.1.2
Low Voltage Circuit Breaker	H-809-ATS-8300-02	800AF 600AT LSI (DAF PRIMARY)	106C	7.6.1.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Low Voltage Circuit Breaker	H-809-ATS-8300-01	800AF 600AT LSI (DAF STANDBY)	106B	7.6.1.2
Low Voltage Circuit Breaker	H-311-MCC-8300-04	800AF 400AT LSI (N. HEADWORKS ELECTRICAL FACILITY)	106A	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 800AT LSI (SPARE)	105D	7.6.1.2
Low Voltage Circuit Breaker	TIE	3200AF 3200AT LSI (N.O.) (BUS A–BUS B TIE)	105C	7.6.1.2

H-931-XMR-8201-01 (TU-8A)

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Medium Voltage Cable	931-E001	13.2kV SHIELDED 3/C (FROM 903 52-16 CUBICLE 103B)		7.3.3
MCOV		13.2kV MCOV (TRANSFORMER PRIMARY LA)		7.19.2
Power Transformer	H-931-XMR-8201-01	TU-8A 2000/2300 kVA KNAN/KNAF 13.2kV-480V		7.2.2, 7.12.3
Low Voltage Cable	931-E101	480V SECONDARY (TRANSFORMER TO LC MAIN 101B)		7.3.2
Neutral Grounding Resistor	H-931-HRG-8201-01	HRG 277V 2.5A CONT. (SE-330) 5:5 / 5:0.05 CT	101C	7.20.4
Current Transformer		5:5	101C TO SE-330 / AMMETER	7.10.1
Current Transformer		5:0.05	101C TO SE-330	7.10.1
Protective Relay		SE-330 NGR MONITOR (AM / 73 / 50G)	101C	7.9.2
Load Center	H-931-LDC-8201-01	LC-8 480V 3Ø 3W 3200A 65kAIC (A BUS / MTM)		7.1
Low Voltage Circuit Breaker	MAIN A	3200AF 3200AT LSI (N.C.)	101B	7.6.1.2
Low Voltage Circuit Breaker	H-931-LPL-8430-01	800AF 200AT LSI (SECONDARY FEED)	102B	7.6.1.2
Low Voltage Circuit Breaker	H-415-MCC-8300-01	800AF 225AT LSI (N. PRIMARY PUMP STATION-3)	102C	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 600AT LSI (SPARE / FUTURE GRAVITY THICKENERS MCC)	102D	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 800AT LSI (SPARE / FUTURE ODOR CONTROL MCC)	103A	7.6.1.2
Low Voltage Circuit Breaker	H-809-ATS-8300-04	800AF 800AT LSI (DAF STANDBY)	103B	7.6.1.2
Low Voltage Circuit Breaker	H-810-ATS-8300-01	800AF 600AT LSI (GRAVITY THICKENERS)	103C	7.6.1.2
Low Voltage Circuit Breaker	H-311-MCC-8300-01	800AF 400AT LSI (N. HEADWORKS ELECTRICAL FACILITY)	103D	7.6.1.2
Low Voltage Circuit Breaker	H-311-MCC-8300-03	800AF 400AT LSI (N. HEADWORKS ELECTRICAL FACILITY)	104A	7.6.1.2
Low Voltage Circuit Breaker	H-809-ATS-8300-01	800AF 800AT LSI (DAF PRIMARY)	104B	7.6.1.2
Low Voltage Circuit Breaker	H-809-ATS-8300-02	800AF 600AT LSI (DAF STANDBY)	104C	7.6.1.2

Device Type	Tag Name	Description	Section / Note	NETA MTS 2023 Spec
Low Voltage Circuit Breaker	H-809-ATS-8300-03	800AF 600AT LSI (DAF PRIMARY)	104D	7.6.1.2
Low Voltage Circuit Breaker	SPARE	800AF 800AT LSI (SPARE)	105B	7.6.1.2
Low Voltage Circuit Breaker	TIE	3200AF 3200AT LSI (N.O.) (BUS A–BUS B TIE)	105C	7.6.1.2

2031 Maintenance Group

The 2031 RWHTF maintenance rotation repeats the 2027 equipment group as identified in Appendix A.