

日立能源干式变压器技术数据 Specification of Hitachi Energy Dry-type Transformer

干式变压器,能适用于户内安装, 分接点采用螺栓联接。

Dry type transformer for indoor installation, tapping re-connectable by bolted links.

符合标准及技术协议 Standard and Tech. Agreement		符合 According to IEC 60076-11	
SAP ID			
合同编号 Contract number			
附件文件数量 Attached Files Count			
客户名称 Client name			
项目名称 Project Name		1002001450 TIL纳米比亚鲸湾港2台岸桥	
技术类型 Technology		真空浇注 VCC	
型号 Type		SCLB-250/11	
数量 Quantity	台 Set	2	
相数 Number of Phase	Phase	3	
频率 Frequency	Hz	50	
容量 Rating	kVA	250	
电压比 Voltage Ratio	kV	11/0.4	
高压分接范围 Tapping On HV	%	±2*2.5	
冷却方式 Cooling Method		AN	
最大系统电压 Highest System Voltage	kV	12/≤1.1	
工频耐压 Power Frequency Withstand Voltage	kV	35/5	
额定冲击电压 Rated Lightning Impulse Withstand Voltage	kV	75/0	
连接组别 Vector Group		Dyn11	
空载损耗 No Load Loss	kW	0.468	
负载损耗 Load Loss	kW	3.4	At 120 °C
短路阻抗 Short Circuit Impedance	%	4	
声压级 Noise Level	dB	设计值 (design value)	
线圈材料 Winding Material		铝 AL	高压线圈 HV Winding
		铝 AL	低压线圈 LV Winding
绝缘等级 insulation class		F	
温升限值 Temperature Rise	K	95 (环境温度45°C) (ambient temperature 45°C)	
局部放电 Partial Discharge	pC	10	
罩壳 Enclosure	防护等级 Enclosure Protection Class	IP23	
	进出线方式 Terminal Incoming/Outgoing	下进下出(bottom in bottom out)	
	罩壳颜色 Painting color	RAL7035	
	罩壳材料 Material	钢板 Steel	
	罩壳门板上配连锁开关 Lockout switch for enclosure	开门常闭 NC	
	是否现场拼装 Enclosure need to be installed on site	No	
	罩壳是否带底网板 Enclosure with bottom board	No	
温控器 thermometer	温控仪计算机接口型式 The output type of thermometer	RS485	
	温控器传感线长度 Length of sensor	标准(4米) Standard(4m)	
辅助电源 Auxiliary Power	辅助电源来源 Auxiliary Power Supply	客户提供 Supply by customer	
	相数 Number of phases	交流(AC) 相数(Phase):	1
	电压 Voltage	V	220±10%

频率 Frequency	Hz	50			
配置滚轮 Roll		无 None			
非常规试验要求 Special Test		No			
变压器负载类型 Load types for the transformer		其他 Others			
		港机设备供电			
变压器安装位置和运输通道对尺寸和重量有无特殊要求 If any special requirements of the size or weight for location and transportation passage		No			
是否已提供变压器技术文件和参考外形图 If the technical documents and the outline drawings of the transformer has been provided		Yes			
是否已提供变压器安装轨距 if the installation roller distance of the transformer has been provided		Yes:需写明或附图(indicate or provide drawing)			
客户是否对设备编号提出要求 If the customer has special requirements for equipment number		No			
客户是否对铭牌或标志牌提出要求 If the customer has special requirements for name plate or marker plate		Yes:需特殊说明(Please indicate) 铭牌都要打CE标识, ABB品牌(CE marking on nameplates, ABB branding)			
环境温度 Environment Temperature	°C	最低 Min	0	最高 Max	45
海拔高度 Altitude	m	≤1000			
包装方法 Packing method		一般包装 Commonly packing			
运输方式 Transportation		公路 Road transport			
随机电子版文件语言 Electronic Documents Language		中英文 Chinese and English 3份纸质版和1份电子版			
最终到货地点 The final destination of the goods		上海			
		1) 带整体无焊接底座; 2) 额定容量基于环境温度的最高温度、并在变压器铭牌上注明; 3) 每相有温度检测, 提供2级常闭温控开关继电器输出触点(报警, 跳闸); 4) 罩壳表面有高压警示牌, 最小尺寸: 至少有一边不小于200mm; 5) 一二次侧铜排接线端子开直径13mm孔; 并配好M12热镀锌螺栓副; 6) 高压分接处带分接防护护套; 7) 铁芯和底座间配橡胶减震垫; 8) 变压器顶部吊装孔需要在内部安装插销, 保证天窗在外部不能被打开; 9) 外壳防腐满足等级C4; 10) 罩壳的外形尺寸和安装轨距需与参考外形图一致 11) 振华提供高压锁, 日立能源负责安装 12) 损耗按EU548, 空, 负损耗偏差按标准值的+5% 13) CE自申明 1) With integral weld-free base:			

备注 Remarks:

- 1) with integral weld-free base;
- 2) The Nameplate capacity is based on the maximum temperature of the ambient temperature and is indicated on the transformer nameplate;
- 3) Each phase has temperature detection, providing 2-level normally closed temperature control switch relay output contacts (alarm, trip);
- 4) There is a high-voltage warning sign, with a minimum size of at least one side not less than 200mm;
- 5) Opening a 13mm diameter hole for the primary and secondary copper bar wiring terminals; And prepare M12 hot-dip galvanized bolt pairs;
- 6) The HV. tap is sheathed with tap connector;
- 7) Equipped with rubber shock absorbers between the iron core and the base;
- 8) The top hoisting hole of the transformer needs to be installed with a bolt inside to ensure that the skylight cannot be opened outside;
- 9) Enclosure Corrosion protection grade C4;
- 10) The installation gauge should be consistent with the reference outline drawing;
- 11) Zhenhua provides high-voltage locks, Hitachi Energy is responsible for installation
- 12) Losses are according to EU548, and no-load and load loss deviations are according to +5% of the standard value
- 13) CE Self-declaration

编制 Author:

日期 Date:

校核 Issued:

日期 Date: