

RAK12500 WisBlock GNSS Location Module Datasheet

Overview




Figure 1: RAK12500 WisBlock GNSS Location Module

Description

The RAK12500 WisBlock GNSS Location Module is designed to be part of a production-ready IoT solution in a modular way and must be combined with a WisBlock Core and a Base module.

The RAK12500 uses the u-blox ZOE-M8Q module. It supports a wide variety of satellite data protocols such as GPS, GLONASS, QZSS, and BeiDou. This ensures the retrieval of precise

location data. The module features exceptional performance, high sensitivity, and minimal acquisition time. A very suitable module for your low-power IoT solution needs.

Features

- **Module Specification**
 - Uses the very accurate GNSS Module: **u-blox ZOE-M8Q chip**
 - Location Accuracy of ± 2.5 meter
 - Velocity Accuracy of ± 0.05 m/s
 - GPS, GLONASS, QZSS, and BeiDou Satellite support
 - Serial and I2C communication to WisBlock Core support
 - 10 Hz Update Rate
 - 29 seconds Location Fix from Cold Start, 1 second from Hot Start
 - Operating Voltage: 3.3 V
 - Operating Current: $< 15 \mu\text{A}$
 - Chipset: u-blox ZOE-M8Q
- **Size**
 - Module Size: 10 mm x 23 mm

Specifications

Overview

Mounting

Figure 2 shows the mounting mechanism of the RAK12500 module on a [WisBlock Base](#)  board. The RAK12500 module can be mounted on the slots: **SLOT A (UART / I2C Communication)** or **SLOT C (I2c Communication Only)**.




Figure 2: RAK12500 WisBlock GNSS Location Module Mounting

Hardware

The hardware specification is categorized into five parts that cover the chipset and pinouts and the corresponding functions and diagrams of the board. It also presents the parameters and their standard values in terms of electrical and mechanical.

Chipset

The RAK12500 utilizes a very accurate u-blox ZOE-M8Q chip. See the manufacturer's [u-blox ZOE-M8Q Page](#)  for more details.

Vendor	Part number
u-blox	ZOE-M8Q

Pin Definition

The RAK12500 WisBlock GNSS Location Module comprises a standard WisBlock connector. The WisBlock connector allows the RAK12500 module to be mounted to a WisBlock Base board. The pin order of the connector and the pinout definition is shown in **Figure 3**.



GND	2	1	UART_TX
NC	4	3	NC
NC	6	5	NC
I2C_SDA	8	7	I2C_SCL
IO6	10	9	NC
1PPS	12	11	3V3_S
3V3_S	14	13	NC
VDD	16	15	NC
NC	18	17	NC
NC	20	19	NC
NC	22	21	NC
UART_RX	24	23	GND

Figure 3: RAK12500 WisBlock GNSS Location Module Pinout

NOTE

Only the UART and I2C related pin, 1PPS pin, RESET pin, VDD, and GND are connected to this module

If a 24-pin WisBlock Sensor connector is used, the IO used for the output pulse depends on what slot the module is plugged in. The following table shows the default IO used for different slots:

SLOT A	SLOT C
UART / I2C	I2C Only

Electrical Characteristics

Recommended Operating Conditions

The table below shows the recommended operating conditions for the RAK12500 WisBlock GNSS Location Module:

Symbol	Description	Min.	Nom.	Max.	Unit
V_{DD}	Power supply for the module	2.7	3.3	3.6	V
I_{BACK}	Backup battery current	-	15	-	μA

Mechanical Characteristics

Board Dimensions

Figure 4 shows the dimensions and mechanical drawing of the RAK12500 module.





Figure 4: RAK12500 WisBlock GNSS Location Module Mechanical Characteristics

WisConnector PCB Layout



Schematic Diagram

