


The Nice logo consists of a solid blue square with the word "Nice" in white, sans-serif font centered within it.

EL-IPD-AMP-2CH

2 Channel Audio Amplifier



Delivers high quality audio to a single zone
or as part of a multi-zone configuration

The Nice EL-IPD-AMP-2CH 2 Channel Audio Amplifier designed to be used in a single chassis configuration or with other amplifiers and pre-amps within the Nice IP audio distribution family of products using Dante® Audio Networking. Nice IP-enabled audio distribution simplifies whole house

audio distribution and enhances the intelligent home by delivering high quality audio over an existing network. Easily scaling from a single chassis solution to a decentralized multi-chassis/multi-source implementation, Nice IP audio distribution meets the needs for projects of any size.

WORKS WITH ELAN
CONTROL SYSTEMS
ELAN
a Nice brand

EL-IPD-AMP-2CH 2 Channel Audio Amplifier



Features

- **Individual Lip Sync Delay for Each Speaker Zone**
 - Delay Time: 0 - 400ms
 - Adjustable: 10ms increments
- **Individual Tone Control for Each Zone**
 - Five-band equalizer
 - Loudness on/off
- **Bridgeable**
- **80WPC @ 8Ω**
- **100WPC @ 4Ω**
- **200W in Bridge Mode**

Specifications

Digital Audio Inputs	1 Optical TOSLINK Inputs
	1 Coaxial RCA Inputs
	Stereo, PCM 96kHz, 24-bit
Max input level	2.0 VRMS
Input Sensitivity	0 dBV (1.0 VRMS)
Input Impedance	47kΩ - 49kΩ
	Stereo Analog RCA
Variable	Follows main volume setting of the amplifier
Subwoofer Output Impedance	470Ω
	RCA
Amplifier Output	2 Stereo Amplifier Outputs – Bridgeable
Output Power	80W at 8Ωm 100 W at 4Ω
	200 W in Bridge Mode
THD	<0.05% @ 1kHz
Frequency Response	20Hz to 20kHz, +.5dB / -.5dB
Crosstalk	>60dB @ 1kHz / 1W
Signal to Noise	90dB
Dimensions	(in) 7D x 7.9W x 1.97H
	(mm) 178D x 201W x 50H
Weight	4.10 lbs / 1.86 Kg
Network	100/1000 ethernet DHCP enabled by Default
	1 RJ45 Jack

