

无人机防御系统

Authentication

Login 登录

Query 查询

JammerCooldownStatus 获取干扰器冷却状态

ListSigRecords 信号记录列表

PackageVersionOnline 在线获取最新软件包版本

UpgradeStatusOnline 获取升级状态

AirDefenceArea 防空区

AutoAttack 无人值守状态

AutoAttackConfig 无人值守配置

AutocaliProgress 以百分比形式查询光电设备自动校准的进度

Blacklist 黑名单信息

Check 升级

DetectingBands 设备检测频段状态

DeviceStat 设备引擎状态信息与收发包信息

Devices 设备信息

Dfgun 察打枪

DhcpStatus 动态主机配置协议信息

Drone 无人机信息

DroneAdsB 航班信息

DroneIDs 按无人机ID查询事件

Dronetraces 历史轨迹

Dronetypes 按无人机类型查询事件

Events 事件

Events aggregation 事件聚合查询

Events_by_paging 事件展开查询

GetSigParseImage 获取信号分析图片

Get_gvs_conf 获取光电设备配置

GfskData 通用检测器列表信息

GfskProto 通用检测器协议信息

LinkNodeList 组网节点（已移入列表）

LocalPatchInfo 可用于切换的本地补丁

Nodes 组网节点信息

Notify 通知信息

ProfileAliasList 查询无人机自定义机型列表

ProfileList 查询无人机属性

ProfilePatternList 查询用于匹配无人机 ID 的模式列表

Report 统计

Screenshot 图传截图

Sensor 传感器

SpdReport 频谱

SpoofStatus 诱骗器状态

Storage 设备存储空间

SysCapability 设备支持打击方式

Time 查看设备系统时间

TimeZone 查看设备时区

UnknownSignal 未知信号

UnlinkNodeList 组网未知节点列表

Upgrade 本地升级版本

Version 当前版本信息

Vsgevent 光电单事件查询

Vsgevents 光电多事件查询
Vsgeventsimage 光电图片查询
Whitelist 白名单列表
WidebandJammer 宽频干扰状态
WidebandJammer2 宽频干扰状态
Wifilist wifi列表

Mutation 操作

AddBlacklist 添加黑名单
AddWhitelist 添加白名单
AirDefenceArea 绘制防空区
Attack 精准打击
AutoAttack 无人值守
ClearStorage 清除内部存储
Ctrl_landing 迫降
DeleteBlacklist 移除黑名单无人机
DeleteEvents 删除事件
DeleteEventsByID 根据无人机ID删除事件
DeleteWhitelist 移除白名单无人机
DetectingBands 检测频段开关
Device 设备设置
DeviceTest 自检测
Dfgun 察打枪
DhcpEnable 开启/关闭动态主机配置服务
DirectionalWBAttack 定向打击
DroneAdsB 开启或关闭ADS-B
DroneProfileAlias 为指定无人机类型添加或删除别名
DroneProfilePattern 添加或删除无人机正则表达式模式
DroneSub 订阅无人机截图信息（图传）
Drone_profile 修改无人机属性
Gfsk 通用检测器
GvsControl 控制光电服务（自动校准服务）
MarkFalseAlarm 标记误报（光电）
MarkFalseAlarmByID 按ID标记误报（光电）
Node 节点
PowerMode 设置电源模式，仅适用于便携式设备
Remove_fake_drone 标记无人机为误报无人机（无人机列表）
Reset 重启设备
RollbackPatch 切换或升级 UI 版本
SetGeoLocation 设置设备位置（非持久化）
Set_gvs_conf 修改光电配置
Set_sensor_mode 设置传感器模式
Set_vsg_license 设置光电授权
SigParse 信号分析
signalCap 信号抓取
SignalRec 信号证据记录
Spd 频谱
Spooferswitch 诱骗设置
StageReset 定向复位
Tdoa_track TDOA跟踪
Time 设置设备系统时间
TimeZone 设置设备时区
Tracking 无人机视觉跟踪
UnknownWifi 未知WIFI

- UpgradePatch 补丁升级
- UpgradeTo 版本升级
- VersionPackage 版本包
- Wideband_attack 宽频干扰
- WifiBgLearning wifi背景学习开关
- WithdrawFalseAlarm 还原误报事件（光电）

Subscription 订阅

- Drone 无人机
- Message 后台消息
- Notify 通知消息

无人机防御系统

Base URLs:

- <https://192.168.100.100/rf/graphql>

Authentication

Login 登录

Method: POST

Request example

```
{
  "username": "user",
  "password": "password"
}
```

Parameter Description

Requests

Name	Type	Description
username	String	用户名
password	String	密码

Responses

HTTP Status Code	Meaning	Description	Data schema
200	OK	成功（后续接口需用token）	Inline

Response Examples

Success

```
{
  "token":
  "eyJhbGciOiJIUzI1NiIsInR5cGU6IjYpZCI6ImQ120NjRmMDJjLTRlOTUuZiLTU3ZTE4NjB1ZjA0MiImIhdCI6MTcwOTE5MTg3M1CwizXjoxNzQwNzI3ODcwfwQ.7eHCVT6-Prm2VHorbcN4zkf5u_vEVihXHSDec91is4",
  "expLen": 3153600000,
  "user": {
    "id": "d464f02c-4e95-11ec-b2fb-67e1860ef042",
    "displayName": "root",
    "imageUrl": "https://s3.amazonaws.com/uifaces/faces/twitter/lepinski/128.jpg",
    "role": "root",
    "create_user_maxnum": null,
    "creator": null,
    "controller2sites": {},
    "controllers": {},
    "sites": {},
    "controller": {}
  }
}
```

Failure

"Unauthorized"

Query 查询

JammerCooldownStatus 获取干扰器冷却状态

Method: POST

Request example

```
query
{
  JammerCooldownStatus {
    band12
    band14
    band15
    band18
    band24
    band4
    band58
    band9
  }
}
```

Parameter Description

Responses

NameRequest example	Type	Description
band12	Boolean	1.2G频段的冷却状态
band14	Boolean	1.4G频段的冷却状态
band15	Boolean	1.5G频段的冷却状态
band18	Boolean	1.8G频段的冷却状态
band24	Boolean	2.4G频段的冷却状态
band4	Boolean	433M波段的冷却状态
band58	Boolean	5.8G频段的冷却状态
band9	Boolean	900M频段的冷却状态

Boolean

Response Examples

Success

```
{
  "data": {
    "JammerCooldownStatus": {
      "band12": null,
      "band14": null,
      "band15": true,
      "band18": null,
      "band24": true,
      "band4": null,
      "band58": true,
      "band9": true
    }
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"JammerCooldownStatusd\" on type \"Query\". Did you mean \"JammerCooldownStatus\"?",
      "locations": [
        {
          "line": 3,
          "column": 3
        }
      ]
    }
  ]
}
```

```
]
}
```

ListSigRecords 信号记录列表

Method: POST

Request example

```
query{
  ListSigRecords
  (
    offset:0
    limit:1
  )
  {
    id
    size
    updated_time
  }
}
```

Parameter Description

Requests

Name	Type	Description
offset	Int	查询记录的偏移量
limit	Int	每页记录数，默认10

Responses

Name	Type	Description
id	String	信号记录ID
size	Int	记录文件大小
updated_time	DateTime	证据记录时间

Response Examples

Success

```
{
  "data": {
    "ListSigRecords": [
      {
        "id": "81",
        "size": 6881392,
        "updated_time": "2025-07-01T19:10:44.94+08:00"
      }
    ]
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"siz\" on type \"SigRecordInfo\". Did you mean \"size\"?",
      "locations": [
        {
          "line": 9,
          "column": 5
        }
      ]
    }
  ]
}
```

PackageVersionOnline 在线获取最新软件包版本

Method: POST

Request example

```
query
{
  PackageVersionOnline
}
```

Parameter Description

None

Response Examples

Success

```
{
  "data": {
    "PackageVersionOnline": "v3.15.0"
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"PackageVersionOnline\" on type \"Query\". Did you mean \"PackageVersionOnline\"?",
      "locations": [
        {
          "line": 3,
          "column": 3
        }
      ]
    }
  ]
}
```

UpgradeStatusOnline 获取升级状态

Method: POST

Request example

```
query
{
  UpgradeStatusOnline
}
```

Parameter Description

None

Response Examples

Success

```
{
  "data": {
    "UpgradeStatusOnline": "UpgradeStatusIdle"
  }
}
```

进度描述：
“UpgradeStatusIdle”：升级尚未开始或已完成；“UpgradeStatusDownloading”：正在下载升级文件；
“UpgradeStatusDownloadErr”：下载升级文件时出错；“UpgradeStatusUnpacking”：正在解压缩升级文件；
“UpgradeStatusUnpackErr”：解压缩升级文件时出错；“UpgradeStatusDoUpgradeing”：正在执行升级过程；
“UpgradeStatusDoUpgradeErr”：升级过程中出错；“UpgradeStatusRestarting”：升级完成后，系统将重新启动。

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"UpgradeStatusOnline\" on type \"Query\". Did you mean \"UpgradeStatusOnline\"?",
      "locations": [
        {
          "line": 2,
          "column": 3
        }
      ]
    }
  ]
}
```

AirDefenceArea 防空区

Method: POST

Request example

```
query
{
  airDefenceArea{
    data
  }
}
```

Parameter Description

Responses

NameRequest example	Type	Description
data	jsonStrType	防空区域

Response Examples

Success

```
{
  "data": {
    "airDefenceArea": [
      {
        "data": "{\"type\":1,\"areatype\":0,\"locations\":
[[116.370964,40.010919]],\"distance\":1401.62623426214,\"hash\":\"2397271306\"}"
      }
    ]
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"date\" on type \"areaDefenceType\". Did you
mean \"data\"?",
      "locations": [
        {
          "line": 4,
          "column": 5
        }
      ]
    }
  ]
}
```

AutoAttack 无人值守状态

Method: POST

Request example

```
query
{
  autoAttack
}
```

Parameter Description

None

Response Examples

Success

```
{
  "data": {
    "autoAttack": "false"
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"auto\" on type \"Query\".",
      "locations": [
        {
          "line": 3,
          "column": 3
        }
      ]
    },
    {
      "message": "Cannot query field \"Attack\" on type \"Query\". Did you mean \"autoAttack\"?",
      "locations": [
        {
          "line": 3,
          "column": 8
        }
      ]
    }
  ]
}
```

AutoAttackConfig 无人值守配置

Method: POST

Request example

```
query
{
  autoAttackConfig {
    dirwbEnabled
    on
    protectWhite
    saEnabled
    spfEnabled
    wbEnabled
  }
}
```

Parameter Description

Responses		
Name	Type	Description
dirWbEnabled	Boolean	是否开启定向打击
on	Boolean	无人值守开关
protectWhite	Boolean	是否开启白名单保护
saEnabled	Boolean	是否开启自动打击
spfEnabled	Boolean	是否开启诱骗
wbEnabled	Boolean	是否开启宽频打击

Response Examples

Success	
	<pre>{ "data": { "autoAttackConfig": { "dirWbEnabled": true, "on": false, "protectWhite": false, "saEnabled": true, "spfEnabled": false, "wbEnabled": true } } }</pre>

Failure	
	<pre>{ "data": null, "errors": [{ "message": "Cannot query field \"one\" on type \"AutoAttackConfig\". Did you mean \"on\"?", "locations": [{ "line": 5, "column": 5 }] }] }</pre>

AutocaliProgress 以百分比形式查询光电设备自动校准的进度

Method: POST

Request example

```
query
{
  autocaliProgress {
    details
    errorCode
    percentage
  }
}
```

Parameter Description

Responses

Name	Type	Description
details	Int	自动协调进度代码详情 0:自动协调停止 1:自动协调开始 2:完成 3:错误
errorCode	Int	autocali 错误 0:正常 1:创建错误 2:写入错误 3:读取错误 4:approch ptz 错误 5.get ptz 错误 6:捕获错误 7:数学计算失败 8:连接错误 9:取消 10:超时
percentage	Int	进度百分比 0~100

Response Examples

Success

```
{
  "data": {
    "autocaliProgress": {
      "details": 0,
      "errorCode": 0,
      "percentage": 0
    }
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"detail\" on type \"ProgressMsgType\". Did you mean \"details\"?",
      "locations": [
        {

```

```
      "line": 3,
      "column": 5
    }
  ]
}
}
```

Blacklist 黑名单信息

Method: POST

Request example

```
query
{
  blacklist {
    alias
    description
    dronetype
    id
  }
}
```

Parameter Description

Responses		
Name	Type	Description
alias	String	无人机别名
description	String	无人机描述
dronetype	String	无人机类型
id	String	无人机ID

Response Examples

```
Success
{
  "data": {
    "blacklist": [
      {
        "alias": "",
        "description": "",
        "dronetype": "CFLY General",
        "id": "a09f10664c66"
      },
      {
        "alias": "",
```

```
        "description": "",
        "dronetype": "POWERSVISION PowerEggX",
        "id": "e09153a9336b"
    }
]
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"i\" on type \"blacklist\". Did you mean\n\"id\"?",
      "locations": [
        {
          "line": 6,
          "column": 5
        }
      ]
    }
  ]
}
```

Check 升级

Method: POST

Request example

```
query
{
  check
  (pkg_size:1.111)
  {
    free_space
    has_enough_space
    local_versions {
      version_id
      version_publish_time
      version_status
    }
    prepare_status
    upgrade_status
  }
}
```

Parameter Description

Requests

Name	Type	Description
pkg_size	Float	版本包大小

Responses

Name	Type	Description
free_space	Int	用于升级的可用空间（单位：Mbytes）
has_enough_space	Boolean	是否有足够的空间进行升级
local_versions	List	有效的本地版本
version_id	String	版本的唯一 ID
version_publish_time	String	发布时间
version_status	String	版本状态和有效性
prepare_status	String	准备升级目录
upgrade_status	String	升级状态

Response Examples

Success

```
{
  "data": {
    "check": {
      "free_space": 93,
      "has_enough_space": true,
      "local_versions": [
        {
          "version_id": "v3.13.0",
          "version_publish_time": "2024-06-27T12:25:17z",
          "version_status": "valid"
        }
      ],
      "prepare_status": "done",
      "upgrade_status": "updated"
    }
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
```

```
      "message": "Cannot query field \"prepare_statuse\" on type \"upgradeType\". Did you mean \"prepare_status\" or \"upgrade_status\"?",
      "locations": [
        {
          "line": 13,
          "column": 5
        }
      ]
    }
  ]
}
```

DetectingBands 设备检测频段状态

Method: POST

Request example

```
query{
  detectingBands {
    Boost24
    band12
    band14
    band18
    band24
    band4
    band58
    band9
    bandext
  }
}
```

Parameter Description

Responses

Name	Type	Description
Boost24	Int	测试功能、 0:不可用，1:禁用，2:启用。
band12	Int	1.2Ghz 频段的状态，0:不可用，1:禁用，2:启用。
band14	Int	1.25hz 频段的状态，0:不可用，1:禁用，2:启用。
band18	Int	1.8Ghz 频段的状态，0:不可用，1:禁用，2:启用。
band24	Int	2.4Ghz 频段的状态，0:不可用，1:禁用，2:启用。
band4	Int	433Mhz 频段的状态，0:不可用，1:禁用，2:启用。
band58	Int	5.8Ghz 频段的状态，0:不可用，1:禁用，2:启用。
band9	Int	900Mhz 频段的状态，0:不可用，1:禁用，2:启用。

Name	Type	Description
bandext	Int	扩展频段状态，0:不可用，1:禁用，2:启用。

Response Examples

Success

```
{
  "data": {
    "detectingBands": {
      "Boost24": 0,
      "band12": 0,
      "band14": 2,
      "band18": 0,
      "band24": 2,
      "band4": 2,
      "band58": 2,
      "band9": 2,
      "bandext": 2
    }
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"band90\" on type \"DetectingBands\". Did you mean \"band14\", \"band9\", \"band12\", \"band4\", or \"band24\"?",
      "locations": [
        {
          "line": 11,
          "column": 5
        }
      ]
    }
  ]
}
```

DeviceStat 设备引擎状态信息与收发包信息

Method: POST

Request example

```
query
{
  deviceStat
    (id:"0")
    {
      id
      class
      pkt_stat
      run_stat
    }
}
```

Parameter Description

Requests

Name	Type	Description
id	String	设备引擎ID

Responses

Name	Type	Description
class	Int	设备名称
id	Int	设备ID
pkt_stat	Int	基于每个传感器的引擎数据包统计
run_stat	Int	引擎的运行状态

Response Examples

Success

```
{
  "data": {
    "deviceStat": [
      {
        "class": "engine",
        "id": "4418",
        "pkt_stat": "{\\\"1\\\":{\\\"DETECT\\\":{\\\"1.4G\\\":
{\\\"alert_rate\\\":0,\\\"pkt_rate\\\":0,\\\"tot_alerts\\\":0,\\\"tot_pkts\\\":2524},\\\"2.4G\\\":
{\\\"alert_rate\\\":0,\\\"pkt_rate\\\":0,\\\"tot_alerts\\\":1,\\\"tot_pkts\\\":2028},\\\"5G\\\":
{\\\"alert_rate\\\":0,\\\"pkt_rate\\\":0,\\\"tot_alerts\\\":6,\\\"tot_pkts\\\":12643},\\\"Sub-1G\\\":
{\\\"alert_rate\\\":0,\\\"pkt_rate\\\":0,\\\"tot_alerts\\\":0,\\\"tot_pkts\\\":5074},\\\"unknown\\\":
{\\\"alert_rate\\\":0,\\\"pkt_rate\\\":0,\\\"tot_alerts\\\":8,\\\"tot_pkts\\\":1514},\\\"all\\\":
{\\\"alert_rate\\\":0,\\\"pkt_rate\\\":0,\\\"tot_alerts\\\":15,\\\"tot_pkts\\\":23783}}}}",
        "run_stat": "
{\\\"cpu_usage\\\":22,\\\"cpu_freq\\\":1412,\\\"cpu_temp\\\":39,\\\"cpu_ram_used\\\":6534,\\\"cpu_ram_total\\\":
7765,\\\"gpu_usage\\\":0,\\\"gpu_temp\\\":38,\\\"gpu_ram_used\\\":6534,\\\"gpu_ram_total\\\":7765,\\\"swap_use
d\\\":1524,\\\"swap_total\\\":3883}"
      }
    ]
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Argument \"id\" has invalid value 0.\nExpected type \"String\",
found 0.",
      "locations": [
        {
          "line": 4,
          "column": 9
        }
      ]
    }
  ]
}
```

Devices 设备信息

Method: POST

Request example

```
query
{
  devices(id:"0"){
    class
    config
    faults
  }
}
```

```
gps_fixed
history {
  dev_id
  dev_type
  time_of_connection
  time_of_disconnection
}
id
node
rec_status
scv_status
sigCap_status
state
status
test_status
toc
}
}
```

Parameter Description

Requests

Name	Type	Description
id	String	设备id，不传显示所有

Responses

Name	Type	Description
class	String	当前设备名称
config	jsonStrTypepele	当前设备配置
faults	String	当前设备故障信息
gps_fixed	Boolean	GPS固定（false未固定-按钮关闭，true固定-按钮开启）
history	String	连接丢失历史
dev_id	String	设备ID
dev_type	String	设备类型
time_of_connection	String	连接时间
time_of_disconnection	String	断开时间
id	String	设备ID
node	String	设备所属节点
rec_status	String	设备记录状态

Name	Type	Description
scv_status	jsonStrType	传感器_收发包状态
sigCap_status	String	捕捉引擎设备状态的信号
state	String	当前设备的当前状态:停止、运行、降级、更新（各个设备的运行状态）
status	String	当前设备状态信息（如：控制器状态、传感器状态等）
test_status	String	当前设备测试状态_测试模式是否开启
toc	String	连接时间_持续时间段（时间戳换算-毫秒级）

Response Examples

Success

```
{
  "data": {
    "devices": [
      {
        "class": "sensor",
        "config": "{\n\"version\": \"2024.03.19\", \"build_time\": \"2024-03-19T01:14:30Z\", \"git_hash\": \"3a79c31c4f3f9698dad3890f9b3f969b733af8be\", \"device_type\": \"DetectionOnly\", \"mqtts_ip\": \"192.178.1.88\", \"mqtts_hostname\": \"1.dcn.local\", \"id\": \"1\", \"group\": \"AT\", \"mac\": \"00:0a:35:00:01:22\", \"sn\": \"SMMMMMMMM0440001R000\", \"pid\": \"DFT-3000AD\", \"hardware_version\": \"2\", \"rfchain_master\": true, \"ttl\": 15, \"geo_location\": {\n\"lat\": 40.02718, \"lng\": 116.0711}, \"location_locked\": true, \"range\": 8000, \"mimo_num\": 1, \"eng_port\": \"8000\", \"eng_ip\": \"192.178.1.88\", \"n_eng\": 2, \"listen_wifi\": \"\", \"watchdog_enable\": false, \"compass_enable\": true, \"dfant_id\": \"\", \"crif_califile\": \"crif_cali.bin\", \"is_sdexist\": true, \"cps_offset\": 0, \"bands\": [\n\"band14\", \"band9\", \"band4\", \"band58\", \"band24\"], \"with_spf\": false}",
        "faults": "",
        "gps_fixed": false,
        "history": null,
        "id": "1",
        "node": "master",
        "rec_status": "",
        "scv_status": "{\n\"version\": \"2024.03.19\", \"built_time\": \"2024-03-19T01:15:06Z\", \"git_hash\": \"5f9136d55dba3274d2a00d93caa2d771b21859a9\", \"temperatures\": [47368, 69843], \"tot_pkts\": [148135, 1], \"pkts_rate\": [4.16, 0]}",
        "sigCap_status": "",
        "state": "operational",
        "status": "{\n\"ip_address\": \"192.178.1.251/24\", \"first_seen\": \"25 Mar 24 15:25 CST\", \"last_seen\": \"\", \"version\": \"2024.03.19\", \"built_time\": \"2024-03-19T01:14:30Z\", \"git_hash\": \"3a79c31c4f3f9698dad3890f9b3f969b733af8be\", \"protected\": false, \"spd_cap\": true, \"spd_running\": false, \"heading\": -1, \"heading_reset\": false, \"gps_status\": \"\", 0.00\", \"test_gen\": 0}",
        "test_status": "{\n\"result\": 0, \"test_cases\": null, \"time\": \"0001-01-01T00:00:00Z\"}",
        "toc": "70364329"
```

```
    }
  ]
}
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"tocc\" on type \"Devices\". Did you mean \"toc\"?",
      "locations": [
        {
          "line": 22,
          "column": 5
        }
      ]
    }
  ]
}
```

Dfgun 察打枪

Method: POST

Request example

```
query
{
  dfgun {
    attack_freq_high
    attack_freq_low
    dBm
    droneid
    freq
    heading
    mode
    rssi
  }
}
```

Parameter Description

Responses

Name	Type	Description
attack_freq_high	Int	可调功率放大器（高）
attack_freq_low	Int	可调功率放大器（低）

Name	Type	Description
dBm	Int	分贝毫瓦
droneid	Int	无人机ID
freq	String	频率
heading	Float	方向
mode	Int	运行模式
rsi	Int	信号强度0~100

Response Examples

Success

```
{
  "data": {
    "dfgun": {
      "attack_freq_high": 0,
      "attack_freq_low": 0,
      "dBm": 0,
      "droneid": "",
      "freq": 0,
      "heading": -1,
      "mode": 0,
      "rsi": 0
    }
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"rsi\" on type \"dfgunStatus\". Did you mean \"rsi\"?",
      "locations": [
        {
          "line": 11,
          "column": 5
        }
      ]
    }
  ]
}
```

DhcpStatus 动态主机配置协议信息

Method: POST

Request example

```
query
{
  dhcpStatus {
    gateway
    ip
    netmask
    on
    status
  }
}
```

Parameter Description

Responses

Name	Type	Description
gateway	String	网关
ip	string	IP地址
netmask	String	子网掩码
on	Boolean	DHCP on/off，如果这个是off，所有其他字段都应该被忽略
status	Int	DHCP状态：0--未连接，1--已连接

Response Examples

Success

```
{
  "data": {
    "dhcpStatus": {
      "gateway": "192.168.85.1",
      "ip": "192.168.85.45",
      "netmask": "255.255.254.0",
      "on": true,
      "status": 1
    }
  }
}
```

Failure

```
{
  "data": null,
```

```
"errors": [
  {
    "message": "Cannot query field \"ip1\" on type \"dhcp\". Did you mean \"ip\"?",
    "locations": [
      {
        "line": 4,
        "column": 5
      }
    ]
  }
]
```

Drone 无人机信息

Method: POST

Request example

```
query
{
  drone
    (id:"NA0921511865")
    {
      altitude
      attack_bands
      attack_type
      attacking
      attacking_ttl
      blacklisted
      can_attack
      can_ctrl_landing
      can_takeover
      confirmed
      created_time
      ctrl_landing
      current_ptz {
        pan
        tilt
        zoom
      }
      custom_name
      deleted_time
      description
      direction
      directional_attack_state
      distance
      has_duplicate
      has_screenshot
      height
      id
      image
      in_ada
```

```

    initial_location {
      lat
      lng
    }
    jamming_conflicts
    lastseen
    lastseen_time
    latitude
    link_id
    localization {
      lat
      lng
    }
    longitude
    name
    rc_distance
    rc_location {
      lat
      lng
    }
    reliability
    screenshot
    seen_sensor {
      bandwidth_khz
      detected_freq_khz
      noise_dbm
      port
      sensor_id
      signal_dbm
      snr_dB
    }
    speed
    state
    tracing
    (from:0)
    {
      lastlen
      origin {
        lat
        lng
      }
      points
    }
    tracking_video
    whitelisted
  }
}

```

Parameter Description

Requests

Name	Type	Descripti
id	String	检测到的无人机id

Responses

Name	Type	Descripti
altitude	Float	海拔
attack_bands	Int	无人机信号
attack_type	String	无人机打击类型（Wideband宽频、Smart_CRPC打击、Smart-II精准打击、null）
attacking	Boolean	是否在精准打击（true是，false否）
attacking_ttl	Int	精准打击时长（倒计时）
blacklisted	Boolean	无人机是否被列入黑名单
can_attack	Boolean	无人机能否被精准打击（true、false）
can_ctrl_landing	Boolean	无人机能否受控迫降
can_takeover	Boolean	无人机是否可以被接管
confirmed	Boolean	确定是无人机或只是可疑
created_time	DateTime	首次检测到的时间
ctrl_landing	Boolean	无人机正在受控降落
current_ptz { pan tilt zoom }	CurrentPtz	无人机最后一次看到的实时PTZ{ 方位角 高度 俯仰角 }
custom_name	String	无人机自定义名称（来自黑名单或白名单）
deleted_time	DateTime	消失时间
description	String	无人机描述
detectors	[String]	检测来源列表[RID、CRPC、DroneID]
direction	Float	无人机角度（365表示无效）
directional_attack_state	Int	定向打击状态（0空闲、1追踪、2攻击）
distance	Float	无人机到设备中心点的距离
has_duplicate	Boolean	无人机是否隐藏
has_screenshot	Boolean	图传

Name	Type	Descripti
height	Float	无人机高度
id	String	无人机ID
image	String	无人机图片
in_ada	Int	无人机在防空区（0不可用、1不在、2预警区、3防御区）
initial_location{lat,lng}	String	无人机初始位置，210表示无效
jamming_conflicts	String	误打列表
lastseen	String	最后发现的时间
lastseen_time	DateTime	最后一次检测到的时间
latitude	String	无人机的纬度，如果“方向”无效，则无效
link_id	Float	无人机关联ID
localization{lat,lng}	{Float}	对无人机进行跟踪（已弃用）
longitude	Float	无人机的经度，如果“方向”无效，则无效
name	String	无人机机型或别名
rc_distance	Float	无人机飞行员距离，“-1”表示无效
rc_location{lat,lng}	GeoPoint	飞手（遥控器）位置（210表示无效）{经纬度}
reliability	Int	无人机可信度
screenshot	String	无人机最新截图（JPG格式）
seen_sensor	SignalObject	传感器检测到无人机信息
bandwidth_khz	Int	信号带宽
detected_freq_khz	Int	信号频点
noise_dbm	Int	天线的射频噪声功率，分贝差为一毫瓦
port	String	检测端口
sensor_id	String	检测的传感器ID
signal_dbm	Int	信号大小
snr_dB	Float	信噪比
speed	Float	无人机速度（m/s）
state	String	无人机状态（attacking打击、danger危险、Smart_打击类型）
tracing{lastlen}	String	无人机轨迹点

Name	Type	Descripti
from	Int	从
lastlen	Int	最后一个点的长度
origin{lat,lng}	Float	无人机轨迹的参考中心点位置
points	[Float]	无人机轨迹点
tracking_video	String	轨迹视频文件
whitelisted	Boolean	是否加入白名单

Response Examples

Success

```
{
  "data": {
    "drone": [
      {
        "altitude": 99,
        "attack_bands": [
          900,
          2400,
          5800
        ],
        "attack_type": "null",
        "attacking": false,
        "attacking_ttl": 0,
        "blacklisted": true,
        "can_attack": false,
        "can_ctrl_landing": false,
        "can_takeover": false,
        "confirmed": true,
        "created_time": "2024-10-17T14:27:23.154497991+08:00",
        "ctrl_landing": false,
        "deleted_time": "0001-01-01T00:00:00Z",
        "description": "",
        "direction": 258.94598,
        "directional_attack_state": 0,
        "distance": 10101,
        "has_duplicate": false,
        "has_screenshot": false,
        "height": -260,
        "id": "NAO921511865",
        "image": "dimages/autel_nano.png",
        "in_ada": 1,
        "initial_location": {
          "lat": 40.02487469946916,
          "lng": 116.3570900976692
        },
        "jamming_conflicts": [],

```

```
"lastseen": null,
"lastseen_time": "2024-10-17T14:27:44.133071015+08:00",
"latitude": 40.02487469946916,
"link_id": "",
"localization": null,
"longitude": 116.3570900976692,
"name": "AUTEL EVO-Nano+",
"rc_location": {
  "lat": 210,
  "lng": 210
},
"screenshot": "",
"seen_sensor": [
  {
    "bandwidth_khz": 10000,
    "detected_freq_khz": 2412000,
    "noise_dbm": 0,
    "port": "rf",
    "sensor_id": "2",
    "signal_dbm": 0,
    "snr_dB": 0
  }
],
"speed": 20,
"state": "safe",
"tracing": {
  "lastlen": 1121,
  "origin": {
    "lat": 40.0423,
    "lng": 116.4736
  },
  "points": [
    [
      -9048,
      -134.2,
      0
    ],
    [
      -9914.4,
      -1936.8,
      0
    ],
    [
      -9914.4,
      -1936.8,
      0
    ],
    .....
  ]
},
"tracking_video": "",
"whitelisted": false
}
```

```
]
}
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"attack_band\" on type \"Drone\". Did you mean\n\"attack_type\", \"attack_bands\", or \"attacking\"?",
      "locations": [
        {
          "line": 5,
          "column": 5
        }
      ]
    }
  ]
}
```

DroneAdsB 航班信息

Method: POST

Request example

```
query
{
  droneAdsB {
    drone
    {
      confirmed
      detected_freq_khz
      height
      id
      latitude
      longitude
      manufacturer
      model
      owner
      registration
      speed
      typecode
      yaw_angle
    }
    support
    switch
  }
}
```

Parameter Description

Responses

Name	Type	Description
drone	List	无人机列表
confirmed	Boolean	无人机状态
detected_freq_khz	Int	ADS-B频数
height	Float	飞机高度
id	String	飞机id
latitude	Float	飞机纬度
longitude	Float	飞机经度
manufacturer	String	飞机制造商
model	String	飞机模型
owner	String	飞机拥有者
registration	String	飞机登记
speed	Float	飞机速度
typecode	String	飞机类型的代码
yaw_angle	Float	飞机偏航角
support	Boolean	是否支持
switch	Boolean	是否开启状态

Response Examples

Success

```
{
  "data": {
    "droneAdsB": {
      "drone": [
        {
          "confirmed": true,
          "detected_freq_khz": 1090000,
          "height": 0,
          "id": "26a59e",
          "latitude": 39.63443562135858,
          "longitude": 114.6409912109375,
          "manufacturer": "",
          "model": "",
          "owner": "",

```

```
        "registration": "",
        "speed": 0,
        "typecode": "",
        "yaw_angle": 70.928375
      }
    ],
    "support": true,
    "switch": true
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"confirme\" on type \"DroneAdsb\". Did you mean \"confirmed\"?",
      "locations": [
        {
          "line": 6,
          "column": 7
        }
      ]
    }
  ]
}
```

DroneIDs 按无人机ID查询事件

Method: POST

Request example

```
query
{
  droneIDs
  (
    begin_time:"2024-10-01T09:47:09.590479Z"
    end_time:"2024-10-17T23:15:14.565626Z"
    pattern:""
    limit:5
  )
}
```

Parameter Description

Requests

Name	Type	Description
begin_time	String	查询开始时间
end_time	String	查询结束时间
pattern	String	模糊查询匹配字段
limit	Int	最大记录数

Response Examples

Success

```
{
  "data": {
    "droneIDs": [
      "000800102b95",
      "0008001042a6",
      "00080010634c",
      "000800106bcc",
      "0008001070bb"
    ]
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"limi\" on field \"droneIDs\" of type \"Query\".
Did you mean \"limit\"?",
      "locations": [
        {
          "line": 8,
          "column": 5
        }
      ]
    }
  ]
}
```

Dronetraces 历史轨迹

Method: POST

Request example

```
query
{
```

```
dronetraces
(
  from:0
  to:30400
)
{
  binding_id
  center_lat
  center_lng
  created_time
  drone_type
  frequency
  id
  points
  zoom
}
```

Parameter Description

Requests

Name	Type	Description
from	Int	传事件序列号（开始）
to	Int	传事件序列号（结束）

Responses

Name	Type	Description
query	String	None
binding_id	地图默认缩放级别	事件序列号
center_lat	String	传感器中心纬度
center_lng	String	传感器中心经度
created_time	DateTime	创建时间
drone_type	String	无人机类型
frequency	String	频率
id	String	无人机唯一ID
points	String	根据中心跟踪点
zoom	Int	地图默认缩放级别

Response Examples

Success

```
{
  "data": {
    "dronetraces": [
      {
        "binding_id": 1057,
        "center_lat": "40.04114",
        "center_lng": "116.36742",
        "created_time": "2025-07-01T08:44:09.411632Z",
        "drone_type": "Skydio 2+SDR35",
        "frequency": "5745.0Mhz",
        "id": "1668BS20JB00T326",
        "points": "[[-20341050.6,996285.7,80,1]]",
        "zoom": 13
      }, .....
    ]
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"binding_i\" on type \"DroneTrace\". Did you mean \"binding_id\"?",
      "locations": [
        {
          "line": 9,
          "column": 5
        }
      ]
    }
  ]
}
```

Dronetypes 按无人机类型查询事件

Method: POST

Request example

```
query
{
  dronetypes
  (
    limit:5
    begin_time:"2024-03-19T09:47:09.590479Z"
    end_time:"2024-03-18T23:15:14.565626Z"
    pattern:"w"
    all:false
  )
}
```

Parameter Description

Requests

Name	Type	Description
limit	Int	最大记录数（每页展示数量）
begin_time	String	查询开始时间
end_time	String	查询结束时间
pattern	String	模糊搜索匹配字段
all	Boolean	如果为 true，搜索所有类型

Response Examples

Success

```
{
  "data": {
    "dronetypes": [
      "WFLY Wft09sii",
      "DJI Air2s",
      "DJI Mavic3",
      "DJI MavicAir2",
      "FEIPAI 6KPro"
    ]
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Argument \"all\" has invalid value fals.\nExpected type \"Boolean\", found fals.",
      "locations": [
```

```
{
  {
    "line": 9,
    "column": 9
  }
}
]
```

Events 事件

Method: POST

Request example

```
query
{
  events
  (
    drone_id:"F45TB22BF00E021U"
    drone_type:"DJI Mavic3"
    begin_time:"2024-03-15 09:44:00"
    end_time:"2024-03-18 09:44:59"
    from:7145
  )

  {
    attacked
    blacklisted
    created_time
    deleted_time
    drone_type
    first_pos
    frequence
    id
    image
    is_false_alarm
    last_pos
    rc_pos
    seen_sensors
    sequence
    severity
    siteLatitude
    siteLongitude
    whitelisted
  }
}
```

Parameter Description

Requests

Name	Type	Description
drone_id	String	查询的无人机ID
drone_type	String	查询的无人机类型
begin_time	String	查询开始时间
end_time	String	查询结束时间
from	Int	传事件序列号开始

Responses

Name	Type	Description
attacked	Boolean	是否受到攻击
blacklisted	DateTime	是否为黑名单
created_time	DateTime	创建时间
deleted_time	DateTime	删除时间
drone_type	String	无人机类型
first_pos	String	首次发现位置
frequence	String	频率
id	String	无人机唯一ID
image	String	无人机图像
is_false_alarm	Boolean	是否标记为误报
last_pos	String	最后发现位置
rc_pos	String	无人机飞手位置
reliability	Int	该历史事件可信度，0 表示无效
seen_sensors	String	由哪个传感器看到的
sequence	String	事件序列号
severity	Int	严重程度：0：不可用（未知），1：低 2：中 3：高
siteLatitude	Float	站点纬度，210--表示无效
siteLongitude	Float	站点经度，210--表示无效
whitelisted	Boolean	是否加入白名单

Response Examples

Success

```
{
  "data": {
    "events": [
      {
        "attacked": false,
        "blacklisted": false,
        "created_time": "2025-06-10T06:24:33.365836Z",
        "deleted_time": "2025-06-10T06:24:53.366071Z",
        "drone_type": "DJI MavicAir2",
        "first_pos": "",
        "frequency": "5830.5Mhz",
        "id": "1WNBH5B00200L5",
        "image": "dimages/mavic_air2.png",
        "is_false_alarm": false,
        "last_pos": "",
        "rc_pos": "",
        "seen_sensors": "1",
        "sequence": 11833,
        "severity": "0",
        "siteLatitude": 45.750248,
        "siteLongitude": 126.63864,
        "whitelisted": false
      }
    ]
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"whiteliste\" on type \"Event\". Did you mean \"whitelisted\"?",
      "locations": [
        {
          "line": 28,
          "column": 5
        }
      ]
    }
  ]
}
```

Events aggregation 事件聚合查询

Method: POST

Request example

```
query
```

```

{
  events_aggregation
  (
    offset:0
    limit:1
    drone_type:"CYRF6936 General"
    drone_id:"3991062614"
    begin_time:"2024-03-01T00:57:53.564197Z"
    end_time:"2024-12-19T23:57:53.564197Z"
    filter_attacked:false
    filter_severity:[SEVERITY_NA,SEVERITY_LOW,SEVERITY_HIGH,SEVERITY_MEDIUM]
    filter_has_rc_pos:false
    filter_has_pos:false
    filter_has_trace:false
    order:"desc"
    order_by:"created_time"
    data_num_limit:false
  )
  {
    count
    data
    {
      count
      data
      {
        attacked
        blacklisted
        created_time
        deleted_time
        drone_type
        first_pos
        frequence
        has_screenshot
        id
        image
        is_false_alarm
        last_pos
        rc_pos
        reliability
        seen_sensors
        sequence
        severity
        siteLatitude
        siteLongitude
        whitelisted
      }
    }
  }
}

```

Parameter Description

Requests

Name	Type	Description
drone_type	String	按无人机类型筛选
data_num_limit	Boolean	是否限制返回数据项的数量
limit	Int	每页记录数，默认10
order_by	String	按此文件排序，值：created_time：检测时间，duration：无人机持续时间，drone_id：无人机 ID，drone_type：无人机类型，count：无人机出现次数。默认值：created_time
offset	Int	从该文件查询
filter_attacked	Boolean	筛选是否被干扰历史事件
filter_severity	[Severity]	筛选无人机危险等级历史事件 SEVERITY_NA：未知等级； SEVERITY_LOW：低危险等级； SEVERITY_MEDIUM：中危险等级； SEVERITY_HIGH：高危险等级。
filter_has_rc_pos	Boolean	筛选是否有飞手位置历史事件
filter_has_pos	Boolean	筛选是否有无人机位置历史事件
filter_has_trace	Boolean	筛选是否有轨迹历史事件
drone_id	String	按无人机id筛选
begin_time	String	查询开始时间
end_time	String	查询结束时间
order	String	数据顺序，asc升序,desc降序，默认降序

Responses

Name	Type	Description
count	Int	记录数
data	List	EventPaging_事件分页
count	Int	记录数
data	List	Event_无人机历史事件
attacked	Boolean	是否受到攻击
blacklisted	Boolean	是否为黑名单
created_time	DateTime	创建时间
deleted_time	DateTime	删除时间

Name	Type	Description
drone_type	String	无人机类型
first_pos	String	首次发现位置
frequency	String	频率
has_screenshot	Boolean	是否有截图
id	String	无人机唯一ID
image	String	无人机图像
is_false_alarm	Boolean	是否标记为误报
last_pos	String	最后发现位置
rc_pos	String	无人机飞手位置
reliability	Int	该历史事件可信度，0 表示无效
seen_sensors	String	发现无人机的传感器ID
sequence	String	事件序列号
severity	Int	严重程度：0：不可用（未知），1：低 2：中 3：高
siteLatitude	Float	站点纬度，210--表示无效
siteLongitude	Float	站点经度，210--表示无效
whitelisted	Boolean	是否加入白名单

Response Examples

Success

```
{
  "data": {
    "events_aggregation": {
      "count": 1,
      "data": [
        {
          "count": 3,
          "data": [
            {
              "attacked": false,
              "created_time": "2024-10-17T06:52:12.953315Z",
              "deleted_time": "2024-10-17T06:52:22.914674Z",
              "drone_type": "CYRF6936 General",
              "first_pos": "",
              "frequency": "2464.0Mhz",
              "id": "3991062614",
              "image": "dimages/uav_spectrum.png",
```

```
        "is_false_alarm": false,  
        "last_pos": "",  
        "rc_pos": "",  
        "seen_sensors": "2",  
        "sequence": 39899,  
        "severity": "1",  
        "whitelisted": false  
    },  
    .....  
]  
  
}  
  
]  
  
}  
  
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"dat\" on type \"EventAggregation\". Did you mean \"data\"?",
      "locations": [
        {
          "line": 16,
          "column": 7
        }
      ]
    }
  ]
}
```

Events_by_paging 事件展开查询

Method: POST

Request example

```
query
{
  events_by_paging
  (
    offset:0
    limit:1
    drone_type:"CYRF6936 General"
    drone_id:"3991062614"
    begin_time:"2024-03-14T00:00:00.564197Z"
    end_time:"2024-12-20T23:59:59.564197Z"
    filter_attacked:false
    filter_severity:[SEVERITY_NA,SEVERITY_LOW,SEVERITY_HIGH,SEVERITY_MEDIUM]
```

```
filter_has_rc_pos:false
filter_has_pos:false
filter_has_trace:false
order:"desc"
order_by:"drone_type"
is_false_alarm:false
)
{
    count
    data
    {
        attacked
        blacklisted
        created_time
        deleted_time
        drone_type
        first_pos
        frequence
        has_screenshot
        id
        image
        is_false_alarm
        last_pos
        rc_pos
        reliability
        seen_sensors
        sequence
        severity
        siteLatitude
        siteLongitude
        whitelisted
    }
}
}
```

Parameter Description

Requests

Name	Type	Description
offset	Int	从该文件查询
limit	Int	每页记录数，默认10
drone_type	String	按无人机类型筛选
drone_id	String	按无人机ID过滤
is_false_alarm	Boolean	是否查看误报
begin_time	String	查询开始时间
end_time	String	查询结束时间

Name	Type	Description
filter_attacked	Boolean	筛选是否被干扰历史事件
filter_severity	[Severity]	筛选无人机危险等级历史事件 SEVERITY_NA：未知等级； SEVERITY_LOW：低危险等级； SEVERITY_MEDIUM：中危险等级； SEVERITY_HIGH：高危险等级。
filter_has_rc_pos	Boolean	筛选是否有飞手位置历史事件
filter_has_pos	Boolean	筛选是否有无人机位置历史事件
filter_has_trace	Boolean	筛选是否有轨迹历史事件
order	String	数据顺序， <i>asc升序</i> ， <i>desc降序</i> ，默认降序
order_by	String	按此文件排序，值：created_time：检测时间，duration：无人机持续时间，drone_id：无人机

Responses

Name	Type	Description
count	Int	记录数
data	String	无人机历史事件
attacked	Boolean	是否受到攻击
blacklisted	Boolean	是否加入黑名单
created_time	DateTime	创建时间
deleted_time	DateTime	删除时间
drone_type	String	无人机类型
first_pos	String	首次发现位置
frequence	String	频率
has_screenshot	Boolean	是否有截图
id	String	无人机唯一ID
image	String	无人机图像
is_false_alarm	Boolean	是否标记为误报
last_pos	String	最后发现位置
rc_pos	String	无人机飞手位置
reliability	Int	该历史事件可信度，0 表示无效

Name	Type	Description
seen_sensors	String	由哪个传感器看到的
sequence	String	事件序列号
severity	Int	严重程度：0：不可用（未知），1：低 2：中 3：高
siteLatitude	Float	站点纬度，210--表示无效
siteLongitude	Float	站点经度，210--表示无效
whitelisted	Boolean	是否加入白名单

Response Examples

Success

```
{
  "data": {
    "events_by_paging": {
      "count": 4,
      "data": [
        {
          "attacked": false,
          "blacklisted": true,
          "created_time": "2024-10-17T07:04:57.223576Z",
          "deleted_time": "2024-10-17T07:05:07.184225Z",
          "drone_type": "CYRF6936 General",
          "first_pos": "",
          "frequence": "2464.0Mhz",
          "has_screenshot": false,
          "id": "3991062614",
          "image": "dimages/uav_spectrum.png",
          "is_false_alarm": false,
          "last_pos": "",
          "rc_pos": "",
          "seen_sensors": "2",
          "sequence": 39901,
          "severity": "1",
          "whitelisted": false
        }
      ]
    }
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
```

```
      "message": "Unknown argument \"offse\" on field \"events_by_paging\" of type\n\"Query\". Did you mean \"offset\"?",\n      "locations": [\n        {\n          "line": 5,\n          "column": 5\n        }\n      ]\n    }\n  ]\n}
```

GetSigParseImage 获取信号分析图片

Method: POST

Request example

```
query\n{\n  getSigParseImage\n  (\n    sensorId:"1"\n  )\n}
```

Parameter Description

Name	Type	Description
sensorId	String	传感器 ID

Response Examples

Success

```
{\n  "data": {\n    "getSigParseImage": [\n      "2380.jpg",\n      "2442.jpg",\n      .....\n      "5925.jpg"\n    ]\n  }\n}
```

Failure

```
{\n  "data": null,\n}
```

```
    "errors": [
      {
        "message": "Unknown argument \"sensorI\" on field \"getSigParseImage\" of type \"Query\". Did you mean \"sensorId\"?",
        "locations": [
          {
            "line": 5,
            "column": 3
          }
        ]
      }
    ]
  }
}
```

Get_gvs_conf 获取光电设备配置

Method: POST

Request example

```
query
{
  get_gvs_conf
  (
    id:"1"
  )
}
```

Parameter Description

Requests

Name	Type	Description
id	String	设备ID

Response Examples

Success

```
{
  "data": {
    "get_gvs_conf": "LogMode: info\nSaveNarrowObjsMode: 1\nPeriodicSaveBg:
true\nPeriodicSaveBgInterval: 30\nSavePlanesMode: 2\nSaveBirdsMode: 1\nSaveDronesMode:
2\nDeviceId: \"1\"\nDeviceLocationLat: 30.123\nDeviceLocationLng: 116.116\nDeviceLocati.....
1500\nDetectDroneMinDistance: 50\nTorchVersion: libtorch2.0\nTrackServiceIP:
127.0.0.1\nTrackServicePort: 9999\nAutoTrackEnable: true\nRotateStopTime:
0\nPushStreamEnable: true\nwideVideoKeepAlive: false\nMaxAutoTrackTime:
30\nTrackVideoSaveRate: 1\nTrackMainTargetColor: Red\nTrackOthreTargetColor:
Blue\nExcludePostList:\n- p120_t0_z6_wide1\n- p0_t0_z2_wide0\n- p0_t345_z2_wide0\n-
p210_t0_z2_wide0\n- p180_t0_z2_wide0\n- p150_t0_z2_wide0\n- p120_t0_z2_wide0\n-
p90_t0_z2_wide0\n- p60_t0_z2_wide0\n- p30_t0_z2_wide0\n"
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"ide\" on field \"get_gvs_conf\" of type
\"Query\". Did you mean \"id\"?",
      "locations": [
        {
          "line": 5,
          "column": 4
        }
      ]
    }
  ]
}
```

GfskData 通用检测器列表信息

Method: POST

Request example

```
query
{
  gfskData
  {
    bandwidth
    bitrate
    chan_lis
    created_time
    options
    protocol
    uid
  }
}
```

Parameter Description

Responses

Name	Type	Description
bandwidth	Int	GFSK带宽（对应高级_通用检测_带宽）
bitrate	Int	GFSK的比特率（对应高级_通用检测_比特率 单位bps）
chan_lis	String	对应高级_通用检测_信道
created_time	DateTime	GFSK 的创建时间
options	String	指定 GFSK 协议类型的条件（对应高级_通用检测_协议类型）
protocol	String	GFSK 协议
uid	Int	GFSK 类型的唯一 ID

Response Examples

Success

```
{
  "data": {
    "gfskData": [
      {
        "bandwidth": 250000,
        "bitrate": 80000,
        "chan_lis":
"2428599100,2433397900,2434597600,2435797300,2436997000,2438196700,2441795800,2444195200,244
5394900,2447794300,2448994000,2450193700,2457391900,2458591600,2460991000",
        "created_time": "2022-05-06T06:43:39Z",
        "options": "
{\\\"preamble_field_len\\\":0,\\\"sync_field\\\":\\\"0xFDFFDFE\\\",\\\"length_field_check\\\":true,\\\"payloa
d_field_len\\\":34,\\\"dewhitening\\\":false,\\\"crc\\\":false,\\\"fec\\\":false}",
        "protocol": "CC2500",
        "uid": 13
      }
    ]
  }
}
```

```
        },
        .....
    ]
}
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"ui\" on type \"GFSK\". Did you mean \"uid\"?",
      "locations": [
        {
          "line": 11,
          "column": 4
        }
      ]
    }
  ]
}
```

GfskProto 通用检测器协议信息

Method: POST

Request example

```
{
  gfskProto
  {
    A7106
    BK5811
    CC2500
    CYRF6936
    GFSK_Customized
    options
  }
}
```

Parameter Description

Responses

Name	Type	Description
A7106	[String]	A7106协议
BK5811	[String]	BK5811协议
CC2500	[String]	CC2500协议

Name	Type	Description
CYRF6936	[String]	CYRF6936协议
GFSK_Customized	[String]	GFSK_Customized协议
option	[String]	协议选项

Response Examples

Success

```
{
  "data": {
    "gfskProto": {
      "A7106": [
        "payload_field_len",
        "fec",
        "crc"
      ],
      "BK5811": [
        "payload_field_len"
      ],
      "cc2500": [
        "preamble_field_len",
        "sync_field",
        "length_field_check",
        "payload_field_len",
        "dewhitening",
        "fec",
        "crc"
      ],
      "CYRF6936": [
        "preamble_field_len",
        "sop_len"
      ],
      "GFSK_Customized": [
        "packet_format",
        "mod_scheme",
        "preamble_field",
        "sync_field_idx",
        "sync_field",
        "length_field_idx",
        "length_field_len",
        "payload_field_idx",
        "payload_field_len",
        "fec",
        "crc",
        "crc_reflect_data",
        "crc_reflect_remainder",
        "crc_init_remainder",
        "crc_final_xor_val"
      ]
    },
  ],
}
```

```
      "options": [
        "A7106",
        "CC2500",
        "BK5811",
        "CYRF6936",
        "GFSK_Customized"
      ]
    }
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"option\" on type \"ProtocolType\". Did you mean \"options\"?",
      "locations": [
        {
          "line": 9,
          "column": 5
        }
      ]
    }
  ]
}
```

LinkNodeList 组网节点（已移入列表）

Method: POST

Request example

```
query
{
  linkNodeList
  {
    id
    info
    ip
    latitude
    longitude
    name
    type
  }
}
```

Parameter Description

Responses

Name	Type	Description
id	String	节点ID
info	String	节点描述
ip	String	节点IP地址
latitude	Float	节点纬度
longitude	Float	节点经度
name	String	节点名称
type	String	节点类型

Response Examples

Success

```
{
  "data": {
    "linkNodeList": [
      {
        "id": "LZA9b080443-3e81-46f9-831f-433984f7a1d0",
        "info": "192.168.100.102 |",
        "ip": "192.168.100.102",
        "latitude": 0,
        "longitude": 0,
        "name": "102",
        "type": "LZA"
      }
    ]
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"typ\" on type \"Node\". Did you mean \"type\"?",
      "locations": [
        {
          "line": 11,
          "column": 9
        }
      ]
    }
  ]
}
```

LocalPatchInfo 可用于切换的本地补丁

Method: POST

Request example

```
query
{
  localPatchInfo
    (class:"engine")
  {
    local_versions {
      version_id
      version_publish_time
      version_status
    }
  }
}
```

Parameter Description

Requests

Name	Type	Description
class	String	补丁类型，当前仅支持：引擎、用户界面

Responses

Name	Type	Description
local_versions	String	有效的本地版本
version_id	Float	版本的唯一 ID
version_publish_time	Float	发布时间
version_status	String	版本状态和有效性

Response Examples

Success

```
{
  "data": {
    "localPatchInfo": {
      "local_versions": [
        {
          "version_id": "2024.10.15",
          "version_publish_time": "2024-10-15T00:54:54",
          "version_status": "current_version"
        }
      ]
    }
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"version_statu\" on type \"versions\". Did you mean \"version_status\", \"version_id\", or \"version_publish_time\"?",
      "locations": [
        {
          "line": 9,
          "column": 7
        }
      ]
    }
  ]
}
```

Nodes 组网节点信息

Method: POST

Request example

```
query
{
  nodes
  (
    id:""
  )
  {
    id
    info
    ip
    latitude
    longitude
    name
    type
  }
}
```

```
}
}
```

Parameter Description

Requests

Name	Type	Description
id	String	节点ID（未填或不传显示所有）

Responses

Name	Type	Description
info	String	节点描述
ip	String	节点IP地址
id	String	节点ID
latitude	Float	节点纬度
longitude	Float	节点经度
name	String	节点名称
type	String	节点类型

Response Examples

Success

```
{
  "data": {
    "nodes": [
      {
        "id": "LZA9b080443-3e81-46f9-831f-433984f7a1d0",
        "info": "192.168.100.102 |",
        "ip": "192.168.100.102",
        "latitude": 0,
        "longitude": 0,
        "name": "102",
        "type": "LZA"
      },
      {
        "id": "LZAb8bcd62b-a95f-4b14-8383-d2a94d867d2f",
        "info": "192.168.100.103 |",
        "ip": "192.168.100.103",
        "latitude": 0,
        "longitude": 0,
        "name": "103",
        "type": "LZA"
      }
    ]
  }
}
```

```
]
}
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"typ\" on type \"Node\". Did you mean\n\"type\"?",
      "locations": [
        {
          "line": 14,
          "column": 7
        }
      ]
    }
  ]
}
```

Notify 通知信息

Method: POST

Request example

```
query{
  notify(
    key:13
  )
  {
    regularNotify {
      extra
      id
      info
      key
      source
      status
      time
    }
    reservedNotify {
      extra
      id
      info
      key
      source
      status
      time
    }
  }
}
```

```
}

```

Parameter Description

Requests

Name	Type	Description
key	Int	定期通知起始键

Responses

Name	Type	Description
regularNotify	[notifyType]	只出现一次的通知
extra	String	额外信息
id	String	设备ID（如控制器_0）
info	String	信息
key	Int	节点名称
source	String	当前通知来源
status	String	通知状态
time	String	时间
reservedNotify	[notifyType]	通知总是出现
extra	String	额外信息
id	String	设备ID（如控制器_0）
info	String	信息
key	Int	节点名称
source	String	当前通知来源
status	String	通知状态
time	String	时间

Response Examples

Success

```
{
  "data": {
    "notify": {
      "regularNotify": [
        {

```

```
        "extra": "",
        "id": "2",
        "info": "",
        "key": 15,
        "source": "sensor",
        "status": "start",
        "time": "2024-10-17 15:25:54"
    },
    {
        "extra": "",
        "id": "1",
        "info": "",
        "key": 14,
        "source": "jammer",
        "status": "start",
        "time": "2024-10-17 15:25:16"
    }
],
"reservedNotify": []
}
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"tim\" on type \"notifyType\". Did you mean\n\"time\"?",
      "locations": [
        {
          "line": 22,
          "column": 7
        }
      ]
    }
  ]
}
```

ProfileAliasList 查询无人机自定义机型列表

Method: POST

Request example

```
query{
  profileAliasList {
    alias
    description
    drone_type
    visible
  }
}
```

Parameter Description

Responses

Name	Type	Description
alias	String	自定义别名
description	String	无人机自定义机型备注
drone_type	String	无人机机型
visible	Boolean	显示无人机时为 "true", 隐藏时为 "false"

Response Examples

Success

```
{
  "data": {
    "profileAliasList": [
      {
        "alias": "12378",
        "description": "456",
        "drone_type": "123",
        "visible": false
      }
    ]
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"visibled\" on type \"ProfileAlias\". Did you mean \"visible\"?",
      "locations": [
        {
          "line": 6,
          "column": 5
        }
      ]
    }
  ]
}
```

```
    }
  ]
}
]
```

ProfileList 查询无人机属性

Method: POST

Request example

```
query
{
  profileList {
    description
    drone_id
    drone_link_id
    drone_type
    visible
  }
}
```

Parameter Description

Responses

Name	Type	Description
description	String	无人机说明
drone_id	String	无人机ID
drone_link_id	String	与其他无人机一起减少ID
drone_type	String	定制型无人机
visible	Boolean	显示无人机时为 "true"，隐藏时为 "false"

Response Examples

Success

```
{
  "data": {
    "profileList": [
      {
        "description": "",
        "drone_id": "1WNBH5B00200L5",
        "drone_link_id": "60601f0916ae",
        "drone_type": "DJI MavicAir2",
        "visible": true
      }
    ]
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"visibl\" on type \"Profile\". Did you mean \"visible\"?",
      "locations": [
        {
          "line": 8,
          "column": 4
        }
      ]
    }
  ]
}
```

ProfilePatternList 查询用于匹配无人机 ID 的模式列表

Method: POST

Request example

```
query{
  profilePatternList {
    description
    drone_type
    pattern
    visible
  }
}
```

Parameter Description

Responses

Name	Type	Description
description	String	无人机备注
drone_type	String	无人机机型
pattern	String	正则表达式模式
visible	Boolean	显示无人机时为 "true"，隐藏时为 "false"

Response Examples

Success

```
{
  "data": {
    "profilePatternList": [
      {
        "description": "09876",
        "drone_type": "67890",
        "pattern": "12345",
        "visible": true
      }
    ]
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"drone_typed\" on type \"ProfilePattern\". Did you mean \"drone_type\"?",
      "locations": [
        {
          "line": 4,
          "column": 5
        }
      ]
    }
  ]
}
```

Report 统计

Method: POST

Request example

```
query{
```

```
report
(
  from: "2025-06-10T02:55:37.665168Z"
  to: "2025-06-10T03:27:43.597138Z"
)
{
  avg_duration
  avg_per_day
  avgdrn_per_day
  daily_data
  hourly_data
  longest_duration
  moments {
    events {
      attacked
      blacklisted
      created_time
      deleted_time
      drone_type
      first_pos
      frequence
      has_screenshot
      id
      image
      is_false_alarm
      last_pos
      rc_pos
      reliability
      seen_sensors
      sequence
      severity
      siteLatitude
      siteLongitude
      whitelisted
    }
    lost_time
    seen_time
  }
  most_in_alarm_region_per_day
  most_per_day
  most_per_hour
  mostdrn_in_alarm_region_per_day
  mostdrn_per_day
  mostdrn_per_hour
  top_drone_type
  top_drones
  total_drones
  total_duration
  total_in_alarm_region
  total_incidents
  total_mitigation
  totaldrn_in_alarm_region
  totaldrn_mitigation
}
```

```
}  
}
```

Parameter Description

Requests

Name	Type	Description
from	DateTime	开始时间
to	DateTime	结束时间

Responses

Name	Type	Description
avg_duration	Int	平均持续时间
avg_per_day	Int	平均每日架次
avgdrn_per_day	Int	平均每日架数
daily_data	datatype	事件趋势_日趋势
hourly_data	datatype	事件趋势_小时趋势
longest_duration	Int	单次最长时间
moments	momentType	关键时刻
events	[Event]	时间范围内的事件
attacked	Boolean	是否受到攻击
blacklisted	Boolean	是否被列入黑名单
created_time	DateTime	创建时间
deleted_time	DateTime	删除时间
drone_type	String	无人机类型
first_pos	String	首次发现位置
frequence	String	频率
has_screenshot	Boolean	是否有截图
id	String	无人机唯一ID
image	String	无人机图像
is_false_alarm	Boolean	是否标记为误报
last_pos	String	最后发现位置

Name	Type	Description
rc_pos	String	无人机飞手位置
reliability	Int	该检测记录的可靠性，0 表示无效
seen_sensors	String	由哪个传感器看到的
sequence	String	事件序列号
severity	Int	严重程度：0：不可用（未知），1：低 2：中 3：高
siteLatitude	Float	站点的纬度，210 "表示无效
siteLongitude	Float	站点的经度，210 "表示无效
whitelisted	Boolean	是否加入白名单
lost_time	DateTime	丢失时间戳
seen_time	DateTime	发现时间戳
most_in_alarm_region_per_day	Int	预警区单日最多架次
most_per_day	Int	单日最多架次
most_per_hour	Int	单小时最多架次
mostdrn_in_alarm_region_per_day	Int	预警区单日总架数
mostdrn_per_day	Int	单日最多架数
mostdrn_per_hour	Int	单小时最多架数
top_drone_type	datatype	检测到无人机类型
top_drones	datatype	检测到无人机
total_drones	Int	总发现架数
total_duration	Int	被入侵总时长（单位 秒 换算为分）
total_in_alarm_region	Int	预警区总发现架次
total_incidents	Int	总发现架次
total_mitigation	Int	总拦截架次
totaldrn_in_alarm_region	Int	预警区总发现架
totaldrn_mitigation	Int	总拦截架数

Response Examples

Success

```
{
  "data": {
```

```
"report": {
  "avg_duration": 154,
  "avg_per_day": 9,
  "avgdrn_per_day": 9,
  "daily_data": [
    [
      "Time",
      "Number of Incidents",
      "Total duration of the day",
      "Number of Drones"
    ],
    [
      "2025-06-10T08:00:00+08:00",
      9,
      1394,
      9
    ]
  ],
  "hourly_data": [
    [
      "Time",
      "Number of Incidents",
      "Total duration of the hour",
      "Number of Drones"
    ],
    [
      "2025-06-10T10:00:00+08:00",
      1,
      20,
      1
    ],
    [
      "2025-06-10T11:00:00+08:00",
      8,
      1374,
      8
    ]
  ],
  "longest_duration": 916,
  "moments": [
    {
      "events": [
        {
          "attacked": false,
          "blacklisted": false,
          "created_time": "2025-06-10T03:02:01.59499Z",
          "deleted_time": "2025-06-10T03:17:17.598394Z",
          "drone_type": "HX/Skydroid Herelink/H16",
          "first_pos": "",
          "frequence": "",
          "has_screenshot": false,
          "id": "d1be",
          "image": ""
        }
      ]
    }
  ]
}
```

```

        "is_false_alarm": false,
        "last_pos": "",
        "rc_pos": "",
        "reliability": 0,
        "seen_sensors": "",
        "sequence": 11772,
        "severity": "0",
        "siteLatitude": 0,
        "siteLongitude": 0,
        "whitelisted": false
    }
],
"lost_time": "2025-06-10T03:17:17.598394z",
"seen_time": "2025-06-10T03:02:01.59499z"
}
],
"most_in_alarm_region_per_day": 0,
"most_per_day": 9,
"most_per_hour": 8,
"mostdrn_in_alarm_region_per_day": 0,
"mostdrn_per_day": 9,
"mostdrn_per_hour": 8,
"top_drone_type": [
    [
        "Drone Type",
        "Number of Incidents"
    ],
    .....
    [
        "FRSKY R9M_LORA",
        1
    ]
],
"top_drones": [
    [
        "Drone Type",
        "ID",
        "Number of Incidents"
    ],
    .....
    [
        "ELRS LoraSF6",
        "06b9ed",
        1
    ]
],
"total_drones": 9,
"total_duration": 1394,
"total_in_alarm_region": 0,
"total_incidents": 9,
"total_mitigation": 0,
"totaldrn_in_alarm_region": 0,
"totaldrn_mitigation": 0

```

```
}  
}  
}
```

Failure

```
{  
  "data": null,  
  "errors": [  
    {  
      "message": "Cannot query field \"avg_durations\" on type \"reportType\". Did you mean  
\"total_duration\", \"avg_duration\", or \"longest_duration\"?",  
      "locations": [  
        {  
          "line": 8,  
          "column": 5  
        }  
      ]  
    }  
  ]  
}
```

Screenshot 图传截图

Method: POST

Request example

```
{  
  screenshot  
  (  
    offset:1  
    order:"desc"  
    seq:949  
    limit:1  
  )  
  {  
    count  
    data {  
      create_time  
      data  
      drone_id  
      drone_type  
      event_sequence  
      file_path  
      id  
    }  
  }  
}
```

Parameter Description

Requests

Name	Type	Description
offset	Int	要返回的 firest 记录的偏移量
order	String	查询顺序，从降序或升序中选择一个
seq	Int	截图事件序列号
limit	Int	返回记录的最大值

Responses

Name	Type	Description
count	Int	总记录数量
data	List	截图数据列表
create_time	DateTime	创建时间
data	String	截图数据
drone_id	String	无人机ID
drone_type	String	无人机类型
event_sequence	String	事件序列
file_path	String	文件路径
id	String	截图ID

Response Examples

Success

[illegible]

```
        "event_sequence": 949,
        "file_path": "/opt/lz/screenshot/2024-10-11/80ff2b/80ff2b-14-28-03.990.img",
        "id": 4
      }
    ]
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"valu\" on type \"request\". Did you mean\n\"value\"?",
      "locations": [
        {
          "line": 7,
          "column": 4
        }
      ]
    }
  ]
}
```

Sensor 传感器

Method: POST

Request example

```
query
{
  sensor
  (
    id:"1"
  )
  {
    config
    faults
    id
    mac
    name
    node
    sensor_status {
      built_time
      component_type
      first_seen
      git_hash
      ip_address
    }
  }
}
```

```
    last_seen
    temperature
    version
  }
  state
  ttl
}
}
```

Parameter Description

Requests

Name	Type	Description
id	Int	传感器ID（不传显示所有）

Responses

Name	Type	Description
config	JsonStrType	传感器配置
faults	String	传感器故障信息
id	String	传感器的唯一 ID
mac	String	传感器的 Mac 地址
name	String	传感器名称
node	String	传感器所属的节点
sensor_status	State	当前传感器的状态
built_time	String	SCV/控制器/传感器的唯一构建时间
component_type	String	SCV/控制器/传感器的组件类型
first_seen	String	当前 SCV/控制器/传感器的登录时间
git_hash	String	scv/controller/sensor 的唯一 git 散列编号
ip_address	String	scv/ 控制器/传感器的唯一 IP 地址
last_seen	String	当前 SCV/控制器/传感器的注销时间
temperature	Int	scv/ 控制器/传感器的温度
version	String	scv/ 控制器/传感器的唯一版本号
state	String	传感器的当前状态，处于“上升”或“下降”状态
ttl	Int	存活时间（传感器过期时间）

Response Examples

Success

```
{
  "data": {
    "sensor": [
      {
        "config": "
{\\\"version\\\":\\\"\\\",\\\"build_time\\\":\\\"\\\",\\\"git_hash\\\":\\\"\\\",\\\"device_type\\\":\\\"DetectionOnly\\\",\\\"
mqttts_ip\\\":\\\"192.178.1.88\\\",\\\"mqttts_hostname\\\":\\\"1.dcn.local\\\",\\\"id\\\":\\\"1\\\",\\\"group\\\":\\\"At\\\"
,\\\"mac\\\":\\\"06:00:20:0A:8C:04\\\",\\\"sn\\\":\\\"S111111117540001P901\\\",\\\"pid\\\":\\\"DAFT-
W1590DPI\\\",\\\"hardware_version\\\":\\\"2\\\",\\\"rfchain_master\\\":true,\\\"ttl\\\":15,\\\"geo_location\\\":
{\\\"lat\\\":40.0423,\\\"lng\\\":116.4736},\\\"location_locked\\\":false,\\\"range\\\":8000,\\\"mimo_num\\\":1,\\\"
eng_port\\\":\\\"8000\\\",\\\"eng_ip\\\":\\\"192.178.1.88\\\",\\\"n_eng\\\":2,\\\"listen_wifi\\\":\\\"\\\",\\\"watchdog
_enable\\\":false,\\\"compass_enable\\\":true,\\\"dfant_id\\\":\\\"\\\",\\\"crif_califile\\\":\\\"crif_cali.bin\\\"
,\\\"is_sdexist\\\":true,\\\"cps_offset\\\":0,\\\"bands\\\":
[\\\"band24\\\",\\\"band58\\\",\\\"band14\\\",\\\"band9\\\",\\\"band4\\\"],\\\"with_spf\\\":false}\\\",
        "faults": "",
        "id": "1",
        "mac": "06:00:20:0A:8C:04",
        "name": "",
        "node": "master",
        "sensor_status": {
          "built_time": "",
          "component_type": null,
          "first_seen": "18 Oct 24 09:19 CST",
          "git_hash": "",
          "ip_address": "192.178.1.251/24",
          "last_seen": "",
          "temperature": null,
          "version": ""
        },
        "state": "operational",
        "ttl": 12
      }
    ]
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \\\"tt\\\" on type \\\"Sensor\\\". Did you mean \\\"ttl\\\"?",
      "locations": [
        {
          "line": 25,
          "column": 5
        }
      ]
    }
  ]
}
```

```
    ]
  }
]
}
```

SpdReport 频谱

Method: POST

Request example

```
query
{
  spdReport
  (
    freq_start: 2400
    freq_stop: 2500
  )
  {
    bandwidth
    description
    frequency
  }
}
```

Parameter Description

Name	Type	Description
freq_start	Int	频谱跨度的起始频率，单位为Khz
freq_stop	String	频谱扫描的终止频率，单位Khz
bandwidth	Int	信号带宽
description	Int	信号描述
frequency	Int	信号频率

Response Examples

Success

```
{
  "data": {
    "spdReport": [
      {
        "bandwidth": 13980,
        "description": "FM调频",
        "frequency": 101400
      },
      .....
    ]
  }
}
```

```
      "bandwidth": 1740,
      "description": "",
      "frequency": 116220
    }
  ]
}
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"frequenc\" on type \"spdReport\". Did you mean \"frequency\"?",
      "locations": [
        {
          "line": 11,
          "column": 4
        }
      ]
    }
  ]
}
```

SpoofStatus 诱骗器状态

Method: POST

Request example

```
query
{
  spoofStatus {
    switch
  }
}
```

Parameter Description

Responses

Name	Type	Description
switch	Int	开关状态，0:关闭，1:打开，2:迫降，3:驱离。

Response Examples

Success

```
{
  "data": {
    "spooofStatus": {
      "switch": 0
    }
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"switc\" on type \"spooofStatus\". Did you mean \"switch\"?",
      "locations": [
        {
          "line": 4,
          "column": 4
        }
      ]
    }
  ]
}
```

Storage 设备存储空间

Method: POST

Request example

```
query
{
  storage {
    externalSize
    internalSize
  }
}
```

Parameter Description

Responses

Name	Type	Description
externalSize	Float	设备外部可用空间（以 MB 为单位）
internalSize	Float	设备内部可用空间（以 MB 为单位）

Response Examples

Success

```
{
  "data": {
    "storage": {
      "externalSize": 80961.80859375,
      "internalSize": 0
    }
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"internalSiz\" on type \"storage\". Did you mean \"internalSize\" or \"externalSize\"?",
      "locations": [
        {
          "line": 5,
          "column": 4
        }
      ]
    }
  ]
}
```

SysCapability 设备支持打击方式

Method: POST

Request example

```
query
{
  sysCapability
}
```

Parameter Description

None

Response Examples

Success

```
{
  "data": {
    "sysCapability": [
      "wideband",
      "Smart",
      "Smart-II"
    ]
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"sysCapabilit\" on type \"Query\". Did you mean \"sysCapability\"?",
      "locations": [
        {
          "line": 3,
          "column": 2
        }
      ]
    }
  ]
}
```

Time 查看设备系统时间

Method: POST

Request example

```
query
{
  time {
    sysTime
  }
}
```

Parameter Description

Responses

Name	Type	Description
sysTime	String	系统时间

Response Examples

Success

```
{
  "data": {
    "time": {
      "sysTime": "2024-03-26 13:56"
    }
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"sysTim\" on type \"time\". Did you mean \"sysTime\"?",
      "locations": [
        {
          "line": 4,
          "column": 4
        }
      ]
    }
  ]
}
```

TimeZone 查看设备时区

Method: POST

Request example

```
query
{
  timeZone {
    allTimeZone
    sysTimeZone
  }
}
```

Parameter Description

Responses

Name	Type	Description
allTimeZone	String	所有时区
sysTimeZone	String	系统时区

Response Examples

Success

```
{
  "data": {
    "timeZone": {
      "allTimeZone": [
        "Africa/Abidjan",
        "Africa/Accra",
        "Africa/Addis_Ababa",
        "Africa/Algiers",
        "Africa/Asmara",
        .....,
        "Universal",
        "W-SU",
        "WET",
        "Zulu"
      ],
      "sysTimeZone": "Asia/Shanghai"
    }
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"sysTimezon\" on type \"timeZone\". Did you mean \"sysTimeZone\" or \"allTimeZone\"?",
      "locations": [
        {
          "line": 5,
          "column": 7
        }
      ]
    }
  ]
}
```

UnknownSignal 未知信号

Method: POST

Request example

```
query
{
  unknownSignal
  {
    bw
    freq
    mod
    seen_sensors
    time
  }
}
```

Parameter Description

Responses

Name	Type	Description
bw	String	信号频宽
freq	String	信号频率
mod	String	信号调制方案
seen_sensors	String	检测到信号的传感器
time	String	信号时间

Response Examples

Success

```
{
  "data": {
    "unknownSignal": []
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"tim\" on type \"unknownSignal\". Did you mean \"time\"?",
      "locations": [
        {
          "line": 9,
          "column": 4
        }
      ]
    }
  ]
}
```

```
]
}
```

UnlinkNodeList 组网未知节点列表

Method: POST

Request example

```
query
{
  unknownSignal
  {
    bw
    freq
    mod
    seen_sensors
    time
  }
}
```

Parameter Description

Responses

Name	Type	Description
conn_type	String	连接类型
id	String	站点ID
info	String	站点信息
name	String	站点名称

Response Examples

Success

```
{
  "data": {
    "unlinkNodeList": [
      {
        "conn_type": "register",
        "id": "LZAf7a94b8c-1438-4178-b20a-601c9ab73486",
        "info": "",
        "name": "940"
      }
    ]
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"nam\" on type \"site\". Did you mean \"name\"?",
      "locations": [
        {
          "line": 8,
          "column": 5
        }
      ]
    }
  ]
}
```

Upgrade 本地升级版本

Method: POST

Request example

```
query
{
  upgrade {
    free_space
    has_enough_space
    local_versions {
      version_id
      version_publish_time
      version_status
    }
    prepare_status
    upgrade_status
  }
}
```

Parameter Description

Responses		
Name	Type	Description
free_space	Int	新升级的可用空间（以 MB 为单位）
has_enough_space	Boolean	是否有足够的空间进行新的升级
local_versions	String	有效的本地版本
version_id	String	版本唯一ID
version_publish_time	String	版本发布时间

Name	Type	Description
version_status	String	版本状态和有效性
prepare_status	String	准备升级目录
upgrade_status	String	升级状态

Response Examples

Success

```
{
  "data": {
    "upgrade": {
      "free_space": 0,
      "has_enough_space": false,
      "local_versions": [
        {
          "version_id": "v2024.09.09",
          "version_publish_time": "2024-09-09T01:03:01Z",
          "version_status": "Valid"
        },
        .....,
        {
          "version_id": "v3.14.0",
          "version_publish_time": "2024-10-12T10:21:05Z",
          "version_status": "Valid"
        }
      ],
      "prepare_status": "",
      "upgrade_status": "updated"
    }
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"upgrade_statu\" on type \"upgradeType\". Did you mean \"upgrade_status\" or \"prepare_status\"?",
      "locations": [
        {
          "line": 12,
          "column": 5
        }
      ]
    }
  ]
}
```

```
}

```

Version 当前版本信息

Method: POST

Request example

```
query
{
  version
}
```

Parameter Description

None

Response Examples

Success

```
{
  "data": {
    "version": "controller\n\tversion: 2024.10.15, built at 2024-10-15T01:01:25Z, git
hash:f448b89e4528165bf16c6a91ae1d792d4c45f8b5\n\ncm\n\tversion: 2024.10.15, built at 2024-
10-15T01:01:51Z, git
hash:7c0d0cf78f71ff2a5a193f0e6d1695381b909df5\n\nengine/'4418'\n\tversion: 2024.10.15, built
at 2024-10-15T00:54:54, ..... \n/opt/lz:\t\t[0 - 100%]\n<log>: 918M <sigrecords>: 4.0K
<sigdump>: 4.0K <sigcollect>: 4.0K <sigrecordcrash>: 4.0K <screenshot>: 96M <upload>:
4.0K \n"
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"versio\" on type \"Query\". Did you mean
\"version\"?",
      "locations": [
        {
          "line": 3,
          "column": 2
        }
      ]
    }
  ]
}
```

Vsgevent 光电单事件查询

Method: POST

Request example

```
query
{
  vsgevent
  (
    uuid:"eeb8ce4b-9633-4fdd-8ba3-5769057bbbc2"
  )
  {
    distance_between_obj_and_cam
    drone_type
    firstseen_ptz
    firstseen_size
    firstseen_time
    icon
    id
    image
    lastseen_ptz
    lastseen_size
    lastseen_time
    seen_sensors
    video
  }
}
```

Parameter Description

Requests

Name	Type	Description
uuid	String	无人机ID

Responses

Name	Type	Description
distance_between_obj_and_cam	Int	估计距离
drone_type	String	预测的无人机类型
firstseen_ptz	String	第一次看到云台
firstseen_size	String	首次看到的尺寸
firstseen_time	DateTime	初见时间
icon	String	图标文件路径


```
},
"errors": [
  {
    "message": "sql: no rows in result set",
    "locations": [
      {
        "line": 3,
        "column": 2
      }
    ],
    "path": [
      "vsgevent"
    ]
  }
]
```

Vsgevents 光电多事件查询

Method: POST

Request example

```
query
{
  vsgevents
  (
    from:1
    to:2
  )
  {
    distance_between_obj_and_cam
    drone_type
    firstseen_ptz
    firstseen_size
    firstseen_time
    icon
    id
    image
    lastseen_ptz
    lastseen_size
    lastseen_time
    seen_sensors
    video
  }
}
```

Parameter Description

Requests

Name	Type	Description
from	Int	从开始
to	Int	结束

Responses

Name	Type	Description
distance_between_obj_and_cam	Int	估计距离
drone_type	String	预测的无人机类型
firstseen_ptz	String	第一次看到云台
firstseen_size	String	首次看到的尺寸
firstseen_time	DateTime	初见时间
icon	String	图标文件路径
id	String	无人机的 UUID
image	String	原始检测图像文件名
lastseen_ptz	String	最后看到的 PTZ（P：方向角；t：俯仰角；z：倍率）
lastseen_size	String	最后看到的尺寸
lastseen_time	DateTime	最后出现时间
seen_sensors	String	由哪个传感器发现
video	String	跟踪视频文件名

Response Examples

Success

```
{
  "data": {
    "vsgevents": [
      {
        "distance_between_obj_and_cam": 7,
        "drone_type": "mavic",
        "firstseen_ptz": "p25.7t348.8z2.0",
        "firstseen_size": "278x139",
        "firstseen_time": "2024-03-26T17:13:06+08:00",
        "icon": "dimages/mavic_pro.png",
        "id": "a96bb6c5-bcab-4547-8adf-3c2c4a7b7760",
        "image": "",
        "lastseen_ptz": "p25.7t348.8z2.0",
        "lastseen_size": "278x139",
        "lastseen_time": "2024-03-26T17:14:13+08:00",
```

```

        "seen_sensors": "1",
        "video": ""
    },
    .....,
    {
        "distance_between_obj_and_cam": 30,
        "drone_type": "mavic",
        "firstseen_ptz": "p131.0t1.9z6.0",
        "firstseen_size": "177x73",
        "firstseen_time": "2024-05-11T17:50:31+08:00",
        "icon": "dimages/mavic_pro.png",
        "id": "db373e96-671d-4784-b979-1d5a6fde5bef",
        "image": "",
        "lastseen_ptz": "p141.7t0.2z6.0",
        "lastseen_size": "201x105",
        "lastseen_time": "2024-05-11T17:52:07+08:00",
        "seen_sensors": "1",
        "video": ""
    }
]
}

```

Failure

```

{
  "data": {
    "vsgevent": []
  },
  "errors": [
    {
      "message": "sql: no rows in result set",
      "locations": [
        {
          "line": 3,
          "column": 2
        }
      ],
      "path": [
        "vsgevent"
      ]
    }
  ]
}

```

Vsgeventsimage 光电图片查询

Method: POST

Request example

```
query
{
  vsgeventsimage
  (
    uuid:"eeb8ce4b-9633-4fdd-8ba3-5769057bbbc2"
    history:false
  )
}
```

Parameter Description

Requests

Name	Type	Description
uuid	Int	从开始
history	Int	true：查询历史事件，false：当前无人机列表

Response Examples

Success

```
{
  "data": {
    "vsgeventsimage":
"/9j/4AAQSkZJRgABAQAAQABAAAD/2wBDAAIBAQEBAQIBAQECAgICAgQDAgICAgUEBAMEBgUGBgYFBgYGBWkIBGcJBWY
GCASICQoKCgoKBg.....
yyzrFsAAVFLYXduHqfimKO+8SeHoL2NZkudZCXCSjcJVCggMD94A8gHvXL63Zwd74vbs7y0i1tk1VQ1vLGGjUNJ8wCng
Z7+twJ7H/2Q=="
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Argument \"history\" has invalid value fals.\nExpected type
\"Boolean\", found fals.",
      "locations": [
        {
          "line": 6,
          "column": 13
        }
      ]
    }
  ]
}
```

Whitelist 白名单列表

Method: POST

Request example

```
query
{
  whitelist {
    alias
    description
    dronetype
    id
  }
}
```

Parameter Description

Responses

Name	Type	Description
alias	String	无人机别名
description	String	无人机描述
dronetype	String	无人机类型
id	String	无人机唯一ID

Response Examples

Success

```
{
  "data": {
    "whitelist": [
      {
        "alias": "DJI Mavic3",
        "description": "permanent,permanent",
        "dronetype": "",
        "id": "F45TB22BF00E021U"
      }
      .....
      {
        "alias": "",
        "description": "2024-03-26 13:23:43,2024-04-26 13:23:43",
        "dronetype": "3DR Solo",
        "id": "undefined"
      }
    ]
  }
}
```

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"i\" on type \"Whitelist\". Did you mean \"id\"?",
      "locations": [
        {
          "line": 7,
          "column": 5
        }
      ]
    }
  ]
}
```

WidebandJammer 宽频干扰状态

Method: POST

Request example

```
query
{
  widebandJammer
  (
    directional:false
  )
  {
    band12
    band14
    band15
    band18
    band24
    band4
    band58
    band9
  }
}
```

Parameter Description

Name	Type	Description
directional	Int	定向干扰器

Name	Type	Description
band12	Int	频段状态 1.2G，0:不可用，1:空闲，其他:繁忙。
band14	Int	频段状态 1.4G，0:不可用，1:空闲，其他:繁忙。
band15	Int	频段状态 1.5G，0:不可用，1:空闲，其他:繁忙。
band18	Int	频段状态 1.8G，0:不可用，1:空闲，其他:繁忙。
band24	Int	频段状态 2.4G，0:不可用，1:空闲，其他:繁忙。
band4	Int	频段状态 433M，0:不可用，1:空闲，其他:繁忙。
band58	Int	频段状态 5.8G，0:不可用，1:空闲，其他:繁忙。
band9	Int	频段状态900M，0:不可用，1:空闲，其他:繁忙。

Response Examples

Success

```
{
  "data": {
    "widebandJammer": {
      "band12": 1,
      "band14": 1,
      "band15": 1,
      "band18": 1,
      "band24": 1,
      "band4": 1,
      "band58": 1,
      "band9": 1
    }
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"band\" on type \"WidebandJammer\". Did you mean \"band4\", \"band58\", \"band9\", \"band12\", or \"band14\"?",
      "locations": [
        {
          "line": 15,
          "column": 4
        }
      ]
    }
  ]
}
```

```
}

```

WidebandJammer2 宽频干扰状态

Method：POST

Request example

```
query
{
  widebandJammer2
  (
    directional:false
  )
  {
    band12
    band14
    band15
    band18
    band24
    band4
    band58
    band9
  }
}
```

Parameter Description

Requests

Name	Type	Description
directional	Int	定向干扰器

Responses

Name	Type	Description
band12	Int	频段状态 1.2G，0:不可用，1:空闲，其他:繁忙。
band14	Int	频段状态 1.4G，0:不可用，1:空闲，其他:繁忙。
band15	Int	频段状态 1.5G，0:不可用，1:空闲，其他:繁忙。
band18	Int	频段状态 1.8G，0:不可用，1:空闲，其他:繁忙。
band24	Int	频段状态 2.4G，0:不可用，1:空闲，其他:繁忙。
band4	Int	频段状态 433M，0:不可用，1:空闲，其他:繁忙。
band58	Int	频段状态 5.8G，0:不可用，1:空闲，其他:繁忙。
band9	Int	频段状态900M，0:不可用，1:空闲，其他:繁忙。

Response Examples

Success

```
{
  "data": {
    "widebandJammer": {
      "band12": 1,
      "band14": 1,
      "band15": 1,
      "band18": 1,
      "band24": 1,
      "band4": 1,
      "band58": 1,
      "band9": 1
    }
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"band\" on type \"WidebandJammer\". Did you mean \"band4\", \"band58\", \"band9\", \"band12\", or \"band14\"?",
      "locations": [
        {
          "line": 15,
          "column": 4
        }
      ]
    }
  ]
}
```

Wifilist wifi列表

Method: POST

Request example

```
query
{
  wifilist
  (
    type:"inactive"
  )
  {
    mac
    reliability
    ssid
    status
  }
}
```

Parameter Description

Requests

Name	Type	Description
type	String	选择活动/非活动/背景列表

Responses

Name	Type	Description
mac	String	无人机的 MAC 地址
reliablitiy	String	无人机的可靠性
ssid	String	无人机的 SSID
status	Int	无人机的状态

Response Examples

Success

```
{
  "data": {
    "wifilist": [
      {
        "mac": "2c:16:db:a3:1e:8c",
        "reliability": "0",
        "ssid": "",
        "status": 0
      },
      .....
      {
        "mac": "f0:1e:34:14:32:4e",
        "reliability": "0",
        "ssid": "",

```

```
        "status": 0
      }
    ]
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"statu\" on type \"wifilist\". Did you mean \"status\"?",
      "locations": [
        {
          "line": 11,
          "column": 5
        }
      ]
    }
  ]
}
```

Mutation 操作

AddBlacklist 添加黑名单

Method: POST

Request example

Requests

```
mutation{
  addBlacklist
  (
    id:"7e70db030e7b123"
    dronetype:"DESKTOP-BLGFE4D 1341"
    alias:"123"
  )
}
```

Parameter Description

Name	Type	Description
id	String	无人机id
dronetype	String	无人机机型

Name	Type	Description
alias	String	无人机别名

Response Examples

成功

```
{
  "data": {
    "addBlacklist": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"dronetyp\" on field \"addBlacklist\" of type \"Mutation\". Did you mean \"dronetype\"?",
      "locations": [
        {
          "line": 5,
          "column": 13
        }
      ]
    }
  ]
}
```

AddWhitelist 添加白名单

Method: POST

Request example

```
mutation{
  addwhitelist
  (
    id:"7e70db030e7b123"
    dronetype:"DESKTOP-BLGFE4D 1341"
    alias:"123"
    timerange:"permanent,permanent"
  )
}
```

Parameter Description

Requests

Name	Type	Description
id	String	无人机id
dronetype	String	无人机机型
alias	String	无人机别名
timerange	String	时效 "permanent,permanent"--永久 "2024-10-18T06:23:57.000Z,2024-10-19T15:59:59.999Z"--时间格式

Response Examples

Success

```
{
  "data": {
    "addwhitelist": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"timerang\" on field \"addwhitelist\" of type \"Mutation\". Did you mean \"timerange\"?",
      "locations": [
        {
          "line": 6,
          "column": 13
        }
      ]
    }
  ]
}
```

AirDefenceArea 绘制防空区

Method: POST

Request example

```
mutation{
  airDefenceArea
  (
    data:"{\"type\":0,\"distance\":388,\"locations\":
[[116.43229,39.557729]],\"hash\":\"436968595\", \"areatype\":1}"
  )
}
```

Parameter Description

Requests

Name	Type	Description
data	String	类型： 0-删除, 1-添加

Response Examples

Success

```
{
  "data": {
    "airDefenceArea": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"date\" on field \"airDefenceArea\" of type
\"Mutation\". Did you mean \"data\"?",
      "locations": [
        {
          "line": 4,
          "column": 9
        }
      ]
    }
  ]
}
```

Attack 精准打击

Method: POST

Request example

```
mutation
{
  attack
  (
    id:"a697b160cabb"
    cancel:true
  )
}
```

Parameter Description

Requests

Name	Type	Description
id	String	已检测到无人机ID
cancel	boolean	如果设置，则取消对无人机的攻击

Response Examples

Success

```
{
  "data": {
    "attack": null
  }
}
```

Failure

```
{
  "data": {
    "attack": null
  },
  "errors": [
    {
      "message": "Can't find drone with id 'a697b160cabb'",
      "locations": [
        {
          "line": 3,
          "column": 9
        }
      ],
      "path": [
        "attack"
      ]
    }
  ]
}
```

AutoAttack 无人值守

Method: POST

Request example

```
mutation
{
  autoAttack
  (
    naviBands:[band12]
    timeRanges:[["12:12:12","13:13:13"],["14:14:14","15:15:15"],["15:16:16","17:17:17"]]
    naviEnabled:false
    on:false
    saEnabled:false
    wbEnabled:true
    dirwbEnabled:false
    spfEnabled:false
    protectWhite:false
  )
}
```

Parameter Description

Requests

Name	Type	Description
on	boolean	开关按钮
saEnabled	boolean	精准打击
wbEnabled	boolean	宽频干扰
dirWbEnabled	boolean	定向打击
spfEnabled	boolean	GNSS诱骗
protectWhite	boolean	白名单保护
naviBands	[naviBands]	导航防御频段：band12/band15（1.2GHz/1.5GHz）
timeRanges	[[String]]	时间范围列表，格式为[[start, end],[..] 每个时间都是HH:MM:SS格式，代表一个每日时间范围； 支持跨日范围。
naviEnabled	Boolean	导航防御

Response Examples

Success

```
{
  "data": {
    "autoAttack": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"protectWhit\" on field \"autoAttack\" of type \"Mutation\". Did you mean \"protectWhite\"?",
      "locations": [
        {
          "line": 10,
          "column": 9
        }
      ]
    }
  ]
}
```

ClearStorage 清除内部存储

Method: POST

Request example

```
mutation
{
  clearStorage
}
```

Parameter Description

None

Response Examples

Success

```
{
  "data": {
    "clearStorage": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"clearStorag\" on type \"Mutation\". Did you mean \"clearStorage\" or \"clearLogs\"?",
      "locations": [
        {
          "line": 3,
          "column": 3
        }
      ]
    }
  ]
}
```

Ctrl_landing 迫降

Method: POST

Request example

```
mutation
{
  ctrl_landing
  (
    id:"60601f0a5004"
    enable:true
  )
}
```

Parameter Description

Requests

Name	Type	Description
id	String	无人机id
enable	Boolean	如果为 "是", 则开始控制无人机着陆。

Response Examples

Success

```
{
  "data": {
    "ctrl_landing": null
  },
  "errors": [
    {
      "message": "not support",
      "locations": [
```

```
        {
            "line": 1,
            "column": 10
        },
        "path": [
            "ctrl_landing"
        ]
    }
]
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"enable\" on field \"ctrl_landing\" of type \"Mutation\". Did you mean \"enable\"?",
      "locations": [
        {
          "line": 6,
          "column": 5
        }
      ]
    }
  ]
}
```

DeleteBlacklist 移除黑名单无人机

Method: POST

Request example

```
mutation
{
  deleteBlacklist
  (
    id:"3qwe2ZXCwqeq1"
  )
}
```

Parameter Description

Requests

Name	Type	Description
id	String	无人机id

Response Examples

Success

```
{
  "data": {
    "deleteBlacklist": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"i\" on field \"deleteBlacklist\" of type \"Mutation\". Did you mean \"id\"?",
      "locations": [
        {
          "line": 5,
          "column": 3
        }
      ]
    }
  ]
}
```

DeleteEvents 删除事件

Method: POST

Request example

```
mutation
{
  deleteEvents
  (
    sequence:[123]
  )
}
```

Parameter Description

Requests

Name	Type	Description
sequence	[Int]	要删除的事件序列数

Response Examples

Success

```
{
  "data": {
    "deleteEvents": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"sequenc\" on field \"deleteEvents\" of type\n\"Mutation\". Did you mean \"sequence\"?",
      "locations": [
        {
          "line": 5,
          "column": 3
        }
      ]
    }
  ]
}
```

DeleteEventsByID 根据无人机ID删除事件

Method: POST

Request example

```
mutation
{
  deleteEventsByID
  (
    drone_id:"123123123123213"
    drone_type:"123"
    all:true
  )
}
```

Parameter Description

Requests

Name	Type	Description
drone_id	String	无人机ID
drone_type	String	无人机类型

Name	Type	Description
all	Boolean	是否删除

Response Examples

Success

```
{
  "data": {
    "deleteEventsByID": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"a1\" on field \"deleteEventsByID\" of type \"Mutation\". Did you mean \"all\"?",
      "locations": [
        {
          "line": 7,
          "column": 5
        }
      ]
    }
  ]
}
```

DeleteWhitelist 移除白名单无人机

Method: POST

Request example

```
mutation
{
  deleteWhitelist
  (
    id:"3asdascz2qwe1"
  )
}
```

Parameter Description

Requests

Name	Type	Description
id	String	无人机id

Response Examples

Success

```
{
  "data": {
    "deletewhitelist": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"i\" on field \"deletewhitelist\" of type \"Mutation\". Did you mean \"id\"?",
      "locations": [
        {
          "line": 5,
          "column": 3
        }
      ]
    }
  ]
}
```

DetectingBands 检测频段开关

Method: POST

Request example

```
mutation
{
  detectingBands
  (
    band:"band24"
    enable:false
  ) {
    Boost24
    band12
    band14
    band18
    band24
    band4
    band58
  }
}
```

```
        band9
    }
}
```

Parameter Description

Requests

Name	Type	Description
band	String	检测频段
enable	boolean	开启或关闭

Responses

Name	Type	Description
Boost24	Int	0：不可用 1：禁用 2：启用
band12	Int	1.2Ghz 频段的状态，0:不可用，1:禁用，2:启用。
band14	Int	1.4Ghz 频段的状态，0:不可用，1:禁用，2:启用。
band18	Int	1.8Ghz 频段的状态，0:不可用，1:禁用，2:启用。
band24	Int	2.4Ghz 频段的状态，0:不可用，1:禁用，2:启用。
band4	Int	443Mhz 频段的状态，0:不可用，1:禁用，2:启用。
band58	Int	5.8Ghz 频段的状态，0:不可用，1:禁用，2:启用。
band9	Int	900Mhz 频段的状态，0:不可用，1:禁用，2:启用。

Response Examples

Success

```
{
  "data": {
    "detectingBands": {
      "Boost24": 0,
      "band12": 0,
      "band14": 2,
      "band18": 0,
      "band24": 1,
      "band4": 2,
      "band58": 2,
      "band9": 2
    }
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"band\" on type \"DetectingBands\". Did you mean \"band14\", \"band9\", \"band12\", \"band4\", or \"band24\"?",
      "locations": [
        {
          "line": 15,
          "column": 7
        }
      ]
    }
  ]
}
```

Device 设备设置

Method: POST

Request example

```
mutation
{
  device
  (
    class:"jammer"
    config:"
{\\\"id\\\":\\\"1\\\",\\\"group\\\":\\\"Bt\\\",\\\"mac\\\":\\\"48:b0:2d:51:2f:ee\\\",\\\"ip\\\":\\\"192.178.1.88/24\\\",\\\"sn\\\":\\\"SFFFFFFFF74300010C1H\\\",\\\"capabilities\\\":[true,false,true,false,false],\\\"geo_location\\\":{\\\"lat\\\":40.041096,\\\"lng\\\":116.367195},\\\"location_locked\\\":true,\\\"pa_cfg\\\":[{\\\"range_mhz\\\":[0,0],\\\"max_dbm\\\":0,\\\"set_dbm\\\":0},{\\\"range_mhz\\\":[0,0],\\\"max_dbm\\\":0,\\\"set_dbm\\\":0},{\\\"range_mhz\\\":[0,0],\\\"max_dbm\\\":0,\\\"set_dbm\\\":0},{\\\"range_mhz\\\":[0,0],\\\"max_dbm\\\":0,\\\"set_dbm\\\":0},{\\\"range_mhz\\\":[0,0],\\\"max_dbm\\\":0,\\\"set_dbm\\\":0},{\\\"range_mhz\\\":[0,0],\\\"max_dbm\\\":0,\\\"set_dbm\\\":0},{\\\"range_mhz\\\":[0,0],\\\"max_dbm\\\":0,\\\"set_dbm\\\":0},{\\\"range_mhz\\\":[0,0],\\\"max_dbm\\\":0,\\\"set_dbm\\\":0},{\\\"range_mhz\\\":[0,0],\\\"max_dbm\\\":0,\\\"set_dbm\\\":0}],\\\"pa_power\\\":[],\\\"attack_wifi\\\":\\\"\\\",\\\"azimuth_start\\\":0,\\\"azimuth_end\\\":360,\\\"elevation_start\\\":-60,\\\"elevation_end\\\":90,\\\"work_mode\\\":0,\\\"jammer_type\\\":-1,\\\"heading\\\":90,\\\"azimuth_init\\\":0,\\\"elevation_init\\\":0,\\\"azimuth_attack_range\\\":60,\\\"elevation_attack_range\\\":45,\\\"dir_delta\\\":2,\\\"version\\\":\\\"2024.03.19|dummy\\\",\\\"build_time\\\":\\\"2024-03-19T00:51:53Z\\\",\\\"git_hash\\\":\\\"6c68418d99c629c6e0eb0becd3ccf14618f68f33\\\"}"
    id:"1"
  )
}
```

Parameter Description

Requests

Name	Type	Descriptio
id	String	设备id
class	String	设备类别
config	jsonStrType	设备 json 对象中的配置

Response Examples

Success

```
{
  "data": {
    "device": null
  }
}
```

Failure

```
{
  "data": {
    "device": null
  },
  "errors": [
    {
      "message": "invalid jammer id",
      "locations": [
        {
          "line": 3,
          "column": 3
        }
      ],
      "path": [
        "device"
      ]
    }
  ]
}
```

DeviceTest 自检测

Method: POST

Request example

```
mutation
{
  deviceTest
  (
    enable:false
  )
}
```

Parameter Description

Requests

Name	Type	Descriptio
enable	String	启动（启用 = true）或停止（启用 = false）测试

Response Examples

Success

```
{
  "data": {
    "deviceTest": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"enabl\" on field \"deviceTest\" of type \"Mutation\". Did you mean \"enable\"?",
      "locations": [
        {
          "line": 5,
          "column": 3
        }
      ]
    }
  ]
}
```

Dfgun 察打枪

Method: POST

Request example

```
mutation
{
  dfgun
  (
    lan_type:123
    mode:123
    droneid:"123"
    attack_freq_low:123
    attack_freq_high:123
    cps_calib:false
  )
}
```

Parameter Description

Requests

Name	Type	Descriptio
lan_type	Int	切换语言，0_英语，1_ 中文
mode	Int	0_ 正常，1_ 锁定
droneid	String	无人机ID
attack_freq_low	Int	千赫兹，大于 300_000
attack_freq_high	Int	千赫兹，小于 2000_000
cps_calib	Boolean	罗盘校准

Response Examples

Success

```
{
  "data": {
    "deviceTest": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"enabl\" on field \"deviceTest\" of type \"Mutation\". Did you mean \"enable\"?",
      "locations": [
        {
          "line": 5,
          "column": 3
        }
      ]
    }
  ]
}
```

```
        }
      ]
    }
  ]
}
```

DhcpEnable 开启/关闭动态主机配置服务

Method: POST

Request example

```
mutation{
  dhcpEnable
  (on:true)
}
```

Parameter Description

Requests

Name	Type	Descriptio
on	Boolean	开关：true--开启，false--关闭

Response Examples

Success

```
{
  "data": {
    "dhcpEnable": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Argument \"on\" has invalid value true1.\nExpected type \"Boolean\", found true1.",
      "locations": [
        {
          "line": 3,
          "column": 7
        }
      ]
    }
  ]
}
```

```
}

```

DirectionalWBAttack 定向打击

Method: POST

Request example

```
mutation
{
  directionalWBAttack
  (
    status:true
    band:"band12"
    gain:100
    droneId:"123"
  ) {
    band12
    band14
    band15
    band18
    band24
    band4
    band58
    band9
  }
}
```

Parameter Description

Requests

Name	Type	Description
status	Boolean	是否开启
band	String	频段
gain	Int	增幅
droneId	String	无人机ID

Responses

Name	Type	Description
band12	Int	频段 1.2G，0:不可用，1:空闲，其他:繁忙
band14	Int	频段 1.4G，0:不可用，1:空闲，其他:繁忙
band15	Int	频段 1.5G，0:不可用，1:空闲，其他:繁忙
band18	Int	频段 1.8G，0:不可用，1:空闲，其他:繁忙

Name	Type	Description
band24	Int	频段 2.4G，0:不可用，1:空闲，其他:繁忙
band4	Int	频段 433M，0:不可用，1:空闲，其他:繁忙
band58	Int	频段 5.8G，0:不可用，1:空闲，其他:繁忙
band9	Int	频段 900M，0:不可用，1:空闲，其他:繁忙

Response Examples

Success

```
{
  "data": {
    "directionalWBAttack": {
      "band12": 1,
      "band14": 1,
      "band15": 1,
      "band18": 1,
      "band24": 1,
      "band4": 1,
      "band58": 1,
      "band9": 1
    }
  }
}
```

DroneAdsB 开启或关闭ADS-B

Method: POST

Request example

```
mutation
{
  droneAdsB
  (
    switch:true
  )
}
```

Parameter Description

Requests

Name	Type	Description
switch	Boolean	是否开启

Response Examples

Success

```
{
  "data": {
    "droneAdsB": true
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"switc\" on field \"droneAdsB\" of type\n\"Mutation\". Did you mean \"switch\"?",
      "locations": [
        {
          "line": 5,
          "column": 3
        }
      ]
    }
  ]
}
```

DroneProfileAlias 为指定无人机类型添加或删除别名

Method: POST

Request example

```
mutation{
  droneProfileAlias(
    action:"add"
    id:"123"
    drone_type:"123"
    alias:"123"
    visible:false
  )
}
```

Parameter Description

Requests

Name	Type	Description
action	String	操作，可以添加或删除
id	String	无人机ID

Name	Type	Description
drone_type	String	无人机类型
alias	String	自定义无人机别名
description	String	机型备注
visible	Boolean	显示无人机为真，隐藏为假，默认为真

Response Examples

Success

```
{
  "data": {
    "droneProfileAlias": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Argument \"visible\" has invalid value falsed.\nExpected type \"Boolean\", found falsed.",
      "locations": [
        {
          "line": 7,
          "column": 13
        }
      ]
    }
  ]
}
```

DroneProfilePattern 添加或删除无人机正则表达式模式

Method: POST

Request example

```
mutation{
  droneProfilePattern(
    new_pattern:"123"
    drone_type:"DJI MavicAir2"
    description:"123"
    visible:false
    action:"add"
    pattern:"123"
  )
}
```

Parameter Description

Requests

Name	Type	Description
new_pattern	String	如果操作为“add”并且此参数不为null，则旧模式将被此新模式替换
drone_type	String	定制无人机类型
description	String	无人机类型和模式描述
visible	Boolean	显示无人机为真，隐藏为假，默认为真
action	String	操作，可以添加或删除
pattern	String	无人机的模式

Response Examples

Success

```
{
  "data": {
    "droneProfilePattern": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Argument \"visible\" has invalid value falsed.\nExpected type \"Boolean\", found falsed.",
      "locations": [
        {
          "line": 6,
          "column": 13
        }
      ]
    }
  ]
}
```

```
}
]
}
```

DroneSub 订阅无人机截图信息（图传）

Method: POST

Request example

```
mutation
{
  droneSub
  (
    id:"false"
    attribute:"123"
    enable:false
  )
}
```

Parameter Description

Requests

Name	Type	Description
id	String	无人机ID
attribute	String	无人机的属性，支持列表：“截图”
enable	Boolean	启用或禁用订阅

Response Examples

Success

```
{
  "data": {
    "droneSub": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"enabl\" on field \"droneSub\" of type \"Mutation\". Did you mean \"enable\"?",
      "locations": [
        {

```

```
        "line": 7,
        "column": 5
      }
    ]
  }
}
```

Drone_profile 修改无人机属性

Method: POST

Request example

```
mutation
{
  drone_profile
  (
    visible:false
    id:"9c2ba6791fd2"
    drone_link_id:"false"
    drone_type:"00001"
    drone_description:"zxc"
  )
}
```

Parameter Description

Requests

Name	Type	Description
id	String	无人机ID
drone_link_id	String	无人机关联ID
drone_type	String	无人机类型
drone_description	String	无人机详细描述

Response Examples

Success

```
{
  "data": {
    "drone_profile": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"drone_descriptio\" on field \"drone_profile\" of
type \"Mutation\". Did you mean \"drone_description\"?",
      "locations": [
        {
          "line": 9,
          "column": 5
        }
      ]
    }
  ]
}
```

Gfsk 通用检测器

Method: POST

Request example

```
mutation {
  gfsk(
    cmd:"Add",
    data:"
{\"bandwidth\":2,\"protocol\":\"A7106\",\"chan_lis\":\"12312321\",\"bitrate\":1}
    option: \"{\"payload_field_len\":3,\"fec\":false,\"crc\":false}\"
  )
}
```

Parameter Description

Requests

Name	Type	Description
cmd	String	add_新增, delete_删除, modify_修改
data	jsonStrType	协议信息
option	jsonStrType	协议剩余信息（如：fec_信道编码、CRC校验等）

Response Examples

Success

```
{
  "data": {
    "gfsk": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"drone_descriptio\" on field \"drone_profile\" of type \"Mutation\". Did you mean \"drone_description\"?",
      "locations": [
        {
          "line": 9,
          "column": 5
        }
      ]
    }
  ]
}
```

GvsControl 控制光电服务（自动校准服务）

Method: POST

Request example

```
mutation
{
  gvsControl
  (
    id:"false"
    obj:"123"
    type:"false"
    action:"123"
    param:123
  )
}
```

Parameter Description

Requests

Name	Type	Description
obj	String	add_ 新增, delete_ 删除, modify_修改
type	String	操作类型, 如: autocali

Name	Type	Description
action	String	操作动作，如：startAutocali
id	String	设备ID
param	List	下发服务需要的附加参数

Response Examples

Success

```
{
  "data": {
    "drone_profile": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"drone_descriptio\" on field \"drone_profile\" of type \"Mutation\". Did you mean \"drone_description\"?",
      "locations": [
        {
          "line": 9,
          "column": 5
        }
      ]
    }
  ]
}
```

MarkFalseAlarm 标记误报（光电）

Method: POST

Request example

```
mutation {
  markFalseAlarm
    (sequence: [1])
}
```

Parameter Description

Requests

Name	Type	Description
sequence	[Int]	要标记的事件序列数组

Response Examples

Success

```
{
  "data": {
    "markFalseAlarm": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Argument \"sequence\" has invalid value asd.\nExpected type \"Int\", found asd.",
      "locations": [
        {
          "line": 3,
          "column": 16
        }
      ]
    }
  ]
}
```

MarkFalseAlarmByID 按ID标记误报（光电）

Method: POST

Request example

```
mutation{
  markFalseAlarmByID
  (
    all:false
    drone_type:"123"
    drone_id:"123"
  )
}
```

Parameter Description

Requests

Name	Type	Description
all	Boolean	是否删除所有事件
drone_type	String	查询无人机类型
drone_id	String	查询无人机ID

Response Examples

Success

```
{
  "data": {
    "markFalseAlarmByID": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Argument \"all\" has invalid value 123.\nExpected type \"Boolean\", found 123.",
      "locations": [
        {
          "line": 4,
          "column": 9
        }
      ]
    }
  ]
}
```

Node 节点

Method: POST

Request example

```
mutation
{
  node
  (
    name:"自行车5"
    info:"自行车"
    cmd:"add"
    id:"LZAac7c57d7-6096-49ce-bfa0-ef1f761dfff01"
  )
}
```

Parameter Description

Requests		
Name	Type	Description
cmd	String	操作：添加、删除、修改、采用、丢弃、重置、日志清理、日志上传
id	String	节点ID
name	String	节点名称
info	String	描述信息

Response Examples

Success

```
{
  "data": {
    "node": true
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"i\" on field \"node\" of type \"Mutation\". Did you mean \"id\"?",
      "locations": [
        {
          "line": 8,
          "column": 7
        }
      ]
    }
  ]
}
```

PowerMode 设置电源模式，仅适用于便携式设备

Method: POST

Request example

```
mutation{
  powerMode
  (mode:"balanced")
}
```

Parameter Description

Requests		
Name	Type	Description
mode	String	“性能”：CRPC+DroneID+RemotelD，默认； “平衡”：DroneID+RemotelD； “省电”：RemotelD

Response Examples

Success	
<pre>{ "data": { "powerMode": null } }</pre>	

Failure	
<pre>{ "data": null, "errors": [{ "message": "Argument \"mode\" has invalid value balanced.\nExpected type \"string\", found balanced.", "locations": [{ "line": 3, "column": 9 }] }] }</pre>	

Remove_fake_drone 标记无人机为误报无人机（无人机列表）

Method：POST

Request example

<pre>mutation { remove_fake_drone (uuid:"eeb8ce4b-9633-4fdd-8ba3-5769057bbbc2") }</pre>

Parameter Description

Requests		
Name	Type	Description
mutation	object	操作
remove_fake_drone	None	误报
uuid	String	无人机UUID

Response Examples

Success

```
{
  "data": {
    "remove_fake_drone": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"engineI\" on field \"rcap\" of type \"Mutation\".
Did you mean \"engineId\"?",
      "locations": [
        {
          "line": 7,
          "column": 5
        }
      ]
    }
  ]
}
```

Reset 重启设备

Method: POST

Request example

```
mutation
{
  reset
  (
    id:"LZAba14df4a-1ded-4bb5-b9da-fa4aac92abac1"
    class:"auth"
    reason:"123"
  )
}
```

Parameter Description

Requests

Name	Type	Description
id	String	设备id
class	String	设备类别（如：controller-控制器）
reason	String	重启原因

Response Examples

Success

```
{
  "data": {
    "reset": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"reaso\" on field \"reset\" of type \"Mutation\".
Did you mean \"reason\"?",
      "locations": [
        {
          "line": 7,
          "column": 5
        }
      ]
    }
  ]
}
```

RollbackPatch 切换或升级 UI 版本

Method: POST

Request example

```
mutation
{
  rollbackPatch
  (
    class:"ui"
    version:0
  )
}
```

Parameter Description

Requests

Name	Type	Description
class	String	补丁类型，当前仅支持：控制器、引擎、用户界面
version	Int	0：默认版本，1：旧版本。

Response Examples

Success

```
{
  "data": {
    "rollbackPatch": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"versio\" on field \"reset\" of type \"Mutation\".
Did you mean \"version\"?",
      "locations": [
        {
          "line": 7,
          "column": 5
        }
      ]
    }
  ]
}
```

SetGeoLocation 设置设备位置（非持久化）

Method: POST

Request example

```
mutation{
  setGeoLocation
  (
    lat:12.1212,
    lng:21.1212
  )
}
```

Parameter Description

Requests

Name	Type	Description
lat	Float	纬度
lng	Float	经度

Response Examples

Success

```
{
  "data": {
    "setGeoLocation": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Argument \"lng\" has invalid value \"21.1212\".\nExpected type \"Float\", found \"21.1212\".",
      "locations": [
        {
          "line": 5,
          "column": 9
        }
      ]
    }
  ]
}
```

Set_gvs_conf 修改光电配置

Method: POST

Request example

```
mutation
{
  set_gvs_conf
  (
    cont:"123"
    id:"123"
  )
}
```

Parameter Description

Requests

Name	Type	Description
cont	String	配置信息
id	String	设备ID

Response Examples

Success

```
{
  "data": {
    "set_gvs_conf": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"i\" on field \"set_gvs_conf\" of type \"Mutation\". Did you mean \"id\"?",
      "locations": [
        {
          "line": 6,
          "column": 5
        }
      ]
    }
  ]
}
```

Set_sensor_mode 设置传感器模式

Method: POST

Request example

```
mutation
{
  set_sensor_mode
  (
    mode:"DirectionFinding"
  )
}
```

Parameter Description

Requests

Name	Type	Description
mode	String	DetectionOnly_ 检测、DirectionFinding_ 定向、Detection+DF_ 检测+定向、SpectrumScanner_ 遗弃

Response Examples

Success

```
{
  "data": {
    "set_sensor_mode": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"mod\" on field \"set_sensor_mode\" of type \"Mutation\". Did you mean \"mode\"?",
      "locations": [
        {
          "line": 5,
          "column": 3
        }
      ]
    }
  ]
}
```

Set_vsg_license 设置光电授权

Method: POST

Request example

```
mutation
{
  set_vsg_license
  (
    id:"1"
    license:"12ASJDHLAKSDAKJLBkjsjgdbkj.....
sdbfalksdhnaslkdnasdaskfdjgabsdkjlbasdkjasbdoiwquheiqouweqoqiwhdqowiehnksja1dajkmdnasd3"
  )
}
```

Parameter Description

Requests

Name	Type	Description
id	String	设备ID
license	String	设备许可证

Response Examples

Success

```
{
  "data": {
    "set_vsg_license": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"mod\" on field \"set_sensor_mode\" of type \"Mutation\". Did you mean \"mode\"?",
      "locations": [
        {
          "line": 5,
          "column": 3
        }
      ]
    }
  ]
}
```

```
}

```

SigParse 信号分析

Method: POST

Request example

```
mutation
{
  sigParse
  (
    short:false
    sensorId:"1"
    bands:["band9"]
    brief:false
    extFreq:0
    antenna:0
  )
}
```

Parameter Description

Requests

Name	Type	Description
sensorId	String	传感器ID
bands	[String]	信号解析的频段
extFreq	Int	信号解析的额外频率（Mhz）。0 为空
short	Boolean	持续时间设置。false（正常）：21ms，ture（短）：10ms
brief	Boolean	true：打开 false：关闭
antenna	Int	天线接受的信号来自：[0-7]

Response Examples

Success

```
{
  "data": {
    "sigParse": null
  }
}
```

Failure

```
{
  "data": null,
}
```

```
    "errors": [
      {
        "message": "Unknown argument \"brie\" on field \"sigParse\" of type\n\"Mutation\". Did you mean \"brief\"?",
        "locations": [
          {
            "line": 9,
            "column": 5
          }
        ]
      }
    ]
  }
}
```

signalCap 信号抓取

Method: POST

Request example

```
mutation
{
  signalCap
  (
    msg:
    "
    {\"sigCap_drone\": \"111\", \"sigCap_distance\": \"222\", \"sigCap_height\": \"11\", \"sigCap_location\": \"shx\", \"sigCap_comment\": \"无备注\"}
    "
  )
}
```

Parameter Description

Requests

Name	Type	Description
msg	String	信号抓取记录信息

Response Examples

Success

```
{
  "data": {
    "sigParse": null
  }
}
```

Failure

```
{
```

```
    "data": null,
    "errors": [
      {
        "message": "Unknown argument \"brie\" on field \"sigParse\" of type\n\"Mutation\". Did you mean \"brief\"?",
        "locations": [
          {
            "line": 9,
            "column": 5
          }
        ]
      }
    ]
  }
}
```

SignalRec 信号证据记录

Method: POST

Request example

```
mutation
{
  signalRec
  (
    id:"4418"
    cmd:"123"
    droneTypes:"123"
  )
}
```

Parameter Description

Requests

Name	Type	Description
id	String	引擎ID
cmd	String	信号记录命令
droneType	String	用于信号记录的无人机类型

Response Examples

Success

```
{
  "data": {
    "signalRec": null
  }
}
```

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"droneType\" on field \"signalRec\" of type \"Mutation\". Did you mean \"droneTypes\"?",
      "locations": [
        {
          "line": 7,
          "column": 5
        }
      ]
    }
  ]
}
```

Spd 频谱

Method: POST

Request example

```
mutation
{
  spd
  (
    sensor_id:"1"
    req_id:1
    freq_start:30
    freq_stop:6000
    span_points:1
  )
}
```

Parameter Description

Name	Type	Description
freq_start	Int	频谱跨度的起始频率，单位 Kh
freq_stop	Int	频谱跨度的结束频率，单位 Khz
span_points	Int	频谱扫描点数
action	String	"add" 添加 or "update"修改 or "remove" _删除
sensor_id	String	SPD 传感器的 ID
req_id	Int	此 SPD 会话的请求 ID

Response Examples

Success

```
{
  "data": {
    "signalRec": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"droneType\" on field \"signalRec\" of type \"Mutation\". Did you mean \"droneTypes\"?",
      "locations": [
        {
          "line": 7,
          "column": 5
        }
      ]
    }
  ]
}
```

Spooferswitch 诱骗设置

Method: POST

Request example

```
mutation
{
  spooferswitch
  (
    id:"3"
    action:1
    timeout:1
    direction:-1
  )
{
  switch
}
}
```

Parameter Description

Requests

Name	Type	Descriptio
id	String	诱骗器ID，空表示自动选择
action	Int	屏蔽开关，0:关闭，1:打开，2:迫降，3:驱离
timeout	Int	开启 诱骗器的超时（秒），0 表示无限超时
direction	Int	驱逐欺骗的方向，-1 表示自动选择

Responses

Name	Type	Descriptio
switch	Int	开关状态，0:关闭，1:打开，2:迫降，3:驱离。

Response Examples

Success

```
{
  "data": {
    "spoofer_switch": {
      "switch": 0
    }
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"switc\" on type \"spooferStatus\". Did you mean \"switch\"?",
      "locations": [
        {
          "line": 11,
          "column": 5
        }
      ]
    }
  ]
}
```

StageReset 定向复位

Method: POST

Request example

```
mutation
{
  stageReset
  (
    direction:0
    elevation:0
    track_enable:true
    id:"123"
  )
}
```

Parameter Description

Requests

Name	Type	Descriptio
elevation	Float	垂直范围（-60<=value<=90）默认0
track_enable	Boolean	true -- 复位后继续跟踪已发现的无人机 false -- 复位后停止追踪无人机
id	String	干扰器ID
direction	Float	水平范围（0<=value<=360）默认0

Response Examples

Success

```
{
  "data": {
    "stageReset": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Cannot query field \"stageReset\" on type \"Query\".",
      "locations": [
        {
          "line": 2,
          "column": 2
        }
      ]
    }
  ]
}
```

Tdoa_track TDOA跟踪

Method: POST

Request example

```
mutation
{
  tdoa_track
  (
    id:"304a262b3a59"
    enable:false
  )
}
```

Parameter Description

Requests

Name	Type	Descriptio
id	Float	无人机的 ID
enable	Boolean	如果已设置，则开始对无人机进行 tdoa 跟踪

Response Examples

Success

```
{
  "data": {
    "tdoa_track": null
  }
}
```

Failure

```
{
  "data": {
    "tdoa_track": null
  },
  "errors": [
    {
      "message": "The drone doesn't exist",
      "locations": [
        {
          "line": 3,
          "column": 3
        }
      ],
      "path": [
        "tdoa_track"
      ]
    }
  ]
}
```

```
    ]
  }
]
}
```

Time 设置设备系统时间

Method: POST

Request example

```
mutation
{
  time
  (
    setTime:1710777670
  )
}
```

Parameter Description

Requests

Name	Type	Description
setTime	Int	设置时间（时间戳）

Response Examples

Success

```
{
  "data": {
    "time": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"setTim\" on field \"time\" of type \"Mutation\".
Did you mean \"setTime\"?",
      "locations": [
        {
          "line": 5,
          "column": 3
        }
      ]
    }
  ]
}
```

```
    ]
  }
}
```

TimeZone 设置设备时区

Method: POST

Request example

```
mutation
{
  timeZone
  (
    setTimeZone:"Africa/Harare"
    auto:false
  )
}
```

Parameter Description

Requests

Name	Type	Description
setTimeZone	String	设置时区
auto	Boolean	True 表示根据 GPS 定位自动配置，false 表示用户手动配置

Response Examples

Success

```
{
  "data": {
    "timeZone": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"setTimeZon\" on field \"timeZone\" of type \"Mutation\". Did you mean \"setTimeZone\"?",
      "locations": [
        {
          "line": 5,
          "column": 3
        }
      ]
    }
  ]
}
```

```
    }
  ]
}
```

Tracking 无人机视觉跟踪

Method: POST

Request example

```
mutation
{
  tracking
  (
    id:"IG2NZMvayzTaMvDwRXN63cd1c6c68"
    uuid:"304a262b3a59"
  )
}
```

Parameter Description

Requests

Name	Type	Descriptio
id	String	设备ID
uuid	Int	设置后，跟踪无人机 未设置，则取消对无人机的跟踪

Response Examples

Success

```
{
  "data": {
    "tracking": null
  }
}
```

Failure

```
{
  "data": {
    "tracking": null
  },
  "errors": [
    {
      "message": "invalid UUID length: 19",
      "locations": [
        {
          "line": 3,
```

```
        "column": 3
      }
    ],
    "path": [
      "tracking"
    ]
  }
]
}
```

UnknownWifi 未知WIFI

Method: POST

Request example

```
mutation
{
  unknownwifi
  (
    mac:"60601f5fb31f"
    tag:"drone"
  )
}
```

Parameter Description

Requests

Name	Type	Descriptio
mac	String	无人机macID
tag	String	设置当前无人机的标签：“热点”、“无人机”、“未知

Response Examples

Success

```
mutation
{
  unknownwifi
  (
    mac:"60601f5fb31f"
    tag:"drone"
  )
}
```

Failure

```
{
  "data": null,
```

```
"errors": [  
  {  
    "message": "Unknown argument \"ta\" on field \"unknownwifi\" of type  
\"Mutation\". Did you mean \"tag\"?",  
    "locations": [  
      {  
        "line": 6,  
        "column": 5  
      }  
    ]  
  }  
]
```

UpgradePatch 补丁升级

Method: POST

Request example

```
mutation  
{  
  upgradePatch  
}
```

Parameter Description

None

Response Examples

Success

```
{  
  "data": {  
    "upgradePatch": null  
  }  
}
```

Failure

```
{  
  "data": {  
    "upgradePatch": null  
  },  
  "errors": [  
    {  
      "message": "the base version is inconsistent, expect version: 2024.10.18  
,reality version: 3.14.0",  
      "locations": [  
        {  
          "line": 3,  
          "column": 3  
        }  
      ]  
    }  
  ]  
}
```

```
        }
      ],
      "path": [
        "upgradePatch"
      ]
    }
  ]
}
```

UpgradeTo 版本升级

Method: POST

Request example

```
mutation
{
  upgradeTo
  (
    versionName:"v2024.03.11"
    upgradeBy:"shengji"
  )
}
```

Parameter Description

Requests

Name	Type	Descriptio
versionName	String	已存在的本地版本名称
upgradeBy	String	升级

Response Examples

Success

```
成功后重启，返回连接失败
错误: socket hang up
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"upgradeB\" on field \"upgradeTo\" of type \"Mutation\". Did you mean \"upgradeBy\"?",
      "locations": [
        {
          "line": 6,
```

```
        "column": 5
      }
    ]
  }
}
```

VersionPackage 版本包

Method: POST

Request example

```
mutation
{
  versionPackage
  (
    filename:"v1.2.3"
    password:"zxcasdqeegsfge3453.....5sdgvdsfg32er"
  )
}
```

Parameter Description

Requests

Name	Type	Descriptio
filename	String	上传更新包的文件名
password	String	上传更新包的密码

Response Examples

Success

```
{
  "data": {
    "versionPackage": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"passwor\" on field \"versionPackage\" of type \"Mutation\". Did you mean \"password\"?",
      "locations": [
        {
```

```
        "line": 6,
        "column": 5
    }
]
}
}
```

Wideband_attack 宽频干扰

Method: POST

Request example

```
mutation
{
  wideband_attack
  (
    band: "band24"
    wb_status:true
    gain:50
    direction:-1
    elevation:5
    directional:false
    jammer_list:["[1]"]
  ) {
    band12
    band14
    band15
    band18
    band24
    band4
    band58
    band9
  }
}
```

Parameter Description

Requests

Name	Type	Description
band	String	指定频段
wb_status	Boolean	宽带干扰器的状态，状态为真时干扰器打开，状态为假时干扰器关闭
gain	Int	宽带干扰器的增益
direction	Float	宽带干扰器的发展方向
elevation	Float	宽带干扰器的提升

Name	Type	Description
directional	String	攻击使用干扰器列表
jammer_list	list	频段列表

Responses

Name	Type	Description
band12	Int	频段状态 1.2G，0:不可用，1:空闲，其他:繁忙。
band14	Int	频段状态 1.4G，0:不可用，1:空闲，其他:繁忙。
band15	Int	频段状态 1.5G，0:不可用，1:空闲，其他:繁忙。
band18	Int	频段状态 1.8G，0:不可用，1:空闲，其他:繁忙。
band24	Int	频段状态 2.4G，0:不可用，1:空闲，其他:繁忙。
band4	Int	频段状态 433M，0:不可用，1:空闲，其他:繁忙。
band58	Int	频段状态 5.8G，0:不可用，1:空闲，其他:繁忙。
band9	Int	频段状态 900M，0:不可用，1:空闲，其他:繁忙。

Response Examples

Success

```
{
  "data": {
    "wideband_attack": {
      "band12": 1,
      "band14": 1,
      "band15": 1,
      "band18": 1,
      "band24": 1,
      "band4": 1,
      "band58": 1,
      "band9": 1
    }
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"jammer_lis\" on field \"wideband_attack\" of type \"Mutation\". Did you mean \"jammer_list\"?",
```

```
      "locations": [
        {
          "line": 11,
          "column": 5
        }
      ]
    }
  ]
}
```

WifiBgLearning wifi背景学习开关

Method: POST

Request example

```
mutation
{
  wifiBgLearning
  (
    enable:false
    reset:false
  )
}
```

Parameter Description

Requests

Name	Type	Description
enable	Boolean	true 表示开始学习，false 表示停止学习
reset	Boolean	为真，删除当前数据并重新创建

Response Examples

Success

```
{
  "data": {
    "wifiBgLearning": null
  }
}
```

Failure

```
{
  "data": null,
  "errors": [
    {
```

```
      "message": "Unknown argument \"rese\" on field \"wifiBgLearning\" of type  
      \"Mutation\". Did you mean \"reset\"?",  
      "locations": [  
        {  
          "line": 6,  
          "column": 5  
        }  
      ]  
    }  
  ]  
}
```

WithdrawFalseAlarm 还原误报事件（光电）

Method: POST

Request example

```
mutation {  
  withdrawFalseAlarm(  
    drone_type: "DJI Mavic"  
    drone_id: "21d5b875-e839-4d33-bcd3-1d4f013e30b4"  
  )  
}
```

Parameter Description

Requests

Name	Type	Description
drone_type	String	无人机类型
drone_id	String	无人机ID

Response Examples

Success

```
{  
  "data": {  
    "wifiBgLearning": null  
  }  
}
```

Failure

```
{  
  "data": null,  
  "errors": [  
    {  
      "message": "Unknown argument \"rese\" on field \"wifiBgLearning\" of type  
      \"Mutation\". Did you mean \"reset\"?",  
      "locations": [  
        {  
          "line": 6,  
          "column": 5  
        }  
      ]  
    }  
  ]  
}
```

```
      "message": "Unknown argument \"rese\" on field \"wifiBgLearning\" of type  
      \"Mutation\". Did you mean \"reset\"?",  
      "locations": [  
        {  
          "line": 6,  
          "column": 5  
        }  
      ]  
    }  
  ]  
}
```

Subscription 订阅

接口：Websocket

Url：wss://192.168.100.100/sub/subscriptions

Drone 无人机

Method：POST

Request example

```
{  
  "id": "2",  
  "type": "add",  
  "payload": {  
    "query": "subscription {  
      drone {  
        id,  
        name,  
        description,  
        image,  
        secret,  
        state,  
        direction,  
        distance,  
        whitelisted,  
        blacklisted,  
        can_attack,  
        can_takeover,  
        can_ctrl_landing,  
        in_ada,  
        speed,  
        attacking,  
        ctrl_landing,  
        attacking_ttl,  
        created_time,  
        deleted_time,  
        lastseen_time,  
        lastseen,  
        longitude,  
        latitude,  
        height,  
        seen_sensor {  
          snr_dB,  
          sensor_id,  
          detected_freq_khz,  
          signal_dbm,  
          port  
        },  
        attack_bands,  
        attack_type,  
        tracing {  
          lastlen  
        },  
        origin {  
          lat  
          lng  
        },  
        points  
      }  
    },  
    "localization {  
      lat,  
      lng  
    },  
    "initial_location {  
      lat,  
      lng  
    },  
    "rc_location {  
      lat,  
      lng  
    },  
    "link_id,  
    "has_duplicate,  
    "jamming_conflicts,  
    "confirmed,  
    "tracking_video,  
    "has_screenshot,  
    "directional_attack_state  
  }  
}",  
  "extensions": {},  
  "operationName": null,  
  "variables": {}  
}
```

Parameter Description

Name	Type	Description
id	String	消息ID
type	String	类型
payload	String	有效载荷
query	Boolean	查询
subscription	None	订阅

Name	Type	Description
query	String	None
drone	None	无人机信息
id	String	检测到的无人机id
altitude	Float	海拔
attack_bands	Int	无人机信号
attack_type	String	无人机打击类型（Wideband宽频、Smart_CRPC打击、Smart-Il精准打击、null）
attacking	Boolean	是否在精准打击（true是，false否）
attacking_ttl	Int	精准打击时长（倒计时）
blacklisted	Boolean	无人机是否被列入黑名单
can_attack	Boolean	无人机能否被精准打击（true、false）
can_ctrl_landing	Boolean	无人机能否受控迫降
can_takeover	Boolean	无人机是否可以被接管
confirmed	Boolean	确定是无人机或只是可疑
created_time	DateTime	首次检测到的时间
ctrl_landing	Boolean	无人机正在受控降落
deleted_time	DateTime	消失时间
description	String	无人机描述
direction	Float	无人机角度（365表示无效）
directional_attack_state	Int	定向打击状态（0空闲、1追踪、2攻击）
distance	Float	无人机到设备中心点的距离
has_duplicate	Boolean	无人机是否隐藏
has_screenshot	Boolean	图传
height	Float	无人机高度
id	String	无人机ID
image	String	无人机图片
in_ada	Int	无人机在防空区（0不可用、1不在、2预警区、3防御区）
initial_location{lat,lng}	String	无人机初始位置，210表示无效
jamming_conflicts	String	误打列表

Name	Type	Description
lastseen	String	最后发现的时间
lastseen_time	DateTime	最后一次检测到的时间
latitude	String	纬度
link_id	Float	无人机关联ID
localization{lat,lng}	{Float}	对无人机进行跟踪（已弃用）
longitude	Float	经度
name	String	无人机机型或别名
rc_location{lat,lng}	GeoPoint	飞手位置（遥控器 210表示无效）{经纬度}
screenshot	String	无人机最新截图（JPG格式）
seen_sensor	SignalObject	传感器检测到无人机
bandwidth_khz	Int	信号带宽
detected_freq_khz	Int	信号频点
noise_dbm	Int	天线的射频噪声功率，分贝差为一毫瓦
port	String	检测端口
sensor_id	String	检测的传感器ID
signal_dbm	Int	信号大小
snr_dB	Float	信噪比
speed	Float	无人机速度（m/s）
state	String	无人机状态（attacking打击、danger危险、Smart_打击类型）
tracing{lastlen}	String	无人机轨迹点
from	Int	从
lastlen	Int	最后一个点的长度
origin{lat,lng}	Float	原地理位置
points	[Float]	追踪点
tracking_video	String	跟踪视频文件
whitelisted	Boolean	是否加入白名单

Response Examples

Success

```
{
  "type": "data",
  "id": "2",
  "payload": {
    "drone": [
      {
        "attack_bands": [],
        "attack_type": "null",
        "attacking": false,
        "attacking_ttl": 0,
        "blacklisted": false,
        "can_attack": false,
        "can_ctrl_landing": false,
        "can_takeover": false,
        "can_tdoa": false,
        "confirmed": false,
        "created_time": "2024-10-21T13:51:41.132761021+08:00",
        "ctrl_landing": false,
        "deleted_time": "0001-01-01T00:00:00Z",
        "description": "",
        "direction": 365,
        "directional_attack_state": 0,
        "distance": 0,
        "has_duplicate": false,
        "has_screenshot": false,
        "height": 0,
        "id": "60601f40e348",
        "image": "dimages/dji_p3_rc.png",
        "in_ada": 0,
        "initial_location": {
          "lat": 210,
          "lng": 210
        },
        "jamming_conflicts": [],
        "lastseen": null,
        "lastseen_time": "2024-10-21T13:51:56.131997501+08:00",
        "latitude": 0,
        "link_id": "",
        "localization": null,
        "longitude": 0,
        "name": "DJI Phantom3_RC",
        "rc_location": {
          "lat": 210,
          "lng": 210
        },
        "secret": "",
        "seen_sensor": [
          {
            "detected_freq_khz": 5748000,
            "port": "rf",
            "sensor_id": "2",
            "signal_dbm": 54,
            "snr_db": -17.173069
          }
        ]
      }
    ]
  }
}
```

```

    }
  ],
  "speed": 0,
  "state": "danger",
  "tdoa_tracking": false,
  "tracing": {
    "lastlen": 0,
    "origin": {
      "lat": 0,
      "lng": 0
    },
    "points": []
  },
  "tracking_video": "",
  "whitelisted": false
},
.....,
{
  "attack_bands": [
    2400,
    5800
  ],
  "attack_type": "Smart-II",
  "attacking": false,
  "attacking_ttl": 0,
  "blacklisted": false,
  "can_attack": true,
  "can_ctrl_landing": false,
  "can_takeover": false,
  "can_tdoa": false,
  "confirmed": true,
  "created_time": "2024-10-21T12:17:56.141919037+08:00",
  "ctrl_landing": false,
  "deleted_time": "0001-01-01T00:00:00Z",
  "description": "zxc",
  "direction": 365,
  "directional_attack_state": 0,
  "distance": 0,
  "has_duplicate": false,
  "has_screenshot": false,
  "height": 0,
  "id": "304a262b3a59",
  "image": "dimages/Feipai_6k_pro.png",
  "in_ada": 0,
  "initial_location": {
    "lat": 210,
    "lng": 210
  },
  "jamming_conflicts": [],
  "lastseen": null,
  "lastseen_time": "2024-10-21T13:51:56.132191293+08:00",
  "latitude": 0,
  "link_id": "false",

```

```

        "localization": null,
        "longitude": 0,
        "name": "00001",
        "rc_location": {
            "lat": 210,
            "lng": 210
        },
        "secret": "",
        "seen_sensor": [
            {
                "detected_freq_khz": 5745000,
                "port": "wifi",
                "sensor_id": "1",
                "signal_dbm": 54,
                "snr_dB": 13.370029
            }
        ],
        "speed": 0,
        "state": "danger",
        "tdoa_tracking": false,
        "tracing": {
            "lastlen": 0,
            "origin": {
                "lat": 0,
                "lng": 0
            },
            "points": []
        },
        "tracking_video": "",
        "whitelisted": false
    }
}

```

Failure

```

{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"rese\" on field \"wifiBgLearning\" of type  

\"Mutation\". Did you mean \"reset\"?",
      "locations": [
        {
          "line": 6,
          "column": 5
        }
      ]
    }
  ]
}

```

Message 后台消息

Request example

```
{
  "id": "2",
  "type": "sub",
  "payload": {
    "query": "subscription{\n      message{\n        msg_type\n        msg_key\n        info\n        source\n      }\n    }",
    "extensions": {},
    "operationName": null,
    "variables": {}
  }
}
```

Parameter Description

Requests

Name	Type	Description
id	object	消息ID
type	String	类型
payload	Boolean	有效载荷
query	Boolean	查询
subscription	None	订阅
message	String	从后台推送信息
msg_type	None	当前信息的类型
msg_key	String	msg 重要关键字
info	Float	信息
source	Int	当前信息的来源

Response Examples

Success

```
{
  {
    "id": "2",
    "type": "sub",
    "payload": {
      "query": "subscription{\n      message{\n        msg_type\n        msg_key\n        info\n        source\n      }\n    }",
      "extensions": {},
      "operationName": null,
      "variables": {}
    }
  }
}
```

Failure

```
{
  // Failure response structure
}
```

```
    "data": null,
    "errors": [
      {
        "message": "Unknown argument \"rese\" on field \"wifiBgLearning\" of type\n\"Mutation\". Did you mean \"reset\"?",
        "locations": [
          {
            "line": 6,
            "column": 5
          }
        ]
      }
    ]
  }
}
```

Notify 通知消息

Request example

```
{
  "id": "2",
  "type": "start",
  "payload": {
    "query": "subscription{\n  notify{\n    id\n    extra\n    key\n    info\n    time\n    source\n    status\n  }\n}",
    "extensions": {},
    "operationName": null,
    "variables": {}
  }
}
```

Parameter Description

Name	Type	Description
id	object	消息ID
type	String	类型
payload	Boolean	有效载荷
query	Boolean	查询
subscription	None	订阅
notify	String	通知
id	String	ID
extra	String	额外信息
info	String	信息
key	Int	msg ID
time	String	时间
source	String	当前通知的来源
status	String	通知状态

Response Examples

Success

```
{"type":"data","id":"1","payload":{"notify":{"extra":"","id":"1","info":"","key":21,"source":"jammer","status":"start","time":"2024-10-21 14:38:40"}}}}
```

Failure

```
{
  "data": null,
  "errors": [
    {
      "message": "Unknown argument \"rese\" on field \"wifiBgLearning\" of type \"Mutation\". Did you mean \"reset\"?",
      "locations": [
        {
          "line": 6,
          "column": 5
        }
      ]
    }
  ]
}
```