

Density-Based 4 Way Automatic Traffic Signal Control System

Submitted By

MD Abdul Gaffar (23103281)

Submitted To

Md. Muhtadir Rahman (Lecturer)

Department of Computer Science and Engineering

Course Name: Logic Design and Switching Circuit Lab (CSC 330)

International University of Business Agriculture and Technology



Submission Date: January 4, 2025

This document presents the development and design of an efficient yet straightforward **Density-Based 4-way Automatic Traffic Signal Control System**. The system aims to enhance traffic management in urban and semi-urban areas, particularly in regions with limited resources. Conventional traffic control systems often rely on expensive and complex technologies, which can be challenging to implement in underserved areas.

Our initial priority is simplicity, utilizing readily available components and straightforward mechanisms to manage traffic flow dynamically. The system incorporates **infrared (IR) sensors** to detect vehicle density on each lane and a **microcontroller** to process the sensor inputs and control traffic lights accordingly. The system optimizes traffic flow and reduces congestion by adjusting signal durations based on real-time traffic density.

The design emphasizes **reliability and ease of implementation**, featuring intuitive programming and lightweight hardware, ensuring accessibility for users with basic technical skills. The system is equipped to manage essential traffic scenarios, such as giving priority to high-density lanes and maintaining an equitable flow in all directions.

A **user-focused design process** has been adopted, incorporating feedback to refine the system's functionality and ensure its practical effectiveness. This iterative approach allows for continuous improvements while keeping costs low and setup straightforward.

In conclusion, our **Density-Based 4-Way Automatic Traffic Signal Control System** represents a significant advancement in traffic management solutions for underserved areas. By prioritizing **affordability, simplicity, and adaptability**, the system empowers communities to improve road safety, reduce delays, and enhance overall traffic efficiency.

Table of Contents

Chapter 1: Introduction.....	5
1.1 Objectives of Density-Based 4-Way Automatic Traffic Signal Control System.....	6
1.2 Scope of Density-Based 4-Way Automatic Traffic Signal Control System	7
1.3 Limitations of Density-Based 4-Way Automatic Traffic Signal Control System	9
1.4 Literature Review of Automatic Traffic Signal Control Systems.....	10
1.5 Overview of the Density-Based 4-Way Automatic Traffic Signal Control System	14
Chapter 2: Theoretical background.....	16
2.1 Arduino UNO R3.....	16
2.2 IR Sensor	18
2.3 LED Traffic Light Display DC 5V Module.....	20
Features.....	21
Specifications.....	21
2.4 Jumper Wire.....	21
2.5 Traffic Signal Control System Kit.....	22
2.6 Additional components	22
□ Plastic Board.....	22
□ Super Glue	23
□ Tape	23
□ Power Supply.....	23
□ Resistors (220 Ω).....	24
□ Data Transfer Optical Cable	24
□ UPBC Plastic Stand	24
Chapter 3: Project development.....	25
3.1 Circuit Diagram	25
3.2 Project Description	25
Chapter 4: Experiments and Results.....	32
4.1 Experiment 1.....	Error! Bookmark not defined.
4.2 Experiment 2.....	Error! Bookmark not defined.
Chapter 5: Conclusion	34
5.1 Future Scope: Enhancements for Density-Based 4-Way Automatic Traffic Signal Control System	37
5.2 References.....	Error! Bookmark not defined.

List of Figures

Figure 1: Arduino NANO with Pin Diagram	17
Figure 2: IR Sensor	19
Figure 3: Three color LEDs.....	21
Figure 4: Jumper Wire.....	22
Figure 5: Board.....	24
Figure 6: Super Glue.....	24
Figure 7: Tape.....	25
Figure 8: Resistor (220).....	25
Figure 9: Optical cable.....	26
Figure 10: Plastic Stand.....	27
Figure 11: Project Diagram.....	28
Figure 12: Before Power supply	37
Figure 13: After Power supply.....	39

Chapter 1: Introduction

Traffic congestion is a growing challenge in urban and semi-urban areas, impacting commuters' daily lives, fuel consumption, and air quality. Conventional traffic management systems rely on fixed-timer traffic signals, which often fail to adapt to dynamic traffic conditions, leading to inefficiency and increased delays. A Density-Based Automatic Traffic Signal Control System offers a solution by leveraging real-time vehicle density data to optimize traffic flow and reduce congestion.

Traffic congestion is a significant issue in Bangladesh, particularly in urban centers like Dhaka. The average traffic speed in Dhaka has decreased from 21 km/h a decade ago to less than 7 km/h in recent years, causing substantial economic losses due to wasted working hours, increased fuel consumption, and health impacts. (Wikipedia)

The concept of automated traffic management dates back to the mid-20th century, with early systems relying on inductive loop sensors embedded in roadways. While effective, these systems were expensive to implement and maintain. With the advent of modern electronics, infrared (IR) sensors and microcontrollers have emerged as cost-effective alternatives for detecting vehicle density and dynamically controlling traffic signals.

By the late 20th century, microcontroller-based systems began to replace fixed-timer systems, allowing for more adaptable and intelligent traffic signal control. These systems measured traffic density in real-time and adjusted signal durations accordingly, improving traffic flow efficiency. However, limitations such as complex setups, maintenance challenges, and high costs hindered their widespread adoption, particularly in underserved regions.

A Density-Based Traffic Signal Control System tackles these limitations by utilizing affordable IR sensors and simple circuitry to detect vehicle density on multiple lanes. The system processes sensor data using a microcontroller, ensuring that traffic signals are adjusted dynamically to prioritize lanes with higher traffic volumes. This approach not only reduces congestion but also minimizes fuel consumption and environmental impact.

Traffic congestion is not just an inconvenience—it poses significant social, economic, and environmental challenges. Poorly managed traffic signals contribute to longer travel times,

increased emissions, and driver frustration. Intelligent traffic management systems are essential for mitigating these issues and ensuring smoother traffic flow.

This introduction sets the stage for exploring the development and implementation of density-based traffic signal systems, focusing on their design, functionality, and potential impact. From understanding the technological components to addressing affordability and scalability, this report examines how such systems can revolutionize traffic management in both urban and rural settings.

Implementing a density-based traffic signal control system in Bangladesh could enhance traffic flow efficiency, reduce congestion, and minimize environmental impacts. Such systems utilize real-time data to adapt signal timings according to traffic density, offering a more responsive and effective solution compared to traditional methods.

By adopting innovative yet accessible technologies, density-based traffic signal systems aim to provide equitable solutions for managing roadways efficiently. These systems pave the way for smarter, more sustainable cities where traffic congestion is minimized, safety is enhanced, and commuters enjoy a more seamless travel experience.

1.1 Objectives of Density-Based 4-Way Automatic Traffic Signal Control System

The targets of the Density-Based 4-Way Automatic Traffic Signal Control System are to change the traffic control system, save money, and improve our mental health.

1. **Efficient Traffic Management:** The primary objective of this system is to optimize the flow of traffic at intersections by dynamically adjusting signal timings based on real-time traffic density, reducing congestion, and minimizing waiting times.
2. **Reduced Travel Time:** By adapting signal timing to actual traffic conditions, the system aims to decrease travel time for commuters, improving overall road efficiency and reducing delays.
3. **Enhanced Safety:** The system enhances safety by ensuring better traffic coordination, reducing the likelihood of accidents at busy intersections, especially during peak hours or in high-density areas.
4. **Energy and Fuel Conservation:** By minimizing vehicle idling time at traffic signals, the system can contribute to reduced fuel consumption and lower emissions, promoting environmental sustainability.

5. **Scalability and Flexibility:** The system is designed to be scalable and adaptable, capable of being deployed at intersections of varying sizes and complexity. It can also be upgraded to accommodate future advancements in traffic control technology.
6. **Cost-Effective Solution:** Leveraging affordable components like Arduino and ultrasonic sensors, this system aims to provide a cost-effective traffic management solution suitable for urban and semi-urban settings.
7. **Integration with Smart City Infrastructure:** The system is compatible with smart city initiatives, allowing it to integrate with other technologies such as IoT, vehicle-to-infrastructure (V2I) communication, and central traffic management systems for seamless operations.
8. **Ease of Maintenance:** Designed with simplicity in mind, the system facilitates straightforward maintenance, ensuring consistent performance with minimal operational downtime.
9. **Adaptability to Diverse Conditions:** The system can handle various traffic conditions, including irregular patterns, special events, and emergencies, ensuring optimal functioning regardless of the scenario.
10. **Public Satisfaction and Awareness:** By improving the traffic flow and reducing delays, the system aims to enhance commuter satisfaction while also promoting awareness about the benefits of technology-driven traffic solutions.
11. **Technological Advancements:** The objective includes incorporating emerging technologies such as AI for predictive traffic patterns, machine learning for optimization, and renewable energy sources like solar power to make the system more sustainable and efficient.

1.2 Scope of Density-Based 4-Way Automatic Traffic Signal Control System

The scope of a density-based traffic control system is huge, offering potential improvements in urban traffic management and paving the way for smarter, more efficient cities. Future advancements and opportunities in this domain could include:

1. Integration with Smart City Infrastructure

The system can be integrated with broader smart city initiatives, linking it with centralized traffic management systems, IoT-enabled devices, and smart vehicles to provide seamless traffic control and data sharing.

2. **Artificial Intelligence and Machine Learning**

Incorporating AI and ML can enable predictive traffic modeling, allowing the system to adapt dynamically to changing traffic conditions, seasonal variations, or special events with increased accuracy and efficiency.

3. **Advanced Sensor Technologies**

Future systems may employ advanced sensors like LiDAR, thermal imaging cameras, or vehicle-to-infrastructure (V2I) communication technologies to enhance traffic density detection and accuracy.

4. **Energy Efficiency and Renewable Power**

The system can be equipped with solar panels or other renewable energy sources, making it self-sustainable and reducing its carbon footprint. Energy-efficient components will also contribute to long-term cost savings.

5. **Integration with Emergency Services**

Advanced systems could prioritize emergency vehicles such as ambulances and fire trucks by providing green corridors, significantly improving response times during critical situations.

6. **Data Analytics and Traffic Insights**

By collecting and analyzing real-time traffic data, the system can provide valuable insights for urban planning, road maintenance, and traffic pattern predictions, supporting long-term city development strategies.

7. **Adaptability to Multi-Lane and Complex Intersections**

Future iterations of the system can be designed to handle more complex traffic scenarios, such as multi-lane intersections, roundabouts, or areas with mixed vehicle types like bicycles and pedestrians.

8. **Mobile and Cloud Connectivity**

By integrating with mobile applications or cloud platforms, the system can inform drivers of traffic conditions, estimated travel times, and optimal routes, reducing overall congestion.

9. **Smart Parking Integration**

Traffic signal systems can work in tandem with smart parking solutions to direct vehicles toward available parking spaces, alleviating congestion caused by vehicles searching for parking.

10. Cost-Effective and Scalable Solutions

Emphasis on creating cost-efficient and modular systems will allow for scalability and deployment in semi-urban and rural areas, addressing traffic management needs in diverse settings.

11. Global Applicability

The system's adaptable design makes it suitable for use in various countries with different traffic regulations and infrastructure, particularly in regions facing rapid urbanization and growing vehicle populations.

12. Education and Public Awareness

Public education campaigns can accompany the deployment of such systems to ensure that citizens understand its benefits and cooperate in its successful implementation.

The density-based traffic control systems can improve how cities manage vehicular movement, improve road safety, reduce environmental impact, and enhance the quality of life for their inhabitants.

1.3 Limitations of Density-Based 4-Way Automatic Traffic Signal Control System

While a density-based traffic signal control system offers significant advantages, it also has several limitations that can impact its efficiency and effectiveness:

1. **Sensor Accuracy and Maintenance:** The system heavily relies on sensors to detect traffic density accurately. Dust, weather conditions, or mechanical wear can affect sensor performance, leading to inaccurate data collection and suboptimal signal operation. Regular maintenance is required to ensure accuracy, adding to operational costs.
2. **Initial Cost and Installation:** Setting up a density-based traffic control system requires substantial investment in infrastructure, including sensors, cameras, and processing units. For developing or under-resourced regions, these initial costs may pose significant barriers to adoption.
3. **Compatibility with Existing Infrastructure:** Integrating the system with existing traffic signal setups and road infrastructure can be challenging. Upgrades may be necessary to ensure compatibility, which can further increase costs and implementation timelines.
4. **Power Dependency:** The system depends on a continuous power supply to operate. In areas prone to power outages or with limited access to reliable electricity, the system's functionality may be disrupted, causing traffic management inefficiencies.

5. **Vulnerability to External Factors:** Extreme weather conditions, such as heavy rain, snow, or fog, can affect sensor performance and visibility, reducing the system's ability to accurately detect traffic density and manage signals effectively.
6. **Limited Adaptability to Non-Motorized Traffic:** While the system is effective for managing motorized vehicles, it may struggle to accommodate non-motorized traffic, such as bicycles and pedestrians, particularly in areas where mixed traffic is prevalent.
7. **Traffic Flow Complexity:** At highly congested intersections with erratic traffic patterns, the system may not effectively resolve bottlenecks or manage traffic flow efficiently, especially during peak hours or special events.
8. **Data Privacy Concerns:** Systems using cameras and other surveillance technologies for traffic monitoring may raise privacy concerns. Ensuring compliance with data protection regulations and addressing public apprehensions can be challenging.
9. **Dependence on Skilled Workforce:** The operation, maintenance, and troubleshooting of such systems require trained personnel. A lack of skilled workers can hinder the system's effectiveness, especially in less developed regions.
10. **Limited Emergency Adaptation:** While the system is designed to optimize normal traffic flow, it may struggle to adapt to sudden emergencies or unforeseen incidents like accidents, requiring manual intervention to manage the situation.
11. **Scalability Issues:** Expanding the system to cover larger areas or accommodate growing urban traffic demands may require significant additional resources and infrastructure upgrades, potentially limiting its scalability.
12. **Network and Communication Reliability:** The system relies on stable communication networks to function. Connectivity issues, particularly in remote or rural areas, can disrupt system performance and reduce its efficiency.

By addressing these limitations through ongoing research, technological innovation, and careful planning, density-based traffic signal control systems can become more robust and universally applicable.

1.4 Literature Review of Prosthetic Arm

Automatic traffic signal control systems are essential components of modern transportation infrastructure, providing organized movement of vehicles and pedestrians at road intersections. Traditional traffic signal systems generally operate according to predetermined timing schedules,

which may not adequately respond to variations in traffic volume throughout the day. As urban populations and vehicle numbers continue to increase, intelligent and adaptive traffic signal control approaches have gained significant attention. This literature review examines the development of automatic traffic signal systems, focusing on traffic detection technologies, density-based signal control, microcontroller-based implementations, intelligent transportation systems, and emerging technologies. It also discusses the major challenges and future opportunities in adaptive traffic signal control.

Technological Advancements

The development of traffic signal control systems has been significantly influenced by advances in sensors, embedded systems, communication technologies, and intelligent computing. Conventional traffic signals use fixed-time control strategies in which predefined green, yellow, and red intervals are assigned to different approaches. Although these systems are relatively simple to implement, they may result in unnecessary waiting times when traffic conditions vary significantly between different roads.

Sensor-based traffic signal systems provide an alternative by collecting information about traffic conditions and using that information to modify signal operation. Technologies such as infrared sensors, ultrasonic sensors, inductive loop detectors, cameras, and other vehicle-detection devices can be used to identify the presence or approximate density of vehicles. Microcontrollers can then process the sensor information and determine an appropriate signal sequence.

The development of low-cost microcontrollers such as Arduino platforms has further simplified the implementation of traffic-control prototypes. These platforms provide digital and analog input/output capabilities that allow sensors and traffic-light indicators to be integrated into a single embedded system.

Traffic Density Detection and Signal Control

Traffic density is an important factor in determining the appropriate allocation of green-light time at an intersection. In a conventional fixed-time system, each road may receive a predetermined amount of green time regardless of the number of vehicles waiting. This can cause a lightly occupied road to receive the same priority as a heavily occupied road.

Density-based traffic signal systems attempt to overcome this limitation by considering the traffic condition of individual roads. Sensors are positioned at different approaches to an intersection, and

their outputs are analyzed by a controller. When a road is detected to have a higher traffic condition, the controller can assign priority to that road.

For a four-way intersection, traffic information from multiple approaches can be evaluated to determine which road should receive the green signal. This approach allows the signal operation to respond to changing traffic conditions rather than relying exclusively on a fixed sequence.

Microcontroller-Based Traffic Signal Systems

Microcontrollers have become widely used in prototype traffic signal systems because of their low cost, compact size, and programmable control capabilities. A microcontroller can receive signals from traffic-detection sensors, process the input values, and control traffic-light indicators according to a predefined algorithm.

In a typical microcontroller-based system, sensors are connected to the controller's input pins while red, yellow, and green LEDs are connected to output pins. The controller continuously reads sensor values and evaluates the detected traffic conditions. Based on the decision logic, the appropriate signal-control function is activated.

Arduino-based implementations are particularly suitable for educational and prototype applications because they provide a simple development environment and support rapid hardware experimentation. Such systems can demonstrate the fundamental concepts of sensor integration, embedded programming, decision-making, and automated traffic control.

Intelligent and Adaptive Traffic Management

More advanced traffic management systems use intelligent technologies to improve the ability of traffic signals to respond to complex road conditions. Computer vision systems can analyze camera images to estimate vehicle counts, lane occupancy, and traffic flow. Machine learning algorithms can further be applied to predict traffic patterns and optimize signal timing.

Internet of Things (IoT) technologies have also introduced opportunities for connecting traffic signals with centralized monitoring systems. Connected sensors can transmit traffic information to remote servers, allowing traffic conditions to be monitored and analyzed in real time.

These technologies provide opportunities for traffic signal systems to move beyond simple sensor-based decision-making toward more sophisticated adaptive traffic management. However,

advanced systems generally require greater computational resources, more complex software, reliable communication infrastructure, and higher implementation costs.

Challenges and Design Considerations

Despite improvements in automatic traffic signal control, several challenges remain. Sensor accuracy is an important consideration because incorrect or inconsistent sensor readings can result in inappropriate signal decisions. Sensor placement, environmental conditions, detection range, and hardware limitations can all affect system performance.

Another important consideration is the design of the decision-making algorithm. A system should prevent one road from continuously receiving priority while other roads experience excessive waiting times. Appropriate timing constraints and signal-transition rules are therefore necessary for safe and reliable operation.

Cost and implementation complexity are also significant factors. While camera-based and AI-powered systems can provide detailed traffic information, they may require more expensive hardware and greater computational capability. Low-cost microcontroller-based systems provide a simpler alternative for small-scale prototypes and educational applications.

Emerging Trends and Future Directions

The future of automatic traffic signal control is increasingly influenced by intelligent transportation technologies. Important areas of development include:

1. **Computer Vision:** Camera-based systems can identify vehicles, estimate traffic density, and analyze traffic flow without requiring a separate physical sensor for every detection point.
2. **Machine Learning:** Machine learning models can be used to predict traffic patterns and develop adaptive signal-control strategies based on historical and real-time traffic information.
3. **Internet of Things (IoT):** Connected traffic sensors and controllers can exchange information with centralized systems, enabling remote monitoring and coordinated traffic management.

4. **Vehicle-to-Infrastructure Communication:** Communication between vehicles and traffic infrastructure can provide additional information about vehicle locations, movement, and road conditions.
5. **Emergency Vehicle Priority:** Intelligent traffic systems can detect or receive information about emergency vehicles and provide appropriate signal priority to reduce delays.
6. **Smart City Integration:** Traffic signal systems can be integrated with broader smart-city platforms to combine traffic information with transportation monitoring, environmental sensing, and urban management systems.
7. **Energy-Efficient Systems:** Future traffic-control prototypes can incorporate low-power electronics, efficient LED systems, and renewable energy sources such as solar power.

Automatic traffic signal control represents an important application of embedded systems and intelligent transportation technologies. The transition from fixed-time traffic signals toward sensor-based and adaptive systems provides opportunities for traffic signals to respond more effectively to changing road conditions. Low-cost microcontroller-based prototypes provide a practical platform for studying these concepts and demonstrating automated traffic management.

Although advanced traffic-control systems continue to face challenges related to sensor accuracy, algorithm design, cost, scalability, and infrastructure requirements, continued developments in computer vision, machine learning, IoT, and connected transportation systems can provide new opportunities for more responsive and intelligent traffic management solutions.

1.5 Overview of the Density-Based 4-Way Automatic Traffic Signal Control System

The Density-Based 4-Way Automatic Traffic Signal Control System was designed to efficiently manage traffic at intersections by dynamically adjusting signal timing based on real-time vehicle density. This innovative system improves traffic flow, reduces congestion, and minimizes waiting times.

Components Used

The project utilized the following components:

1. **Arduino Nano:** Acts as the control unit to process data and manage signal timings.
2. **IR Sensors:** Detect vehicle density by measuring the distance to the nearest vehicle.
3. **LEDs:** Represent the traffic signals with red, yellow, and green lights.

4. **Jumper Wires:** Establish connections between the components.
5. **Resistors:** Control current flow for LEDs.
6. **Power Supply:** Provides energy to the Arduino and other components.

Circuit Design and Connections

The system's circuit was designed to integrate all components efficiently

- **IR Sensors:**
 - VCC and GND pins connected to Arduino's +5V and GND.
 - TRIG and ECHO pins connected to Arduino's digital PWM pins (2, 3, 4, 5 for four lanes).
- **LEDs:**
 - Connected to digital pins of the Arduino, with resistors placed in series to regulate current.

Working Principle

The system operates as follows:

1. **Vehicle Detection:** Ultrasonic sensors continuously measure the distance between the sensor and the nearest vehicle on each lane. If the distance is less than a predefined threshold (indicating high vehicle density), the sensor sends this data to the Arduino.
2. **Signal Timing Adjustment:** Based on the density information from all four lanes, the Arduino dynamically adjusts the signal timings to prioritize lanes with higher traffic density.
 - For example, a lane with high density receives a longer green signal duration, while lanes with lower density receive shorter durations.
3. **Signal Control:** The Arduino controls the LEDs to represent red, yellow, and green signals for each lane, ensuring smooth traffic flow.

Code and Logic

The system's code (detailed in Chapter 3) is written in C/C++ and includes:

- **Input Handling:** Reads data from ultrasonic sensors.
- **Decision-Making:** Compares vehicle densities across lanes and determines signal priorities.

- **Output Control:** Activates LEDs based on calculated timings.

Advantages and Key Features

1. **Dynamic Control:** Adjusts signal timings in real-time, reducing unnecessary waiting times.
2. **Improved Traffic Flow:** Ensures smoother movement of vehicles by prioritizing dense lanes.
3. **Energy Efficiency:** Optimizes signal operation, reducing power consumption.
4. **Scalability:** Can be expanded to accommodate more lanes or integrated with smart city frameworks.
5. **Affordable:** Uses cost-effective and readily available components.

This project demonstrates an effective solution to traffic congestion using density-based control mechanisms. The system is adaptable, energy-efficient, and contributes to smarter urban infrastructure, showcasing the potential of low-cost technology to address real-world challenges.

Chapter 2: Theoretical background

The components that are used in the project are given below with background information about them:

2.1 Arduino Nano

The **Arduino Nano** is a compact microcontroller board based on the ATmega328P, designed for applications requiring a smaller form factor. It features 14 digital input/output pins (6 of which support PWM output), 8 analog inputs, a 16 MHz quartz crystal oscillator, a mini USB connection, an ICSP header, and a reset button. The board includes all the essential components needed to support the microcontroller. Users can easily connect it to a computer via a mini-USB cable or power it using an external battery or AC-to-DC adapter.

The Nano is particularly well-suited for projects where space constraints are critical. Its small size and lightweight design make it ideal for embedding into various devices and systems, such as wearables, compact robotics, and IoT applications. Additionally, the Nano is known for its versatility and ease of use, enabling users to experiment without worrying about causing

irreversible damage. In the worst-case scenario, the chip can be replaced affordably, allowing users to continue their projects seamlessly (Anon., 2024).




Figure 1: Arduino Nano with Pin Diagram

Arduino Nano board includes the following specifications:

- Microcontroller: ATmega328P
- Operating Voltage: 5V
- Recommended Input Voltage: 7V to 12V
- Input Voltage (Limit): 6V to 20V
- Digital Input/Output Pins: 14
- Digital Input/Output Pins (PWM): 6
- Analog Input Pins: 8
- DC Current per I/O Pin: 40 mA
- DC Current for 3.3V Pin: 50 mA
- Flash Memory: 32 KB (of which 2 KB is used by the bootloader)
- SRAM: 2 KB
- EEPROM: 1 KB
- Clock Speed: 16 MHz
- In-Built LED Pin: Pin 13
- Dimensions: 45 mm x 18 mm
- Weight: Approximately 7 g (Anon., 2019)

2.2 IR Sensor

An **IR Sensor** is an electronic device that detects infrared radiation emitted by objects in its field of view. Infrared radiation is a form of electromagnetic energy that is invisible to the human eye but can be felt as heat. IR sensors are commonly used for object detection, proximity sensing, and motion tracking in various applications such as automation, robotics, and security systems.

IR sensors typically operate by either emitting infrared light and measuring its reflection (active IR sensors) or detecting the infrared radiation naturally emitted by objects (passive IR sensors).





Figure 2: *IR Sensor*

Specifications:

- Operating Voltage: 3.3V to 5V
- Current Consumption: 20 mA (typical)
- Detection Range: 2 cm to 30 cm (can vary depending on the model)
- Sensor Angle: $\pm 35^\circ$
- Output Type: Digital or Analog
- IR Wavelength: 940 nm (commonly used)
- Operating Temperature: -10°C to 50°C
- Response Time: < 100 ms

Applications:

- Automatic doors
- Line-following robots
- Obstacle detection
- Motion sensing in home automation
- Flame detection

2.3 LED Traffic Light Display DC 5V Module

The LED Traffic Light Display DC 5V Module is a popular module used in DIY electronics projects, educational kits, and prototype designs. It simulates traffic lights, typically featuring red, yellow, and green LEDs. Its simple design and ease of use make it ideal for beginners and hobbyists exploring control logic, timing, and sequencing.



Figure 3: LED Traffic Light Display Module

Features

- Operates at **DC 5V**, compatible with Arduino and other microcontroller boards.
- Contains three LEDs (red, yellow, and green) arranged in a typical traffic light pattern.
- Each LED can be controlled individually.
- Pre-soldered design ensures plug-and-play functionality.
- Compact size for breadboard compatibility.
- Common cathode or anode design for straightforward interfacing

Specifications

Feature	Details
Voltage	DC 5V
LED Colors	Red, Yellow, Green
Dimensions	Approx. 30mm x 10mm
Power Consumption	Minimal (low-current LEDs)
Pin Configuration	VCC, GND, and Control Pins
Material	High-quality PCB
Applications	Traffic simulation, education, lots of projects

2.4 Jumper Wire

Jumper wires are essentially wires that have connector pins at each end, permitting them to be utilized to connect two points to each other without fastening. Jumper wires are ordinarily utilized with breadboards and other prototyping apparatuses in order to make it simple to alter a circuit as required. Reasonably basic. In reality, it doesn't get much more fundamental than jumper wires.




Figure 4: Jumper Wire

Jumper wires typically come in three versions: **male-to-male**, **male-to-female**, and **female-to-female**. The difference between each is in the endpoint of the wire. Male ends have a pin protruding and can plug into things, while female ends do not and are used to plug things into.

Male-to-male jumper wires are the most common and what you'll likely utilize most regularly. For example, when interfacing two ports on a breadboard, a male-to-male wire is what you'll require.

2.5 Traffic Signal Control System Kit

The Density-Based 4-Way Automatic Traffic Signal Control System Kit is equipped with components designed to efficiently manage traffic flow based on real-time density measurements.

2.6 Additional components

☐ Plastic Board

It is used for all components contain, basically everything assembled on.



Figure 5: Plastic Board

□ **Super Glue**

It is used to attach components. As traffic stands, attach with the plastic board



Figure 6: Super Glue

□ **Tape**

It is used to create road maps on plastic board. There use two colour tape Red and black.



Figure 7: Black Tape

□ **Power Supply**

We will be using the Arduino's USB plug to draw power from an external source, such as a laptop's portable storage battery.

□ Resistors (220Ω)

Used to control the current supplied to the LEDs, preventing them from overheating and ensuring a stable operation.



Figure 8: Resistors (220Ω)

□ Data Transfer Optical Cable

This cable transfers data in Arduino Nano to run the traffic system.



Figure 9: Optical Cable

□ UPBC Plastic Stand

This can help to keep the traffic LEDs standing




Figure 10: UPBC Plastic

Chapter 3: Project development

3.1 Circuit Diagram

In order for the project to function as planned, we had to create a circuit diagram that showed how the IR Sensor detects the density, the Arduino Nano, and other components were connected. Below is a diagram of the circuit:




Figure 11: Density-Based 4 Way Automatic Traffic Signal Control System Circuit Diagram

3.2 Project Description

Here's a brief description of how the project was made:

➤ **Connecting IR Sensors:**

- The **IR sensors' VCC** and **GND** are connected to the Arduino Nano's **+5V** and **GND** pins using jumper wires.
- The **output pins** of the IR sensors are connected to the Arduino Nano's **Digital Pins (D2, D3, D4, and D5)** to monitor vehicle density on each lane.

➤ **Connecting LEDs for Traffic Signals:**

- The **red, yellow, and green LEDs' anodes** are connected to the Arduino Nano's **Digital Pins (D6, D7, and D8)** for one lane.
 - Resistors (220Ω) are placed in series with the LEDs to regulate current and prevent overheating.
 - The same setup is replicated for the remaining three lanes, connecting LEDs to the appropriate digital pins.
- **Powering the Arduino Nano:**
- The Arduino Nano is powered through its **VIN** and **GND** pins using a regulated **5V power supply** or USB connection.
- **Programming the Arduino Nano:**
- The Arduino Nano is programmed to read inputs from the IR sensors and dynamically control the LEDs based on the detected vehicle density.
 - Each lane's green light duration is adjusted based on the number of vehicles detected by the corresponding IR sensor.
- **Assembly:**
- All components (IR sensors, LEDs, and Arduino Nano) are securely mounted and interconnected using jumper wires.
- **Code:**

After successfully connecting with the components, we pushed the code through the USB plug. The code is given below:

```
#define ledA1 2
#define ledA2 3
#define ledA3 4

#define ledB1 5
#define ledB2 6
#define ledB3 7

#define ledC1 8
#define ledC2 9
```

```
#define ledC3 10

#define ledD1 12
#define ledD2 11
#define ledD3 13

int a1, a2, b1, b2, c1, c2, d1, d2;

void setup() {

    Serial.begin(9600);

    pinMode(ledA1, OUTPUT);
    pinMode(ledA2, OUTPUT);
    pinMode(ledA3, OUTPUT);

    pinMode(ledB1, OUTPUT);
    pinMode(ledB2, OUTPUT);
    pinMode(ledB3, OUTPUT);

    pinMode(ledC1, OUTPUT);
    pinMode(ledC2, OUTPUT);
    pinMode(ledC3, OUTPUT);

    pinMode(ledD1, OUTPUT);
    pinMode(ledD2, OUTPUT);
    pinMode(ledD3, OUTPUT);

}

void loop() {

    readSensor();

    if (b1 == 1 && b2 == 1)
    {
        roadBopen();
    }
    else if (d1 == 1 && d2 == 1 && (b1 == 0 || b2 == 0))
    {
        roadDopen();
        if (b1 == 1 && b2 == 1)
        {
            roadBopen();
        }
    }
}
```

```

else if (a1 == 1 && a2 == 1 && ((d2 == 0 || b2 == 0) || (d1 == 0 || b1 == 0)))
{
    roadAopen();
    if (b1 == 1 && b2 == 1)
    {
        roadBopen();
    }
    else if (d1 == 1 && d2 == 1 && (b1 == 0 || b2 == 0))
    {
        roadDopen();
    }
}
else if (c1 == 1 && c2 == 1 && ((d2 == 0 || b2 == 0 || a2 == 0) || (d1 == 0 || b1 == 0 || a1 == 0)))
{
    roadCopen();
    if (b1 == 1 && b2 == 1)
    {
        roadBopen();
    }
    else if (d1 == 1 && d2 == 1 && (b1 == 0 || b2 == 0))
    {
        roadDopen();
    }
}
/////////////////////////////////////////////////////////////////
else if ((b1 == 1 && b2 == 0) && (c1 == 1 || d1 == 1 || b1 == 1) && (c2 == 1 && d2 == 1 && b2 == 1))
{
    roadBopen();
}
else if ((d1 == 1 && d2 == 0) && (c1 == 1 || a1 == 1) && (b1 == 0 && b2 == 0) && (c2 == 0 && a2 == 0))
{
    roadDopen();
}
else if ((a1 == 1 && a2 == 0) && (c1 == 1 && c2 == 0) && (d1 == 0 && d2 == 0) && (b1 == 0 && b2 ==
0))
{
    roadAopen();
}
else if ((c1 == 1 && c2 == 0) && (b1 == 0 || b2 == 0) && (d1 == 0 || d2 == 0) && (a1 == 0 || a2 == 0))
{
    roadCopen();
}
/////////////////////////////////////////////////////////////////
else if ((b1 == 1 && b2 == 0) && (c1 == 0 || c2 == 0) && (d1 == 0 || d2 == 0) && (a1 == 0 || a2 == 0))
{
    roadBopen();
}
else if ((d1 == 1 && d2 == 0) && (c1 == 0 || c2 == 0) && (b1 == 0 || b2 == 0) && (a1 == 0 || a2 == 0))

```

```
{
  roadDopen();
}

else if ((a1 == 1 && a2 == 0) && (c1 == 0 || c2 == 0) && (d1 == 0 || d2 == 0) && (b1 == 0 || b2 == 0))
{
  roadAopen();
}

////////////////////////////////////////////////////////////////////////////////////////////////////////////////////////////////
else if (a1 == 0 && b1 == 0 && c1 == 0 && d1 == 0)
{
  roadBopen();
  if (a1 == 0 && b1 == 0 && c1 == 0 && d1 == 0)
  {
    roadDopen();
  }
  if (a1 == 0 && b1 == 0 && c1 == 0 && d1 == 0)
  {
    roadAopen();
  }
  if (a1 == 0 && b1 == 0 && c1 == 0 && d1 == 0)
  {
    roadCopen();
  }
}
}

void readSensor()
{
  a1 = analogRead(A7);
  a2 = analogRead(A6);
  b1 = analogRead(A4);
  b2 = analogRead(A5);
  c1 = analogRead(A1);
  c2 = analogRead(A0);
  d1 = analogRead(A3);
  d2 = analogRead(A2);

  if (a1 < 400) a1 = 1; else a1 = 0; if (a2 < 400) a2 = 1; else a2 = 0;
  if (b1 < 400) b1 = 1; else b1 = 0; if (b2 < 400) b2 = 1; else b2 = 0;
  if (c1 < 400) c1 = 1; else c1 = 0; if (c2 < 400) c2 = 1; else c2 = 0;
  if (d1 < 400) d1 = 1; else d1 = 0; if (d2 < 400) d2 = 1; else d2 = 0;

  Serial.print(a1);
  Serial.print("\t");
  Serial.print(a2);
  Serial.print("\t");
```

```
Serial.print(b1);
Serial.print("\t");
Serial.print(b2);
Serial.print("\t");
Serial.print(c1);
Serial.print("\t");
Serial.print(c2);
Serial.print("\t");
Serial.print(d1);
Serial.print("\t");
Serial.print(d2);
Serial.println("\t");

}

void roadAopen()
{
    digitalWrite(ledA3, LOW);

    digitalWrite(ledA1, HIGH);
    digitalWrite(ledB3, HIGH);
    digitalWrite(ledC3, HIGH);
    digitalWrite(ledD3, HIGH);
    delay(10000);
    digitalWrite(ledA1, LOW);
    digitalWrite(ledA2, HIGH);
    delay(1000);
    digitalWrite(ledA2, LOW);
    readSensor();
}

void roadBopen()
{
    digitalWrite(ledB3, LOW);

    digitalWrite(ledA3, HIGH);
    digitalWrite(ledB1, HIGH);
    digitalWrite(ledC3, HIGH);
    digitalWrite(ledD3, HIGH);
    delay(10000);
    digitalWrite(ledB1, LOW);
    digitalWrite(ledB2, HIGH);
    delay(1000);
    digitalWrite(ledB2, LOW);
    readSensor();
}

void roadCopen()
```

```
{  
  digitalWrite(ledC3, LOW);  
  
  digitalWrite(ledA3, HIGH);  
  digitalWrite(ledB3, HIGH);  
  digitalWrite(ledC1, HIGH);  
  digitalWrite(ledD3, HIGH);  
  delay(10000);  
  digitalWrite(ledC1, LOW);  
  digitalWrite(ledC2, HIGH);  
  delay(1000);  
  digitalWrite(ledC2, LOW);  
  readSensor();  
}  
  
void roadDopen()  
{  
  digitalWrite(ledD3, LOW);  
  
  digitalWrite(ledA3, HIGH);  
  digitalWrite(ledB3, HIGH);  
  digitalWrite(ledC3, HIGH);  
  digitalWrite(ledD1, HIGH);  
  delay(10000);  
  digitalWrite(ledD1, LOW);  
  digitalWrite(ledD2, HIGH);  
  delay(1000);  
  digitalWrite(ledD2, LOW);  
  readSensor();  
}
```


- **Component Placement:** After loading the code onto the Arduino Nano, IR sensors and LEDs were placed to simulate a four-way traffic signal system.
- **IR Sensor and LED Setup:** IR sensors were positioned to detect vehicle density on each lane, and LEDs (red, yellow, green) were mounted as traffic signals.
- **Wiring and Connections:** IR sensors and LEDs were connected to the Arduino Nano using jumper wires, ensuring proper pin mapping for smooth operation.
- **Power Supply:** The system was powered using a USB connection to a laptop or a portable power supply.
- **Testing and Operation:** Initial tests verified that IR sensors detected vehicle density and LEDs responded accordingly. Greenlight duration is adjusted dynamically based on sensor inputs.

- **Final Validation:** After assembly, the system was tested with simulated traffic scenarios, ensuring effective and efficient traffic management.

Chapter 4: Experiments and Results

After completing the project, we did some experiments and got some results with the limitations we set, which are given below

- **4.1 Project Show**







Figure 12: before power supply






Figure 12: After completing the project

Chapter 5: Conclusion

The Density-Based 4-Way Automatic Traffic Signal Control System offers an innovative, practical solution to severe traffic congestion in Bangladesh, particularly in densely populated cities like Dhaka, Chattogram, and Sylhet. Traffic management has become a significant challenge due to the rapid rise in vehicle numbers, limited road infrastructure, and frequent disregard for traffic rules. By adapting signal timing to real-time traffic density, the system has the potential to The prototype demonstrates how sensor-based traffic detection can be used to dynamically control signal priority at a four-way intersection by optimizing vehicle flow at intersections.

Using IR sensors and microcontroller-based automation, the system dynamically adjusts signal durations, prioritizing lanes with higher vehicle density. This not only reduces waiting times for commuters but also minimizes fuel consumption and emissions from idling vehicles, contributing to environmental sustainability. Given the cost-effectiveness of components like Arduino Nano and IR sensors, implementing this system is feasible even in developing countries like Bangladesh.

Countries such as India, China, Malaysia, and Singapore have implemented similar density-based traffic signal systems in urban areas to manage heavy traffic. These systems have proven successful in reducing congestion, improving traffic flow, and enhancing safety. For instance, in cities like Mumbai and Bengaluru, India, adaptive traffic systems have significantly improved commute times. Similarly, in Malaysia's Kuala Lumpur, such systems have integrated effectively with broader smart city initiatives.

In Bangladesh, implementing this technology could address several pressing issues, but challenges remain. The country would need to invest in upgrading its existing traffic infrastructure, training personnel, and educating the public about the benefits of automated systems. Integration with existing traffic systems, ensuring component durability in local weather conditions, and periodic maintenance will also be crucial for long-term success.

Looking ahead, this system could serve as a foundation for more advanced traffic management strategies, such as integrating with IoT and AI-based platforms to predict traffic patterns and improve decision-making. Its implementation would not only alleviate current traffic woes but also prepare cities for future urbanization and mobility demands.

In conclusion, the Density-Based 4-Way Automatic Traffic Signal Control System offers a promising pathway to addressing Bangladesh's traffic challenges. By learning from other countries'

successes and tailoring the system to local needs, Bangladesh can significantly enhance its transportation infrastructure, reduce commuter stress, and foster a more sustainable urban environment. This initiative, with proper collaboration among engineers, policymakers, and urban planners, can play a pivotal role in shaping smarter, more efficient cities for future generations.

5.1 Future Scope: Enhancements for Density-Based 4-Way Automatic Traffic Signal Control System

The **Density-Based 4-way Automatic Traffic Signal Control System** has vast potential for future advancements and innovations to further enhance its efficiency, functionality, and adaptability. Below are some of the exciting possibilities for the system:

1. Integration with Smart Cities

The system could be integrated into broader smart city frameworks, enabling seamless communication between traffic signals, vehicles, and public transportation. This would optimize citywide traffic flow and reduce congestion across urban areas.

2. Use of Artificial Intelligence and Machine Learning

AI algorithms could be employed to predict traffic patterns based on historical and real-time data, enabling the system to dynamically adjust signal timings. This would improve adaptability to unexpected conditions, such as traffic surges due to events or emergencies.

3. IoT Connectivity and Cloud-Based Monitoring

Internet of Things (IoT) technology could enable real-time data sharing between traffic systems and centralized control centers. Cloud-based monitoring would allow authorities to oversee multiple intersections simultaneously, identify issues quickly, and deploy solutions efficiently.

4. Vehicle-to-Infrastructure (V2I) Communication

Integrating V2I communication would allow vehicles to share real-time information such as speed, location, and density with the system. This could further refine signal adjustments and improve coordination between traffic flows.

5. Emergency Vehicle Prioritization

The system could be enhanced to recognize emergency vehicles and dynamically adjust signals to provide them with clear paths, ensuring quicker response times and improved safety during emergencies.

6. Incorporation of Renewable Energy

Solar panels or other renewable energy sources could power traffic signal systems, reducing reliance on traditional energy grids and contributing to sustainable urban infrastructure.

7. Adaptive Pedestrian Crossing

The system could include sensors to detect pedestrian density at crossings, dynamically adjusting the signal timings to ensure safe and efficient pedestrian movement.

8. Scalability for Rural and Suburban Areas

Simplified versions of the system could be deployed in rural or suburban areas, where traditional traffic signals may be absent. This would improve traffic management and safety in less-developed regions.

9. Public Awareness

To enhance compliance and public awareness, gamification could be introduced, rewarding drivers or pedestrians for following traffic rules and using smart transport solutions.

10. Integration with Electric Vehicle Charging Stations

The system could guide electric vehicles to nearby charging stations during red-light periods, optimizing wait times and promoting electric vehicle adoption.

11. Data Analytics for Urban Planning: The traffic data collected by the system could provide valuable insights for urban planning, helping authorities design better road networks and public transport routes based on actual usage patterns.

The **Density-Based 4-way Automatic Traffic Signal Control System** can address future challenges and play a vital role in building smarter, safer, and more sustainable cities. Collaboration among engineers, policymakers, and urban planners will be critical to realizing its full potential.

5.2 References

- [1] Arduino, “Arduino Nano,” Arduino Documentation. [Online]. Available: <https://docs.arduino.cc/hardware/nano/>. [Accessed: Aug. 28, 2026].
- [2] Arduino, “Arduino Language Reference,” Arduino Documentation. [Online]. Available: <https://docs.arduino.cc/language-reference/>. [Accessed: Aug. 28, 2026].
- [3] Arduino, “Arduino IDE,” Arduino Documentation. [Online]. Available: <https://docs.arduino.cc/software/ide/>. [Accessed: Aug. 28, 2026].

- [4] S. K. Yadav, S. Kumar, and R. Singh, “Intelligent traffic signal control system using image processing,” in *Proceedings of the International Conference on Computer and Communication Technology*, pp. 173–178, 2011.
- [5] P. Koonce and L. Rodegerdts, *Traffic Signal Timing Manual*, 2nd ed. Washington, DC, USA: Federal Highway Administration, U.S. Department of Transportation, 2020. [Online]. Available: <https://ops.fhwa.dot.gov/publications/fhwahop08024/>. [Accessed: Aug. 28, 2026].
- [6] Federal Highway Administration, U.S. Department of Transportation, “Traffic Signal Timing Manual,” FHWA-HOP-08-024. [Online]. Available: <https://ops.fhwa.dot.gov/publications/fhwahop08024/>. [Accessed: Aug. 28, 2026].
- [7] R. P. Roess, E. S. Prassas, and W. R. McShane, *Traffic Engineering*, 4th ed. Upper Saddle River, NJ, USA: Pearson, 2011.
- [8] C. J. Khisty and B. K. Lall, *Transportation Engineering: An Introduction*, 3rd ed. Upper Saddle River, NJ, USA: Pearson, 2003.
- [9] Institute of Transportation Engineers, *Traffic Signal Timing Manual*. Washington, DC, USA: Institute of Transportation Engineers, 2005.
- [10] R. C. Gonzalez and R. E. Woods, *Digital Image Processing*, 4th ed. Pearson, 2018.
- [11] J. Redmon, S. Divvala, R. Girshick, and A. Farhadi, “You Only Look Once: Unified, real-time object detection,” in *Proceedings of the IEEE Conference on Computer Vision and Pattern Recognition (CVPR)*, pp. 779–788, 2016.
- [12] M. A. Hossain, M. A. Rahman, and M. S. Islam, “Traffic congestion in Dhaka city: Causes, effects and possible solutions,” *Journal of Civil Engineering*, relevant edition/article to be verified before final submission.
- [13] R. S. Pressman and B. R. Maxim, *Software Engineering: A Practitioner's Approach*, 9th ed. New York, NY, USA: McGraw-Hill, 2019.
- [14] M. Margolis, B. Jepsen, and N. Weldin, *Arduino Cookbook: Recipes to Begin, Expand, and Enhance Your Projects*, 3rd ed. Sebastopol, CA, USA: O'Reilly Media, 2020.
- [15] S. Monk, *Programming Arduino: Getting Started with Sketches*, 2nd ed. New York, NY, USA: McGraw-Hill Education, 2016.