

Query Private Component Library Interface

Request URL :

<https://open.jlpcb.com/overseas/openapi/component/getPrivateComponentLibrary>

Request Type : POST

Interface Description:

Query the private component library of authenticated customers

Request Parameters :

Parameter Description :

Parameter name	Type	Required	Description
currentPage	Integer	Yes	Page number, starting from 1, default value:1
pageSize	Integer	Yes	Number of records per page. Default value: 30, maximum: 1000.

Code Example:

```
OkHttpClient client = new OkHttpClient().newBuilder().build();
MediaType mediaType = MediaType.parse("application/json");
RequestBody body = RequestBody.create(mediaType,
"{\"currentPage\":1,\"pageSize\":100}");
Request request = new Request.Builder()
    .url("https://your-domain.com/overseas/openapi/component/getPrivateComponentLibrary")
    .method("POST", body)
    .addHeader("Content-Type", "application/json")
    .build();
Response response = client.newCall(request).execute();
```

Response Data:

```

{
  "code": 200,
  "message": "success",
  "data": [
    {
      "componentModel": "STM32F103C8T6",          // Model
      "componentSpecification": "LQFP-48",        // Package
      "componentCode": "C8734",                  // cCode
      "jlcpcbParts": 1000,                       // JLCPCB Parts
      "globalSourcingParts": 500,                // Global Sourcing Parts
      "consignedParts": 200,                     // Consigned Parts
      "idleStock": 50                            // Idle Stock
    },
    {
      "componentModel": "ESP32-WROOM-32",
      "componentSpecification": "SMD-38",
      "componentCode": "C82899",
      "jlcpcbParts": 800,
      "globalSourcingParts": 300,
      "consignedParts": 100,
      "idleStock": 25
    }
  ]
}

```

Response Status	Status Description
200	success
401	unauthorized
403	forbidden
429	too many requests
4XX	param error
500	inner server error